

(19) World Intellectual Property Organization
International Bureau



(43) International Publication Date
14 December 2006 (14.12.2006)

PCT

(10) International Publication Number
WO 2006/133151 A1

(51) International Patent Classification:
H04B 7/26 (2006.01)

(74) Agents: **TILLMAN, Chad, D.** et al.; TILLMAN
WRIGHT, PLLC, P.O. Box 471581, Charlotte, NC 28247
(US).

(21) International Application Number:

PCT/US2006/021859

(81) Designated States (*unless otherwise indicated, for every kind of national protection available*): AE, AG, AL, AM, AT, AU, AZ, BA, BB, BG, BR, BW, BY, BZ, CA, CH, CN, CO, CR, CU, CZ, DE, DK, DM, DZ, EC, EE, EG, ES, FI, GB, GD, GE, GH, GM, HR, HU, ID, IL, IN, IS, JP, KE, KG, KM, KN, KP, KR, KZ, LC, LK, LR, LS, LT, LU, LV, LY, MA, MD, MG, MK, MN, MW, MX, MZ, NA, NG, NI, NO, NZ, OM, PG, PH, PL, PT, RO, RU, SC, SD, SE, SG, SK, SL, SM, SY, TJ, TM, TN, TR, TT, TZ, UA, UG, US, UZ, VC, VN, YU, ZA, ZM, ZW.

(22) International Filing Date: 5 June 2006 (05.06.2006)

(25) Filing Language: English

(26) Publication Language: English

(30) Priority Data:

60/687,415 3 June 2005 (03.06.2005) US
60/691,884 17 June 2005 (17.06.2005) US

(71) Applicant (*for all designated States except US*): **TERA-HOP NETWORKS, INC.** [US/US]; 1225 Old Alpharetta Road, Suite 210, Alpharetta, GA 30005 (US).


(84) Designated States (*unless otherwise indicated, for every kind of regional protection available*): ARIPO (BW, GH, GM, KE, LS, MW, MZ, NA, SD, SL, SZ, TZ, UG, ZM, ZW), Eurasian (AM, AZ, BY, KG, KZ, MD, RU, TJ, TM), European (AT, BE, BG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, HU, IE, IS, IT, LT, LU, LV, MC, NL, PL, PT, RO, SE, SI, SK, TR), OAPI (BF, BJ, CF, CG, CI, CM, GA, GN, GQ, GW, ML, MR, NE, SN, TD, TG).

(72) Inventor; and


(75) Inventor/Applicant (*for US only*): **TWITCHELL, Robert, W., Jr.** [US/US]; 2475 Flat Stone Drive, Cumming, GA 30041 (US).

[Continued on next page]

(54) Title: USING WAKE-UP RECEIVERS FOR SOFT HAND-OFF IN WIRELESS COMMUNICATIONS



(57) Abstract: Multiple standards based radio ("SBR") devices, each having a high-gain directional antenna, are utilized in a remote sensor interface ("RSI") unit to optimize detection and reception by the RSI of radio signals from gateway controllers, hopping radios, and other wireless devices.





Published:

— *with international search report*

For two-letter codes and other abbreviations, refer to the "Guidance Notes on Codes and Abbreviations" appearing at the beginning of each regular issue of the PCT Gazette.

USING WAKE-UP RECEIVERS FOR SOFT HAND-OFF IN WIRELESS COMMUNICATIONS

CROSS-REFERENCE TO RELATED APPLICATION

This application is entitled to the benefit of, and claims priority to, provisional U.S. Patent Application Serial No. 60/687,415 filed June 3, 2005 and titled "CLASS-BASED SOFT HAND-OFF IN WIRELESS COMMUNICATIONS," and provisional U.S. Patent Application Serial No. 60/691,884 filed June 17, 2005 and titled "REMOTE SENSOR INTERFACE (RSI) STEPPED WAKE-UP SEQUENCE," the entirety of each of which is incorporated herein by reference.

INCORPORATION BY REFERENCE

The present application hereby incorporates by reference: U.S. Patent No. 6,753,775 B2 (titled "Smart Container Monitoring System"); U.S. Patent No. 6,745,027 B2 (titled "Class Switched Networks for Tracking Articles"); U.S. Patent No. 6,665,585 B2 (titled "Method and Apparatus for Container Management"); U.S. Patent No. 5,458,042 (titled "Container for Packaging an Object Provided with a Radio Frequency Transmission Device and Removable Element for Such a Container"); International Patent Application Publication No. WO 03/032501 A2, which international patent application designated the United States and was published in English (titled "Network Formation in Asset-Tracking System Based on Asset Class"); International Patent Application Publication No. WO 03/098851 A1, which international patent application designated the United States and was published in English (titled "LPRF Device Wake Up Using Wireless Tag"); U.S. Patent Application Publication No. 2004/0082296 A1; U.S. Patent Application Publication No. 2004/0183673 A1; U.S. Patent Application Publication No. 2004/0021572 A1 ("Electronic baggage tracking and identification"); and U.S. Patent Application Serial No. 11/306,765 (titled "Keyhole Communication Device for Tracking and Monitoring Shipping Container and Contents Thereof").

COPYRIGHT STATEMENT

All of the material in this patent document is subject to copyright protection under the copyright laws of the United States and of other countries. The copyright owner has no objection to the facsimile reproduction by anyone of the patent document or the patent disclosure, as it appears in the Patent and Trademark Office patent file or records, but otherwise reserves all copyright rights whatsoever.

BACKGROUND OF THE PRESENT INVENTION

Field of the Present Invention

The present invention generally relates to an assembly comprising a remote sensor interface and a plurality of selectable two-way wireless communication devices, and, in particular, to a method and assembly for selecting one of a plurality of two-way wireless communication devices on the basis of one or more wake-up receivers.

Background

RSIs are utilized for remotely collecting data in the field and communicating the collected data to one or more centralized locations. For example, RSIs are utilized in tracking and/or monitoring assets that are stored and/or transported in association with wireless transceivers, such as radio frequency identification tags (RFIDs). In such implementations, such as those described in U.S. Patent Application Publication No. 2005/0093702 A1, an RSI has sometimes been previously referred to as a “wireless reader tag” or “WRT.” The data regarding the tracked and/or monitored assets is communicated by an RSI to one or more central servers for processing. Such data is useful, for instance, in supply chain management. Such data further is useful, for instance, in homeland security, especially when the assets being

tracked and/or monitored are being imported into the United States from foreign countries.

Of course, the RSIs of the present invention are preferably capable of wireless communications with external devices. For example, the RSI preferably communicates with other RSIs in forming one or more wireless networks. Furthermore, the RSI preferably communicates with a gateway that itself serves as a bridge to other networks, such as the Internet, a cellular network, or a Satellite network.

Unfortunately, wireless communications in urban environments can pose difficult and unpredictable challenges. Signal fading, multi-path transmission routes and reflections, environmental conditions, and other complications can cause radio signal degradations to occur thereby impairing radio communications. Low signal strengths, cancellations, and attenuations as signals propagate through construction materials impair signal reception by a wireless device. The US military has called for initiatives to address these issues due to problems experienced in urban combat environments.

One approach to solving some of these problems is to utilize a plurality of wireless communication devices arrayed to maximize the possibility that at least one of the devices is able to maintain wireless communication with a gateway, another device, or the like. Such an approach may be enhanced using, for example, high gain directional antennas arranged to provide overlapping patterns of coverage. Unfortunately, devoting multiple radios or other wireless communication devices to a single RSI results in considerably greater power consumption, among other problems. Power consumption could be reduced, however, if the RSI could select an individual radio for carrying out wireless communications on behalf of the RSI based on strength of signal and other criteria, and could hold radios in a standby mode when signals not directed specifically to that RSI are received. Thus, a need exists for a system and method for selecting one of a plurality of two-way wireless communication devices, particularly for use by an RSI in carrying out wireless

communications, on the basis of determinations made by one or more wake-up receivers.

BRIEF DESCRIPTION OF THE DRAWINGS

Further features, embodiments, and advantages of the present invention will become apparent from the following detailed description with reference to the drawings, wherein:

FIG. 1 is a block diagram of a system for using wake-up receivers for soft hand-off in wireless communications, according to a preferred embodiment of the present invention;

FIG. 2 is a block diagram of one of the gateway controllers of FIG. 1;

FIG. 3A is a block diagram of one of the remote sensor interfaces of FIG. 1;

FIG. 3B is a block diagram of the RSI link device of FIG. 1;

FIG. 4 is a schematic diagram illustrating the receipt and transmission, by the RSI controller, of data streams to and from a gateway controller according to the currently most reliable communication channel;

FIGS. 5A-5G are schematic diagrams illustrating the operation of an RSI in accordance with a first implementation of the present invention;

FIGS. 6A-6E are schematic diagrams illustrating the operation of an RSI in accordance with a second implementation of the present invention; and

FIGS. 7A-7G are schematic diagrams illustrating the operation of an RSI in accordance with a third implementation of the present invention.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

As a preliminary matter, it will readily be understood by one having ordinary skill in the relevant art (“Ordinary Artisan”) that the present invention has broad utility and application. Furthermore, any embodiment discussed and identified as being “preferred” is considered to be part of a best mode contemplated for carrying out the present invention. Other embodiments also may be discussed for additional illustrative purposes in providing a full and enabling disclosure of the present invention. Moreover, many embodiments, such as adaptations, variations, modifications, and equivalent arrangements, will be implicitly disclosed by the embodiments described herein and fall within the scope of the present invention.

Accordingly, while the present invention is described herein in detail in relation to one or more embodiments, it is to be understood that this disclosure is illustrative and exemplary of the present invention, and is made merely for the purposes of providing a full and enabling disclosure of the present invention. The detailed disclosure herein of one or more embodiments is not intended, nor is to be construed, to limit the scope of patent protection afforded the present invention, which scope is to be defined by the claims and the equivalents thereof. It is not intended that the scope of patent protection afforded the present invention be defined by reading into any claim a limitation found herein that does not explicitly appear in the claim itself.

Thus, for example, any sequence(s) and/or temporal order of steps of various processes or methods that are described herein are illustrative and not restrictive. Accordingly, it should be understood that, although steps of various processes or methods may be shown and described as being in a sequence or temporal order, the steps of any such processes or methods are not limited to being carried out in any particular sequence or order, absent an indication otherwise. Indeed, the steps in such processes or methods generally may be carried out in various different sequences and orders while still falling within the scope of the present invention. Accordingly, it is intended that the

scope of patent protection afforded the present invention is to be defined by the appended claims rather than the description set forth herein.

Additionally, it is important to note that each term used herein refers to that which the Ordinary Artisan would understand such term to mean based on the contextual use of such term herein. To the extent that the meaning of a term used herein—as understood by the Ordinary Artisan based on the contextual use of such term—differs in any way from any particular dictionary definition of such term, it is intended that the meaning of the term as understood by the Ordinary Artisan should prevail.

Furthermore, it is important to note that, as used herein, “a” and “an” each generally denotes “at least one,” but does not exclude a plurality unless the contextual use dictates otherwise. Thus, reference to “a picnic basket having an apple” describes “a picnic basket having at least one apple” as well as “a picnic basket having apples.” In contrast, reference to “a picnic basket having a single apple” describes “a picnic basket having only one apple.”

When used herein to join a list of items, “or” denotes “at least one of the items,” but does not exclude a plurality of items of the list. Thus, reference to “a picnic basket having cheese or crackers” describes “a picnic basket having cheese without crackers”, “a picnic basket having crackers without cheese”, and “a picnic basket having both cheese and crackers.” Finally, when used herein to join a list of items, “and” denotes “all of the items of the list.” Thus, reference to “a picnic basket having cheese and crackers” describes “a picnic basket having cheese, wherein the picnic basket further has crackers,” as well as describes “a picnic basket having crackers, wherein the picnic basket further has cheese.”

Referring now to the drawings, in which like numerals represent like components throughout the several views, the preferred embodiments of the present invention are next described. The following description of the

preferred embodiment(s) is merely exemplary in nature and is in no way intended to limit the invention, its application, or uses.

FIG. 1 is a block diagram of a system **10** for using wake-up receivers for soft hand-off in wireless communications, according to a preferred embodiment of the present . The system **10** includes one or more gateway controllers **20** linked to a server **16** via a network interface **18** via wired or wireless communication, depending on the implementation of the system **10**. Each gateway controller **20** may further communicate wirelessly with one or more remote sensor interface (“RSI”) **40**. As will be evident to the Ordinary Artisan, the gateway controller **20** may be any central radio unit, the design and implementation of which will likewise be apparent to the Ordinary Artisan, that is capable of initiating and carrying out wireless communication with RSIs **40**. Indeed, it will likewise be evident that the specific communication devices and methods described and illustrated herein may be used for wireless communication between other types of radio devices. As illustrated in FIG. 1, one or more RSI **40**, such as those designated “RSI C” and “RSI H,” may be linked to a gateway controller **20** only via another RSI **40**, such as the one designated “RSI F,” or an RSI link **140**. In this regard, RSI F and the RSI link **140** each provide hopping capability, thereby permitting gateway controllers **20** to communicate with RSIs **40** with which they are not in direct contact.

FIG. 2 is a block diagram of one of the gateway controllers **20** of FIG. 1. As shown therein, the gateway controller **20** includes a power source **13** such as a battery or connection to an external power source for powering systems of the gateway controller **20**; a central processing unit (CPU) section **25** for controlling operations of the gateway controller **20**; a wake-up transmitter **28** coupled to an external patch antenna **30**, such as a 6.5dBi omnidirectional antenna, for transmitting wake-up signals; and a two-way wireless communication device **32** including an antenna **34** for two-way communications. The two-way wireless communication device **32** is preferably a standards based radio (“SBR”) such as, for example, a Bluetooth

radio, a WiFi radio, a Zigbee radio, an Ultra-Wideband (UWB) radio, or a WiMAX radio, with a Bluetooth radio being the most preferred. The CPU section **35** most predominantly includes a microprocessor and 802.11 or other communication capability, but optionally, may further include a global positioning system (GPS) and cellular telephony communications capabilities. The gateway controller **20** serves as a fixed-area or mobile interface between RSIs **40** and the network interface **18**, which in turn may connect to other networks, such as the Internet, a cellular network, or a Satellite network.

FIG. 3A is a block diagram of one of the RSIs **40** of FIG. 1. As shown therein, the RSI **40** includes a controller **42** and a plurality of low power radio systems **44**. Each low power radio system **44** includes a wake-up receiver **46**, for receiving wake-up signals from the gateway controller **20** and/or other RSIs **40**, and a two-way wireless communication device **48**, including a high gain antenna **54**, for two-way communications. Each two-way wireless communication device **48** is preferably an SBR such as, for example, a Bluetooth radio, a WiFi radio, a Zigbee radio, an Ultra-Wideband (UWB) radio, or a WiMAX radio, but which in any case is generally selected to match the two-way wireless communication radio **22** of the gateway controller **20**. The wake-up receiver **46** further includes an ultra-low power consumption, wide band receiver and includes an antenna etched on a printed circuit board.

The RSI **40** may be associated with one or more sensors **50**, or the RSI **40** itself may serve as a gateway to other RSIs **40**. One particularly common application for RSIs **40** is in the tracking of various assets, wherein each of a plurality of RSIs **40** is associated with a particular asset and/or an RSI **40** is associated with an asset, such as a shipping container, pallet, or the like, that carries or contains other assets. The use of devices similar to RSIs **40** to track assets has been described in U.S. Patent Application Publication No. 2005/0093702 A1, in which such devices are often generally referred to as “wireless transceivers” or “WRTs.” Insofar as the RSI **40** is associated with assets, such as shipping containers and/or contents thereof, the RSI **40** further preferably is capable of interfacing or interacting with asset monitoring

sensors **50** that monitor conditions, phenomena, or the like inside or outside the container and/or inside or outside a particular asset in the container. Such sensors **50** may include, without limitation, electronic seals capable of detecting openings and/or closures of the container, cameras, microphones, RF signal detectors, light detectors, temperature sensors, radiation sensors, chemical sensors, and motion detectors. The particular use and implementation of RSIs in shipping containers has been further described in U.S. Patent Application Serial No. 11/306,765. The RSI controller **42** preferably includes a sensor board (not shown) having circuitry for interfacing with such asset monitoring sensors **50**.

Two-way wireless communications are used to convey commands and queries from the gateway controller **20** to the RSI **40** and to convey data, which may include sensor data acquired from the monitoring sensors **50**, from the RSI **40** to the gateway controller **20**.

FIG. 3B is a block diagram of the RSI link **140** of FIG. 1. For general purposes of the discussion that follows, RSI links **140** are understood to be similar in design and operation to RSIs **40** themselves. Of course, it will be apparent to the Ordinary Artisan that RSI links **140** may include additional functionality, but such differences are not particularly relevant to the discussion that follows.

FIG. 4 is a schematic diagram illustrating the receipt and transmission, xxx by the RSI controller **42**, of data streams to and from a gateway controller **20** according to the currently most reliable communication channel. As one or more of the low power radio systems **44** receives wireless communication signals from the gateway controller **20**, the RSI controller **42** monitors signal strengths, Bit Error Rates (BER's), and other parameters available during reception and determines which of the multiple on-board SBR devices **48** currently represents the most reliable communication channel. The controller **42** then routes wireless communications through the SBR device **48** that represents the most reliable channel. After an initial channel is selected, the

RSI controller 42 then continuously or intermittently monitors the parameters of the multiple on-board SBR devices 48 for updating the determination and selection of the optimal SBR device 48. As changes in conditions occur, the RSI controller 42 looks for other wakeup signals as potential alternatives to the current SBR communication channel. If a valid wakeup is seen, the RSI controller will monitor the channel and may determine that a second on-board SBR device 48 has become the most reliable channel. In this case the RSI controller 42 triggers a "soft" handoff wherein wireless communications of the RSI 40 are handed off to the second on-board SBR device 48. When two or more on-board SBR devices 48 represent equivalently reliable channels, the controller 42 routes communications through an arbitrarily selected one of the two or more devices 48 until a further change in conditions occurs.

Based on the protocols available with the SBR, the RSI controller will determine the best times for the SBRs to transmit. Transmission must be tightly controlled due to close proximity of the SBR antennas and issues with saturating the receiver front ends. Also this prevents the respective transmitters/transceivers of the various SBR devices 48 from conflicting with each other and also reduces power consumption for the RSI 40 as a whole.

In each low power radio system 44, the wake-up receiver (also called the TRX or Tag Turn-On Receiver) 46 minimizes power consumption by controlling whether the corresponding SBR device 48 is active, and the level of that activation. The wake-up receiver or TRX 46 tightly controls power so that standby current is driven down to micro-amps. The TRX signal is used to select the first radio that will engage in communications. The other radios are booted up and begin listening to the RF signal. The other low power radios 44 are preferably not utilized in transmitting signals to the gateway controller unless the first radio system 44 begins to lose the signal and the other radio systems 44 have better reception.

One or more of the wake-up receivers 46 of a particular RSI 40 may be activated, thereby waking up the corresponding SBR devices 48, by

specifically directing a wake-up signal toward the particular RSI 40 using some sort of data identifier. In particular, a wake-up signal may be specifically directed toward a particular RSI 40 by including a unique identifier of the RSI 40 in the wake-up signal. Preferably, however, the wake-up receiver 46 may operate at least partly on the basis of class designations. In this regard, each RSI 40 (or each "Wireless Tag," as that term is used in U.S. Patent Application Publication No. 2005/0093702 A1) includes a "class designation" representative of an attribute, characteristic, relation, or behavior of the RSI 40 or associated asset or assets, and each RSI 40 or Wireless Tag is said to belong to, or be a member of, a particular Class based on its class designation. Identification of the Class for which a particular RSI 40 or Wireless Tag is designated preferably is stored on the RSI 40 or Wireless Tag and is utilized by the RSI 40 or Wireless Tag in screening broadcasts for determining whether to respond thereto with a transmission. The Class may represent any type of identification, as desired. Further information about class designations and their uses may be found in the aforementioned U.S. Patent Application Publication No. 2005/0093702 A1.

When a broadcast or multicast is made to the RSIs 40 or Wireless Tags, each RSI 40 or Wireless Tag is capable of identifying a specified Class in the broadcast and replying to the broadcast with its own transmission when the specified Class matches its Class. If the Class does not match its class designation, then the RSI 40 or Wireless Tag does not respond to the broadcast and it makes no transmission. In this regard, each RSI 40 or Wireless Tag is a transponder that may be selectively activated. Semi-passive transceivers that are capable of being used to respond to targeted broadcasts in accordance with the present invention, and not to every broadcast received, are well known within the art and, accordingly, the specific design of such semi-passive transceivers forms no part of the present invention.

The class designations are used by each wake-up receiver 46 to screen each broadcast or multicast intended for receipt by a particular class. A command, query, or the like (sometimes generically referred to as a message)

is communicated in a transmission to members of a particular class in an RSI broadcast as part of a data packet that begins with a preamble including an identification of the Class intended as the target of the broadcast. Other information may also be included in the data packet for screening purposes by one or more of the wake-up receivers **46** in each RSI **40**. Wake-up receivers **46** within range of the broadcast awake from a standby mode to receive the data packet, but only process the message therein with possible transmissions in response thereto when the Class of the preamble matches the Class of the RSI **40** (and when the other screening information, if present, also is matched). If there is no match, then the particular RSI **40** does not process the message, drops the data packet, and returns to standby mode.

Thus, rather than direct a wake-up signal toward a particular RSI **40** using a unique identifier of the RSI **40**, a wake-up signal may alternatively be specifically directed toward a particular class of RSIs **40** as identified by a class designation. In this regard, the wake-up signal would include the class to which the wake-up signal is directed. In yet another alternative, a wake-up signal may be directed to all RSIs **40**. In this regard, the wake-up signal would include an indication to this effect. Preferably in class-based systems, such a wake-up signal would include a class designation that includes, as members of the class, all of the RSIs **40** (i.e., an all encompassing or root class).

In general, wireless communication between the gateway controller **20** and the RSI **40** may thus be carried out as follows. The gateway controller **20** first transmits, via the wake-up transmitter **28**, a wake-up signal to the RSI **40**. At the RSI **40**, the wake-up signal is received by a wake-up receiver **46** of the RSI **40**. Upon wake-up of the RSI **40**, the gateway controller **20** and RSI **40** engage in the two-way communications **16** using the SBR device **48** corresponding to the first wake-up receiver **46** and the standards based radio **32** of the gateway controller **20**.

If a gateway controller **20** is unable to communicate directly with a particular RSI **40**, it may still be able to communicate with such an RSI **40**, using conventional hopping techniques, via an RSI link **140** or another RSI **40**. Such communication paths are schematically represented in FIG. 1 between a first gateway controller **20** and the RSI **40** designated "RSI C" via the RSI link **140** and between a second gateway controller **20** and the RSI **40** designated "RSI H" via the RSI **40** designated "RSI F." The remote RSIs **40** ("RSI C" and "RSI H") may still be awakened in the same manner as the other RSIs **40** (i.e., using class designations).

Although considerable reduction in power consumption may be achieved using a class-based wake-up signal process as described above, still further reduction in power consumption may be achieved using a stepped wake-up sequence such as one described in U.S. Patent Application No. 11/422,321. For example, as set forth therein, the low power radio system **44** may generally reside in a low or no power consumption state, wherein the RSI **12** draws electrical current that is only on the order of magnitude of tens of microamps. When the wake-up receiver **46** determines that a wake-up signal is likely present, for example, by way of a measured signal strength that prevails over any present RF noise, the low power radio system **44**, and specifically, the wake-up receiver **46** enters a second state in which the low power radio system **44** overall draws on the order of hundreds of microamps of electrical current.

In this second state, the wake-up receiver **46** evaluates the signal for one or more particular criteria, such as the presence of a particular modulation in the possible wake-up signal. For example, the signal may be analyzed with regard to amplitude, frequency and/or phase to determine if the signal is modulated according to the applicable standard, such as GFSK or FSK, that is being utilized in the operation of the wake-up receiver **46**. If the signal is not modulated according to the applicable standard (a situation where digital information is not going to be extracted from the signal), then the signal is deemed not to be a wake-up signal and the low power radio system **44** returns

to the first state, i.e., the standby state. On the other hand, if the signal is modulated according to the applicable standard, then the low power radio system **44**, and specifically the wake-up receiver **26**, enters a third state in which the low power radio system **44** overall draws on the order of magnitude of a milliamp of electrical current.

In this third state, the wake-up receiver **46** receives a modulated signal and extracts and interprets digital information therefrom. In this regard, the wake-up receiver **46** extracts digital information such as class and/or other data from the modulated signal. For example, the digital information embedded in the wake-up signal transmitted by the gateway controller **20** may include a class that is determinative of whether the low power radio system **44** enters a fourth state or returns to the first, or standby, state, wherein if the class of the wake-up signal matches a class of the RSI **40**, then a fourth state is preferably entered, and if the class of the wake-up signal does not match a class of the RSI **40**, then the first, or standby, state is preferably re-entered.

In the fourth state, the low power radio system **44** overall draws on the order of tens to hundreds of milliamps of electrical current. In this state, the wake-up receiver **46** “wakes up” the corresponding SBR device **48** of the RSI **40** whereby the RSI **40** begins to actively receive data in communications from a gateway **20** or another RSI **40**. Such communications received by the RSI **40** may configure the RSI **40** with regard to sensors **50** with which the RSI **40** is associated. Alternatively, the commands received may configure the RSI **40** with regard to a periodic wake-up schedule for periodic exchanges of communications with the gateway controller **20**. The communications received further may alter a class designation of the RSI **40**, may prompt the RSI **40** to communicate with other RSIs **40**, may relate to network formations among multiple RSIs **40**, or the like.

A fifth state is entered when the SBR device **48** corresponding to the wake-up receiver **46** actively transmits data. In this fifth state, the low power radio system **44** overall draws on the order of magnitude of hundreds to

thousands of milliamps of electrical current. In particular, the SBR device 48 of the RSI 40 actively transmits wireless communications to the gateway controller 20 or to one or more other RSIs 40. Thus, though the two-way wireless communication device 48 of the RSI 40 is active in both the fourth state and the fifth state, the two states being distinguished because actively transmitting signals generally draws substantially more electrical current than actively receiving signals.

The multiple SBR devices 48 are utilized in the RSI 40 to optimize detection and reception by the RSI 40 of radio signals from gateway controllers 20, hopping radios, and other wireless devices. The wake-up technology described herein may be used in a variety of ways to reduce power consumption in the multi-SBR environment while helping to ensure reliable two-way communications whenever possible. For example, the RSI controller 42 may be arranged to awaken each SBR device 48 whenever any of the corresponding wake-up receivers 46 determine that a signal intended for the RSI 40 has been received. Alternatively, each SBR device 48 may be controlled according to its own wake-up receiver 46, wherein each respective SBR device 48 remains in standby mode until its corresponding wake-up receiver 46 causes it to awaken. Still further alternatively, the entire wake-up sequence may be used when all SBR devices 48 are in standby mode and a wake-up signal is first received, but a portion of the wake-up sequence may be used when one SBR device 48 is already communicating with a gateway controller 20. Other variations will be apparent to the Ordinary Artisan.

FIGS. 5A-5G are schematic diagrams illustrating the operation of an RSI 40 in accordance with a first implementation of the present invention. FIG. 5A shows a single RSI 40, designated "RSI-A" and having two low power radio systems 44 designated "A1" and "A2," that may communicate with one or both of two gateway controllers 20, designated "GC-A" and "GC-B," but with which neither gateway controller 20 has yet established communication. In FIG. 5B, the gateway controllers 20 have transmitted wake-up signals to a class of RSIs 40 that includes RSI-A 40, but RSI-A 40

has only received (via low power radio system A1 44) the wake-up signal from GC-A 20 and in FIG. 5C, two-way communications have been established between RSI-A 40 (still via low power radio system A1 44) and GC-A 20. In FIG. 5D, RSI-A 40 has begun to move relative to the gateway controllers 20, and RSI-A's second low power radio system A2 44 has now received a wake-up signal from GC-B 20. By the time RSI-A 40 has reached the point shown in FIG. 5E, communication has been established with (i.e., transmissions are being received from) both GC-A 20 and GC-B 20. However, with RSI-A 40 still approximately equidistant from GC-A 20 and GC-B 20, communication with GC-A 20 is still as reliable as communication with GC-B 20 and thus there is no need to hand-off communications from low power radio system A1 44 (with GC-A 20) to low power radio system A2 44 (with GC-B 20). On the other hand, as RSI-A 40 reaches the point shown in FIG. 5F, communication with GC-A 20 has become less reliable than communication with GC-B 20, and thus the controller 42 of RSI-A 40 has triggered a soft handoff from low power radio system A1 44 to low power radio system A2 44. Because low power radio system A1 44 continues to receive a signal from GC-A 20, it remains active, receiving signals from GC-A 20, which are monitored by the RSI controller 42, but the low power radio system A2 44 does not transmit. Finally, by the time RSI-A 40 reaches the point shown in FIG. 5G, low power radio system A1 44 is no longer receiving any communications from GC-A 20.

FIGS. 6A-6E are schematic diagrams illustrating the operation of an RSI 40 in accordance with a second implementation of the present invention. In this implementation, an RSI link 140 is in constant communication with a gateway controller, designated "GC-A," as it moves around searching for RSIs 40. In FIG. 6A, low power radio system A2 44 is in communication with an RSI 40 designated "RSI-A." In FIG. 6B, low power radio system A1 44 has begun receiving communications from RSI-A, but because the communication channel previously established by low power radio system A2 44 is still as good, no handoff has occurred. In FIG. 6C, the communication channel

established by low power radio system A1 44 is as good as that maintained by low power radio system A2 44, but there is still no need to trigger a handoff. Finally, as the RSI link 140 moves farther past RSI-A 40, the communication channel established by low power radio system A1 44 is more reliable, and a soft handoff occurs to low power radio system A1 44, and by the time the RSI link 140 reaches the point shown in FIG. 6E, the original low power radio system A2 44 is no longer receiving communications at all.

FIGS. 7A-7G are schematic diagrams illustrating the operation of an RSI 40 in accordance with a third implementation of the present invention. FIG. 7A shows a single RSI link 140 that may communicate with an RSI 40, designated "RSI-A," using one or both of two low power radio systems 44 designated "A1" and "A2," but with neither of which has the RSI link 140 yet established communication. In FIG. 7B, the RSI link 140 has transmitted a wake-up signal to a class of RSIs 40 that includes RSI-A 40, but only low power radio system A1 44 of RSI-A 40 has received the wake-up signal and in FIG. 7C, two-way communications have been established between RSI-A 40, via low power radio system A1 44, and the RSI link 140. In FIG. 7D, the RSI link 140 has begun to move relative to RSI-A 40, and RSI-A's second low power radio system A2 44 has now received a wake-up signal from the RSI link 140. By the time the RSI link 140 has reached the point shown in FIG. 7E, communication has been established with (i.e., transmissions are being received by) both low power radio system A1 44 and low power radio system A2 44. However, with the RSI link 140 still approximately equidistant from low power radio system A1 44 and low power radio system A2 44, communication with low power radio system A1 44 is still as reliable as communication with low power radio system A2 44 and thus there is no need to hand-off communications from low power radio system A1 44 to low power radio system A2 44. On the other hand, as the RSI link 140 reaches the point shown in FIG. 7F, communication with low power radio system A1 44 has become less reliable than communication with low power radio system A2 44, and thus the controller 42 of the RSI link 140 has triggered a soft handoff from

low power radio system A1 **44** to low power radio system A2 **44**. Because low power radio system A1 **44** continues to receive a signal from the RSI link **140**, it remains active, receiving signals from the RSI link **140**, which are monitored by the RSI controller **42**, but the low power radio system A1 **44** does not transmit. Finally, by the time the RSI link **140** reaches the point shown in FIG. 7G, low power radio system A1 **44** is no longer receiving any communications from the RSI link **140**.

Antennas **54** can be oriented in directions that will best enable reception. For example, an antenna **54** oriented vertically upwards may optimally detect reflected signals and those from aircraft. Antennas **54** oriented vertically upwards and downwards may optimize receptions of signals in a building having multiple floors.

Multiple low power radio systems **44** may be used with directional antennas **54** that create a uniform coverage pattern around a circle, in a semi-circular arrangement, or in whatever arrangement is appropriate for a particular application. Moreover, the directional antennas **54** for the on-board SBR devices **48** preferably have overlapping RF patterns so that smooth hopping transitions among the devices is possible without signal dropping. The overlapping of the RF patterns of the antennas **54** avoids directional dead zones in the overall communications capability of the RSI **40** and minimizes signal dropping. For example, three SBR devices **48** having respective antennas **54** each with 180 degree RF patterns can be oriented such that the centers of the patterns are mutually separated by 120 degrees. Thus, each antenna RF pattern overlaps with a neighboring RF pattern by 60 degrees at each extreme of its 180 degree breadth.

Other configurations could be used driving the gain choices. A trade-off will occur between the number of radios and the high gain that will improve the range of the radio. A minimum of two radios are needed in the constellation to perform the soft handoff.

In another implementation, the TTO (Tag Turn-On) signal can be periodically sent to simplify switching between standards based radios that do not support simple listening modes. The RF transmission can also be controlled with RF switches in order to reduce the complexity required by the software in the controller.

In yet another implementation of the present invention (not illustrated), a gateway controller **20** may be equipped with the hand off technology described and illustrated herein, wherein the gateway controller **20** includes a controller **42**, a wake-up receiver (which may be a wake-up receiver **46** as described hereinabove) for receiving wake-up signals from another gateway controller **20** and/or other wireless base station devices, and a plurality of two-way wireless communication devices **48**, each including a high gain directional antenna **54**, for two-way communications. Each two-way wireless communication device **48** is preferably an SBR such as, for example, a Bluetooth radio, a WiFi radio, a Zigbee radio, an Ultra-Wideband (UWB) radio, or a WiMAX radio, but which in any case is generally selected to match the two-way wireless communication devices **48** used in RSIs **40**. Such a gateway controller **20** may be particularly well adapted for communicating with nearby RSIs **40** or RSI links **140** that are moving while the gateway controller remains stationary. More particularly, as the respective RSI **40** or RSI link **140** moves past or around the gateway controller **20**, the controller **42** controls the SBR devices **48** such that all SBR devices **48** receiving a signal from the RSI **40** or RSI link **140** are activated to listen to such signal, but the controller **42** chooses when the SBR device **48** transmits to the RSI **40** or RSI link **140**. Soft handoff technology may be utilized to switch transmission capability from one SBR device **48** to another based on which SBR device **48** is likely to have the most reliable communication channel.

There are many benefits provided by one or more embodiments of the invention. Improved sensitivity and diversity provide robust communications. Gain makes communications more directional, thereby improving reception and minimizing the potential for interception. The wake-up receiver **46**

minimizes power consumption. Since standards based radios are point to point, two-way communications can be accomplished.

Based on the foregoing information, it is readily understood by those persons skilled in the art that the present invention is susceptible of broad utility and application. Many embodiments and adaptations of the present invention other than those specifically described herein, as well as many variations, modifications, and equivalent arrangements, will be apparent from or reasonably suggested by the present invention and the foregoing descriptions thereof, without departing from the substance or scope of the present invention. Accordingly, while the present invention has been described herein in detail in relation to its preferred embodiment, it is to be understood that this disclosure is only illustrative and exemplary of the present invention and is made merely for the purpose of providing a full and enabling disclosure of the invention. The foregoing disclosure is not intended to be construed to limit the present invention or otherwise exclude any such other embodiments, adaptations, variations, modifications or equivalent arrangements; the present invention being limited only by the claims appended hereto and the equivalents thereof. Although specific terms are employed herein, they are used in a generic and descriptive sense only and not for the purpose of limitation.

CLAIMS

What is claimed is:

1. A method of facilitating a soft hand-off in wireless communications, comprising:
 - (a) providing a first wireless component and a second wireless component, the second wireless component including a controller and first and second low power radio systems;
 - (b) receiving, at a wake-up receiver of the first low power radio system in the second wireless component, a first wake-up signal;
 - (c) in response to receiving the first wake-up signal, sending a first electronic signal to the controller;
 - (d) in response to receiving the first electronic signal at the controller, activating a two-way wireless communication device of the first low power radio system, thereby facilitating two-way wireless communication with the first wireless component;
 - (e) receiving, at a wake-up receiver of the second low power radio system in the second wireless component, a second wake-up signal;
 - (f) in response to receiving the second wake-up signal, sending a second electronic signal to the controller;
 - (g) in response to receiving the second electronic signal at the controller, activating a two-way wireless communication device of the second low power radio system and deactivating the two-way wireless communication device of the first low power radio system, thereby facilitating two-way wireless communication with the first wireless component.
2. The method of Claim 1, wherein the step of sending the first electronic signal to the controller is conditioned on the first wake-up signal including a class designation corresponding to the second wireless component.

3. The method of Claim2, wherein each two-way wireless communication device is a standards based radio.
4. The method of Claim3, wherein each standards based radio is a Bluetooth radio.
5. The method of Claim2, wherein the step of providing a second wireless component includes providing a second wireless component having a first directional antenna connected to the first low power radio system and a second directional antenna connected to the second low power radio system.
6. A remote sensor interface, comprising:
 - (a) a sensor input adapted to receive data from a sensor device;
 - (b) a plurality of low power radio systems, each including:
 - (i) a two-way wireless communication device, and
 - (ii) a wake-up receiver; and
 - (c) a controller, connected to each wake-up receiver to receive signals therefrom and further connected to each two-way wireless communications device to effect two-way communication therethrough, wherein the controller is adapted to select one of the plurality of two-way wireless communication devices for external two-way wireless communications, the selection being made on the basis of an electronic signal received from at least one of the plurality of wake-up receivers;
 - (d) wherein the controller is adapted to wirelessly transmit data, received from the sensor device connected to the sensor input, via the selected two-way wireless communications device.
7. The remote sensor interface of Claim 6, wherein the wake-up receiver is adapted to transmit the electronic signal only upon receiving a wake-up signal that includes a class designation corresponding to the remote sensor interface.

8. The remote sensor interface of Claim 7, wherein the two-way wireless communication device is a standards based radio.
9. The remote sensor interface of Claim 8, wherein the standards based radio is a Bluetooth radio.
10. The remote sensor interface of Claim 7, wherein each low power radio system further includes a directional antenna, the directional antennas being arranged in an array to provide disparate, overlapping coverage zones.
11. A remote sensor interface link, comprising:
 - (a) a plurality of low power radio systems, each including:
 - (i) a two-way wireless communication device, and
 - (ii) a wake-up receiver; and
 - (b) a controller, connected to each wake-up receiver to receive signals therefrom and further connected to each two-way wireless communications device to effect two-way communication therethrough, wherein the controller is adapted to select one of the plurality of two-way wireless communication devices for external two-way wireless communications, the selection being made on the basis of an electronic signal received from at least one of the plurality of wake-up receivers;
 - (c) wherein the controller is adapted to wirelessly transmit sensor data, received from a remote sensor interface, via the selected two-way wireless communications device.
12. The remote sensor interface of Claim 11, wherein the wake-up receiver is adapted to transmit the electronic signal only upon receiving a wake-up signal that includes a class designation corresponding to the remote sensor interface.
13. The remote sensor interface of Claim 12, wherein the two-way wireless communication device is a standards based radio.

14. The remote sensor interface of Claim 13, wherein the standards based radio is a Bluetooth radio.
15. The remote sensor interface of Claim 12, wherein each low power radio system further includes a directional antenna, the directional antennas being arranged in an array to provide disparate, overlapping coverage zones.
16. A wireless communication system, comprising:
 - (a) a first wireless communication component;
 - (b) a sensor device; and
 - (c) a second wireless communication component, adapted to receive sensor data from at least one sensor device, including:
 - (i) a plurality of low power radio systems, each having a two-way wireless communication device and a wake-up receiver, and
 - (ii) a controller, connected to each wake-up receiver to receive signals therefrom and further connected to each two-way wireless communications device to effect two-way communication therethrough, wherein the controller is adapted to select one of the plurality of two-way wireless communication devices for two-way wireless communications with the first wireless communication component, the selection being made on the basis of an electronic signal received from at least one of the plurality of wake-up receivers,
 - (iii) wherein the controller is adapted to wirelessly transmit sensor data, received from the sensor device, to the first wireless communication component via the selected two-way wireless communications device.
17. The remote sensor interface of Claim 16, wherein the wake-up receiver is adapted to transmit the electronic signal only upon receiving a wake-up signal that includes a class designation corresponding to the remote sensor interface.

18. The wireless communication system of Claim 17, wherein the first wireless communication component is a gateway controller.
19. The wireless communication system of Claim 18, wherein the second wireless communication component is a remote sensor interface, and the sensor device communicates directly with the remote sensor interface.
20. The wireless communication system of Claim 19, wherein the second wireless communication component is a remote sensor interface link, the wireless communication system further comprising a third wireless communication component, wherein the sensor device communicates indirectly with the remote sensor interface link via the third wireless communication component.
21. The wireless communication system of Claim 20, wherein the third wireless communication component is a remote sensor interface, and wherein the sensor device communicates directly with the remote sensor interface.
22. The wireless communication system of Claim 17, wherein the first wireless communication component is a remote sensor interface link.
23. The wireless communication system of Claim 22, wherein the second wireless communication component is a remote sensor interface, and the sensor device communicates indirectly with the remote sensor interface link via the remote sensor interface.
24. The wireless communication system of Claim 17, wherein the two-way wireless communication device is a standards based radio.
25. The wireless communication system of Claim 24, wherein the standards based radio is a Bluetooth radio.
26. The wireless communication system of Claim 17, wherein each low power radio system further includes a directional antenna, the directional antennas being arranged in an array to provide disparate, overlapping coverage zones.

1/24


10

FIG. 1




FIG. 2




FIG. 3A




FIG. 3B

5/24




FIG. 4

6/24






FIG. 5A

7/24




FIG. 5B

8/24




FIG. 5C

9/24




FIG. 5D

10/24




FIG. 5E

11/24




FIG. 5F

12/24




FIG. 5G




FIG. 6A




FIG. 6B




FIG. 6C




FIG. 6D

17/24




FIG. 6E

18/24




FIG. 7A




FIG. 7B




FIG. 7C




FIG. 7D




FIG. 7E




FIG. 7F




FIG. 7G

INTERNATIONAL SEARCH REPORT

International application No.
PCT/US2006/021859

A. CLASSIFICATION OF SUBJECT MATTER

H04B 7/26(2006.01)i

According to International Patent Classification (IPC) or to both national classification and IPC

B. FIELDS SEARCHED

Minimum documentation searched (classification system followed by classification symbols)

IPC8 H04B 7/26, 5/00, G08C 19/00, G08B 13/14, G06K 19/00

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched
KOREAN PATENTS AND APPLICATIONS FOR INVENTIONS SINCE 1975
KOREAN UTILITY MODELS AND APPLICATIONS FOR UTILITY MODELS SINCE 1975

Electronic data base consulted during the international search (name of data base and, where practicable, search terms used)
eKIPASS, DELPHION, ESPACENET & Keywords : wireless, Tag, sensor, RFID, RSI, LPRF, wake-up and similar terms.

C. DOCUMENTS CONSIDERED TO BE RELEVANT

Category*	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
X	US 6,617,962 B1 (Horwitz et al.) 9 September 2003	1-15
Y	* abstract, Col. 5 line 30 - Col. 7 line 6, figure 1 *	16-26
Y	US 6,127,928 (Issacman et al.) 3 October 2000	16-26
A	* abstract, Col. 8 line 50 - Col. 9 line 18, figure 4 *	1-15
A	EP 1,209,615 A2 (ADVANCED MICROWAVE ENGINEERING) 29 May 2002	1-26
	* abstract, paragraphs [0018]-[0042], figure 1 *	
A	WO2004-15625 A1 (BNC IP SWITZERLAND GMBH et al.) 19 February 2004	1-26
	* abstract, Page 8 line 14 - Page 9 line 6, figure 4 *	
A	US2004-203352 A1 (Hall et al.) 14 October 2004	1-26
	* abstract, paragraphs [0028]-[0033], figure 4 *	



Further documents are listed in the continuation of Box C.



See patent family annex.

* Special categories of cited documents:
"A" document defining the general state of the art which is not considered to be of particular relevance
"E" earlier application or patent but published on or after the international filing date
"L" document which may throw doubts on priority claim(s) or which is cited to establish the publication date of citation or other special reason (as specified)
"O" document referring to an oral disclosure, use, exhibition or other means
"P" document published prior to the international filing date but later than the priority date claimed

"T" later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention
"X" document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone
"Y" document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art
"&" document member of the same patent family

Date of the actual completion of the international search

29 SEPTEMBER 2006 (29.09.2006)

Date of mailing of the international search report

29 SEPTEMBER 2006 (29.09.2006)

Name and mailing address of the ISA/KR



Korean Intellectual Property Office
920 Dunsan-dong, Seo-gu, Daejeon 302-701,
Republic of Korea

Facsimile No. 82-42-472-7140

Authorized officer

KIM, Sang Woo

Telephone No. 82-42-481-8324



INTERNATIONAL SEARCH REPORT

International application No.

PCT/US2006/021859

Patent document cited in search report	Publication date	Patent family member(s)	Publication date
US 6,617,962 B1	09.09.2003	AT321309E	15.04.2006
		AU200126595A1	16.07.2001
		CA2395847A1	12.07.2001
		DE60118153C0	11.05.2006
		EP01244997A1	02.10.2002
		EP01244997B1	22.03.2006
		US2004085191A1	06.05.2004
		US2005083180A1	21.04.2005
		W0200150407A1	12.07.2001
US 6,127,928	03.10.2000	NONE	
EP 1,209,615 A2	29.05.2002	EP01209615A3	23.07.2003
W02004-15625 A1	19.02.2004	AU2003253210A1	25.02.2004
		CA2494175A1	19.02.2004
		MXPA05001550A	05.10.2005
		US2004089707A1	13.05.2004
		US7091860BB	15.08.2006
US2004-203352 A1	14.10.2004	NONE	