



(51) International Patent Classification:

H04N 5/225 (2006.01) H04N 5/235 (2006.01)

H04N 5/232 (2006.01)

(21) International Application Number:

PCT/CN2018/085359

(22) International Filing Date:

02 May 2018 (02.05.2018)

(25) Filing Language:

English

(26) Publication Language:

English

(30) Priority Data:

201710305278.3 03 May 2017 (03.05.2017) CN

(71) Applicant: GUANGDONG OPPO MOBILE TELECOMMUNICATIONS CORP., LTD. [CN/CN];

No. 18, Haibin Road, Wusha, Chang'an, Dongguan, Guangdong 523860 (CN).

(72) Inventors: ZHOU, Yibao; No. 18, Haibin Road, Wusha, Chang'an, Dongguan, Guangdong 523860 (CN). CHENG, Jiao; No. 18, Haibin Road, Wusha, Chang'an, Dongguan, Guangdong 523860 (CN). ZHANG, Haiping; No. 18,

Haibin Road, Wusha, Chang'an, Dongguan, Guangdong 523860 (CN).

(74) Agent: TSINGYIHUA INTELLECTUAL PROPERTY

LLC; Room 301 Trade Building, Zhaolanyuan, Tsinghua University, Qinghuayuan, Haidian District, Beijing 100084 (CN).

(81) Designated States (unless otherwise indicated, for every

kind of national protection available): AE, AG, AL, AM, AO, AT, AU, AZ, BA, BB, BG, BH, BN, BR, BW, BY, BZ, CA, CH, CL, CN, CO, CR, CU, CZ, DE, DJ, DK, DM, DO, DZ, EC, EE, EG, ES, FI, GB, GD, GE, GH, GM, GT, HN, HR, HU, ID, IL, IN, IR, IS, JO, JP, KE, KG, KH, KN, KP, KR, KW, KZ, LA, LC, LK, LR, LS, LU, LY, MA, MD, ME, MG, MK, MN, MW, MX, MY, MZ, NA, NG, NI, NO, NZ, OM, PA, PE, PG, PH, PL, PT, QA, RO, RS, RU, RW, SA, SC, SD, SE, SG, SK, SL, SM, ST, SV, SY, TH, TJ, TM, TN, TR, TT, TZ, UA, UG, US, UZ, VC, VN, ZA, ZM, ZW.

(84) Designated States (unless otherwise indicated, for every

kind of regional protection available): ARIPO (BW, GH, GM, KE, LR, LS, MW, MZ, NA, RW, SD, SL, ST, SZ, TZ, UG, ZM, ZW), Eurasian (AM, AZ, BY, KG, KZ, RU, TJ,

(54) Title: CAMERA ASSEMBLY AND MOBILE ELECTRONIC DEVICE




Fig. 1

(57) Abstract: A camera assembly (100) and a mobile electronic device (1000) are provided. The camera assembly (100) includes at least two image sensors (12). Each image sensor (12) includes a pixel array (122) and a control circuit (124). The pixel array (122) includes a light sensing region (1222) and an imaging region (1224). The control circuit (124) is configured to receive a light sensing instruction to control the light sensing region (1222) to detect an illumination intensity and to receive an imaging instruction to control the light sensing region (1222) and the imaging region (1224) to collectively perform a photographic process to obtain an image. The present disclosure further provides a mobile electronic device (1000).

TM), European (AL, AT, BE, BG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, HR, HU, IE, IS, IT, LT, LU, LV, MC, MK, MT, NL, NO, PL, PT, RO, RS, SE, SI, SK, SM, TR), OAPI (BF, BJ, CF, CG, CI, CM, GA, GN, GQ, GW, KM, ML, MR, NE, SN, TD, TG).

Published:

— *with international search report (Art. 21(3))*

CAMERA ASSEMBLY AND MOBILE ELECTRONIC DEVICE

CROSS-REFERENCE TO RELATED APPLICATIONS

This application is based on and claims priority of Chinese Patent Application No. 201710305278.3, filed on May 3, 2017, the entire contents of which are incorporated herein by reference.

FIELD

The present disclosure relates to electronic devices, and more particularly to a camera assembly, and a mobile electronic device.

BACKGROUND

Typically, a front camera configured to capture a selfie and a light sensor configured to detect ambient brightness and adjust brightness of a display screen according to the ambient brightness can be set on a phone. However, since the front camera and the light sensor are separately set in the most of phones at present, the space for locating the display screen in the phone decreases, thus leading to a low screen-to-body ratio of the phone.

DISCLOSURE

Embodiments of the present disclosure provide a camera assembly. The camera assembly includes at least two image sensors. Each image sensor includes a pixel array and a control circuit. The pixel array includes a light sensing region and an imaging region. The control circuit is configured to receive a light sensing instruction to control the light sensing region to detect an illumination intensity; and to receive an imaging instruction to control the light sensing region and the imaging region to collectively perform a photographic process to acquire an image.

In an embodiment, the control circuit is further configured to: receive the imaging instruction to control the light sensing region to detect a color temperature of a current environment; and control the imaging region to perform the photographic process according to the color temperature to acquire a color-temperature adjusted image.

In an embodiment, the control circuit is further configured to receive the imaging instruction to control the light sensing region and the imaging region to collectively perform the photographic process to acquire a merged image.

In an embodiment, the imaging region of each image sensor is contiguous and located in the middle of the pixel array, and the light sensing region of each image sensor is located around the imaging region.

In an embodiment, the light sensing region of each image sensor comprises at least two light sensing sub-regions having basically a same area and spaced from each other.

In an embodiment, the at least two light sensing sub-regions comprise a left light sensing

sub-region on the left of the imaging region and a right light sensing sub-region on the right of the imaging region. The left light sensing sub-region and the right light sensing sub-region are arranged symmetrically. The left light sensing sub-region is configured to detect a left illumination intensity. The right light sensing sub-region is configured to detect a right illumination intensity.

5 The illumination intensity detected by the light sensing region is a mean value of the left illumination intensity and the right illumination intensity.

In an embodiment, the at least two light sensing sub-regions comprise an upper light sensing sub-region above the imaging region and a lower light sensing sub-region below the imaging region. The upper light sensing sub-region and the lower light sensing sub-region are arranged symmetrically. The upper light sensing sub-region is configured to detect an upper illumination intensity. The lower light sensing sub-region is configured to detect a lower illumination intensity. The illumination intensity detected by the light sensing region is a mean value of the upper illumination intensity and the lower illumination intensity.

In an embodiment, the at least two light sensing sub-regions comprise a left light sensing sub-region on the left of the imaging region, a right light sensing sub-region on the right of the imaging region, an upper light sensing sub-region above the imaging region and a lower light sensing sub-region below the imaging region. The left light sensing sub-region and the right light sensing sub-region are arranged symmetrically. The upper light sensing sub-region and the lower light sensing sub-region are arranged symmetrically. The left light sensing sub-region is configured to detect a left illumination intensity. The right light sensing sub-region is configured to detect a right illumination intensity. The upper light sensing sub-region is configured to detect an upper illumination intensity. The lower light sensing sub-region is configured to detect a lower illumination intensity. The illumination intensity detected by the light sensing region is a mean value of the left illumination intensity, the right illumination intensity, the upper illumination intensity and the lower illumination intensity.

In an embodiment, the pixel array is in a shape of one of a circle and an ellipse, the imaging region is in a shape of an inscribed rectangle of the pixel array, and the light sensing region comprises a region other than the inscribed rectangle of the one of the circle and the ellipse.

In an embodiment, the pixel array is in a shape of a rectangle, the imaging region is in a shape of one of an inscribed circle and an inscribed ellipse of the pixel array, and the light sensing region comprises a region other than the one of the inscribed circle and the inscribed ellipse of the rectangle.

In an embodiment, the imaging region of each image sensor is contiguous and the light sensing region of each image sensor is contiguous; the imaging region and the light sensing region of each image sensor share a common boundary.

In an embodiment, the camera assembly comprises two image sensors, and two imaging regions of the two image sensors are located between two light sensing regions of the two image sensors.

In an embodiment, the pixel array of each image sensor is configured such that at least one of following conditions is satisfied: a ratio of an area of the imaging region of said image sensor to an area of the pixel array of said image sensor being greater than or equal to 0.6; and a ratio of an area of the light sensing region of said image sensor to the area of the pixel array of said image sensor being greater than or equal to 0.1.

The mobile electronic device according to embodiments of the present disclosure includes the camera assembly described above. The mobile electronic device further includes a processor. The processor is configured to generate the light sensing instruction and the imaging instruction.

In an embodiment, the mobile electronic device comprises one camera assembly configured as a front camera assembly. When light sensing regions of at least two image sensors of the camera assembly detect a first illumination intensity and a second illumination intensity respectively, the processor is configured to: determine a maximum of the first illumination intensity and the second illumination intensity as a final illumination intensity; or obtain a mean value of the first illumination intensity and the second illumination intensity as a final illumination intensity.

In an embodiment, the mobile electronic device comprises at least two camera assemblies, one of the at least two camera assemblies is configured as a front camera assembly and a further one of the at least two camera assemblies is configured as a rear camera assembly. When two light sensing regions of the front camera assembly detect a first illumination intensity and a second illumination intensity respectively, and two light sensing regions of the rear camera assembly detect a third illumination intensity and a fourth illumination intensity respectively, the processor is configured to: determine a maximum of the first illumination intensity, the second illumination intensity, the third illumination intensity and the fourth illumination intensity as a final illumination intensity; or obtain a mean value of the first illumination intensity and the second illumination intensity as a front illumination intensity, obtain a mean value of the third illumination intensity and the fourth illumination intensity as a rear illumination intensity, and determine a maximum of the front illumination intensity and the rear illumination intensity as a final illumination intensity; or determine a maximum of the first illumination intensity and the second illumination intensity as a front illumination intensity, obtain a mean value of the third illumination intensity and the fourth illumination intensity as a rear illumination intensity, and determine a maximum of the front illumination intensity and the rear illumination intensity as a final illumination intensity; or obtain a mean value of the first illumination intensity and the second illumination intensity as a front illumination intensity, determine a maximum of the third illumination intensity and the fourth illumination intensity as a rear illumination intensity, and determine a maximum of the front illumination intensity and the rear illumination intensity as a final illumination intensity.

In an embodiment, the mobile electronic device comprises at least two camera assemblies, one of the at least two camera assemblies is configured as a front camera assembly and a further one of the at least two camera assemblies is configured as a rear camera assembly. When a light

sensing region of the front camera assembly detects a first illumination intensity, and a light sensing region of the rear camera assembly detects a second illumination intensity, the processor is configured to: determine a maximum of the first illumination intensity and the second illumination intensity as a final illumination intensity.

5 In an embodiment, the mobile electronic device comprises at least two camera assemblies, one of the at least two camera assemblies is configured as a front camera assembly and a further one of the at least two camera assemblies is configured as a rear camera assembly. When two light sensing regions of the front camera assembly detect a first illumination intensity and a second illumination intensity respectively, and a light sensing region of the rear camera assembly detects a
10 third illumination intensity, the processor is configured to: determine a maximum of the first illumination intensity and the second illumination intensity as a front illumination intensity, and determine a maximum of the front illumination intensity and the third illumination intensity as a final illumination intensity; or obtain a mean value of the first illumination intensity and the second illumination intensity as a front illumination intensity, and determine a maximum of the
15 front illumination intensity and the third illumination intensity as a final illumination intensity.

In an embodiment, the mobile electronic device comprises at least two camera assemblies, one of the at least two camera assemblies is configured as a front camera assembly and a further one of the at least two camera assemblies is configured as a rear camera assembly. When a light sensing region of the front camera assembly detects a first illumination intensity, and two light
20 sensing regions of the rear camera assembly detect a second illumination intensity and a third illumination intensity respectively, the processor is configured to: determine a maximum of the second illumination intensity and the third illumination intensity as a rear illumination intensity, and determine a maximum of the rear illumination intensity and the first illumination intensity as a final illumination intensity; or obtain a mean value of the second illumination intensity and the
25 third illumination intensity as a rear illumination intensity, and determine a maximum of the rear illumination intensity and the first illumination intensity as a final illumination intensity.

In an embodiment, the mobile electronic device further comprises another camera assembly, wherein the another camera assembly comprises an image sensor. The image sensor comprises a pixel array and a control circuit. The pixel array comprises a light sensing region and an imaging
30 region. The control circuit is configured to: determine whether the another camera assembly is in an imaging mode; receive a light sensing instruction to control the light sensing region of the imaging sensor of the another camera assembly to detect an illumination intensity when the another camera assembly is not in the imaging mode; and receive an imaging instruction to control the light sensing region and the imaging region of the imaging sensor of the another camera
35 assembly to collectively perform a photographic process to acquire an image when the another camera assembly is in the imaging mode.

In an embodiment, the mobile electronic device comprises one camera assembly configured as one of a front camera assembly and a rear camera assembly, and the another camera assembly is

configured as the other one of the front camera assembly and the rear camera assembly.

In an embodiment, the image sensors in the camera assembly are configured such that, when one image sensor in the camera assembly is in an imaging mode, the other image sensor in the camera assembly is in a light sensing mode; an illumination intensity detected by the image sensor
5 in the light sensing mode is configured as the illumination intensity of the camera assembly.

Additional aspects and advantages of embodiments of present disclosure will be given in part in the following descriptions, become apparent in part from the following descriptions, or be learned from the practice of the embodiments of the present disclosure.

10 BRIEF DESCRIPTION OF THE DRAWINGS

These and other aspects and advantages of embodiments of the present disclosure will become apparent and more readily appreciated from the following descriptions made with reference to the drawings.

Fig. 1 is a schematic diagram of a camera assembly according to an embodiment of the
15 present disclosure.

Fig. 2 is a schematic stereogram of an electronic device according to an embodiment of the present disclosure.

Fig. 3 is a front view and a back view of an electronic device according to an embodiment of the present disclosure.

20 Fig. 4 is a schematic diagram of a different camera assembly according to an embodiment of the present disclosure.

Fig. 5 is a front view and a back view of an electronic device according to an embodiment of the present disclosure.

25 Fig. 6 is a front view and a back view of an electronic device according to an embodiment of the present disclosure.

Figs. 7-15 are schematic diagrams of a pixel array according to an embodiment of the present disclosure.

EMBODIMENTS OF THE PRESENT DISCLOSURE

30 Reference will now be made in detail to exemplary embodiments, examples of which are illustrated in the accompanying drawings, in which the same or similar reference numbers throughout the drawings represent the same or similar elements or elements having same or similar functions. Embodiments described below with reference to drawings are merely exemplary and used for explaining the present disclosure, and should not be understood as limitation to the
35 present disclosure.

In the present disclosure, unless specified or limited otherwise, a structure in which a first feature is “on” a second feature may include an embodiment in which the first feature directly contacts the second feature, and may also include an embodiment in which the first feature

indirectly contacts the second feature via an intermediate medium. Moreover, a structure in which a first feature is “on”, “over” or “above” a second feature may indicate that the first feature is right above the second feature or obliquely above the second feature, or just indicate that a horizontal level of the first feature is higher than the second feature. A structure in which a first feature is “below”, or “under” a second feature may indicate that the first feature is right under the second feature or obliquely under the second feature, or just indicate that a horizontal level of the first feature is lower than the second feature.

Referring to Fig. 1 and Fig. 2, the camera assembly 100 according to embodiments of the present disclosure includes two lens assemblies 10. Each assembly 10 includes an image sensor 12. Each image sensor 12 includes a pixel array 122 and a control circuit 124. The pixel array 122 includes a light sensing region 1222 and an imaging region 1224. The control circuit 124 is configured to receive a light sensing instruction to control the light sensing region 1222 to detect an illumination intensity. The control circuit 124 is further configured to receive an imaging instruction to control the light sensing region 1222 and the imaging region 1224 to collectively perform a photographic process to acquire an image.

In some implementations, the lens assembly 10 further includes a filter 14. The filter 14 and the pixel array 122 are arranged correspondingly. Light L would reach the light sensing region 1222 and the imaging region 1224 in the pixel array 122 after passing through the filter 14.

In some implementations, the filter 14 may be an RGB filter. The RGB filter can be arranged in Bayer array to allow light L to pass through the filter 14 and pass through the light sensing region 1222 and the imaging region 1224, so as to acquire a color image.

Further, in some implementations, the filter 14 may be a visible filter. The visible filter and the pixel array 122 are arranged correspondingly to allow light L to pass through the filter 14 and to reach the light sensing region 1222 and the imaging region 1224 in the pixel array 122. In this way, after the light L passes through the visible filter, only visible light of the light L can reach the light sensing region 1222 and the imaging region 1224 while light with other wavelengths is blocked, such that the light sensing region 1222 can be configured to detect the illumination intensity of the visible light and the light sensing region 1222 and the imaging region 1224 can be configured to acquire the image, thus avoiding interference of invisible light such as infrared light, ultraviolet light or the like in the light, and improving accuracy of light detection and quality of the image.

The camera assembly 100 according to embodiments of the present disclosure can be applied in an electronic device 1000 according to embodiments of the present disclosure. The electronic device 1000 further includes a processor 200. The processor 200 is configured to generate the light sensing instruction and the imaging instruction. In some implementations, the electronic device 1000 further includes a display screen 300. The display screen 300 is configured to display data information such as video, image, text, icon and the like.

In the camera assembly 100 and the electronic device 1000 mentioned above, the light

sensing region 1222 and the imaging region 1224 are integrally disposed in one pixel array 122. In this way, it is unnecessary to set both a camera component and a light sensor component, such that the number of components is reduced, a ratio of space for locating the display screen 300 can be increased, thus increasing the screen-to-body ratio of the electronic device 1000. The light sensing region 1222 may further assists the imaging region 1224 in imaging, such that the imaging effect can be optimized. Further, the camera assembly 100 according to embodiments of the present disclosure includes two lens assemblies 10. The light sensing regions 1222 in the two lens assemblies 10 can detect the illumination intensity of the current environment simultaneously, such that the accuracy of detecting the illumination intensity can be improved. The two lens assemblies 10 can realize imaging simultaneously or on time-sharing, thus optimizing the imaging effect.

The electronic device 1000 may be a cell phone, a tablet computer, a notebook computer or the like, which is not limited herein. The electronic device 1000 according to embodiments of the present will be explained by taking a cell phone as an example. The illumination intensity obtained by the image sensor 12 or the camera assembly 100 can be considered as the basis for adjusting display brightness of the display screen 300 of the electronic device 1000. For example, when the illumination intensity is high, the display brightness of the display screen 300 can be increased. When the illumination intensity is changed from a high value to a value less than a certain threshold, it can be determined that a user is answering the phone, such that the display screen 300 can be turned off. The image acquired by the image sensor 12 or the camera assembly 10 can be displayed on the display screen 300, or stored in storage medium of the electronic device 1000 for reading or transmitting.

The camera assembly 100 together with the display screen 300 can be set on a front face 400 of the electronic device 1000. The camera assembly 100 can also be disposed on a back face 500 or side face of the electronic device 1000. The two lens assemblies 10 of the camera assembly 100 can be arranged laterally or longitudinally.

The processor 200 is configured to generate the light sensing instruction and the imaging instruction. Further, the processor 200 is configured to transmit the light sensing instruction and the imaging instruction to the control circuit 124 corresponding to the lens assembly 10. In some embodiments, the processor 200 can separately generate and transmit the light sensing instruction, or separately generate and transmit the imaging instruction. The light sensing instruction and the imaging instruction can be generated by the processor 200 when receiving an input operation. The input operation can be an operation inputted by the user or by an application environment. For example, in the cell phone according to embodiments of the present disclosure, the light sensing instruction and the imaging instruction can be generated by the processor 200 after receiving an operation of touching the cell phone or pressing a certain function key (including a physical key, a virtual key) from the user. In some embodiments, the light sensing instruction and the imaging instruction can be generated by the processor 200 when the system time of the cell phone reaches a predetermined time point.

A single control circuit 124 can be configured to separately receive the light sensing instruction to control the light sensing region 1222 to detect the illumination intensity, or separately receive the imaging instruction to control the light sensing region 1222 and the imaging region 1224 to collectively acquire the image. When the control circuit 124 does not receive the light sensing instruction or the imaging instruction, the light sensing region 1222 and the imaging region 1224 may be in the non-operating state.

The two control circuits 124 may receive the light sensing instruction and the imaging instruction separately. The camera assembly 100 may generate two light sensing instructions and two imaging instructions, which may be a first light sensing instruction, a second light sensing instruction, a first imaging instruction and a second imaging instruction. The first light sensing instruction may be sent only to a first control circuit 124, but not to a second control circuit 124. The second light sensing instruction may be sent only to the second control circuit 124, but not to the first control circuit 124. Similarly, the first imaging instruction may be sent only to the first control circuit 124, but not to the second control circuit 124. The second imaging instruction may be sent only to the second control circuit 124, but not to the first control circuit 124. The two control circuits 124 may receive the light sensing instruction and the imaging instruction simultaneously. For example, the camera assembly 100 may generate a light sensing instruction or an imaging instruction. The light sensing instruction is sent to the first control circuit 124 and the second control circuit 124 simultaneously. In other words, one light sensing instruction may be used to control two light sensing regions 1222 to detect the illumination intensity. Similarly, the imaging instruction is sent to the first control circuit 124 and the second control circuit 124 simultaneously. In other words, one imaging instruction may be used to control two light sensing regions 1222 and two imaging regions 1224 to acquire images.

In some embodiments, the pixel array 122 includes a plurality of pixels arranged in an array 122. The pixels in the imaging region 1224 are configured to acquire the image. The pixels in the light sensing region 1222 are configured to detect the illumination intensity or acquire the image together with the imaging region 1224. Each pixel in the pixel array 122 can generate corresponding electric quantity change according to the illumination intensity of light L reaching the pixel. The control circuit 124 is electrically connected to each pixel. The control circuit 124 acquires the electric quantity change generated by the corresponding pixel according to the received light sensing instruction or imaging instruction, and further analyzes the changing value of the electric quantity via the processor 200 to obtain the illumination intensity of the light reaching the corresponding pixel or further performs comprehensive analysis on the illumination intensities of light reaching several pixels via the processor 200 to acquire the image.

In some implementations, the control circuit 124 is further configured to receive the light sensing instruction to control the light sensing region 1222 to perform a photographic process to detect a color temperature of a current environment when the image sensor is in an imaging mode; and to control the imaging region 1224 to perform the photographic process according to the color

temperature to acquire a color-temperature adjusted image.

In some embodiments, both the light sensing region 1222 and the imaging region 1224 in each image sensor 12 have a filter 14 disposed thereabove. In embodiments of the present disclosure, the filter is explained by taking the RGB color filter 14 as an example. When the control circuit 124 receives an imaging instruction, the control circuit 124 controls the light sensing region 1222 to perform the photographic process. Light in the current environment passes through the RGB filter 14 above the light sensing region 1222 and reaches each pixel of the light sensing region 1222. The light sensor component corresponding to each pixel in the light sensing region 1222 may generate the electric quantity change to obtain a red pixel value, a blue pixel value or a green pixel value corresponding to each pixel. The processor 200 detects the color temperature of the current environment by analyzing the red pixel value, the blue pixel value and the green pixel value. The color temperature of the current environment reflects a gain value of each color (R, G, B) in light of the current environment. Subsequently, the control circuit 124 controls each pixel in the imaging region 1224 to perform the photographic process and realize imaging to obtain a plurality of pixel values. The processor 200 adjusts the gain values of each color R, G or B of each pixel in the imaging region 1224 according to the color temperature, and performs an interpolation processing and a de-mosaic processing, such that the color-temperature adjusted image obtained finally has color approaching to actual color of each object in the current environment. In this way, color cast of the acquired image can be avoided. When the electronic device 1000 is used to take a picture at night, it is required to supplement light due to a dim light in night scene. However, light emitted by a related supplementary light source typically influences the color temperature in the current environment, such that it is required to realize auxiliary imaging based on the color temperature detected by the light sensing region 1222 to optimize the imaging effect.

In some implementations, the control circuit 1224 is further configured to receive an imaging instruction to control the light sensing region 1222 and the imaging region 1224 to collectively perform the photographic process to acquire a merged image.

In some embodiments, both the light sensing region 1222 and the imaging region 1224 in each image sensor 12 have a filter 14 disposed thereabove. In embodiments of the present disclosure, the filter is explained by taking the RGB color filter 14 as an example. When the electronic device 1000 is in the imaging mode, the light L in the current environment passes through the RGB filter 14 above the light sensing region 1222 and the imaging region 1224 and reaches each pixel in the light sensing region 1222 and the imaging region 1224. Each pixel in the light sensing region 1222 and the imaging region 1224 can obtain a red pixel value, a blue pixel value or a green pixel value. Subsequently, an interpolation and de-mosaic processing is performed on each pixel value to acquire the merged image. The merged image indicates an image obtained when the light sensing region 1222 and the imaging region 1224 collectively realize imaging. To this, when the number of pixels in the light sensing region 1222 is increased to realize imaging, an

area of the finally acquired image can be increased, thus optimizing the imaging quality.

Referring Fig. 2 again, in some implementations, there is a single camera assembly 100. The single camera assembly 100 is configured as a front camera assembly 100a. When light sensing sensors 1222 of two imaging sensors 12 detect a first illumination intensity and a second illumination intensity respectively, the processor 200 is configured to select a maximum of the first illumination intensity and the second illumination intensity as a final illumination intensity; or the processor 200 is configured to obtain a mean value of the first illumination intensity and the second illumination intensity as the final illumination intensity.

The front camera assembly 100a and the display screen 300 are disposed on the front face 400 of the electronic device 1000. The front camera assembly 100a may be configured to detect the illumination intensity on the front face 400 and acquire the image opposite to the front face 400 simultaneously.

In this way, the processor 200 can obtain the final illumination intensity after perform the comprehensive analysis on the first illumination intensity and the second illumination intensity respectively obtained by two light sensing regions 1222. The electronic device 1000 further performs corresponding control according to the final illumination intensity, for example adjusting the display brightness of the display screen 300. In some implementations, during the usage, there may be a situation that two lens assemblies 10 receive very different illumination intensities. For example, when the user operates the electronic device 1000 under the shade of a tree, one lens assembly 10 may be in the shade while the other lens assembly 10 may be exposed under direct sunlight, such that there may be large difference between the first illumination intensity and the second illumination intensity detected by two light sensing regions 1222. The processor 200 processes the first illumination intensity and the second illumination intensity to obtain the final illumination intensity and adjusts the display brightness of the display screen 300 according to the final illumination intensity, thus preventing the display brightness from being too high or too low.

Further, the two lens assemblies 10 in the front camera assembly may realize imaging simultaneously or on time-sharing.

Referring to table 1, each light sensing region 1222 in the front camera assembly 100a has three operating modes, which are light sensing mode, imaging mode, and idle mode. Each imaging region 1224 has two operating modes, which are imaging mode and idle mode. Thus, the operating mode of the front camera assembly 100a may be one of nine situations in the table 1.

The light sensing mode means that the light sensing region 1222 detects the illumination intensity. The imaging mode means that the light sensing region 1222 and the imaging region 1224 collectively perform the photographic process to acquire the image. The idle mode of the light sensing region 1222 means that the light sensing region 1222 is not in the light sensing mode or in the imaging mode. The idle mode of the imaging region 1224 means that the imaging region 1224 is not in the imaging mode. Further, when the imaging region 1224 is in the imaging mode, the light sensing region 1222 is in the imaging mode too.

operating mode component No.	Front camera assembly			
	Image sensor 1		Image sensor 2	
	Light sensing region 1	Imaging region 1	Light sensing region 2	Imaging region 2
1	Light sensing mode	idle mode	Light sensing mode	idle mode
2	Light sensing mode	idle mode	idle mode	idle mode
3	idle mode	idle mode	Light sensing mode	idle mode
4	Light sensing mode	idle mode	Imaging mode	Imaging mode
5	idle mode	idle mode	Imaging mode	Imaging mode
6	Imaging mode	Imaging mode	Light sensing mode	idle mode
7	Imaging mode	Imaging mode	idle mode	idle mode
8	Imaging mode	Imaging mode	Imaging mode	Imaging mode
9	idle mode	idle mode	idle mode	idle mode

Table 1

In some operation modes in table 1, the two lens assemblies 10 in the front camera assembly 100a can realize imaging simultaneously to optimize the imaging quality. For example, the two lens assemblies 10 in the front camera assembly 100a can realize imaging simultaneously to obtain multiple frames of first images and multiple frames of second images. The processor 200 may analyze the multiple frames of first images and the multiple frames of second images and screens out a frame of image with highest imaging quality as a final image. In another embodiment, the processor 200 may perform merging and splicing processing on the first image and the second image to enhance color and definition of the final image.

In some operation modes in table 1, one lens assembly 10 in the front camera assembly 100a may be configured to assist the other lens assembly 10 in imaging, so as to optimize the imaging quality. For example, the one lens assembly 10 in the front camera assembly 100a may detect the current ambient brightness, and the processor 200 analyzes the ambient brightness to control exposure time of each light sensor component corresponding to each pixel in the lens assembly 10 to obtain the image with suitable brightness. In this way, during the imaging of the camera assembly 100, one lens assembly 10 is used to detect the ambient brightness to assist the other lens assembly 10 in imaging, such that problems that the final image is subject to overexposure or has too low brightness can be avoided, thus improving the image quality.

Further, the front camera assembly 10 can be configured that, when one lens assembly 10 in the front camera assembly 100a is in the imaging mode, the other lens assembly 10 is in the light sensing mode. The lens assembly being in the imaging mode refers to the image sensor of the lens assembly being in the imaging mode, which means that both the imaging region and the light sensing region in the image sensor are in the imaging mode. The lens assembly being in the light

sensing mode refers to the image sensor of the lens assembly being in the light sensing mode, which means that the light sensing region in the image sensor is in the light sensing mode. The light sensing region 1222 of the lens assembly 10 in the light sensing mode detects the illumination intensity as the illumination intensity of the camera assembly 100. In this way, when one lens assembly 10 in the front camera assembly 100a realizes imaging, the other lens assembly may detect the illumination intensity of the environment to control the brightness of the display screen 300 to change, thus facilitating a preview when the user takes a picture, and improving the user experience.

In some operation modes in table 1, the two lens assemblies 10 in the front camera assembly 100a may be enabled in sequence to realize imaging so as to optimize the imaging quality. For example, one lens assembly 10 in the front camera assembly 100a adopts a wide-angle lens, while the other lens assembly 10 adopts a telephoto lens. When the camera assembly 100 realizes imaging, the processor 200 enables the lens assembly 10 using the wide-angle lens to realize imaging. If the electronic device 1000 detects that the user takes a scaling-up operation for a preview image and the processor 200 derives an enlarging scale of the preview image higher than a predetermined value, the processor 200 immediately enables the lens assembly 10 using the telephoto lens to realize imaging. The wide-angle lens has a big field of view and a short focal length, while the telephoto lens has a small field of view and a long focal length. When the user takes the scaling-up operation for the preview image, it indicates that the user would like to take a picture of distant view, in this case, it needs to adopt the telephoto lens to get a clear picture of the distant view, thus it needs to switch the camera assembly 100 to the lens assembly 10 using the telephoto lens to realize imaging so as to improve the definition of the image.

However, in some usage scenarios of the electronic device 1000, there may be a situation that the illumination intensities on the front face 400 and the back face 500 of the electronic device 1000 are different obviously. For example, the user may put the cell phone on the table with the front face 400 opposite to the table top. If the display brightness of the display screen 300 is controlled only according to the illumination intensity on the front face 400 detected by the front camera assembly 100a, the display screen 300 may be in a non-display state or in a low-brightness-display state. When the user suddenly picks up the electronic device 1000 for using, the electronic device 1000 needs to awaken the display screen 300 or to increase the brightness of the display screen 300 in a short time. When the user frequently picks up and puts down the electronic device 1000, the electronic device 1000 would consume a great quantity of electricity energy for controlling the brightness of the display screen 300. For another example, if the user operates the electronic device 1000 when he/she lies down indoor, the back face 500 may be opposite to a light source (such as a ceiling lamp) amounted on the ceiling, such that the illumination intensity on the back face 500 may be greater than that on the front face 400. In this case, if the brightness of the display screen 300 is adjusted only according to the illumination intensity on the front face 400, it is possible that the user cannot make out the displayed content

due to the low brightness. Thus, if the processor 200 can process both the illumination intensity on the front face 400 and the illumination intensity on the back face 500 of the electronic device 1000, an optimum illumination intensity can be obtained.

Referring to Fig. 3, in some implementations, there are a plurality of camera assemblies 100. One of them is configured as a front camera assembly 100a, a further of them is configured as a rear camera assembly 100b. The front camera assembly 100a and the display screen 300 are disposed on the front face 400 of the electronic device 1000. The front camera assembly 100a may be configured to detect the illumination intensity on the front face 400 and acquire the image opposite to the front face 400 simultaneously. The rear camera assembly 100b is disposed on the back face 500 of the electronic device 1000. The rear camera assembly 100b may be configured to detect the illumination intensity on the back face 500 and acquire the image opposite to the back face 500 simultaneously.

Referring to table 2, each light sensing region 1222 in the front camera assembly 100a has three operating modes, which are light sensing mode, imaging mode and idle mode. Each imaging region 1224 in the front camera assembly 100a has two operating modes, which are imaging mode and idle mode. Each light sensing region 1222 in the rear camera assembly 100b has three operating modes, which are light sensing mode, imaging mode and idle mode. Each imaging region 1224 in the rear camera assembly 100b has two operating modes, which are imaging mode and idle mode. The operating mode of the front camera assembly 100a may include several situations in table 2. The operating mode of the rear camera assembly 100b may include several situations in table 2.

The light sensing mode means that the light sensing region 1222 detects the illumination intensity. The imaging mode means that the light sensing region 1222 and the imaging region 1224 collectively perform the photographic process to acquire the image. The idle mode of the light sensing region 1222 means that the light sensing region 1222 is not in the light sensing mode or in the imaging mode. The idle mode of the imaging region 1224 means that the imaging region 1224 is not in the imaging mode. Further, when the imaging region 1224 is in the imaging mode, the light sensing region 1222 is in the imaging mode too.

No.	operating mode component	Front camera assembly				Rear camera assembly			
		Image sensor 1		Image sensor 2		Image sensor 1		Image sensor 2	
		Light sensing region 1	Imaging region 1	Light sensing region 2	Imaging region 2	Light sensing region 1	Imaging region 1	Light sensing region 2	Imaging region 2
1		Light sensing mode	idle mode	Light sensing mode	idle mode	Light sensing mode	idle mode	Light sensing mode	idle mode
2		Light sensing mode	idle mode	idle mode	idle mode	Light sensing mode	idle mode	idle mode	idle mode
3		idle mode	idle mode	Light sensing mode	idle mode	idle mode	idle mode	Light sensing mode	idle mode
4		Light sensing mode	idle mode	Imaging mode	Imaging mode	Light sensing mode	idle mode	Imaging mode	Imaging mode
5		idle mode	idle mode	Imaging mode	Imaging mode	idle mode	idle mode	Imaging mode	Imaging mode
6		Imaging mode	Imaging mode	Light sensing mode	idle mode	Imaging mode	Imaging mode	Light sensing mode	idle mode
7		Imaging mode	Imaging mode	idle mode	idle mode	Imaging mode	Imaging mode	idle mode	idle mode
8		Imaging mode	Imaging mode	Imaging mode	Imaging mode	Imaging mode	Imaging mode	Imaging mode	Imaging mode
9		idle mode	idle mode	idle mode	idle mode	idle mode	idle mode	idle mode	idle mode
...		...	...	...	...	...	...	...	...

Table 2

The operating mode of the front camera assembly 100a and the operating mode of the rear camera assembly 100b form a plurality of combinations. However, because the length is limited, table 2 only lists some combinations of operating modes. There may be other combinations of operating modes for the front camera assembly 100a and the rear camera assembly 100b, which are not listed herein.

In some operating modes, for example, in the operating state No. 1, two light sensing regions 1222 in the front camera assembly 100a detect a first illumination intensity and a second illumination intensity respectively, and two light sensing regions 1222 in the rear camera assembly 100b detect a third illumination intensity and a fourth illumination intensity respectively. In this case, the final illumination intensity of the electronic device 1000 can be calculated based on one of the following four ways.

Way one, the processor 200 may be configured to select a maximum of the first illumination intensity, the second illumination intensity, the third illumination intensity and the fourth illumination intensity as the final illumination intensity.

Way two, the processor 200 may be configured to obtain a mean value of the first illumination intensity and the second illumination intensity as a front illumination intensity (the front illumination intensity refers to an illumination intensity detected by the light sensing region in the front camera assembly), to obtain a mean value of the third illumination intensity and the fourth illumination intensity as a rear illumination intensity (the rear illumination intensity refers to an illumination intensity detected by the light sensing region in the rear camera assembly), and to select a maximum of the front illumination intensity and the rear illumination intensity as the final illumination intensity.

Way three, the processor 200 may be configured to select a maximum of the first illumination intensity and the second illumination intensity as the front illumination intensity, to obtain a mean value of the third illumination intensity and the fourth illumination intensity as the rear illumination intensity, and to select a maximum of the front illumination intensity and the rear illumination intensity as the final illumination intensity.

Way four, the processor 200 may be configured to obtain a mean value of the first illumination intensity and the second illumination intensity as the front illumination intensity, to select a maximum of the third illumination intensity and the fourth illumination intensity as the rear illumination intensity, and to select a maximum of the front illumination intensity and the rear illumination intensity as the final illumination intensity.

In some embodiments, the processor 200 can switch the calculation way among the above four ways, which can be realized by the user manually or automatically according to specific values of the illumination intensities. For example, when each of the first illumination intensity, the second illumination intensity, the third illumination intensity and the fourth illumination intensity is less than a predetermined illumination intensity threshold, it may be determined that the user may use the electronic device 1000 in a dark environment, thus the processor 200 can switch the calculation way to way one, i.e., selecting the maximum as the final illumination intensity.

To this, all of the four light sensing regions 1222 in the front camera assembly 100a and the rear camera assembly 100b are configured to detect illumination intensities, and the final illumination intensity obtained by the processor 200 can reflect the actual illumination intensity of the environment objectively.

In some operating modes in table 2, one light sensing region 1222 in the front camera assembly 100a detects a first illumination intensity, one light sensing region 1222 in the rear camera assembly 100b detects a second illumination intensity. The processor 200 is configured to select a maximum of the first illumination intensity and the second illumination intensity as the final illumination intensity.

To this, each of the front camera assembly 100a and the rear camera assembly 100b enables one light sensing region 1222 when working to save energy. When one light sensing region 1222 in the front camera assembly 100a breaks down, the other light sensing region 1222 in the front camera assembly 100a can be used to detect the first illumination intensity. When one light sensing region 1222 in the rear camera assembly 100b breaks down, the other light sensing region 1222 in the rear camera assembly 100b can be used to detect the second illumination intensity. Thus, the normal use of the electronic device 1000 will be not affected.

In some operating modes in table 2, two light sensing regions 1222 in the front camera assembly 100a detect a first illumination intensity and a second illumination intensity respectively, and one light sensing region 1222 in the rear camera assembly 100b detects a third illumination intensity. In this way, the final illumination intensity of the electronic device 1000 can be calculated based on one of the following two ways.

Way one, the processor 200 is configured to select a maximum of the first illumination intensity and the second illumination intensity as the front illumination intensity, and to select a maximum of the front illumination intensity and the third illumination intensity as the final illumination intensity.

Way two, the processor 200 is configured to obtain a mean value of the first illumination intensity and the second illumination intensity as the front illumination intensity, and to select a maximum of the front illumination intensity and the third illumination intensity as the final illumination intensity.

In some embodiments, the processor 200 can switch the calculation way between the above two ways. The rear camera assembly 100b only enables one light sensing region 1222 when working, to save energy. When one light sensing region 1222 in the rear camera assembly 100b breaks down, the other light sensing region 1222 in the rear camera assembly 100b can be used to detect the third illumination intensity. Thus, the normal use of the electronic device 1000 will be not affected.

In some operating modes in table 2, one light sensing region 1222 in the front camera assembly 100a detects a first illumination intensity, and two light sensing regions 1222 in the rear camera assembly 100b detect a second illumination intensity and a third illumination intensity respectively. In this way, the final illumination intensity of the electronic device 1000 can be calculated based on one of the following two ways.

Way one, the processor 200 is configured to select a maximum of the second illumination intensity and the third illumination intensity as the rear illumination intensity, and to select a maximum of the rear illumination intensity and the first illumination intensity as the final illumination intensity.

Way two, the processor 200 is configured to obtain a mean value of the second illumination intensity and the third illumination intensity as the rear illumination intensity, and to select a maximum of the rear illumination intensity and the first illumination intensity as the final

illumination intensity.

In some embodiments, the processor 200 can switch the calculation way between the above two ways. The front camera assembly 100a only enables one light sensing region 1222 when working, to save energy. When one light sensing region 1222 in the front camera assembly 100a breaks down, the other light sensing region 1222 in the front camera assembly 100a can be used to detect the first illumination intensity. Thus, the normal use of the electronic device 1000 will be not affected.

Further, the front camera assembly 100a and the rear camera assembly 100b can realize imaging simultaneously or on time-sharing.

In one embodiment, the front camera assembly 100a and the rear camera assembly 100b can realize imaging simultaneously. For example, the processor 200 enables both the front camera assembly 100a and the rear camera assembly 100b. The rear camera assembly 100b is configured to take a picture of the scenery behind the electronic device 1000. The front camera assembly 100a is configured to take a picture of face of the user. The display screen 300 of the electronic device 1000 displays the images captured by both the front camera assembly 100a and the rear camera assembly 100b simultaneously. Further, the processor 200 may store the images captured at the same time by both the front camera assembly 100a and the rear camera assembly 100b in association with each other. When the user browses the stored images, both the scenery and the face of the user who enjoys the scenery can be checked, thus improving the user experience.

In another embodiment, the front camera assembly 100a and the rear camera assembly 100b may realize imaging on time-sharing. For example, the front camera assembly 100a is working while the rear camera assembly 100b is disabled, or the front camera assembly 100a is disabled but the rear camera assembly 100b is working. In this way, the electronic device 1000 not only can take a picture of the scenery behind the electronic device 1000 but also can capture the selfie.

The two lens assemblies 10 in the front camera assembly 100a may realize imaging simultaneously or on time-sharing to optimize the imaging quality. The two lens assemblies 10 in the rear camera assembly 100b may also realize imaging simultaneously or on time-sharing to optimize the imaging quality, which will not be described herein.

Further, when one light sensing region 1222 in the front camera assembly 100a is in the light sensing mode and the other light sensing region 1222 is in the imaging mode, the lens assembly 10 in the imaging mode in the front camera assembly 100a is configured to realize imaging, and the light sensing region 1222 of the lens assembly 10 in the light sensing mode in the front camera assembly 100a is configured to detect the illumination intensity as the final illumination intensity of the front camera assembly 100a and to control the brightness of the display screen 300 to change according to the detected illumination intensity of the environment. Similarly, when one light sensing region 1222 in the rear camera assembly 100b is in the light sensing mode and the other light sensing region 1222 is in the imaging mode, the lens assembly 10 in the imaging mode in the rear camera assembly 100b is configured to realize imaging, and the light sensing region

1222 of the lens assembly 10 in the light sensing mode in the rear camera assembly 100b is configured to detect the illumination intensity as the final illumination intensity of the rear camera assembly 100b and to control the brightness of the display screen 300 to change according to the detected illumination intensity of the environment. In this way, the preview can be realized when the user takes a picture, thus improving the user experience.

Referring to Figs. 4-6, in some implementations, the electronic device 1000 further includes a different camera assembly 600. The different camera assembly 600 includes an image sensor 30. The image sensor 30 includes a pixel array 32 and a control circuit 34. The pixel array 30 includes a light sensing region 322 and an imaging region 324. The control circuit 34 is configured to control the light sensing region 322 of the image sensor 30 to detect an illumination intensity when a light sensing instruction is received, and to control the light sensing region 322 and the imaging region 324 of the image sensor 30 to collectively acquire an image when an imaging instruction is received.

Referring to Fig. 5, in some implementations, there is a single camera assembly 100 configured as the front camera assembly 100a. The different camera assembly 600 is configured as the rear camera assembly 600b.

Referring to Fig. 6, in some implementations, there is a single camera assembly 100 configured as the rear camera assembly 100b. The different camera assembly 600 is configured as the front camera assembly 600a.

The processor 200 can perform comprehensive processing on the illumination intensities detected by the different camera assembly 600 and the camera assembly 100 and the acquired images to acquire a final illumination intensity and a final image. The processing ways may be similar to those used by the processor 200 to acquire the final illumination intensity and the final image according to the illumination intensities detected by two camera assemblies 100 and the images acquired by the two camera assemblies 100, which will not be described herein. The different camera assembly 600 further includes a filter 40. Light passing through the filter 40 of the different camera assembly 600 reaches the imaging region 324 of the image sensor 30.

In some embodiments, a ratio of an area of the imaging region 1224 to an area of the pixel array 122 is greater than or equal to 0.6, and/or a ratio of an area of light sensing region 1222 to the area of the pixel array 122 is greater than or equal to 0.1. In some embodiments, the ratio of the area of the imaging region 1224 to the area of the pixel array 122 may be 0.6, 0.68, 0.74, 0.8, 0.9 or the like. The ratio of the area of light sensing region 1222 to the area of the pixel array 122 may be 0.1, 0.23, 0.3, 0.4 or the like. Accordingly, it ensures that the image sensor 12 has a better imaging effect on the basis of having the function of detecting the illumination intensity.

In some implementations, the two pixel arrays 122 of the two lens assemblies 10 may be the same, or may not be the same.

Referring to Figs. 7 and 8, in some implementations, the imaging region 1224 in each pixel array 122 is contiguous and located in the middle of the pixel array 122. The light sensing region

1222 is located around the imaging region 1224. Thus, it is easy for the contiguous imaging region 1224 to generate a continuous and complete image. In some embodiments, the center of the imaging region 1224 and the center of the pixel array 122 may coincide. The imaging region 1224 may adopt a central symmetry structure. The light sensing region 1222 may be located at one or
5 more sides of the imaging region 1224.

In some implementations, the light sensing region 1222 may include a plurality of light sensing sub-regions 1225 having the same area and spaced from each other.

The illumination intensity detected by the light sensing region 1222 may be obtained by taking illumination intensities detected by all the pixel points in the light sensing region 1222 into
10 account. Thus, in order to obtain an objective illumination intensity, the light sensing region 1222 is decentralized as much as possible. In other words, the light sensing region 1222 is decentralized as a plurality of spaced light sensing sub-regions 1225.

The plurality of light sensing sub-regions 1225 spaced from each other may extend a detection range of the light sensing region 1222 and may improve an accuracy of detection of the
15 light sensing region 1222. In an embodiment, there are four light sensing sub-regions 1225. The ratio of the area of each light sensing sub-region 1225 to the area of the pixel array 122 may be 0.05. The plurality of light sensing sub-regions 1225 may be arranged above, under, on the left, right of the imaging region 1224 respectively.

Referring to Fig. 9, in some implementations, the plurality of light sensing sub-regions 1225
20 include a left light sensing sub-region 1226 and a right light sensing sub-region 1227. The left light sensing sub-region 1226 is on the left of the imaging region 1224, and the right light sensing sub-region 1227 is on the right of the imaging region 1224. The left light sensing sub-region 1226 and the right light sensing sub-region 1227 are arranged symmetrically. The left light sensing sub-region 1226 detects a left illumination intensity (the left illumination intensity refers to an
25 illumination intensity detected by the left light sensing sub-region). The right light sensing sub-region 1227 detects a right illumination intensity (the right illumination intensity refers to an illumination intensity detected by the right light sensing sub-region). The illumination intensity detected by the light sensing region 1222 is a mean value of the left illumination intensity and the right illumination intensity.

To this, influences of the left light sensing sub-region 1226 and the right light sensing sub-region 1227 to the illumination intensity detected by the light sensing region 1222 are the same essentially, thus the problem that the detection result is inaccurate because the light sensing region 1222 is too sensitive to light change on the left or right of the imaging region can be avoided.
30

In some implementations, the plurality of light sensing sub-regions 1225 include an upper light sensing sub-region 1228 and a lower light sensing sub-region 1229. The upper sensing sub-region 1228 is above the imaging region 1224. The lower light sensing sub-region 1229 is under the imaging region 1224. The upper light sensing sub-region 1228 and the lower light
35

sensing sub-region 1229 are arranged symmetrically. The upper light sensing sub-region 1228 detects an upper illumination intensity (the upper illumination intensity refers to an illumination intensity detected by the upper light sensing sub-region). The lower light sensing sub-region 1229 detects a lower illumination intensity (the lower illumination intensity refers to an illumination intensity detected by the lower light sensing sub-region). The illumination intensity detected by the light sensing region 1222 is a mean value of the upper illumination intensity and the lower illumination intensity.

To this, influences of the upper light sensing sub-region 1228 and the lower light sensing sub-region 1229 to the illumination intensity detected by the light sensing region 1222 are the same essentially, thus the problem that the detection result is inaccurate because the light sensing region 1222 is too sensitive to light change above or under the imaging region can be avoided.

In some implementations, the plurality of light sensing sub-regions 1225 include a left light sensing sub-region 1226, a right light sensing sub-region 1227, an upper light sensing sub-region 1228 and a lower light sensing sub-region 1229. In an embodiment, the left light sensing sub-region 1226, the right light sensing sub-region 1227, the upper light sensing sub-region 1228 and the lower light sensing sub-region 1229 are centrally symmetric. The left light sensing sub-region 1226 and the right light sensing sub-region 1227 are arranged symmetrically, and the upper light sensing sub-region 1228 and the lower light sensing sub-region 1229 are arranged symmetrically. The left light sensing sub-region 1226 detects a left illumination intensity. The right light sensing sub-region 1227 detects a right illumination intensity. The upper light sensing sub-region 1228 detects an upper illumination intensity. The lower light sensing sub-region 1229 detects a lower illumination intensity. The illumination intensity detected by the light sensing region 1222 is a mean value of the left illumination intensity, the right illumination intensity, the upper illumination intensity and the lower illumination intensity.

To this, influences of the left light sensing sub-region 1226, the right light sensing sub-region 1227, the upper light sensing sub-region 1228 and the lower light sensing sub-region 1229 to the illumination intensity detected by the light sensing region 1222 are the same essentially, thus the problem that the detection result is inaccurate because the light sensing region 1222 is too sensitive to light change above, under, on the left or right of the imaging region can be avoided.

The sub-regions being arranged symmetrically means that the sub-regions are symmetric in area and shape with regard to the imaging region 1224.

To this, the left light sensing sub-region 1226, the right light sensing sub-region 1227, the upper light sensing sub-region 1228 and the lower light sensing sub-region 1229 can detect light in several directions on the upside, downside, left side and right side of the imaging region 1224 simultaneously, thus improving the accuracy of the detection result of the light sensing region 1222.

As illustrated in Fig. 9, in the pixel array 122, the light sensing region 1222 and the imaging region 1224 collectively acquire the merged image which is in the shape of “+”. The enlarged light

sensing region 1222 can obtain more information of the current environment, such that the field of view of the merged image is enlarged, thus optimizing the photographing effect. Accordingly, when the user uses the electronic device 1000 to take a picture, the image in the shape of “+” can be acquired, such that the personalized demand of the user can be satisfied, thus improving the user experience.

Referring to Figs. 10 and 11, in some implementations, the pixel array 122 is in a shape of a circle or an ellipse. The imaging region 1224 is in a shape of an inscribed rectangle of the pixel array 122. The light sensing region 1222 includes a region other than the inscribed rectangle of the circle or the ellipse.

Accordingly, the imaging region 1224 is in the middle of the pixel array 122, which can acquire the image easily. The light sensing region 1222 is decentralized. The light sensing region 1222 on the left of the imaging region 1224 and the light sensing region 1222 on the right of the imaging region 1224 are symmetric. The light sensing region 1222 has the same sensitivity to light change on the left and right of the imaging region 1224. The light sensing region 1222 above the imaging region 1224 and the light sensing region 1222 under the imaging region 1224 are symmetric. The light sensing region 1222 has the same sensitivity to light change above and under the imaging region 1224. Thus, the light sensing region 1222 can obtain an accurate detection result.

Referring to Figs. 12 and 13, the pixel array is in a shape of rectangle. The imaging region 1224 is in a shape of an inscribed circle or an inscribed ellipse of the rectangle. The light sensing region 1222 includes a region other than the inscribed circle or the inscribed ellipse of the rectangle.

Accordingly, the imaging region 1224 is in the shape of the circle or ellipse. The user can obtain an image in the shape of circle or ellipse via the imaging region 1224 without further post-processing, thus satisfying the user's personalized demand. The light sensing region 1222 is decentralized, such that the accuracy of the illumination intensity detected by the light sensing region 1222 can be improved.

Thus, the imaging region 1224 is in the middle of the pixel array 122, which can acquire the image easily. The light sensing region 1222 above the imaging region 1224 and the light sensing region 1222 under the imaging region 1224 are symmetric. The light sensing region 1222 on the left of the imaging region 1224 and the light sensing region 1222 on the right of the imaging region 1224 are symmetric.

Referring to Figs. 14 and 15, in some implementations, the imaging region 1224 is contiguous and the light sensing region 1222 is contiguous. The imaging region 1224 and the light sensing region 1222 share a common boundary. Two imaging regions 1224 of the two lens assemblies 10 are located between two light sensing regions 1222 of the two lens assemblies 10. Thus, the pixel array 122 has a simple structure. The control circuit 124 may easily find the pixels in the corresponding imaging region 1224 or the corresponding light sensing region 1222 after

receiving the light sensing instruction or the imaging instruction. In some embodiments, the ratio of the area of the imaging region 1224 to the area of the pixel array 122 is 0.8. The ratio of the area of the light sensing region 1222 to the area of the pixel array 122 is 0.2. The imaging region 1224 may be in the shape of a rectangle, such that the imaging region 124 may obtain an image in the shape of the rectangle. The light sensing region 1222 may also be in the shape of a rectangle, and a long edge of the light sensing region 1222 may intersect a long edge of the imaging region 1224 or a short edge of the imaging region 1224.

Two imaging regions 1224 of the two lens assemblies 10 are arranged between two light sensing regions 1222 of the two lens assemblies 10. In some embodiments, as illustrated in Fig. 14, when the two lens assemblies 10 are arranged laterally, one light sensing region 1222 is arranged on the left of a left image sensor 12 and the other light sensing region 1222 is arranged on the right of a right image sensor 12. As illustrated in Fig. 15, when the two lens assemblies 10 are arranged longitudinally, one light sensing region 1222 is arranged above an upper image sensor 12 and the other light sensing region 1222 is arranged under a lower image sensor 12. In this way, the two light sensing regions 1222 of the camera assembly 10 can detect in wide range and obtain more accurate detection result.

The arrangement of the pixel array 122 of the image sensor 12 may be also suitable to the arrangement of the pixel array 32 of the image sensor 30, which will be not described herein.

Reference throughout this specification to “an embodiment,” “some embodiments,” “an example,” “a specific example,” or “some examples,” means that a particular feature, structure, material, or characteristic described in connection with the embodiment or example is included in at least one embodiment or example of the present disclosure. In this specification, exemplary descriptions of aforesaid terms are not necessarily referring to the same embodiment or example. Furthermore, the particular features, structures, materials, or characteristics may be combined in any suitable manner in one or more embodiments or examples. Moreover, those skilled in the art could combine different embodiments or different characteristics in embodiments or examples described in the present disclosure.

Moreover, terms of “first” and “second” are only used for description and cannot be seen as indicating or implying relative importance or indicating or implying the number of the indicated technical features. Thus, the features defined with “first” and “second” may comprise or imply at least one of these features. In the description of the present disclosure, “a plurality of” means two or more than two, unless specified otherwise.

Any process or method described in a flow chart or described herein in other ways may be understood to include one or more modules, segments or portions of codes of executable instructions for achieving specific logical functions or steps in the process, and the scope of a preferred embodiment of the present disclosure includes other implementations, wherein the order of execution may differ from that which is depicted or discussed, including according to involved function, executing concurrently or with partial concurrence or in the contrary order to perform the

function, which should be understood by those skilled in the art.

The logic and/or step described in other manners herein or shown in the flow chart, for example, a particular sequence table of executable instructions for realizing the logical function, may be specifically achieved in any computer readable medium to be used by the instruction
5 execution system, device or equipment (such as the system based on computers, the system comprising processors or other systems capable of acquiring the instruction from the instruction execution system, device and equipment and executing the instruction), or to be used in combination with the instruction execution system, device and equipment. As to the specification, “the computer readable medium” may be any device adaptive for including, storing,
10 communicating, propagating or transferring programs to be used by or in combination with the instruction execution system, device or equipment. More specific examples of the computer-readable medium comprise but are not limited to: an electronic connection (an electronic device) with one or more wires, a portable computer enclosure (a magnetic device), a random access memory (RAM), a read-only memory (ROM), an erasable programmable read-only
15 memory (EPROM or a flash memory), an optical fiber device and a portable compact disk read-only memory (CDROM). In addition, the computer-readable medium may even be a paper or other appropriate medium capable of printing programs thereon, this is because, for example, the paper or other appropriate medium may be optically scanned and then edited, decrypted or processed with other appropriate methods when necessary to obtain the programs in an electric
20 manner, and then the programs may be stored in the computer memories.

It should be understood that each part of the present disclosure may be realized by hardware, software, firmware or their combination. In the above embodiments, a plurality of steps or methods may be realized by the software or firmware stored in the memory and executed by the appropriate instruction execution system. For example, if it is realized by the hardware, likewise in
25 another embodiment, the steps or methods may be realized by one or a combination of the following techniques known in the art: a discrete logic circuit having a logic gate circuit for realizing a logic function of a data signal, an application-specific integrated circuit having an appropriate combination logic gate circuit, a programmable gate array (PGA), a field programmable gate array (FPGA), etc..

Those skilled in the art shall understand that all or parts of the steps in the above exemplifying method for the present disclosure may be achieved by commanding the related hardware with programs , the programs may be stored in a computer-readable storage medium, and the programs comprise one or a combination of the steps in the method embodiments of the present disclosure when running on a computer.

35 In addition, each function cell of the embodiments of the present disclosure may be integrated in a processing module, or these cells may be separate physical existence, or two or more cells are integrated in a processing module. The integrated module may be realized in a form of hardware or in a form of software function modules. When the integrated module is realized in a form of

software function module and is sold or used as a standalone product, the integrated module may be stored in a computer-readable storage medium.

The storage medium mentioned above may be read-only memories, magnetic disks, CD, etc.

WHAT IS CLAIMED IS:

1. A camera assembly (100), comprising at least two image sensors (12), wherein each image sensor (12) comprises:

5 a pixel array (122), comprising a light sensing region (1222) and an imaging region (1224);
and

a control circuit (124), configured to:

receive a light sensing instruction to control the light sensing region (1222) to detect an illumination intensity; and

10 receive an imaging instruction to control the light sensing region (1222) and the imaging region (1224) to collectively perform a photographic process to acquire an image.

2. The camera assembly (100) according to claim 1, wherein the control circuit (124) is further configured to:

15 receive the imaging instruction to control the light sensing region (1222) to detect a color temperature of a current environment; and

control the imaging region (1224) to perform the photographic process according to the color temperature to acquire a color-temperature adjusted image.

3. The camera assembly (100) according to claim 1, wherein the control circuit (124) is further configured to receive the imaging instruction to control the light sensing region (1222) and
20 the imaging region (1224) to collectively perform the photographic process to acquire a merged image.

4. The camera assembly (100) according to any of claims 1-3, wherein the imaging region (1224) of each image sensor (12) is contiguous and located in the middle of the pixel array (122),
25 and the light sensing region (1222) of each image sensor (12) is located around the imaging region (1224); and/or

the pixel array (122) of each image sensor (12) is configured such that at least one of following conditions is satisfied: a ratio of an area of the imaging region (1224) of said image sensor (12) to an area of the pixel array (122) of said image sensor (12) being greater than or equal to 0.6; and a ratio of an area of the light sensing region (1222) of said image sensor (12) to the area
30 of the pixel array (122) of said image sensor (12) being greater than or equal to 0.1.

5. The camera assembly (100) according to claim 4, wherein the light sensing region (1222) of each image sensor (12) comprises at least two light sensing sub-regions (1225) having basically a same area and spaced from each other.

6. The camera assembly (100) according to claim 5, wherein,

35 the at least two light sensing sub-regions (1225) comprise a left light sensing sub-region (1226) on the left of the imaging region (1224) and a right light sensing sub-region (1227) on the right of the imaging region (1224); wherein the left light sensing sub-region (1226) and the right

light sensing sub-region (1227) are arranged symmetrically, the left light sensing sub-region (1226) is configured to detect a left illumination intensity, the right light sensing sub-region (1227) is configured to detect a right illumination intensity, and the illumination intensity detected by the light sensing region (1222) is a mean value of the left illumination intensity and the right illumination intensity; or

the at least two light sensing sub-regions (1225) comprise an upper light sensing sub-region (1228) above the imaging region (1224) and a lower light sensing sub-region (1229) below the imaging region (1224); wherein the upper light sensing sub-region (1228) and the lower light sensing sub-region (1229) are arranged symmetrically, the upper light sensing sub-region (1228) is configured to detect an upper illumination intensity, the lower light sensing sub-region (1229) is configured to detect a lower illumination intensity, and the illumination intensity detected by the light sensing region (1222) is a mean value of the upper illumination intensity and the lower illumination intensity; or

the at least two light sensing sub-regions (1225) comprise a left light sensing sub-region (1226) on the left of the imaging region (1224), a right light sensing sub-region (1227) on the right of the imaging region (1224), an upper light sensing sub-region (1228) above the imaging region (1224) and a lower light sensing sub-region (1229) below the imaging region (1224); wherein the left light sensing sub-region (1226) and the right light sensing sub-region (1227) are arranged symmetrically, the upper light sensing sub-region (1228) and the lower light sensing sub-region (1229) are arranged symmetrically, the left light sensing sub-region (1226) is configured to detect a left illumination intensity, the right light sensing sub-region (1227) is configured to detect a right illumination intensity, the upper light sensing sub-region (1228) is configured to detect an upper illumination intensity, the lower light sensing sub-region (1229) is configured to detect a lower illumination intensity, and the illumination intensity detected by the light sensing region (1222) is a mean value of the left illumination intensity, the right illumination intensity, the upper illumination intensity and the lower illumination intensity.

7. The camera assembly (100) according to any of claims 1-6, wherein

the pixel array (122) is in a shape of one of a circle and an ellipse, the imaging region (1224) is in a shape of an inscribed rectangle of the pixel array (122), and the light sensing region (1222) comprises a region other than the inscribed rectangle of the one of the circle and the ellipse; and/or

the pixel array (122) is in a shape of a rectangle, the imaging region (1224) is in a shape of one of an inscribed circle and an inscribed ellipse of the pixel array (122), and the light sensing region (1222) comprises a region other than the one of the inscribed circle and the inscribed ellipse of the rectangle.

8. The camera assembly (100) according to any of claims 1-6, wherein the camera assembly (100) comprises two image sensors (12), the imaging region (1224) of each image sensor (12) is contiguous and the light sensing region (1222) of each image sensor (12) is contiguous; the imaging region (1224) and the light sensing region (1222) of each image sensor (12) share a

common boundary, and two imaging regions (1224) of the two image sensors (12) are located between two light sensing regions (1222) of the two image sensors (12).

9. A mobile electronic device (1000), comprising a camera assembly (100) according to any of claims 1-8 and a processor (200); wherein,

5 the processor (200) is configured to generate the light sensing instruction and the imaging instruction.

10. The mobile electronic device (1000) according to claim 9, wherein the mobile electronic device (1000) comprises one camera assembly (100) configured as a front camera assembly (100a);

10 wherein when light sensing regions (1222) of at least two image sensors (12) of the camera assembly (100) detect a first illumination intensity and a second illumination intensity respectively, the processor (200) is configured to:

determine a maximum of the first illumination intensity and the second illumination intensity as a final illumination intensity; or

15 obtain a mean value of the first illumination intensity and the second illumination intensity as a final illumination intensity.

11. The mobile electronic device (1000) according to claim 9, wherein the mobile electronic device (1000) comprises at least two camera assemblies (100), one of the at least two camera assemblies (100) is configured as a front camera assembly (100a) and a further one of the at least
20 two camera assemblies (100) is configured as a rear camera assembly (100b);

wherein when two light sensing regions (1222) of the front camera assembly (100a) detect a first illumination intensity and a second illumination intensity respectively, and two light sensing regions (1222) of the rear camera assembly (100b) detect a third illumination intensity and a fourth illumination intensity respectively, the processor (200) is configured to:

25 determine a maximum of the first illumination intensity, the second illumination intensity, the third illumination intensity and the fourth illumination intensity as a final illumination intensity; or

obtain a mean value of the first illumination intensity and the second illumination intensity as a front illumination intensity, obtain a mean value of the third illumination intensity and the fourth illumination intensity as a rear illumination intensity, and determine a maximum of the front
30 illumination intensity and the rear illumination intensity as a final illumination intensity; or

determine a maximum of the first illumination intensity and the second illumination intensity as a front illumination intensity, obtain a mean value of the third illumination intensity and the fourth illumination intensity as a rear illumination intensity, and determine a maximum of the front
illumination intensity and the rear illumination intensity as a final illumination intensity; or

35 obtain a mean value of the first illumination intensity and the second illumination intensity as a front illumination intensity, determine a maximum of the third illumination intensity and the fourth illumination intensity as a rear illumination intensity, and determine a maximum of the front illumination intensity and the rear illumination intensity as a final illumination intensity.

12. The mobile electronic device (1000) according to claim 9, wherein the mobile electronic device (1000) comprises at least two camera assemblies (100), one of the at least two camera assemblies (100) is configured as a front camera assembly (100a) and a further one of the at least two camera assemblies (100) is configured as a rear camera assembly (100b);

5 wherein when a light sensing region (1222) of the front camera assembly (100a) detects a first illumination intensity, and a light sensing region (1222) of the rear camera assembly (100b) detects a second illumination intensity, the processor (200) is configured to:

determine a maximum of the first illumination intensity and the second illumination intensity as a final illumination intensity.

10 13. The mobile electronic device (1000) according to claim 9, wherein the mobile electronic device (1000) comprises at least two camera assemblies (100), one of the at least two camera assemblies (100) is configured as a front camera assembly (100a) and a further one of the at least two camera assemblies (100) is configured as a rear camera assembly (100b);

15 wherein when two light sensing regions (1222) of the front camera assembly (100a) detect a first illumination intensity and a second illumination intensity respectively, and a light sensing region (1222) of the rear camera assembly (100b) detects a third illumination intensity, the processor (200) is configured to:

determine a maximum of the first illumination intensity and the second illumination intensity as a front illumination intensity, and determine a maximum of the front illumination intensity and the third illumination intensity as a final illumination intensity; or

20 obtain a mean value of the first illumination intensity and the second illumination intensity as a front illumination intensity, and determine a maximum of the front illumination intensity and the third illumination intensity as a final illumination intensity.

25 14. The mobile electronic device (1000) according to claim 9, wherein the mobile electronic device (1000) comprises at least two camera assemblies (100), one of the at least two camera assemblies (100) is configured as a front camera assembly (100a) and a further one of the at least two camera assemblies (100) is configured as a rear camera assembly (100b);

30 wherein when a light sensing region (1222) of the front camera assembly (100a) detects a first illumination intensity, and two light sensing regions (1222) of the rear camera assembly (100b) detect a second illumination intensity and a third illumination intensity respectively, the processor (200) is configured to:

determine a maximum of the second illumination intensity and the third illumination intensity as a rear illumination intensity, and determine a maximum of the rear illumination intensity and the first illumination intensity as a final illumination intensity; or

35 obtain a mean value of the second illumination intensity and the third illumination intensity as a rear illumination intensity, and determine a maximum of the rear illumination intensity and the first illumination intensity as a final illumination intensity.

15. The mobile electronic device (1000) according to any of claims 9-14, further comprising

another camera assembly (600), wherein the another camera assembly (600) comprises an image sensor (30) comprising:

a pixel array (32), comprising a light sensing region (322) and an imaging region (324); and
a control circuit (34), configured to:

- 5 determine whether the another camera assembly (600) is in an imaging mode;
 receive a light sensing instruction to control the light sensing region (322) of the image
 sensor (30) of the another camera assembly (600) to detect an illumination intensity when the
 another camera assembly (600) is not in the imaging mode; and
- 10 receive an imaging instruction to control the light sensing region (322) and the imaging
 region (324) of the image sensor (30) of the another camera assembly (600) to collectively
 perform a photographic process to acquire an image when the another camera assembly (600)
 is in the imaging mode.




Fig. 1




Fig. 2




Fig. 3




Fig. 4




Fig. 5




Fig. 6




Fig. 7




Fig. 8




Fig. 9




Fig. 10




Fig. 11




Fig. 12




Fig. 13




Fig. 14




Fig. 15

INTERNATIONAL SEARCH REPORT

International application No.

PCT/CN2018/085359

A. CLASSIFICATION OF SUBJECT MATTER

H04N 5/225(2006.01)i; H04N 5/232(2006.01)i; H04N 5/235(2006.01)n

According to International Patent Classification (IPC) or to both national classification and IPC

B. FIELDS SEARCHED

Minimum documentation searched (classification system followed by classification symbols)

H04N, G06F

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched

Electronic data base consulted during the international search (name of data base and, where practicable, search terms used)

CNABS, CNKI, CNTXT, VEN: camera, module, light sense, imaging sense, illuminate, spatial, illumination, light sensitive, dual sense, two sense?, double sense?, pixel array, sensor, size

C. DOCUMENTS CONSIDERED TO BE RELEVANT

Category*	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
PX	CN 107426470 A (GUANGDONG OPPO MOBILE TELECOM CORP LTD) 01 December 2017 (2017-12-01) claims 1-18	1-15
PX	CN 107249109 A (GUANGDONG OPPO MOBILE TELECOM CORP LTD) 13 October 2017 (2017-10-13) claims 1-15	1-15
Y	US 2014211054 A1 (SAMSUNG ELECTRO MECH) 31 July 2014 (2014-07-31) description, paragraphs 0003-0034 and 0079-0083, figures 1 and 2	1-3, 9
Y	CN 103118231 A (LIU LIEJUN) 22 May 2013 (2013-05-22) description, paragraphs 0042-0091	1-3, 9
A	WO 2004008755 A1 (SEIKO EPSON CORP. ET AL.) 22 January 2004 (2004-01-22) the whole document	1-15
A	WO 2008140896 A1 (MICRON TECHNOLOGY INC. ET AL.) 20 November 2008 (2008-11-20) the whole document	1-15



Further documents are listed in the continuation of Box C.



See patent family annex.

* Special categories of cited documents:

“A” document defining the general state of the art which is not considered to be of particular relevance

“E” earlier application or patent but published on or after the international filing date

“L” document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)

“O” document referring to an oral disclosure, use, exhibition or other means

“P” document published prior to the international filing date but later than the priority date claimed

“T” later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention

“X” document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone

“Y” document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art

“&” document member of the same patent family

Date of the actual completion of the international search

16 July 2018

Date of mailing of the international search report

09 August 2018

Name and mailing address of the ISA/CN

STATE INTELLECTUAL PROPERTY OFFICE OF THE
P.R.CHINA
6, Xitucheng Rd., Jimen Bridge, Haidian District, Beijing
100088
China

Facsimile No. (86-10)62019451

Authorized officer

GE, Xiaolan

Telephone No. 86- (010) -62411470

INTERNATIONAL SEARCH REPORT
Information on patent family members

International application No.

PCT/CN2018/085359

Patent document cited in search report			Publication date (day/month/year)	Patent family member(s)			Publication date (day/month/year)
CN	107426470	A	01 December 2017	IN	201834016081	A	11 May 2018
CN	107249109	A	13 October 2017	None			
US	2014211054	A1	31 July 2014	KR	20140095759	A	04 August 2014
				US	9392197	B2	12 July 2016
				GB	2510227	B	30 March 2016
				GB	2510227	A	30 July 2014
				KR	101442390	B1	17 September 2014
				CN	103973945	B	03 May 2017
				CN	103973945	A	06 August 2014
				GB	201320376	D0	01 January 2014
CN	103118231	A	22 May 2013	None			
WO	2004008755	A1	22 January 2004	EP	1517553	A1	23 March 2005
				EP	1517553	A4	25 January 2006
				US	2005254691	A1	17 November 2005
				US	2005052540	A1	10 March 2005
				US	7511853	B2	31 March 2009
				US	2010085445	A1	08 April 2010
				US	8203755	B2	19 June 2012
				US	2009167872	A1	02 July 2009
				CN	100553315	C	21 October 2009
				US	7646405	B2	12 January 2010
				CN	1669313	A	14 September 2005
				JP	4007368B2	B2	14 November 2007
WO	2008140896	A1	20 November 2008	TW	200903792	A	16 January 2009
				US	2008278610	A1	13 November 2008
				US	7812869	B2	12 October 2010