

(12) INTERNATIONAL APPLICATION PUBLISHED UNDER THE PATENT COOPERATION TREATY (PCT)

(19) World Intellectual Property Organization
International Bureau



(43) International Publication Date
26 October 2006 (26.10.2006)

PCT

(10) International Publication Number
WO 2006/112992 A1

(51) International Patent Classification:
H04N 7/26 (2006.01) *H04N 7/34* (2006.01)
H04N 7/50 (2006.01)

(74) Agents: LAKS, Joseph, J. et al.; Thomson Licensing Inc.,
Two Independence Way, Suite #200, Princeton, New Jersey
08540 (US).

(21) International Application Number:
PCT/US2006/009381

(81) Designated States (unless otherwise indicated, for every
kind of national protection available): AE, AG, AL, AM,
AT, AU, AZ, BA, BB, BG, BR, BW, BY, BZ, CA, CH, CN,
CO, CR, CU, CZ, DE, DK, DM, DZ, EC, EE, EG, ES, FI,
GB, GD, GE, GH, GM, HR, HU, ID, IL, IN, IS, JP, KE,
KG, KM, KN, KP, KR, KZ, LC, LK, LR, LS, LT, LU, LV,
LY, MA, MD, MG, MK, MN, MW, MX, MZ, NA, NG, NI,
NO, NZ, OM, PG, PH, PL, PT, RO, RU, SC, SD, SE, SG,
SK, SL, SM, SY, TJ, TM, TN, TR, TT, TZ, UA, UG, US,
UZ, VC, VN, YU, ZA, ZM, ZW.

(22) International Filing Date: 16 March 2006 (16.03.2006)

(84) Designated States (unless otherwise indicated, for every
kind of regional protection available): ARIPO (BW, GH,
GM, KE, LS, MW, MZ, NA, SD, SL, SZ, TZ, UG, ZM,
ZW), Eurasian (AM, AZ, BY, KG, KZ, MD, RU, TJ, TM),
European (AT, BE, BG, CH, CY, CZ, DE, DK, EE, ES, FI,
FR, GB, GR, HU, IE, IS, IT, LT, LU, LV, MC, NL, PL, PT,
RO, SE, SI, SK, TR), OAPI (BF, BJ, CF, CG, CI, CM, GA,
GN, GQ, GW, ML, MR, NE, SN, TD, TG).

(25) Filing Language: English

(26) Publication Language: English

(30) Priority Data:
60/671,255 13 April 2005 (13.04.2005) US
60/700,834 20 July 2005 (20.07.2005) US


(71) Applicant (for all designated States except US): THOM-
SON LICENSING [FR/FR]; 46, Quai A. Le Gallo,
F-92100 Boulogne-Billancourt (FR).

Published:

— with international search report

For two-letter codes and other abbreviations, refer to the "Guid-
ance Notes on Codes and Abbreviations" appearing at the begin-
ning of each regular issue of the PCT Gazette.

(54) Title: LUMA-CHROMA CODING WITH ONE COMMON OR THREE DISTINCT SPATIAL PREDICTORS



WO 2006/112992 A1

(57) Abstract: There are provided video encoders, video decoders, and corresponding methods. A video encoder for encoding video signal data for an image block includes an encoder (100) for encoding all color components of the video signal data using a common predictor.

LUMA-CHROMA CODING WITH ONE COMMON OR THREE DISTINCT SPATIAL PREDICTORS

CROSS-REFERENCE TO RELATED APPLICATIONS

5 This application claims the benefit of U.S. Provisional Application Serial No. 60/671,255, filed April 13, 2005 and U.S. Provisional Application Serial No. 60/700,834, filed July 20, 2005 both of which are incorporated by reference herein in their respective entireties. Moreover, this application is related to the U.S. Patent Applications, Attorney Docket Nos. PU050051, PU060023 entitled "METHOD AND
10 APPARATUS FOR VIDEO ENCODING"; and PU060029, PU060030 entitled "METHOD AND APPARATUS FOR VIDEO DECODING"; each filed concurrently herewith.

FIELD OF THE INVENTION

15 The present invention relates generally to video encoders and decoders and, more particularly, to methods and apparatus for video encoding and decoding.

BACKGROUND OF THE INVENTION

Presently, the 4:4:4 format of the International Telecommunication Union, 20 Telecommunication Sector (ITU-T) H.264 standard (hereinafter the "H.264 standard") only codes one of three channels as luma, with the other two channels being coded as chroma using less efficient tools. When an input to a codec is in the 4:4:4 format with full resolution in every input component, coding two out of the three input components with the less effective chroma coding algorithm results in the use 25 of more bits in those two channels. This particular problem is more noticeable in intra frames. For example, the H.264 standard running in the Intra-Only mode is less efficient than JPEG2k for overall compression quality at 40 dB (PSNR) and above.

Accordingly, it would be desirable and highly advantageous to have methods 30 and apparatus for video encoding and decoding that overcome the above-described disadvantages of the prior art.

SUMMARY OF THE INVENTION

These and other drawbacks and disadvantages of the prior art are addressed by the present invention, which is directed to methods and apparatus for video encoding and decoding.

5 According to an aspect of the present invention, there is provided a video encoder for encoding video signal data for an image block. The video encoder includes an encoder for encoding the video signal data using unique predictors for each of color components of the video signal data.

10 According to another aspect of the present invention, there is provided a method for encoding video signal data for an image block. The method includes encoding the video signal data using unique predictors for each of color components of the video signal data.

15 According to yet another aspect of the present invention, there is provided a video decoder for decoding video signal data for an image block. The video decoder includes a decoder for decoding the video signal data using unique predictors for each of color components of the video signal data.

20 According to still another aspect of the present invention, there is provided a method for decoding video signal data for an image block, the method comprising decoding the video signal data using unique predictors for each of color components of the video signal data.

These and other aspects, features and advantages of the present invention will become apparent from the following detailed description of exemplary embodiments, which is to be read in connection with the accompanying drawings.

25 BRIEF DESCRIPTION OF THE DRAWINGS

The present invention may be better understood in accordance with the following exemplary figures, in which:

FIG. 1 is a block diagram illustrating an exemplary video encoding apparatus to which the present principles may be applied;

30 FIG. 2 is a block diagram illustrating an exemplary video decoding apparatus to which the present principles may be applied;

FIG. 3 is a flow diagram illustrating an exemplary video encoding process with a pre-encoding, color transform block, in accordance with the present principles;

FIG. 4 is a flow diagram illustrating an exemplary video decoding process with a post-decoding, inverse color transform block, in accordance with the present principles;

5 FIG. 5 is a block diagram illustrating a simplified model of residual color transform (RCT);

FIGs. 6A and 6B are plots of average PSNR versus bit rate for ATV intra-only in accordance with the present principles;

FIGs. 7A and 7B are plots of average PSNR versus bit rate for CT intra-only in accordance with the present principles;

10 FIGs. 8A and 8B are plots of average PSNR versus bit rate for DT intra-only in accordance with the present principles;

FIGs. 9A and 9B are plots of average PSNR versus bit rate for MIR_HD intra-only in accordance with the present principles;

15 FIGs. 10A and 10B are plots of average PSNR versus bit rate for RT intra-only in accordance with the present principles;

FIGs. 11A and 11B are plots of average PSNR versus bit rate for STB_HD intra-only in accordance with the present principles;

FIG. 12 is a table illustrating H.264 sequence parameter syntax in accordance with the present principles;

20 FIG. 13 is a table illustrating H.264 residual data syntax in accordance with the present principles;

FIG. 14 is a flow diagram illustrating an exemplary video encoding process with a pre-encoding, color transform block, in accordance with the present principles;

25 FIG. 15 is a flow diagram illustrating an exemplary video decoding process with a post-decoding, inverse color transform step block, in accordance with the present principles; and

FIG. 16 is a table illustrating H.264 macroblock prediction syntax in accordance with the present principles.

30 **DETAILED DESCRIPTION**

The present invention is directed to methods and apparatus for video encoding and decoding video signal data. It is to be appreciated that while the present invention is primarily described with respect to video signal data sampled using the 4:4:4 format of the International Telecommunication Union,

Telecommunication Sector (ITU-T) H.264 standard, the present invention may also be applied to video signal data sampled using other formats (e.g., the 4:2:2 and/or 4:2:0 format) of the H.264 standard as well as other video compression standards while maintaining the scope of the present invention.

5 It is to be appreciated that methods and apparatus in accordance with the present principles do not require use of any new tool(s) for the luma or chroma compression algorithm. Instead, the existing luma coding tools can be used. Accordingly, one advantageous result there from is that the coding performance of the 4:4:4 format may be maximized while preserving backward compatibility and
10 minimizing any change to the existing H.264 (or other applicable) standard.

In accordance with the principles of the present invention as configured in an embodiment, a luma coding algorithm is used to code all three component channels of, e.g., 4:4:4 content. Advantages of this embodiment include an improvement in the overall coding performance for compressing 4:4:4 content with respect to the
15 prior art. Presently, in the existing H.264 standard, only one of three channels is coded as luma, and the other two are coded as chroma using less efficient tools.

Further, in accordance with the principles of the present invention as configured in an embodiment, color transformation is performed as a pre-processing step. Thus, in accordance with this embodiment, a Residual Color Transform (RCT) 20 is not performed inside the compression loop. Advantages of this embodiment include the providing of consistent encoder/decoder architecture among all color formats.

Moreover, in accordance with the principles of the present invention as configured in an embodiment, the same motion/spatial prediction mode is used for
25 all three components. Advantages of this embodiment include reduced codec complexity and backwards compatibility.

Also, in accordance with another embodiment, instead of using the same predictor for all three components, a set (or subset) of three (3) restricted spatial predictors may be utilized for the three components. Advantages of this
30 embodiment include an improvement in the overall coding performance for compressing 4:4:4 content with respect to the prior art.

It is to be appreciated that the various embodiments described above and subsequently herein may be implemented as stand alone embodiments or may be combined in any manner as readily appreciated by one of ordinary skill in this and

related arts. Thus, for example, in a first combined embodiment, a luma coding algorithm is advantageously used to code all three component channels, color transformation is performed as a pre-processing step, and a single predictor is used for all three component channels. In a second combined embodiment, a luma coding algorithm is advantageously used to code all three component channels, color transformation is performed as a pre-processing step, and a set (or subset) of three (3) restricted spatial predictors may be utilized for the three component channels. Of course, as noted above, other combinations of the various embodiments may also be implemented given the teachings of the present principles provided herein, while maintaining the scope of the present invention.

The present description illustrates the principles of the present invention. It will thus be appreciated that those skilled in the art will be able to devise various arrangements that, although not explicitly described or shown herein, embody the principles of the invention and are included within its spirit and scope.

All examples and conditional language recited herein are intended for pedagogical purposes to aid the reader in understanding the principles of the invention and the concepts contributed by the inventor to furthering the art, and are to be construed as being without limitation to such specifically recited examples and conditions.

Moreover, all statements herein reciting principles, aspects, and embodiments of the invention, as well as specific examples thereof, are intended to encompass both structural and functional equivalents thereof. Additionally, it is intended that such equivalents include both currently known equivalents as well as equivalents developed in the future, i.e., any elements developed that perform the same function, regardless of structure.

Thus, for example, it will be appreciated by those skilled in the art that the block diagrams presented herein represent conceptual views of illustrative circuitry embodying the principles of the invention. Similarly, it will be appreciated that any flow charts, flow diagrams, state transition diagrams, pseudocode, and the like represent various processes which may be substantially represented in computer readable media and so executed by a computer or processor, whether or not such computer or processor is explicitly shown.

The functions of the various elements shown in the figures may be provided through the use of dedicated hardware as well as hardware capable of executing

software in association with appropriate software. When provided by a processor, the functions may be provided by a single dedicated processor, by a single shared processor, or by a plurality of individual processors, some of which may be shared. Moreover, explicit use of the term "processor" or "controller" should not be construed

5 to refer exclusively to hardware capable of executing software, and may implicitly include, without limitation, digital signal processor ("DSP") hardware, read-only memory ("ROM") for storing software, random access memory ("RAM"), and non-volatile storage.

Other hardware, conventional and/or custom, may also be included.

10 Similarly, any switches shown in the figures are conceptual only. Their function may be carried out through the operation of program logic, through dedicated logic, through the interaction of program control and dedicated logic, or even manually, the particular technique being selectable by the implementer as more specifically understood from the context.

15 In the claims hereof, any element expressed as a means for performing a specified function is intended to encompass any way of performing that function including, for example, a) a combination of circuit elements that performs that function or b) software in any form, including, therefore, firmware, microcode or the like, combined with appropriate circuitry for executing that software to perform the function. The invention as defined by such claims resides in the fact that the 20 functionalities provided by the various recited means are combined and brought together in the manner which the claims call for. It is thus regarded that any means that can provide those functionalities are equivalent to those shown herein.

25 Turning to FIG. 1, an exemplary video encoding apparatus is indicated generally by the reference numeral 199. The video encoding apparatus 199 includes a video encoder 100 and a pre-encoding color transform module 105.

The pre-encoding color transform module 105 is for performing color pre-processing of video signals prior to inputting the same to the video encoder 100. The color pre-processing performed by the pre-encoding, color transform module 30 105 is further described herein below. It is to be appreciated that the pre-encoding, color transform module 105 may be omitted in some embodiments.

An input of the pre-encoding color transform module 105 and an input of the video encoder 100 are available as inputs of the video encoding apparatus 199.

An output of the pre-encoding, color transform module 105 is connected in signal communication with the input of the video encoder 100.

The input of the video encoder 100 is connected in signal communication with a non-inverting input of a summing junction 110. The output of the summing junction 110 is connected in signal communication with a transformer/quantizer 120. The output of the transformer/quantizer 120 is connected in signal communication with an entropy coder 140. An output of the entropy coder 140 is available as an output of the video encoder 100 and also as an output of the video encoding apparatus 199.

The output of the transformer/quantizer 120 is further connected in signal communication with an inverse transformer/quantizer 150. An output of the inverse transformer/quantizer 150 is connected in signal communication with an input of a deblock filter 160. An output of the deblock filter 160 is connected in signal communication with reference picture stores 170. A first output of the reference picture stores 170 is connected in signal communication with a first input of a motion and spatial prediction estimator 180. The input to the video encoder 100 is further connected in signal communication with a second input of the motion and spatial prediction estimator 180. The output of the motion and spatial prediction estimator 180 is connected in signal communication with a first input of a motion and spatial prediction compensator 190. A second output of the reference picture stores 170 is connected in signal communication with a second input of the motion and spatial compensator 190. The output of the motion and spatial compensator 190 is connected in signal communication with an inverting input of the summing junction 110.

Turning to FIG. 2, an exemplary video decoding apparatus is indicated generally by the reference numeral 299. The video decoding apparatus 299 includes a video decoder 200 and a post-decoder, inverse color transform module 293.

An input of the video decoder 200 is available as an input of the video decoding apparatus 299. The input to the video decoder 200 is connected in signal communication with an input of the entropy decoder 210. A first output of the entropy decoder 210 is connected in signal communication with an input of an inverse quantizer/transformer 220. An output of the inverse quantizer/transformer

220 is connected in signal communication with a first input of a summing junction 240.

The output of the summing junction 240 is connected in signal communication with a deblock filter 290. An output of the deblock filter 290 is connected in signal communication with reference picture stores 250. The reference picture store 250 is connected in signal communication with a first input of a motion and spatial prediction compensator 260. An output of the motion spatial prediction compensator 260 is connected in signal communication with a second input of the summing junction 240. A second output of the entropy decoder 210 is connected in signal communication with a second input of the motion compensator 260. The output of the deblock filter 290 is available as an output of the video decoder 200 and also as an output of the video decoding apparatus 299.

Moreover, an output of the post-decoding, inverse color transform module 293 may be available as an output of the video decoding apparatus 299. In such a case, the output of the video decoder 200 may be connected in signal communication with an input of the post-decoding, inverse color transform module 293, which is a post-processing module with respect to the video decoder 200. An output of the post-decoding, inverse color transform module 293 provides a post-processed, inverse color transformed signal with respect to the output of the video decoder 200. It is to be appreciated that use of the post-decoding, inverse color transform module 293 is optional.

A description is now presented for enhanced 4:4:4 coding in accordance with the principles of the present invention. A first described embodiment is a combined embodiment in which the luma coding algorithm is used for all color components, the same spatial prediction mode is used for all color components, and the Residual Color Transform (RCT) is omitted from inside the compression loop. Test results for this combined embodiment are also provided. Subsequently thereafter, a second combined embodiment is described wherein the luma coding algorithm is used for all color components, a set (or subset) of restricted spatial predictors is used for all color components (instead of a single spatial prediction mode), and the Residual Color Transform (RCT) is omitted from inside the compression loop. Thus, a difference between the first and second combined embodiments is the use of a single spatial prediction mode for all color components in the first combined embodiment versus the use of a set (or subset) of restricted spatial predictors for all

color components in the second combined embodiment. Of course, as noted above, the embodiments described herein may be implemented as stand alone embodiments or may be combined in any manner, as readily appreciated by one of ordinary skill in this and related arts. For example, in accordance with the principles 5 of the present invention as configured in an embodiment, only a single spatial prediction mode is used, without combination with other embodiments such as the omission of RCT from the compression loop. It is to be appreciated that given the teachings of the present principles provided herein, these and other variations, implementations, and combinations of the embodiments of the present invention will 10 be readily ascertainable by one of ordinary skill in this and related arts, while maintaining the scope of the present invention.

Turning to FIG. 3, an exemplary video encoding process with a pre-encoding, color transform block, are indicated generally by the reference numerals 300 and 301, respectively.

15 It is to be appreciated that the pre-encoding, color transform block 301 includes blocks 306, 308, and 310. Moreover, it is to be appreciated that the pre-encoding, color transform block 301 is optional and, thus, may be omitted in some embodiments of the present invention.

20 The pre-encoding, color transform block 301 includes a loop limit block 306 that begins a loop for each block in an image, and passes control to a function block 308. The function block 308 performs color pre-processing of the video signal data of the current image block, and passes control to a loop limit block 310. The loop limit block 310 ends the loop. Moreover, the loop limit block 310 passes control to a loop limit block 312, the latter being included in the video encoding process 300.

25 The loop limit block 312 begins a loop for each block in the image, and passes control to a function block 315. The function block 315 forms a motion compensated or spatial prediction of the current image block using a common predictor for each color component of the current image block, and passes control to a function block 320. The function block 320 subtracts the motion compensated or 30 spatial prediction from the current image block to form a prediction residual, and passes control to a function block 330. The function block 330 transforms and quantizes the prediction residual, and passes control to a function block 335. The function block 335 inverse transforms and quantizes the prediction residual to form a coded prediction residual, and passes control to a function block 345. The function

block 345 adds the coded residual to the prediction to form a coded picture block, and passes control to an end loop block 350. The end loop block 350 ends the loop and passes control to an end block 355.

Turning to FIG. 4, an exemplary video decoding process with a post-decoding, inverse color transform block, are indicated generally by the reference numerals 400 and 460, respectively.

It is to be appreciated that the post-decoding, inverse color transform block 460 includes blocks 462, 464, 466, and 468. Moreover, it is to be appreciated that the post-decoding, inverse color transform block 460 is optional and, thus, may be omitted in some embodiments of the present invention.

The decoding process 400 includes a loop limit block 410 that begins a loop for a current block in an image, and passes control to a function block 415. The function block 415 entropy decodes the coded residual, and passes control to a function block 420. The function block 420 inverse transforms and quantizes the decoded residual to form a coded residual, and passes control to a function block 430. The function block 430 adds the coded residual to the prediction formed from a common predictor for each color component to form a coded picture block, and passes control to a loop limit block 435. The loop limit block 435 ends the loop and passes control to an end block 440.

In some embodiments, the loop limit block 435 optionally passes control to the post-decoding, inverse color transform block 460, in particular, the loop limit block 462 included in the post-decoding, inverse color transform block 460. The loop limit block 462 begins a loop for each block in an image, and passes control to a function block 464. The function block 464 performs an inverse color post-processing of the video signal data of the current image block, and passes control to a loop limit block 466. The loop limit block 466 ends the loop, and passes control to an end block 468.

In the H.264 4:4:4 format, every component channel has full resolution. Thus, in accordance with the first combined embodiment set forth above, the luma coding algorithm is used on every color component to achieve the maximum overall compression efficiency. Accordingly, in the embodiment, for intra frames, every color component may be compressed, e.g., using those prediction modes listed in Table 8-2, Table 8-3, and Table 8-4 in ISO/IEC 14496 10 Advanced Video Coding

3rd Edition (ITU-T Rec. H.264), ISO/IEC JTC1/SC29/WG11 and ITU-T SG16 Q.6, Document N6540, July 2004.

In addition, in the embodiment, the same spatial prediction mode is used for all three pixel components, to further reduce the complexity of the codec and

5 improve performance. For example, the prediction mode set by the prev_intra4x4_pred_mode_flag, rem_intra4x4_pred_mode, prev_intra8x8_pred_mode_flag, and rem_intra8x8_pred_mode parameters for the luma in the macroblock prediction header may be used by all three components.

Therefore, no extra bits and syntax elements are needed. For the B and P 10 (predictive) frames, the reference pixels at fractional pixel locations may be calculated by the interpolation methods described in Section 8.4.2.2.1 of the H.264 standard for all three channels. The detailed syntax and semantic changes to the current H.264 standard are further discussed herein below.

Residual Color Transform (RCT) was added to the encoder/decoder in the 15 High 4:4:4 Profile. As a result, the compression structure for the 4:4:4 format is different from the one currently used in all of the other profiles in the H.264 standard for 4:2:0 and 4:2:2 formats. This results in some extra complexity to the implementation. Moreover, similar to any other color transforms, YCOCG does not always improve the overall compression performance. The effectiveness of YCOCG 20 is highly content dependent. Thus, to improve the overall compression and robustness, in the embodiment, the color transform is placed outside of the prediction loop as a part of the preprocessing block. By doing this, selecting an optimum color transform for a specific compression task is an operational issue and the best answer for a particular input sequence could be found among a number of 25 options. In accordance with an embodiment where all three components are using the same spatial predictors for the intra frames and the same interpolation filters for the B and P (predictive or inter-coded) frames, having the color transform performed on the prediction residues is identical to performing the color transform on the source images outside of the codec when the rounding/truncation errors are ignored.

30 This will be discussed further herein below. Thus, the RCT block is removed from the coding structure to make the coding structure consistent among all of the color formats.

Turning to FIG. 5, a simplified model of RCT is indicated generally by the reference numeral 500. The RCT model 500 includes a reference pixel generator

510, a summing junction 520, and a linear transform module 530. Inputs to the reference pixel generator 510 are configured to receive motion/edge information and vectors $[X_1], [X_2], \dots, [X_n]$. An output of the reference pixel generator 510 is connected in signal communication with an inverting input of the summing junction

5 520, which provides prediction vector $[X_p]$ thereto. A non-inverting input of the summing junction 520 is configured to receive input vector $[X_{in}]$. An output of the summing junction 520 is connected in signal communication with an input of the linear transform module 530, which provides vector $[X_d]$ thereto. An output of the linear transform module 530 is configured to provide vector $[Y_d]$.

10 In the simplified model of RCT 500, the color transform represented by a 3x3 matrix $[A]$ (a linear transform) is defined as follows:

$$\begin{bmatrix} Y \\ u \\ v \end{bmatrix} = [A] \begin{bmatrix} R \\ G \\ B \end{bmatrix} \quad (1)$$

15 The $[X_{in}], [X_d], [X_p], [X_1], [X_2], \dots, [X_n]$ are 3x1 vectors representing the pixels in the RGB domain. The $[Y_d]$ is a 3x1 vector representing the result of the color transform. Therefore,

$$[Y_d] = [A][X_d] = [A][X_{in}] - [A][X_p] \quad (2)$$

20 Since, in the embodiment, the same spatial predictors and interpolation filters are used for all three components in a macroblock in accordance with the principles of the present invention as configured in an embodiment, the reference pixel $[X_p]$ can be expressed as follows:

25

$$[X_p] = [X_1 \ X_2 \ X_3 \ \dots \ X_n] \begin{bmatrix} c_1 \\ c_2 \\ c_3 \\ \vdots \\ c_n \end{bmatrix} = \begin{bmatrix} R_1 & R_2 & R_3 & \dots & R_n \\ G_1 & G_2 & G_3 & \dots & G_n \\ B_1 & B_2 & B_3 & \dots & B_n \end{bmatrix} \begin{bmatrix} c_1 \\ c_2 \\ c_3 \\ \vdots \\ c_n \end{bmatrix}, \quad (3)$$

where a $nx1$ vector $[C]$ represents the linear operations involved in the spatial predictors and interpolation filters defined in the H.264 standard. Here, it is presumed that the reference pixel is calculated by using a total number of n neighboring pixels $[X_1], [X_2], \dots, [X_n]$.

5 Substituting $[X_p]$ in equation (3) into equation (2) results in the following:

$$[Y_d] = [A][X_{in}] - [A] \begin{pmatrix} R_1 & R_2 & R_3, \dots, R_n \\ G_1 & G_2 & G_3, \dots, G_n \\ B_1 & B_2 & B_3, \dots, B_n \end{pmatrix} \begin{bmatrix} c_1 \\ c_2 \\ c_3 \\ \vdots \\ c_n \end{bmatrix}. \quad (4)$$

Ignoring the rounding/truncation errors and assuming the same prediction
10 mode is selected in either the RGB or Y domain results in the following:

$$[Y_d] = [A][X_{in}] - \left([A] \begin{pmatrix} R_1 & R_2 & R_3, \dots, R_n \\ G_1 & G_2 & G_3, \dots, G_n \\ B_1 & B_2 & B_3, \dots, B_n \end{pmatrix} \begin{bmatrix} c_1 \\ c_2 \\ c_3 \\ \vdots \\ c_n \end{bmatrix} \right) = [Y_{in}] - \begin{pmatrix} Y_1 & Y_2 & Y_3, \dots, Y_n \\ u_1 & u_2 & u_3, \dots, u_n \\ v_1 & v_2 & v_3, \dots, v_n \end{pmatrix} \begin{bmatrix} c_1 \\ c_2 \\ c_3 \\ \vdots \\ c_n \end{bmatrix}. \quad (5)$$

Therefore,

15

$$[Y_d] = [Y_{in}] - [Y_1 Y_2 Y_3, \dots, Y_n] \begin{bmatrix} c_1 \\ c_2 \\ c_3 \\ \vdots \\ c_n \end{bmatrix}. \quad (6)$$

Thus, equation (6) clearly shows that using YUV as the input to the
encoder/decoder in accordance with the principles of the present invention as
20 configured in this embodiment, is identical to performing RCT.

Also, in accordance with the principles of the present invention as configured in an embodiment, a new 4:4:4 profile is added to the H.264 standard, referred to herein as "Advanced 4:4:4 Profile with profile_idc=166". This new profile_idc may be added in the sequence parameter header, and may be used in the macroblock 5 layer header, as well as the residual data header.

To support using the luma algorithm to code all three color components, some changes may be made to the residual data syntax. In addition, changes may also be made to the semantics of some of the elements in the macroblock header, residue data header, and so forth. In general, the existing syntax for luma in the 10 H.264 specification will remain unchanged and be used to code one of the three components. The changes are backward compatible. The detailed syntax and semantics changes are described herein below.

A description will now be given regarding simulation results performed in accordance with the principles of the present invention as configured in various 15 embodiments.

Turning to FIGs. 6A and 6B, plots of average PSNR versus bit rate for ATV intra-only are indicated generally by the reference numerals 600 and 650, respectively.

Turning to FIGs. 7A and 7B, plots of average PSNR versus bit rate for CT intra-only are indicated generally by the reference numerals 700 and 750, respectively.

Turning to FIGs. 8A and 8B, plots of average PSNR versus bit rate for DT intra-only are indicated generally by the reference numerals 800 and 850.

Turning to FIGs. 9A and 9B, plots of average PSNR versus bit rate for 25 MIR_HD intra-only are indicated generally by the reference numerals 900 and 950, respectively.

Turning to FIGs. 10A and 10B, plots of average PSNR versus bit rate for RT intra-only are indicated generally by the reference numerals 1000 and 1050, respectively.

30 Turning to FIGs. 11A and 11B, plots of average PSNR versus bit rate for STB_HD intra-only are indicated generally by the reference numerals 1100 and 1150.

In particular, FIGs. 6A, 7A, 8A, 9A, 10, and 11A illustrate test results for the proposed Advanced 4:4:4 profile (indicated and preceded by the term "new") versus

approximation results corresponding thereto. Moreover, FIGs. 6B, 7B, 8B, 9B, 10B, and 11B illustrate test results for the proposed Advanced 4:4:4 profile (indicated and preceded by the term "new") versus JPEK2k.

5 In all of FIGs. 6A, 6B through 11A, 11B, the PSNR is indicated in decibels (dB) and the bit rate is indicated in bits per second (bps). ATV, CT, DT, MIR, RT, STB are the names of the test clips.

All JVT/FRExt test sequences described in JVT-J042, Film-Originated Test Sequences, were used in the tests. They are all 4:4:4 10 bit film material and each clip has 58 frames.

10 The proposed advanced 4:4:4 profiles were implemented in the JVT Reference software JM9.6. Both intra-only and IBBP coding structure were used in the tests. The quantization parameter was set at 6, 12, 18, 24, 30, and 42 for each of the R-D curves. The RD-optimized mode selection was used.

15 The proposed Advanced 4:4:4 Profile was also compared with the results that were done by running the reference software with the YUVFormat=0(4:0:0) on every individual input component. Three separate individual compressed bit counts were simply added together to get the total compressed bits for calculating the compressed bit rate.

20 Regarding JPEG2k, KaKadu V2.2.3 software was used in the tests. The test results were generated by using 5 levels of wavelet decompression with the 9/7-tap bi-orthogonal wavelet filter. There was only one tile per frame and the RD-Optimization for a given target rate was also used.

25 All of the PSNR measurements were done in the RGB domain. Average PSNR, defined as $(\text{PSNR}(\text{red}) + \text{PSNR}(\text{green}) + \text{PSNR}(\text{blue})) / 3$, is used to compare the overall compression quality. This is mainly because the JPEG2k compressed data are computed using an unknown rate control algorithm provided by the software. For some cases, the RGB PSNR values are quite far apart from each other, especially when the JPEG2k color transform was used.

30 The compression comparison was performed as follows:

- New1: the proposed Advanced 4:4:4 Profile with a single prediction mode.
- New3: the proposed Advanced 4:4:4 Profile with three prediction modes.
- RCT-OFF: RGB input with RCT=off.
- RCT-ON: RGB input with RCT=on.

- YCOCG: RGB to YCOCG conversion was done outside the codec. Then the converted YCOCG was used as the input to the JVT software.
- R+G+B: Proposed method approximated by compressing the R, G, and B signals separately.
- Y+CO+CG: Proposed method approximated by compressing the converted Y, CO, and CG signals separately.
- J2k_RGB: The JPEG2k compression was done in the RGB domain. The JPEG2k color transform was turned off.
- J2k_YUV: The JPEG2k compression was done in the YUV domain. The JPEG2k color transform was used.

According to the test results, an implementation in accordance with the principles of the present invention as configured in an embodiment, in general, is very similar to JPEG2k in terms of overall compression efficiency. In some cases, it is even slightly better.

Further, an implementation in accordance with the principles of the present invention as configured in an embodiment, provides significantly greater performance (compression) than the current High 4:4:4 Profile for quality above 40 dB (PSNR). Specifically, New1-YCOCG or New3-YCOCG is better than YCOCG and RCT-ON; New1-RGB or New3-RGB is better than RCT-OFF. At a PSNR equal to and greater than 45 dB (PSNR), the average improvement in the average PSNR is more than 1.5 dB. In the last example, the improvement can be translated to more than 25% bit savings at a PSNR equal to 45 dB.

According to the test results, it seems that color transforms will help the coding performance when the content is more color saturated, such as TP, RT. That is, if the color is neutral and less saturated, coding in the RGB domain might be the right choice. The above observation is independent from what color transform is used.

Comparing the results of New1-YCOCG or New3-YCOCG and JPEG-2k_YUV, it has been observed that the performance of a specific color transform in terms of improving coding efficiency is very content dependent. No single color transform is always the best. Therefore, our data confirmed that having a color transform, such as RCT, inside the encoding (or decoding) loop might not be a good idea. Instead, performing the color transform, if it is necessary, outside the encoder/decoder could make the entire compression system provide a better and more robust performance.

Comparing YCOCG with RCT-ON, the test results do not show any coding efficiency improvement from RCT. In addition, it should be noted that running the reference software with the RCT turned on significantly increased the coding time. The running time was more than 2.5 times longer.

5 A description will now be given regarding syntax and semantics changes in accordance with the principles of the present invention as configured in an embodiment.

Turning to FIG. 12, a table for H.264 sequence parameter syntax is indicated generally by the reference numeral 1200. Changes to the syntax in accordance with 10 the principles of the present invention as configured in an embodiment, are indicated by italic text.

Turning to FIG. 13, a table for H.264 residual data syntax is indicated generally by the reference numeral 1300. Additions/changes to the syntax in accordance with the principles of the present invention as configured in an 15 embodiment, are indicated by italic text. In the table 1300, the luma section in the residual data header along with some necessary text modifications are repeated twice to support the luma1 and luma2, respectively.

As noted above, the above described first combined embodiment was evaluated and tested by implementing the present principles in the JVT reference 20 software JM9.6. The test results marked with New1-RGB or New1-YCOCG represent the first combined embodiment.

As noted above, in accordance with the principles of the present invention as configured in an embodiment, a set (or subset) of three (3) restricted spatial predictors is utilized for the component channels (e.g., RGB, YUV, YCrCb formats, 25 and so forth) instead of a single spatial prediction mode. Moreover, as noted above, this embodiment may be combined with other embodiments described herein, such as, e.g., the use of only the luma coding algorithm to code all three component channels of content and/or the use of color transformation as a pre-processing step.

A description will now be given regarding the above described second 30 combined embodiment involving the use of a set (or subset) of three (3) restricted spatial predictors for the color components, the use of only the luma coding algorithm to code all three color components, and the use of color transformation as a pre-processing step (i.e., no RCT within the compression loop). Some variations of this embodiment will also be described there with.

Turning to FIG. 14, an exemplary video encoding process with a pre-encoding, color transform step are indicated generally by the reference numerals 1400 and 1401, respectively.

It is to be appreciated that the pre-encoding, color transform block 1401 includes blocks 1406, 1408, and 1410. Moreover, it is to be appreciated that the pre-encoding, color transform block 1401 is optional and, thus, may be omitted in some embodiments of the present invention.

The pre-encoding, color transform block 1401 includes a loop limit block 1406 that begins a loop for each block in an image, and passes control to a function block 1408. The function block 1408 performs color pre-processing of the video signal data of the current image block, and passes control to a loop limit block 1410. The loop limit block 1410 ends the loop. Moreover, the loop limit block 1410 passes control to a loop limit block 1412, the latter being included in the video encoding process 1400.

The loop limit block 1412 begins a loop for each block in the image, and passes control to a function block 1415. The function block 1415 forms a motion compensated or spatial prediction of the current image block using a common predictor for each color component of the current image block, and passes control to a function block 1420. The function block 1420 subtracts the motion compensated or spatial prediction from the current image block to form a prediction residual, and passes control to a function block 1430. The function block 1430 transforms and quantizes the prediction residual, and passes control to a function block 1435. The function block 1435 inverse transforms and quantizes the prediction residual to form a coded prediction residual, and passes control to a function block 1445. The function block 1445 adds the coded residual to the prediction to form a coded picture block, and passes control to an end loop block 1450. The end loop block 1450 ends the loop and passes control to an end block 1455.

Turning to FIG. 15, an exemplary video decoding process with a post-decoding, inverse color transform step are indicated generally by the reference numerals 1500 and 1560, respectively.

It is to be appreciated that the post-decoding, inverse color transform block 1560 includes blocks 1562, 1564, 1566, and 1568. Moreover, it is to be appreciated that the post-decoding, inverse color transform block 1560 is optional and, thus, may be omitted in some embodiments of the present invention.

The decoding process 1500 includes a loop limit block 1510 that begins a loop for a current block in an image, and passes control to a function block 1515. The function block 1515 entropy decodes the coded residual, and passes control to a function block 1520. The function block 1520 inverse transforms and quantizes 5 the decoded residual to form a coded residual, and passes control to a function block 1530. The function block 1530 adds the coded residual to the prediction formed from a common predictor for each color component to form a coded picture block, and passes control to a loop limit block 1535. The loop limit block 1535 ends the loop and passes control to an end block 1540.

10 In some embodiments, the loop limit block 1535 optionally passes control to the post-decoding, inverse color transform block 1560, in particular, the loop limit block 1562 included in the post-decoding, inverse color transform block 1560. The loop limit block 1562 begins a loop for each block in an image, and passes control to a function block 1564. The function block 1564 performs an inverse color post- 15 processing of the video signal data of the current image block, and passes control to a loop limit block 1566. The loop limit block 1566 ends the loop, and passes control to an end block 1568.

As noted above, a new profile (profile_idc=166) for the Advanced 4:4:4 Profile is disclosed. This new profile may also be used for the second combined 20 embodiment, with corresponding semantic and syntax changes as described herein below for the second combined embodiment. This new profile_idc is added in the Sequence Parameter Set and will be mainly used in the subsequent headers to indicate that the input format is 4:4:4 and all three input channels are coded similarly as luma.

25 To minimize the necessary changes to the H.264 standard, no new macroblock type is disclosed for the Advanced 4:4:4 Profile. Instead, all of the macroblock types along with the associated coding parameters listed in Table 7-11, Table 7-13, and Table 7-14 of the H.264 standard are still valid. For the case of intra macroblocks, all three input channels, luma, Cr, and Cb, will be encoded based on 30 the MbPartPredMode defined in Table 7-11 of the H.264 standard. For example, an Intra_4x4 macroblock in the Advanced 4:4:4 Profile means every input component channel may be encoded by using all of the 9 possible prediction modes given in Table 8-2 of the H.264 standard. For reference, in the current High 4:4:4 Profile, two of the channels for an Intra_4x4 macroblock will be treated as chroma and only one

of the 4 possible intra prediction mode in Table 8-5 of the H.264 standard will be used. For the B and P macroblocks, the changes made for the Advanced 4:4:4 Profile occur at the interpolation process for the calculation of the reference pixel value at the fractional pixel location. Here, the procedure described in Section 5 8.4.2.2.1 of the H.264 standard, Luma sample interpolation process, will be applied for luma, Cr, and Cb. Again for reference, the current High 4:4:4 Profile uses Section 8.4.2.2.2 of the H.264 standard, Chroma sample interpolation process, for two of the input channels.

In the case when the CABAC is chosen as the entropy coding mode, two 10 separate sets of context models identical to those currently defined for luma will be created for Cr and Cb. They will also be updated independently during the course of encoding.

Finally, in the embodiment, since there is no RCT block in the coding loop, the ResidueColorTransformFlag is removed from the sequence parameter set in the 15 Advanced 4:4:4 Profile.

Up to this point, most syntax changes occur in the residue data as shown in FIG. 13, where the original syntax for luma are repeated twice to support Cr and Cb in the proposed Advanced 4:4:4 profiles.

Regarding the H.264 macroblock layer table (not shown), semantic changes 20 to the corresponding syntax include the following.

coded_block_pattern (Add). When chroma_format_idc is equal to 3 and coded_block_pattern is present, CodedBlockPatternChroma shall be set to 0. In addition, CodedBlockPatternLuma specifies, for each of the twelve 8x8 luma, Cb, 25 and Cr blocks of the macroblock, one of the following cases : (1) All transform coefficient levels of the twelve 4x4 luma blocks in the 8x8 luma, 8x8 Cb and 8x8 Cr blocks are equal to zero; (2) One or more transform coefficient levels of one or more of the 4x4 luma blocks in the 8x8 luma, 8x8 Cb, and 8x8 Cr blocks shall be non-zero valued.

30 A description will now be given regarding spatial prediction mode selection for the intra blocks in accordance with the second combined embodiment (or the sole embodiment relating to the use of the set (or subset) of three restricted spatial predictors).

For each component to choose its best MbPartPredMode and the subsequent best spatial prediction mode independently, as in the case while encoding each input channel separately, some new intra block types may be added to Table 7-11 of the H.264 standard. As a result, a large amount of changes to the H.264 standard will 5 be made. In an embodiment relating to the second combined embodiment, the current mb_types remain unchanged and an alternative solution is provided. In the embodiment, the three input channels are restricted to be encoded with the same MbPartPredMode or macroblock type. Then, a small amount of new elements are added into the Macroblock Prediction Syntax to support three separate prediction 10 modes. Therefore, each component can still theoretically choose its best spatial prediction mode independently in order to minimize the prediction error for each component channel. For example, assuming an Intra_4x4 macroblock is chosen as the mb_type, luma, Cr, or Cb could still find its own best spatial prediction mode in Table 8-2 in Section 8.3.1.1 of the H.264 standard such as, e.g., Intra_4x4_Vertical 15 for luma, Intra_4_4_Horizontal for Cr, and Intra_4x4_Diagonal_Down_Left for Cb.

Another approach, relating to the first combined embodiment described above, is to constrain all three input channels to share the same prediction mode. This can be done by using the prediction information that is currently carried by the existing syntax elements, such as prev_intra4x4_pre_mode_flag, 20 rem_intra4x4_pred_mode, pre_intra8x8_pred_mode_flag, and rem_intra8x8_pred_mode, in the Macroblock Prediction syntax. This option will result in less change to the H.264 standard and some slight loss of the coding efficiency as well.

Based on the test results, using three prediction modes could improve the 25 overall coding performance by about 0.2 dB over the first combined embodiment.

Turning to FIG. 16, a table for H.264 macroblock prediction syntax is indicated generally by the reference numeral 1700. For reference, the modified Macroblock Prediction Syntax to support using the three prediction modes is listed below, where:

30

prev_intra4x4_pred_mode_flag0 and rem_intra4x4_pred_mode0 are for luma;

prev_intra4x4_pred_mode_flag1 and rem_intra4x4_pred_mode1 are for Cr;

prev_intra4x4_pred_mode_flag2 and rem_intra4x4_pred_mode2 are for Cb;

A description will now be given regarding simulation results performed in accordance with the principles of the present invention as configured in an embodiment, for the second combined embodiment.

All JVT/FRExt test sequences described in JVT-J042, Film-Originated Test Sequence, JVT-J039 (Viper). They are all 4:4:4 10-bit materials and each clip has 58 frames.

10 The proposed algorithm was implemented in the JVT Reference software
JM9.6 and the modified software was used in the tests. Both Intra-only and IBRrBP
were tested. Here, "Br" means the recorded B pictures. The intra-only case was
done for all of the sequences with the quantization parameter equal to 6, 12, 18, 24,
30, 36 and 42. Due to the large amount of time involved in the simulation, the
15 IBRrBP GOP structure was only done for the film clips with a quantization parameter
equal to 12, 18, 24, 30 and 36. According to the discussion in the 4:4:4 AHG, the
following key parameters were used in the tests:

```
SymbolMode = 1
RDOptimization = 1
ScalingMatrixPresentFlag = 0
OffsetMatrixPresentFlag = 1
QoffsetMatrixFile = "q_offset.cfg"
AdaptiveRounding = 1
AdaptRndPeriod = 1
AdaptRndChroma = 1
AdaptRndWFactorX = 8
SearchRange = 64
UseFME = 1
```

30 Regarding JPEG2k, KaKadu V2.2.3 software was used in the tests. The test results were generated by using 5 levels of wavelet decompression with the 9/7-tap bi-orthogonal wavelet filter. There was only one tile per frame and the RD-Optimization for a given target rate was also used.

The PSNR measurements were primarily calculated in the original color domain of the source contents, which is RGB for the clips described above. Average PSNR, defined as $(\text{PSNR}(\text{red}) + \text{PSNR}(\text{green}) + \text{PSNR}(\text{blue})) / 3$, is used to compare the overall compression quality.

5 The compression comparison was performed as follows:

New1: the proposed Advanced 4:4:4 Profile with a single prediction mode.

New3: the proposed Advanced 4:4:4 Profile with three prediction modes.

RCT-OFF: RGB input with RCT=off.

10 RCT-ON: RGB input with RCT=on.

YCOCG: RGB to YCOCG conversion was done outside the codec. Then the converted YCOCG was used as the input to the JVT software.

R+G+B: Proposed method approximated by compressing the R, G, and B signals separately.

15 Y+CO+CG: Proposed method approximated by compressing the converted Y, CO, and CG signals separately.

JPEG2k_RGB: The JPEG2k compression was done in the RGB domain. The JPEG2k color transform was turned off.

20 JPEG2k_YUV: The JPEG2k compression was done in the YUV domain. The JPEG2k color transform was used.

For the Intra-Only case, the proposed Advanced 4:4:4 Profile in accordance with the present principles is very similar to JPEK2k in terms of overall compression efficiency. In some cases, it is even slightly better.

25 The approach in accordance with the principles of the present invention, is clearly better than the current High 4:4:4 Profile. At a PSNR equal to and greater than 45 dB (PSNR), the average improvement in the average PSNR is more than 1.5 dB. In some case, the improvement can be translated to more than 25% bit savings at a PSNR equal to 45 dB.

30 Even with the same block type, using three prediction modes is slightly better than a single one. However, more syntax and semantic changes may be utilized.

A description will now be given of some of the many attendant advantages/features provided by the principles of embodiments of the present invention.

The test results demonstrate that the proposed Advanced 4:4:4 Profile, utilizing the improvements corresponding to the principles of the present invention, delivers improved performance when compared to the current High 4:4:4 Profile. The performance gain is significant. In addition, moving the color transform outside 5 the codec will make the architecture of the codec consistent among all of the color formats. As a result, it will make the implementation easier and reduce the cost. It will also make the codec more robust in terms of selecting the optimum color transform for achieving better coding efficiency. Also, the proposed approach does not add any new coding tools and requires only some slight changes to the syntax 10 and semantics.

Thus, in accordance with the principles of the present invention as configured in an embodiment, a method and apparatus are provided for video encoding and decoding. Modifications to the existing H.264 standard are provided which improve performance beyond that currently achievable. Moreover, performance is improved 15 even beyond JPEG-2000 for high quality applications. In accordance with the principles of the present invention as configured in an embodiment, significant 4:4:4 coding performance improvements in the H.264 standard can be achieved by using the luma coding algorithm to code all of the three color components of 4:4:4 content. That is, no new tools are necessary for the luma (or chroma, which is not used) 20 compression algorithm. Instead, the existing luma coding tools are utilized. Further, syntax and semantic changes to the current 4:4:4 profile may be implemented in accordance with the present principles to support the luma coding of all three component channels. In tests conducted in accordance with an embodiment of the present invention, when the source content has lots of spatial textures and edges, 25 the spatial prediction tools used in luma clearly exhibited their superior performance to those used in chroma. For some of the test sequences, when every color component was encoded as luma, more than a 30% bit reduction was observed at a compressed quality greater than or equal to 45dB(Average PSNR).

It is to be appreciated that while the present invention has primarily been 30 described herein with respect to video signal data sampled using the 4:4:4 format of the H.264 standard, the present invention may also be readily implemented with respect to video signal data sampled using other formats (e.g., the 4:2:0 format and/or the 4:2:2 format) of the H.264 standard, as well as other video compression standards. Given the teachings of the present invention provided herein, these and

other variations of the present invention may also be readily implemented by one of ordinary skill in this and related arts, while maintaining the scope of the present invention.

These and other features and advantages of the present invention may be 5 readily ascertained by one of ordinary skill in the pertinent art based on the teachings herein. It is to be understood that the teachings of the present invention may be implemented in various forms of hardware, software, firmware, special purpose processors, or combinations thereof.

Most preferably, the teachings of the present invention are implemented as a 10 combination of hardware and software. Moreover, the software may be implemented as an application program tangibly embodied on a program storage unit. The application program may be uploaded to, and executed by, a machine comprising any suitable architecture. Preferably, the machine is implemented on a computer platform having hardware such as one or more central processing units 15 ("CPU"), a random access memory ("RAM"), and input/output ("I/O") interfaces. The computer platform may also include an operating system and microinstruction code. The various processes and functions described herein may be either part of the microinstruction code or part of the application program, or any combination thereof, which may be executed by a CPU. In addition, various other peripheral units may be 20 connected to the computer platform such as an additional data storage unit and a printing unit.

It is to be further understood that, because some of the constituent system 25 components and methods depicted in the accompanying drawings are preferably implemented in software, the actual connections between the system components or the process function blocks may differ depending upon the manner in which the present invention is programmed. Given the teachings herein, one of ordinary skill in the pertinent art will be able to contemplate these and similar implementations or configurations of the present invention.

Although the illustrative embodiments have been described herein with 30 reference to the accompanying drawings, it is to be understood that the present invention is not limited to those precise embodiments, and that various changes and modifications may be effected therein by one of ordinary skill in the pertinent art without departing from the scope or spirit of the present invention. All such changes

and modifications are intended to be included within the scope of the present invention as set forth in the appended claims.

CLAIMS:

1. A video encoder for encoding video signal data for an image block, the video encoder comprising an encoder (100) for encoding the video signal data using unique predictors for each of color components of the video signal data.
5
2. The video encoder of claim 1, wherein the unique predictors are used to encode the video signal data irrespective of whether the video signal data is partitioned using a common block partition or a multiple block partition.
10
3. The video encoder of claim 1, wherein the unique predictors are all luma predictors.
15
4. The video encoder of claim 1, wherein the unique predictors consist of unique luma predictors used for both luma and chroma components of the video signal data.
20
5. The video encoder of claim 1, wherein sampling of the video signal data corresponds to any of the 4:4:4, 4:2:2 and 4:2:0 formats of the International Telecommunication Union, Telecommunication Sector H.264 standard.
25
6. The video encoder of claim 1, wherein the unique predictors are used for both intra and inter coding of the video signal data.
30
7. The video encoder of claim 1, wherein a first spatial prediction mode for a first one of the color components is set by prev_intra4x4_pred_mode_flag0 and rem_intra4x4_pred_mode0 parameters, a second prediction mode for a second one of the color components is set by prev_intra4x4_pred_mode_flag1 and rem_intra4x4_pred_mode1 parameters, and a third prediction mode for a third one of the color components is set by prev_intra4x4_pred_mode_flag2 and rem_intra4x4_pred_mode2 parameters of the International Telecommunication Union, Telecommunication Sector H.264 standard.

8. The video encoder of claim 1, wherein said encoder (100) encodes all of the color components of the video signal data without applying a residual color transform thereto.

5 9. A method for encoding video signal data for an image block, the method comprising encoding (1415) the video signal data using unique predictors for each of color components of the video signal data.

10 10. The method of claim 9, wherein the unique predictors are used to encode the video signal data irrespective of whether the video signal data is partitioned using a common block partition or a multiple block partition.

15 11. The method of claim 9, wherein the unique predictors are all luma predictors.

12. The method of claim 9, wherein the unique predictors consist of unique luma predictors used for both luma and chroma components of the video signal data.

20 13. The method of claim 9, wherein sampling of the video signal data corresponds to any of the 4:4:4, 4:2:2 and 4:2:0 formats of the International Telecommunication Union, Telecommunication Sector H.264 standard.

25 14. The method of claim 9, wherein the unique predictors are used for both intra and inter coding of the video signal data.

15. The method of claim 9, wherein a first spatial prediction mode for a first one of the color components is set by prev_intra4x4_pred_mode_flag0 and rem_intra4x4_pred_mode0 parameters, a second prediction mode for a second one 30 of the color components is set by prev_intra4x4_pred_mode_flag1 and rem_intra4x4_pred_mode1 parameters, and a third prediction mode for a third one of the color components is set by prev_intra4x4_pred_mode_flag2 and rem_intra4x4_pred_mode2 parameters of the International Telecommunication Union, Telecommunication Sector H.264 standard.

16. The method of claim 9, wherein said encoding step encodes all of the color components of the video signal data without applying a residual color transform thereto.

5

17. A video decoder for decoding video signal data for an image block, the video decoder comprising a decoder (200) for decoding the video signal data using unique predictors for each of color components of the video signal data.

10 18. The video decoder of claim 17, wherein the unique predictors are used to decode the video signal data irrespective of whether the video signal data is partitioned using a common block partition or a multiple block partition.

15 19. The video decoder of claim 17, wherein the unique predictors are all luma predictors.

20. The video decoder of claim 17, wherein the unique predictors consist of unique luma predictors used for both luma and chroma components of the video signal data.

20

21. The video decoder of claim 17, wherein sampling of the video signal data corresponds to any of the 4:4:4, 4:2:2 and 4:2:0 formats of the International Telecommunication Union, Telecommunication Sector H.264 standard.

25

22. The video decoder of claim 17, wherein the unique predictors are used for both intra and inter coding of the video signal data.

30

23. The video decoder of claim 17, wherein a first spatial prediction mode for a first one of the color components is set by prev_intra4x4_pred_mode_flag0 and rem_intra4x4_pred_mode0 parameters, a second prediction mode for a second one of the color components is set by prev_intra4x4_pred_mode_flag1 and rem_intra4x4_pred_mode1 parameters, and a third prediction mode for a third one of the color components is set by prev_intra4x4_pred_mode_flag2 and

rem_intra4x4_pred_mode2 parameters of the International Telecommunication Union, Telecommunication Sector H.264 standard.

24. The video decoder of claim 17, wherein said decoder (200) decodes all 5 of the color components of the video signal data without applying a residual color transform thereto.

25. A method for decoding video signal data for an image block, the method comprising decoding (1415) the video signal data using unique predictors for 10 each of color components of the video signal data.

26. The method of claim 25, wherein the unique predictors are used to decode the video signal data irrespective of whether the video signal data is partitioned using a common block partition or a multiple block partition.

15 27. The method of claim 25, wherein the unique predictors are all luma predictors.

28. The method of claim 25, wherein the unique predictors consist of 20 unique luma predictors used for both luma and chroma components of the video signal data.



29. The method of claim 25, wherein sampling of the video signal data corresponds to any of the 4:4:4, 4:2:2 and 4:2:0 formats of the International 25 Telecommunication Union, Telecommunication Sector H.264 standard.

30. The method of claim 25, wherein the unique predictors are used for both intra and inter coding of the video signal data.


31. The method of claim 25, wherein a first spatial prediction mode for a first one of the color components is set by prev_intra4x4_pred_mode_flag0 and rem_intra4x4_pred_mode0 parameters, a second prediction mode for a second one 5 of the color components is set by prev_intra4x4_pred_mode_flag1 and rem_intra4x4_pred_mode1 parameters, and a third prediction mode for a third one of the color components is set by prev_intra4x4_pred_mode_flag2 and rem_intra4x4_pred_mode2 parameters of the International Telecommunication Union, Telecommunication Sector H.264 standard.

10


32. The method of claim 25, wherein said decoding step decodes all of the color components of the video signal data without applying a residual color transform thereto.




2/18

**FIG. 3**

3/18

**FIG. 4**

**FIG. 5**


1200

seq_parameter_set_rbsp()	C	Descriptor
profile_idc	0	u(8)
constraint_set0_flag	0	u(1)
constraint_set1_flag	0	u(1)
constraint_set2_flag	0	u(1)
constraint_set3_flag	0	u(1)
reserved_zero_4bits /* equal to 0 */	0	u(4)
level_idc	0	u(8)
seq_parameter_set_id	0	ue(v)
if(profile_idc == 100 profile_idc == 110 profile_idc == 122 profile_idc == 166 profile_idc == 188){		
chroma_format_idc	0	ue(v)
bit_depth_luma_minus8	0	ue(v)


FIG. 12

5/18

600


**FIG. 6A**

650


**FIG. 6B**



6/18



700

**FIG. 7A**

750


**FIG. 7B**

**FIG. 8A****FIG. 8B**


**FIG. 9A****FIG. 9B**



9/18

1000

**FIG. 10A**

1050

**FIG. 10B**

**FIG. 11A****FIG. 11B**

11/18

FIG. 13

FIG. 13A
FIG. 13B
FIG. 13C
FIG. 13D

FIG. 13A

Residual()	C	Descriptor
if(!entropy_coding_mode_flag)		
residual_block = residual_block_cavlc		
else		
residual_block = residual_block_cabac		
if(MbPartPredMode(mb_type, 0) == Intra_16x16)		
residual_block(Intra16x16DCLevel, 16)	3	
for(i8x8 = 0; i8x8 < 4; i8x8++) /* each luma 8x8 block */		
if(!transform_size_8x8_flag !entropy_coding_mode_flag)		
for(i4x4 = 0; i4x4 < 4; i4x4++) { /* each 4x4 sub-block of block */		
if(CodedBlockPatternLuma & (1 << i8x8))		
if(MbPartPredMode(mb_type, 0) == Intra_16x16)		
residual_block(Intra16x16ACLevel[i8x8 * 4 + i4x4], 15)	3	
else		
residual_block(LumaLevel[i8x8 * 4 + i4x4], 16)	3 4	
else if(MbPartPredMode(mb_type, 0) == Intra_16x16)		
for(i = 0; i < 15; i++)		
Intra16x16ACLevel[i8x8 * 4 + i4x4][i] = 0		
else		
for(i = 0; i < 16; i++)		
LumaLevel[i8x8 * 4 + i4x4][i] = 0		
if(!entropy_coding_mode_flag && transform_size_8x8_flag)		
for(i = 0; i < 16; i++)		
LumaLevel8x8[i8x8][4 * i + i4x4] =		
LumaLevel[i8x8 * 4 + i4x4][i]		
}		

12/18

FIG. 13B

else if(CodedBlockPatternLuma & (1 << i8x8))		
residual_block(LumaLevel8x8[i8x8], 64)	3 4	
else		
for(i = 0; i < 64; i++)		
LumaLevel8x8[i8x8][i] = 0		
if(chroma_format_idc == 1 chroma_format_idc == 2) {		
NumC8x8 = 4 / (SubWidthC * SubHeightC)		
for(iCbCr = 0; iCbCr < 2; iCbCr++)		
if(CodedBlockPatternChroma & 3) /* chroma DC residual present */		
residual_block(ChromaDCLevel[iCbCr], 4 * NumC8x8)	3 4	
else		
for(i = 0; i < 4 * NumC8x8; i++)		
ChromaDCLevel[iCbCr][i] = 0		
for(iCbCr = 0; iCbCr < 2; iCbCr++)		
for(i8x8 = 0; i8x8 < NumC8x8; i8x8++)		
for(i4x4 = 0; i4x4 < 4; i4x4++)		
if(CodedBlockPatternChroma & 2)		
/* chroma AC residual present */		
residual_block(ChromaACLevel[iCbCr][i8x8*4+i4x4], 15)	3 4	
else		
for(i = 0; i < 15; i++)		
ChromaACLevel[iCbCr][i8x8*4+i4x4][i] = 0		
} else if(chroma_format_idc == 3) {		
if(MbPartPredMode(mb_type, 0) == Intra_16x16) /*Cb for 4:4:4*/		
residual_block(CbIntra16x16DCLevel, 16)	3	
for(i8x8 = 0; i8x8 < 4; i8x8++) /* each Cb 8x8 block */		
if(!transform_size_8x8_flag !entropy_coding_mode_flag)		
for(i4x4 = 0; i4x4 < 4; i4x4++) { /* each 4x4 sub-block of block */		
if(CodedBlockPatternLuma & (1 << i8x8))		

13/18


FIG. 13C

if(MbPartPredMode(mb_type, 0) == Intra_16x16)		
residual_block(CbIntra16x16ACLevel[i8x8*4+i4x4],15)	3	
else		
residual_block(CbLevel[i8x8 * 4 + i4x4], 16)	3 4	
else if(MbPartPredMode(mb_type, 0) == Intra_16x16)		
for(i = 0; i < 15; i++)		
CbIntra16x16ACLevel[i8x8 * 4 + i4x4][i] = 0		
else		
for(i = 0; i < 16; i++)		
CbLevel[i8x8 * 4 + i4x4][i] = 0		
if(!entropy_coding_mode_flag && transform_size_8x8_flag)		
for(i = 0; i < 16; i++)		
CbLevel8x8[i8x8][4 * i + i4x4] =		
CbLevel[i8x8 * 4 + i4x4][i]		
}		
else if(CodedBlockPatternLuma & (1 << i8x8))		
residual_block(CbLevel8x8[i8x8], 64)	3 4	
else		
for(i = 0; i < 64; i++)		
CbLevel8x8[i8x8][i] = 0		
if(MbPartPredMode(mb_type, 0) == Intra_16x16) /*Cr for 4:4:4 */		
residual_block(CrIntra16x16DCLevel, 16)	3	
for(i8x8 = 0; i8x8 < 4; i8x8++) /* each Cr 8x8 block */		
if(!transform_size_8x8_flag !entropy_coding_mode_flag)		
for(i4x4 = 0; i4x4 < 4; i4x4++) { /* each 4x4 sub-block of block */		
*/		
if(CodedBlockPatternLuma & (1 << i8x8))		
if(MbPartPredMode(mb_type, 0) == Intra_16x16)		
residual_block(CrIntra16x16ACLevel[i8x8*4+i4x4],15)	3	
else		


14/18

FIG. 13D

residual_block(CrLevel[i8x8 * 4 + i4x4], 16)	3 4	
else if(MbPartPredMode(mb_type, 0) == Intra_16x16)		
for(i = 0; i < 15; i++)		
CrIntra16x16ACLevel[i8x8 * 4 + i4x4][i] = 0		
else		
for(i = 0; i < 16; i++)		
CrLevel[i8x8 * 4 + i4x4][i] = 0		
if(!entropy_coding_mode_flag && transform_size_8x8_flag)		
for(i = 0; i < 16; i++)		
CrLevel8x8[i8x8][4 * i + i4x4] =		
CrLevel[i8x8 * 4 + i4x4][i]		
}		
else if(CodedBlockPatternLuma & (1 << i8x8))		
residual_block(CrLevel8x8[i8x8], 64)	3 4	
else		
for(i = 0; i < 64; i++)		
CrLevel8x8[i8x8][i] = 0		
}		



16/18

**FIG. 15**

17/18

FIG. 161600**FIG. 16A****FIG. 16A****FIG. 16B**

mb_pred(mb_type) {	C	Descriptor
if(MbPartPredMode(mb_type, 0) == Intra_4x4		
MbPartPredMode(mb_type, 0) == Intra_8x8		
MbPartPredMode(mb_type, 0) == Intra_16x16) {		
if(profile_idc != 166) {		
if(MbPartPredMode(mb_type, 0) == Intra_4x4)		
for(luma4x4BblkIdx=0; luma4x4BblkIdx<16; luma4x4BblkIdx++) {		
prev_intra4x4_pred_mode_flag[luma4x4BblkIdx]	2	u(1) ae(v)
if(!prev_intra4x4_pred_mode_flag[luma4x4BblkIdx])		
rem_intra4x4_pred_mode[luma4x4BblkIdx]	2	u(3) ae(v)
}		
if(MbPartPredMode(mb_type, 0) == Intra_8x8)		
for(luma8x8BblkIdx=0; luma8x8BblkIdx<4; luma8x8BblkIdx++) {		
prev_intra8x8_pred_mode_flag[luma8x8BblkIdx]	2	u(1) ae(v)
if(!prev_intra8x8_pred_mode_flag[luma8x8BblkIdx])		
rem_intra8x8_pred_mode[luma8x8BblkIdx]	2	u(3) ae(v)
}		
if(chroma_format_idc != 0)		
intra_chroma_pred_mode	2	u(v) ae(v)
} else {		
if(MbPartPredMode(mb_type, 0) == Intra_4x4)		
for(luma4x4BblkIdx=0; luma4x4BblkIdx<16; luma4x4BblkIdx++) {		
prev_intra4x4_pred_mode_flag0[luma4x4BblkIdx]	2	u(1) ae(v)
if(!prev_intra4x4_pred_mode_flag0[luma4x4BblkIdx])		
rem_intra4x4_pred_mode0[luma4x4BblkIdx]	2	u(3) ae(v)
prev_intra4x4_pred_mode_flag1[luma4x4BblkIdx]	2	u(1) ae(v)

FIG. 16B

if(!prev_intra4x4_pred_mode_flag1[luma4x4BlkIdx])		
rem_intra4x4_pred_mode1[luma4x4BlkIdx]	2	u(3) ae(v)
prev_intra4x4_pred_mode_flag2[luma4x4BlkIdx]	2	u(1) ae(v)
if(!prev_intra4x4_pred_mode_flag2[luma4x4BlkIdx])		
rem_intra4x4_pred_mode2[luma4x4BlkIdx]	2	u(3) ae(v)
}		
if(MbPartPredMode(mb_type, 0) == Intra_8x8)		
for(luma8x8BlkIdx=0; luma8x8BlkIdx<4; luma8x8BlkIdx++) {		
prev_intra8x8_pred_mode_flag0[luma8x8BlkIdx]	2	u(1) ae(v)
if(!prev_intra8x8_pred_mode_flag0[luma8x8BlkIdx])		
rem_intra8x8_pred_mode0[luma8x8BlkIdx]	2	u(3) ae(v)
prev_intra8x8_pred_mode_flag1[luma8x8BlkIdx]	2	u(1) ae(v)
if(!prev_intra8x8_pred_mode_flag1[luma8x8BlkIdx])		
rem_intra8x8_pred_mode1[luma8x8BlkIdx]	2	u(3) ae(v)
prev_intra8x8_pred_mode_flag2[luma8x8BlkIdx]	2	u(1) ae(v)
if(!prev_intra8x8_pred_mode_flag2[luma8x8BlkIdx])		
rem_intra8x8_pred_mode2[luma8x8BlkIdx]	2	u(3) ae(v)
}		
}		
} else if(MbPartPredMode(mb_type, 0) != Direct) {		
.....		

INTERNATIONAL SEARCH REPORT

International application No
PCT/US2006/009381

A. CLASSIFICATION OF SUBJECT MATTER
INV. H04N7/26 H04N7/50 H04N7/34

According to International Patent Classification (IPC) or to both national classification and IPC

B. FIELDS SEARCHED

Minimum documentation searched (classification system followed by classification symbols)
H04N

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched

Electronic data base consulted during the international search (name of data base and, where practical, search terms used)

EPO-Internal, COMPENDEX, INSPEC, IBM-TDB

C. DOCUMENTS CONSIDERED TO BE RELEVANT

Category*	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
X	<p>WOO-SHIK KIM, DAE-SUNG CHO, HYUN MUN KIM: "Proposal for the unsolved issues in Professional Extensions II, Document JVT-J018" JOINT VIDEO TEAM (JVT) OF ISO/IEC MPEG & ITU-T VCEG (ISO/IEC JTC1/SC29/WG11 AND ITU-T SG16 Q.6), 10TH JVT MEETING 8-12 DECEMBER, 2003, HAWAII, US, [Online] 8 December 2003 (2003-12-08), pages 1-11, XP002390616 Hawaii, US Retrieved from the Internet: URL:ftp3.itu.int/av-arch/jvt-site/2003_12_Waikoloa/JVT-J018.doc> [retrieved on 2006-07-14] Sections 2.1, 2.2 and 2.3, pages 1-3</p> <p style="text-align: center;">-/-</p>	1-32

Further documents are listed in the continuation of Box C.

See patent family annex.

* Special categories of cited documents :

- *A* document defining the general state of the art which is not considered to be of particular relevance
- *E* earlier document but published on or after the international filing date
- *L* document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)
- *O* document referring to an oral disclosure, use, exhibition or other means
- *P* document published prior to the international filing date but later than the priority date claimed

- *T* later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention
- *X* document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone
- *Y* document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art.
- *&* document member of the same patent family

Date of the actual completion of the international search

24 July 2006

Date of mailing of the international search report

09/08/2006

Name and mailing address of the ISA

European Patent Office, P.B. 5818 Patentlaan 2
NL - 2280 HV Rijswijk
Tel. (+31-70) 340-2040, Tx. 31 651 epo nl,
Fax: (+31-70) 340-3016

Authorized officer

Colesanti, C

INTERNATIONAL SEARCH REPORT

International application No PCT/US2006/009381

C(Continuation). DOCUMENTS CONSIDERED TO BE RELEVANT		
Category*	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
A	<p>SULLIVAN G J ET AL: "The H.264/AVC advanced video coding standard: overview and introduction to the fidelity range extensions" PROCEEDINGS OF THE SPIE, SPIE, BELLINGHAM, VA, US, vol. 5558, November 2004 (2004-11), pages 454-474, XP002340590 ISSN: 0277-786X Section 1.2, pages 455-456 Section 2.1.1, page 460 Section 2.7, pages 467-468 -----</p>	1-32
X	<p>WOO-SHIK KIM,DMITRY BIRINOV,HYUN MUN KIM: "Adaptive Residue Transform and Sampling, Document JVT-K018r1" JOINT VIDEO TEAM (JVT) OF ISO/IEC MPEG & ITU-T VCEG (ISO/IEC JTC1/SC29/WG11 AND ITU-T SG16 Q.6), 11TH JVT MEETING 15-19 MARCH, 2004, MUNICH, GERMANY, [Online] 15 March 2004 (2004-03-15), pages 1-16, XP002390617 Munich, Germany Retrieved from the Internet: URL:ftp3.itu.int/av-arch/jvt-site/2004_03_ Munich/JVT-K018r1.zip> [retrieved on 2006-07-14] Sections 1. and 2., pages 1-3 as well as Table 9-11 -----</p>	1,2,5,9, 10,13, 17,18, 21,25, 26,29
A	<p>GARY SULLIVAN, TOM MCMAHON,THOMAS WIEGAND,DETLEV MARPE,AJAY LUTHRA: "Draft Text of H.264/AVC Fidelity Range Extensions Amendment, Document JVT-L047d2" JOINT VIDEO TEAM (JVT) OF ISO/IEC MPEG & ITU-T VCEG (ISO/IEC JTC1/SC29/WG11 AND ITU T SG16 Q.6), 12TH MEETING 17-23 JULY, 2004, REDMOND, WA, USA, 17 July 2004 (2004-07-17), pages 1-110, XP002390664 REDMOND, WA, USA Subclause 7.3.5.1, page 11 Subclause 7.4.51, page 23 -----</p>	1-32
A	<p>US 5 724 450 A (CHEN ET AL) 3 March 1998 (1998-03-03) column 2, lines 20-30; figures 3a,3b column 5, line 13 - line 18 -----</p>	1-32

INTERNATIONAL SEARCH REPORT

Information on patent family members

International application No

PCT/US2006/009381

Patent document cited in search report	Publication date	Patent family member(s)	Publication date
US 5724450	A 03-03-1998	AU 3685995 A WO 9610882 A1	26-04-1996 11-04-1996