



(86) Date de dépôt PCT/PCT Filing Date: 2016/02/05
(87) Date publication PCT/PCT Publication Date: 2016/08/11
(45) Date de délivrance/Issue Date: 2023/05/23
(85) Entrée phase nationale/National Entry: 2017/07/24
(86) N° demande PCT/PCT Application No.: US 2016/016883
(87) N° publication PCT/PCT Publication No.: 2016/127125
(30) Priorités/Priorities: 2015/02/06 (US62/113,054);
2015/04/24 (US62/152,733)

(51) Cl.Int./Int.Cl. *H01R 13/24* (2006.01),
A61B 5/00 (2006.01), *H01R 13/627* (2006.01),
H01R 13/64 (2006.01), *H01R 13/648* (2006.01)


(72) Inventeurs/Inventors:
SCRUGGS, STEPHEN, US;
AL-ALI, AMMAR, US;
SCHMIDT, JOHN, US;
ABDUL-HAFIZ, YASSIR KAMEL, US;
TRIMAN, BENJAMIN, US;
MACNEISH, WILLIAM III, US

(73) Propriétaire/Owner:
MASIMO CORPORATION, US

(74) Agent: SMART & BIGGAR LP

(54) Titre : ENSEMBLE CONNECTEUR A BROCHES POGO DESTINE A ETRE UTILISE AVEC DES CAPTEURS MEDICAUX

(54) Title: CONNECTOR ASSEMBLY WITH POGO PINS FOR USE WITH MEDICAL SENSORS



(57) Abrégé/Abstract:

Various connector and sensor assemblies are described. In some embodiments, the connector and sensor assembly comprises a connector and a sensor assembly. The connector can have an opening that has a first surface and second surface that are opposite each other. The connector can have a plurality of retractable electrical connectors that extend from the first surface and a lock structure that is located on the second surface. The sensor assembly is comprised of a body portion and a proximal end. The proximal end has a top side and a bottom side. The top side includes a plurality of electrical contacts that is configured to interact with the plurality of retractable electrical connectors. The bottom side includes a key structure that is configured to interact with the lock structure in the connector.

(12) INTERNATIONAL APPLICATION PUBLISHED UNDER THE PATENT COOPERATION TREATY (PCT)

(19) World Intellectual Property
Organization
International Bureau



(10) International Publication Number
WO 2016/127125 A1

(43) International Publication Date
11 August 2016 (11.08.2016)

(51) International Patent Classification:

H01R 13/24 (2006.01) *A61B 5/00* (2006.01)
H01R 13/627 (2006.01) *H01R 12/71* (2011.01)
H01R 13/648 (2006.01) *H01R 12/72* (2011.01)

(21) International Application Number:

PCT/US2016/016883

(22) International Filing Date:

5 February 2016 (05.02.2016)

(25) Filing Language:

English

(26) Publication Language:

English

(30) Priority Data:

62/113,054 6 February 2015 (06.02.2015) US
62/152,733 24 April 2015 (24.04.2015) US

(71) Applicant: **MASIMO CORPORATION** [US/US]; 52
Discovery, Irvine, CA 92618 (US).

(72) Inventors: **SCRUGGS, Stephen**; 52 Discovery, Irvine,
CA 92618 (US). **AL-ALI, Ammar**; 52 Discovery, Irvine,
CA 92618 (US). **SCHMIDT, John**; 52 Discovery, Irvine,
CA 92618 (US). **ABDUL-HAFIZ, Yassir, Kamel**; 52 Dis-
covery, Irvine, CA 92618 (US). **TRIMAN, Benjamin**; 52
Discovery, Irvine, CA 92618 (US). **MACNEISH, Willi-
am, III**; 603 Clubhouse Avenue #a, Newport Beach, CA
92663 (US).

(74) Agent: **ALTMAN, Daniel, E.**; Knobbe Martens Olson &
Bear, LLP, 2040 Main Street, 14th Floor, Irvine, CA
92614 (US).

(81) Designated States (unless otherwise indicated, for every
kind of national protection available): AE, AG, AL, AM,
AO, AT, AU, AZ, BA, BB, BG, BH, BN, BR, BW, BY,
BZ, CA, CH, CL, CN, CO, CR, CU, CZ, DE, DK, DM,
DO, DZ, EC, EE, EG, ES, FI, GB, GD, GE, GH, GM, GT,
HN, HR, HU, ID, IL, IN, IR, IS, JP, KE, KG, KN, KP, KR,
KZ, LA, LC, LK, LR, LS, LU, LY, MA, MD, ME, MG,
MK, MN, MW, MX, MY, MZ, NA, NG, NI, NO, NZ, OM,
PA, PE, PG, PH, PL, PT, QA, RO, RS, RU, RW, SA, SC,
SD, SE, SG, SK, SL, SM, ST, SV, SY, TH, TJ, TM, TN,
TR, TT, TZ, UA, UG, US, UZ, VC, VN, ZA, ZM, ZW.

(84) Designated States (unless otherwise indicated, for every
kind of regional protection available): ARIPO (BW, GH,
GM, KE, LR, LS, MW, MZ, NA, RW, SD, SL, ST, SZ,
TZ, UG, ZM, ZW), Eurasian (AM, AZ, BY, KG, KZ, RU,
TJ, TM), European (AL, AT, BE, BG, CH, CY, CZ, DE,
DK, EE, ES, FI, FR, GB, GR, HR, HU, IE, IS, IT, LT, LU,
LV, MC, MK, MT, NL, NO, PL, PT, RO, RS, SE, SI, SK,
SM, TR), OAPI (BF, BJ, CF, CG, CI, CM, GA, GN, GQ,
GW, KM, ML, MR, NE, SN, TD, TG).

Published:

- with international search report (Art. 21(3))
- before the expiration of the time limit for amending the
claims and to be republished in the event of receipt of
amendments (Rule 48.2(h))

(54) Title: CONNECTOR ASSEMBLY WITH POGO PINS FOR USE WITH MEDICAL SENSORS




FIG. 1A

(57) Abstract: Various connector and sensor assemblies are described. In some embodiments, the connector and sensor assembly comprises a connector and a sensor assembly. The connector can have an opening that has a first surface and second surface that are opposite each other. The connector can have a plurality of retractable electrical connectors that extend from the first surface and a lock structure that is located on the second surface. The sensor assembly is comprised of a body portion and a proximal end. The proximal end has a top side and a bottom side. The top side includes a plurality of electrical contacts that is configured to interact with the plurality of retractable electrical connectors. The bottom side includes a key structure that is configured to interact with the lock structure in the connector.

WO 2016/127125 A1

CONNECTOR ASSEMBLY WITH POGO PINS FOR USE WITH MEDICAL SENSORS

FIELD OF THE DISCLOSURE

[0001] The present disclosure relates to electrical connectors. More specifically, the present disclosure relates to the connection of medical sensors to instruments responsive to signals from the sensors.

BACKGROUND

[0002] Energy is often transmitted through or reflected from a medium to determine characteristics of the medium. For example, in the medical field, instead of extracting material from a patient's body for testing, light or sound energy may be caused to be incident on the patient's body and transmitted (or reflected) energy may be measured to determine information about the material through which the energy has passed. This type of non-invasive measurement is more comfortable for the patient and can be performed more quickly

[0003] Non-invasive physiological monitoring of bodily function is often required. For example, during surgery, blood pressure and the body's available supply of oxygen, or the blood oxygen saturation, are often monitored. Measurements such as these are often performed with non-invasive techniques where assessments are made by measuring the ratio of incident to transmitted (or reflected) light through a portion of the body, for example a digit such as a finger, or an earlobe, or a forehead.

[0004] Durable and disposable sensors are often used for such physiological measurements. These sensors have connectors which allow detachment from the instrument or cable from the instrument.

SUMMARY OF THE DISCLOSURE

[0005] The present disclosure relates to a connector that is configured to attach both disposable and durable sensors to instruments that are responsive to signals from the sensors or the cables from the instruments. To ensure proper operation, the connector is designed to prevent incorrect attachment of the probe to the connector. Additionally, the connector allows for easy connection and release, yet prevents accidental disconnection.

[0006] In some aspects of the present disclosure are disclosed a sensor that has a low profile structure and a connector that can be configured to accommodate various sensors that measure different bodily functions. In one embodiment, the connector can accommodate a plurality of staggered retractable contacts that interact with a sensor with a plurality of staggered electrical contacts on the sensor.

[0007] In some embodiments, the present disclosure involves a connector and sensor assembly. The sensor assembly includes a connector with an opening that has a first surface and a second surface that are opposite each other. In this example, a plurality of retractable electrical connectors can extend from the first surface and a lock structure can be located on the second surface. In this embodiment, the sensor assembly includes a body portion and a proximal end. The proximal end includes a top side and a bottom side, wherein the top side includes a plurality of electrical contacts and the bottom side comprises a key structure and detent structure configured to fit into the lock structure of the connector. In this example, the proximal end of the sensor assembly is configured to be removably inserted into the opening of the connector.

[0007a] In one embodiment there is provided a connector and sensor assembly. The assembly includes a connector including: an opening with an internal surface, and a plurality of retractable electrical connectors extending from the internal surface. The assembly further includes a sensor assembly including: a body portion and a proximal end with a top side including a plurality of electrical contacts. The proximal end is configured to be removably inserted into the opening of the connector. The plurality of electrical contacts include an electrical contact which serves as a grounding line. Any of the plurality of retractable electrical connectors contacts the grounding line first before contacting any of the remaining plurality of electrical contacts. The grounding line is electrically connected entirely on a top side of the proximal end of the sensor assembly.

[0007b] In another embodiment there is provided a male connector assembly which physically connects to and electrically communicates with corresponding female connector. The male connector includes: a flat board portion, and a plurality of electrical contacts arranged on the flat board portion in a staggered configuration. At least one of the electrical contacts is a ground contact. The ground contact is arranged to physically contact and electrically communicate with a corresponding electrical contact of a female connector

before any other contact of the electrical contacts come into electrical communication with a corresponding electrical contact of the female connector. The ground contact is electrically connected entirely on a surface of the flat board portion.

BRIEF DESCRIPTION OF THE DRAWINGS

[0008] FIGS. **1A – 1D** illustrate perspective views of a complete assembly including one embodiment of a sensor assembly and one embodiment of a connector.

[0009] FIGS. **2A – 2B** illustrate a perspective and top view of one embodiment of a connector.

[0010] FIG. **3** illustrates side perspective view of one embodiment of a connector of FIGS. **2A – 2B** with the outer jacket removed.

[0011] FIGS. **4A - 4B** illustrate a side and front perspective view of one embodiment of a connector of FIG. **3** with the outer shield removed.

[0012] FIGS. **4C – 4D** illustrate a side and front perspective view of another embodiment of a connector of FIG. **3** with the outer shield removed.

[0013] FIG. **5A** illustrates a perspective bottom view of one embodiment of the printed circuit board.

[0014] FIG. **5B** illustrates a perspective bottom view of another embodiment of the printed circuit board.

[0015] FIG. **6A** illustrates a perspective view of one embodiment of the inner shield with pogo pins disposed within each of the pogo pin holes.

[0016] FIG. 6B illustrates a perspective view of another embodiment of the inner shield with pogo pins disposed within each of the pogo pin holes.

[0017] FIG. 6C illustrates a perspective view of the embodiment of the inner shield of FIG. 6B with the pogo pins removed.

[0018] FIG. 7A illustrates a bottom view of one embodiment of the connector of FIGS. 5A & 6A with the pogo pins removed.

[0019] FIG. 7B illustrates a bottom view of another embodiment of the connector of FIGS. 5B & 6B with the pogo pins removed.

[0020] FIGS. 8A – B illustrate a bottom perspective view of one embodiment of the connector of FIGS. 4A – B with the inner shield removed.

[0021] FIGS. 8C – D illustrate a bottom perspective view of another embodiment of the connector of FIGS. 4C – D with the inner shield removed.

[0022] FIGS. 9A – C illustrate perspective and cross-sectional views of one embodiment of a pogo pin.

[0023] FIGS. 9D – E illustrate cross-sectional views of one embodiment of a plurality of pogo pins retained between the inner shield and the printed circuit board.

[0024] FIGS. 10A – K illustrate various views of five embodiments of sensor assembly receivers.

[0025] FIGS. 11A – H illustrate various views of five embodiments of sensor assemblies.

[0026] FIGS. 11I – K illustrate bottom views of alternative embodiments of the sensor assemblies illustrated in FIGS. 11F – H.

[0027] FIGS. 11L-M illustrate a proximal end view of two embodiments of the sensor assembly.

[0028] FIG. 12A illustrates a top view of a sensor assembly proximal end configured with one embodiment of a sensor with a plurality of electrical contacts.

[0029] FIGS. 12B – C illustrate a proximal end view of another embodiment of the sensor assembly proximal end configured with embodiments of a sensor with a plurality of electrical contacts wherein a ground trace is included.

[0030] FIGS. 13A – B illustrate top views of one embodiment of a sensor assembly and a connector that are configured to interact.

[0031] FIGS. 14A – I illustrate various cross-sectional views of embodiments of sensor assemblies inserted into corresponding embodiments of sensor assembly receivers.

DETAILED DESCRIPTION

[0032] The present disclosure discloses a connector for attaching a sensor or probe to a monitor or processor so that signals from the sensor are transmitted to the processor or monitor. The connector provides easy connection and removal of the sensor to the connector while maintaining a solid connection. To ensure proper operation, the connector is designed to prevent incorrect attachment of the probe to the connector. Further, in some embodiments, the connector and sensor are configured such that both the connector and sensor structures can be adjusted to accommodate a variety of sensors that measure a variety of bodily functions.

[0033] As used in the specification, the terms “proximal” and “distal” should be understood as being relative to the contact point between the connector and sensor assembly described. Hence, the term distal means a portion of the connector and/or sensor assembly that is furthest away from the point of contact (connection point) between the connector and/or sensor. The term proximal means a portion of the connector and/or sensor assembly that is closest to the point of contact (connection point) between the connector and/or sensor assembly.

[0034] FIGS. 1A – 1D illustrate a side perspective of an embodiment of the assembly 100 which includes a connector 200 and a sensor assembly 800a. The connector 200 is configured to connect with the sensor assembly 800a through the opening 420a at the proximal end of the connector 200. This allows the sensor tab 810a to be secured by the sensor assembly receiver 400a. Connector 200 can be configured to have electrical connectors that are configured to interact with a specific sensor assembly or a plurality of sensor assemblies. In one embodiment, to ensure that the proper sensor assembly is connected to the corresponding connector 200, the sensor assembly receiver 400a of the connector 200 can have an internal structure that is configured to accept only sensor assemblies with corresponding structures. This prevents errors in attaching sensors with incompatible connectors. In some examples, the connector 200 has a receptor that only accepts sensor assemblies with a corresponding key. As can be seen in FIGS. 1A – 1D, the sensor assembly receiver 400a has a receptor 445a located along the bottom inner surface of the sensor assembly receiver 400a and the sensor tab 810a has a key 860a

located on the underside of the sensor tab 810a. As discussed, the receptor 445a only allows a sensor assembly with a corresponding key 860a to fit into the connector 200. The location of the receptor 445a and the key 860a ensures that the user connects the sensor tab 810a with the connector 200 in the correct configuration such that the sensor side 812a sits face up.

[0035] In some embodiments, the connector 200 and the sensor assembly 800a are further configured with a surface to facilitate the connection of the sensor assembly 800a with the connector 200. For example, the proximal end of the connector 200 has a front edge 220 and a tapered surface 430a which angles into the opening 420a of the sensor assembly receiver 400a. Similarly, as shown in **FIG. 1D** the sensor assembly 800a has a proximal end with a tapered surface 820a that is distal to the sensor tab 810a with the connector tab 840a. The angle of the tapered surface 820a corresponds with the angle of the tapered surface 430a of the connector 200 and provides a surface that allows the user to easily slide the sensor assembly 800a into the sensor assembly receiver 400a of the connector 200. The front edge 220 of the connector 200 extends to enclose the tapered surface 820a of the sensor assembly 800a such that the front edge 220 lies flush over the outer edge of the distal end of the tapered surface 820a. The flush connection between the connector 200 and the sensor assembly 800a provides a continuous structure or seal that indicates to the user that the connector 200 and the sensor assembly 800a are properly connected. The aforementioned structures allow the user to correctly attach the sensor with the connector by feel alone. This assists patients and medical practitioners in attaching the connector 200 with the sensor assembly 800a in situations where light is insufficient; thereby allowing the user to connect the connector 200 with the sensor assembly 800a without needing to look at the connector itself.

[0036] **FIGS. 2A – B** provide various views of an embodiment of the connector 200. As well, **FIGS. 2A – B** provide a perspective and front view of the connector 200. **FIG. 3** illustrates the connector 200 with the outer jacket 210 removed such that additional internal structures of the connector 200 are visible. **FIGS. 4A – B** illustrate two views of the connector 200 with the outer shield 300 removed such that the printed circuit board 500 and part of the inner shield 600 are visible. **FIGS. 4A – B** also illustrate the plurality of pogo pins 1000 disposed in the holes of the printed circuit board 500 and inner shield 600. **FIG. 5A** illustrates a perspective view of the printed circuit board 500. **FIG. 6A** shows the embodiment shown in **FIGS. 4A – B** with the printed

circuit board 500 removed. **FIG. 7A** shows a bottom perspective view of the printed circuit board 500 and the inner shield 600. **FIGS. 8A – B** illustrate a bottom and top perspective view of the embodiment shown in **FIGS. 4A – B** with the inner shield 600 removed.

[0037] **FIGS. 2A – 2B** illustrates a perspective and front view of the connector 200. The connector 200 includes a number of features that will be described in more detail below. The connector 200 has an outer jacket 210, a front edge 220 on the proximal end, and a cable attachment 230 at the distal end. As discussed above, the front edge 220 is configured to be disposed about the outer edge of the distal end of the tapered surface 820a. The cable attachment 230 at the distal end of the connector 200 is configured to be connected to and disposed about a cable. In some examples, the cable connects the connector 200 to a patient monitor. In some embodiments, the cable attachment 230 can be disposed about a cable with a diameter sufficient to surround a corresponding cable attachment.

[0038] **FIG. 2B** provides a frontal view of the connector 200. As can be seen, inside the front edge 220 of the connector 200, connector 200 has a tapered surface 430b that leads to the opening 420b of the sensor assembly receiver 400b. The top tab 450b of the sensor assembly receiver 400b protrudes from an opening on top of the outer jacket 210. This helps to retain the outer jacket 210 to the outside of the connector 200. In some embodiments, the sensor assembly receiver 400b can be one of a plurality of colors that corresponds with the color of the sensor assembly. In one example, the protruding top tab 450b can serve as a visual indicator to the user as to what sensor assembly the connector 200 can receive. The inside surface of the sensor assembly receiver 400b contains a receptor 445b that has a raised structure. As was discussed earlier, in some examples, the receptor 445b can couple with a keyed structure on the underside surface of a sensor tab such that the correct sensor assembly is connected to the proper connector 200. In some embodiments, the inside surface of the sensor assembly receiver 400b can include a detent 440b. As illustrated here, the detent 440b forms a groove on the sensor assembly receiver 400b. In some examples, the detent 440b can receive a key detent 865b. In some variants, the purpose of the detent 440b and key detent 865b is to provide the user with a tactile or mechanical feedback (e.g. a “click”) to indicate to the user that the sensor assembly has been properly inserted. As will be seen and described further below, in some embodiments the connector 200 can be configured with a number of

different sensor assembly receivers, each with a different receptor that is configured to accept a different shaped sensor key and different shaped detents. This provides certain manufacturing and assembly efficiencies as the outer jacket 210 and other internal components of the connector 200 can be used with sensors requiring different numbers of electrical contacts.

[0039] Connector 200 can also be structured such that it can be configured for a number of different sensors because of the manner in which the electrical connection is established between the sensor and the connector 200. As can be seen in **FIG. 2B**, the connector 200 can contain a plurality of electrical connectors that extend downward from the top surface of the connector 200. In some embodiments, the electrical connectors are pogo pins 1000. The configuration of the pogo pins 1000 can be adapted to connect to sensors with one of a number of electrical contacts. As will be discussed in further detail below, the pogo pins 1000 of the connector 200 can be in a staggered configuration. This configuration allows the connector 200 to accommodate sensors with varying numbers of electrical contacts.

[0040] **FIGS. 3 and 4A – B** illustrate various views of the connector 200 with various parts of the connector 200 removed so as to better visualize the internal connections between the parts of the connector 200. **FIG. 3** shows the connector 200 with the outer jacket 210 removed such that the outer shield 300, sensor assembly receiver 400b, and the hot melt 700 are visible.

[0041] **FIGS. 4A – 4B** show the connector 200 with the outer shield 300 removed. In this figure, the outer shield 300, sensor assembly receiver 400b, printed circuit board 500, and inner shield 600 are visible. **FIG. 4A** shows a side perspective view of the connector 200 with the outer shield 300 removed. **FIG. 4B** shows a back perspective view of the connector 200 with the outer shield 300 removed.

[0042] As can be seen in **FIG. 3**, in some embodiments, the outer shield body 340 of the outer shield 300 is disposed about the various parts of the connector 200. The outer shield body 340 is disposed about the sensor assembly receiver 400b such that the proximal end 410b of the sensor assembly receiver 400b extends past the proximal end of the outer shield body 340. The top tab 450b can be located on the top of the proximal end 410b of the sensor assembly receiver 400b. At the distal end, the outer shield body 340 has a distal end holder 350. In some embodiments, the distal end holder 350 has a circular structure that can be disposed about the surface of a cable. As discussed above,

the cable enters the outer jacket 210 of the connector 200 through the cable attachment 230 where it is held in place by the distal end holder 350 of the outer shield body 340. In some embodiments, to secure the cable to the connector 200, the cavity of the distal end of the connector 200 includes a hot melt 700 that secures the cable to the distal end holder 350 of the outer shield body 340. In some embodiments, the hot melt distal end 710 of the hot melt 700 secures the cable attachment 230 at the distal end of the outer jacket 210 to the cable. Depending on the internal cavity of the distal end of the connector 200, the hot melt 700 can come in a variety of sizes and shapes and can be made of a variety of materials so long as it serves to secure the cable to the connector 200.

[0043] The outer shield body 340 of the outer shield 300 can have a plurality of openings on the top surface of the outer shield body 340 in order to secure the plurality of parts of the connector 200 together. The outer shield body 340 can have two proximal openings – a first proximal opening 310 and a second proximal opening 320 – located on either side of the proximal end of the outer shield body 340 and a distal opening 330 located near the distal end of the top surface of the outer shield body 340. As will be seen in subsequent figures, the sensor assembly receiver 400b has a plurality of arms that retain the plurality of interior parts of the connector 200. Each of these arms can have an end that protrudes from the outer openings of the outer shield 300 discussed above so as to retain the interior parts of the connector 200. In the embodiment pictured in **FIG. 3**, the sensor assembly receiver 400b has a first arm 465b with a first proximal tab 460b and a second arm 475b with a second proximal tab 470b. Both the first proximal tab 460b and the second proximal tab 470b has a top end that protrudes from the first proximal opening 310 and the second proximal opening 320 respectively. Similarly, the distal arm 485b has a pointed end 480b. The pointed end 480b has a top end that protrudes from the distal opening 330. Each of the openings of the sensor assembly receiver 400b help to contain the top ends of the first proximal tab 460b, second proximal tab 470b, and the pointed end 480b to keep the sensor assembly receiver 400b retained in the proper configuration. In some embodiments, the outer shield 300 can provide electrical shielding to the connector 200. In some embodiments, the outer shield 300 shields the connector 200 from other noise in the surrounding area.

[0044] **FIGS. 4A – 4B** illustrate a perspective side and back view of the connector 200 with the outer shield 300 removed. As discussed above, the outer shield 300 retains a plurality of interior parts of the connector 200. In some embodiments, this

includes the sensor assembly receiver 400b, the printed circuit board 500, and the inner shield 600. As will be discussed in more detail, the proximal and distal arms of the sensor assembly receiver 400b extend through openings in the printed circuit board 500 and the inner shield 600 to retain and secure the parts within the connector 200. As pictured here, the inner shield 600 and the printed circuit board 500 are stacked and located above the sensor assembly receiver 400b. In some configurations, the inner shield 600 is sandwiched between the printed circuit board 500 and the sensor assembly receiver 400b.

[0045] Similar to the outer shield body 340 discussed above, the printed circuit board 500 has a plurality of openings so as to secure the inner shield 600 and sensor assembly receiver 400b together through the arms of the sensor assembly receiver 400b. The printed circuit board 500 can have two proximal openings – a first proximal opening 540 and a second proximal opening 550 – located on either side of the proximal end of the printed circuit board 500. The printed circuit board 500 can also have a distal opening 530 located at the distal end of the printed circuit board 500. As will be seen in subsequent figures, the arms of the sensor assembly receiver 400b extend through a plurality of openings in the inner shield 600 and then through the plurality of openings of the printed circuit board 500. The first arm 465b and the second arm 475b each include a lipped end – the first proximal tab 460b and the second proximal tab 470b respectively. As seen in **FIG. 4B**, in one embodiment, the lip 462b of the first proximal tab 460b and the lip 472b of the second proximal tab 470b extend over the first proximal opening 540 and the second proximal opening 550 and onto the outer surface of the printed circuit board 500. The lip 462b and lip 472b help to secure the sensor assembly receiver 400b to the printed circuit board 500 and the inner shield 600.

[0046] The distal opening 530 of the printed circuit board 500 and the distal arm 485b of the sensor assembly receiver 400b can also be configured to secure the printed circuit board 500 and inner shield 600 together with the sensor assembly receiver 400b. The printed circuit board 500 and the inner shield 600 can have structures that interact with the distal arm 485b. In one embodiment, the distal arm 485b has a pair of legs 482b that form an opening 484b. In this example, the printed circuit board 500 has a distal opening 530 with a distal tab 570 and the inner shield 600 has a distal tab 690. As seen in **FIG. 4B**, the opening 484b is disposed about the distal tab 690 and distal tab 570 that protrude from the distal ends of the inner shield 600 and printed circuit board 500

respectively. The legs 482b of the distal arm 485b extend from the base of the body 490b of the sensor assembly receiver 400b past the surface of the printed circuit board 500 to form the pointed end 480b. In one example, the size of the opening 484b is the distance between the top surface of the body 490b of the sensor assembly receiver 400b and the top surface of the distal tab 570. The opening 484b can be configured such that it contains the distal tab 570 and distal tab 690 in order to prevent the printed circuit board 500 and inner shield 600 from moving relative to each other.

[0047] FIGS. 5 – 8 provide various views of the printed circuit board 500 and inner shield 600 with and without the pogo pins 1000 inserted through the printed circuit board 500 and inner shield 600. FIG. 5 shows a bottom perspective view of the printed circuit board 500. FIG. 6 shows a perspective view of the inner shield 600 with a plurality of pogo pins 1000 located through the holes of the printed circuit board 500. FIG. 7 shows a bottom view of the interconnected printed circuit board 500 and inner shield 600 without the pogo pins 1000. Finally, FIGS. 8A – 8B illustrate a top and bottom perspective view of the interconnected printed circuit board 500 and inner shield 600 with a plurality of pogo pins 1000 inserted in the aligned holes of the printed circuit board 500 and inner shield 600.

[0048] As shown in FIGS. 5 – 8, in some embodiments, the printed circuit board 500 and inner shield 600 house can retain the pogo pins 1000 that form the electrical connections between the electrical contacts in the connector 200 and the sensor. In order to retain the pogo pins 1000 and provide for their movement, the printed circuit board 500 and inner shield 600 have a plurality of holes. The holes for the printed circuit board 500 and inner shield 600 must be aligned in the connector 200 to allow for movement of the pogo pins 1000. In some embodiments, as discussed above, the printed circuit board 500 and inner shield 600 are retained in the proper configuration in the connector 200 by the plurality of arms of the sensor assembly receiver 400b.

[0049] As seen in FIG. 5, the printed circuit board 500 can be thin with a flat proximal end and a curved distal end. As discussed above, the printed circuit board 500 can have a first proximal opening 540 and a second proximal opening 550 on either side of the proximal end of the printed circuit board 500. As shown in FIG. 4A, each of these openings is configured to be disposed about the arms of the sensor assembly receiver 400b. As well, the printed circuit board 500 has a distal opening 530 at the distal end of the printed circuit board 500. In the distal opening 530, a distal tab 570 protrudes into the

distal opening 530. As was discussed earlier with regard to **FIG. 4B**, the distal tab 570 fits in the opening 484b of the distal arm 485b. The opening 484b can secure both the distal tab 570 and the distal tab 690 against the sensor assembly receiver 400b to prevent the printed circuit board 500 and inner shield 600 from moving relative to each other.

[0050] The printed circuit board 500 can also include a plurality of small holes 510, large holes 520, and outer holes 560. In one embodiment, the small holes 510 accommodate the plurality of pogo pins 1000. In some embodiments, the large holes 520 can accommodate the plurality of connector pins 660 of the inner shield 600. The plurality of connector pins 660 can retain the printed circuit board 500 to the inner shield 600. This can provide additional structure to secure the inner shield 600 with the circuit board. As seen in **FIG. 5**, in one embodiment, the small holes 510 are located on the printed circuit board 500 in a staggered configuration. In some embodiments, electrical contacts can be located on top side of the printed circuit board 500. Finally, in some embodiments, the printed circuit board 500 can include a plurality of outer holes 560 located near the border of the printed circuit board 500 for ease in manufacturing and assembly.

[0051] **FIG. 6** illustrates the inner shield 600 with a plurality of pogo pins 1000 located in the inner shield 600. In some embodiments, the inner shield 600 includes a plurality of structures that ensures the proper positioning of the inner shield 600 in the connector 200. Like the printed circuit board 500 and the outer shield 300, the inner shield 600 can include a plurality of openings and tabs to interact with the arms of the sensor assembly receiver 400b such that the inner shield 600 is retained in a proper configuration on the sensor assembly receiver 400b and in the connector 200. The inner shield 600 has a first opening 630, a second opening 640, and a distal tab 690. As discussed earlier, the first opening 630 and second opening 640 are aligned with the first proximal opening 540 and second proximal opening 550 of the printed circuit board 500 respectively. These openings are disposed about the first arm 465b and second arm 475b of the sensor assembly receiver 400b. As well, the printed circuit board 500 and inner shield 600 are secured by the first proximal tab 460b and the second proximal tab 470b. The inner shield 600 further has a distal tab 690. The distal tab 690 protrudes from the distal end of the inner shield 600 and, as described above, can be retained by the opening 484b of the distal arm 485b of the sensor assembly receiver 400b.

[0052] The inner shield 600 can also include a plurality of legs to secure the inner shield 600 on the sensor assembly receiver 400b. As shown in FIG. 6, the inner shield 600 has a first leg 610 and a second leg 620 located at the proximal end of the inner shield 600. As can be seen in FIG. 4A, the sensor assembly receiver 400b has a plurality of gaps 492b that are located on either side of the proximal end of the sensor assembly receiver 400b. In some embodiments, the gaps 492b are formed on the side of the sensor assembly receiver 400b by the space between the proximal end of the arm (e.g. the first arm 465b or the second arm 475b) and the distal side of the proximal end 410b of the sensor assembly receiver 400b. The gaps 492b can be configured to fit the width of the legs (e.g. the first leg 610 and second leg 620) and secure the inner shield 600 in place to prevent it from moving relative to the sensor assembly receiver 400b. In this embodiment, the first leg 610 and second leg 620 bring the proximal shelf 670 such that it lies flush against the distal side of the proximal end 410b of the sensor assembly receiver 400b.

[0053] The inner shield 600 can also include a number of structures so as to retain and properly position the printed circuit board 500 on the surface of the printed circuit board 500. As shown in FIG. 6, the inner shield 600 can have a plurality of connector pins 660 and a proximal shelf 670. As discussed above the plurality of connector pins 660 can align with the plurality of large holes 520 of the printed circuit board 500 such that the large holes 520 are configured to be disposed about the connector pins 660. The inner shield 600 also includes a plurality of pogo pin holes 650. The plurality pogo pin holes 650 are located in a staggered configuration such that each of the plurality of the pogo pin holes 650 can be aligned to correspond with the small holes 510 of the printed circuit board 500. The connector pin 660 of the inner shield 600 can interact with the large holes 520 to maintain the passageway created by the small holes 510 and pogo pin holes 650. This connection can be further seen in FIG. 7. FIG. 7 shows a bottom view of the inner shield 600 with the printed circuit board 500 aligned over it. The pogo pin holes 650 of the inner shield 600 can be larger in diameter than the small holes 510 of the printed circuit board 500. In the embodiment shown in FIG. 7, each of the small holes 510 can be coaxially aligned with each of the pogo pin holes 650 so as to allow a pogo pin 1000 to be retained and move within the passage (e.g. channel, pathway) created by the pogo pin hole 650 and small hole 510.

[0054] As can be seen in FIGS. 8A and B, the pogo pin holes 650 are configured such that the plurality of pogo pins 1000 are positioned in the pogo pin holes 650 such that both ends of each of the pogo pins 1000 can protrude from the inner shield 600. The distal end 1110 of the pogo pins 1000 contacts the printed circuit board 500 and allows for an electrical connection to be formed between the printed circuit board 500 and the pogo pins 1000. As will be further discussed below, the small holes 510 of the printed circuit board 500 and the internal structure of each of the pogo pin holes 650 help to retain each of the pogo pins 1000 to prevent it from moving out of the pogo pin holes 650 of the inner shield 600. Also, as will be discussed below, the pogo pins 1000 are retained in a staggered configuration that can accommodate sensors with a range of electrical contacts. This staggered configuration can help to reduce the profile of the connector 200 and allow the same connector 200 structure to be used in a large number of sensors.

[0055] In some examples, the connector 200 can have internal components (e.g. the sensor assembly receiver, printed circuit board, and inner shield) with different configurations. FIGS. 4C – D, 5B, 6B, 7B, and 8C – D, illustrate another embodiment of the internal components of the connector 200.

[0056] FIGS. 4C – 4D illustrate a perspective side and back view of another embodiment of connector 200 with the outer shield 300 removed. As discussed above, the outer shield 300 retains a plurality of interior parts of the connector 200. In some embodiments, this includes the sensor assembly receiver 400c, the printed circuit board 500b, and the inner shield 600b. As pictured here, the inner shield 600b and the printed circuit board 500b can be stacked and located above the sensor assembly receiver 400c. In some configurations, the inner shield 600b can be sandwiched between the printed circuit board 500b and the sensor assembly receiver 400c.

[0057] The printed circuit board 500b can have a plurality of openings so as to secure the printed circuit board 500b on the inner shield 600b. As will be discussed in more detail below, the printed circuit board 500b can include a plurality of large holes 520b that are disposed about the connector pin 660b of the inner shield 600b.

[0058] The sensor assembly receiver 400c can include a plurality of arms that secure the inner shield 600b to the sensor assembly receiver 400c so as to prevent movement of the inner shield 600b relative to the sensor assembly receiver 400c. In some embodiments the sensor assembly receiver 400c can include a first arm 460c, a

second arm 470c, and a distal arm 480c. As seen in **FIGS. 4C** and **4D**, in some embodiments the first arm 460c and second arm 470c can be located on the proximal end 410c of the sensor assembly receiver 400c. In one embodiment, the first arm 460c and second arm 470c extend away from the body 490c.

[0059] Similarly, in some embodiments, the inner shield 600b can include a plurality of arms that are configured to engage with the sensor assembly receiver 400c in order to secure the sensor assembly receiver 400c to the inner shield 600b. In one embodiment, the inner shield 600b can include a first arm 610b, a second arm 620b, and a distal arm 630b. In some embodiments, the first arm 610b and second arm 620b can be located on the proximal end of the inner shield 600b and the first arm 610b and second arm 620b extend outward from the inner shield 600b. The distal arm 630b can be located on the distal end of the first arm 610b. In some embodiments, the distal arm 630b can be composed of two legs 635b that extend away from the distal end of the inner shield 600b. In some embodiments, the two legs 635b bend away from the distal end of the inner shield 600b. In some embodiments, the ends of the two legs 635b have a connected end 640b and form an opening.

[0060] **FIGS. 4C – 4D** illustrate one example of the connections between the sensor assembly receiver 400c and the inner shield 600b on the proximal end. In some embodiments, the first arm 460c and second arm 470c can extend outward to engage the proximal end of the inner shield 600b. In some variants, this engagement can allow the proximal shelf 670b to lie flush against the distal surface of the proximal end 410c of the sensor assembly receiver 400c. In some embodiments, the proximal shelf 670b is located between the first arm 460c and the second arm 470c.

[0061] **FIG. 4D** provides an illustration of one example of the connection between the sensor assembly receiver 400c and the inner shield 600b. As illustrated, the two legs 635b of the connected end 640b of the distal arm 630b can form an opening. As seen in **FIG. 4D**, the opening can allow the distal tab 485c of the distal arm 480c to protrude over the top surface of the connected end 640b. In some embodiments, this connection can prevent the inner shield 600b and sensor assembly receiver 400c from moving relative to each other. As well, as was discussed above, this securement can ensure the proper placement of the plurality of pogo pins 1000 within the body of the sensor assembly receiver 400c.

[0062] FIGS. 5B, 6B – C, 7B, and 8C – 8D provide various views of alternative embodiments of the printed circuit board 500b and inner shield 600b with and without the pogo pins 1000 inserted through the printed circuit board 500b and inner shield 600b. FIG. 5B shows a bottom perspective view of the printed circuit board 500b. FIG. 6B shows a perspective view of the inner shield 600b with a plurality of pogo pins 1000 located through the holes of the printed circuit board 500b. FIG. 6C illustrates another perspective view of the inner shield 600b with the pogo pins 1000 removed. FIG. 7B shows a bottom view of the interconnected printed circuit board 500b and inner shield 600b without the pogo pins 1000. Finally, FIGS. 8C – 8D illustrate a top and bottom perspective view of the interconnected printed circuit board 500b and inner shield 600b with a plurality of pogo pins 1000 inserted in the aligned holes of the printed circuit board 500b and inner shield 600b.

[0063] The printed circuit board 500b is similar to the printed circuit board 500 described above in FIG. 5. Like the printed circuit board 500, the printed circuit board 500b can include a plurality of small holes 510b, large holes 520b, and outer holes 540b. Like the printed circuit board 500, the printed circuit board 500b can include small holes 510b that can accommodate the plurality of pogo pins 1000. As well, like the large holes 520 of the printed circuit board 500, the large holes 520b can accommodate the plurality of connector pins 660b of the inner shield 600b. As noted above, in some embodiments, the plurality of connector pins 660b can retain the printed circuit board 500b to the inner shield 600b. As seen in FIG. 5B, the small holes 510 can be located on the printed circuit board 500b in a staggered configuration. Each of the small holes 510b can be disposed about a pogo pin 1000 and allow for a portion of the pogo pin 1000 to protrude through the printed circuit board 500b. In some embodiments, electrical contacts 515b can be located on the inside surface of each of the small holes 510b. Finally, in some embodiments, the printed circuit board 500b can include a plurality of outer holes 540b located near the border of the printed circuit board 500b. In some embodiments, each of the outer holes 540b can include electrical contacts 545b on the inside surface of the outer holes 540b. In some examples, the electrical contacts 545b can provide an electrical connection between the printed circuit board 500b and the attached cable.

[0064] FIG. 6B illustrates another embodiment of the inner shield. FIG. 6B illustrates an inner shield 600b with a plurality of pogo pins 1000 located inner shield

600b. In some embodiments, the inner shield 600b can include a plurality of structures that ensures the proper positioning of the inner shield 600b in the connector 200b. As discussed above, the inner shield 600b can include a plurality of structures to interact with sensor assembly receiver 400c and the printed circuit board 500b such that the inner shield 600b is retained in a proper configuration on the sensor assembly receiver 400c and in the connector 200.

[0065] The inner shield 600b can also include a number of structures so as to retain and properly position the printed circuit board 500b on the surface of the printed circuit board 500b. As shown in **FIG. 6C**, the inner shield 600b can have a plurality of connector pins 660b and a proximal shelf 670b. As discussed above the plurality of connector pins 660b can align with the plurality of large holes 520b of the printed circuit board 500b such that the large holes 520b are configured to be disposed about the connector pins 660b. The inner shield 600b can also include a plurality of pogo pin holes 650b. The plurality pogo pin holes 650b can be located in a staggered configuration such that each of the plurality of the pogo pin holes 650b can be aligned to correspond with the small holes 510b of the printed circuit board 500b. The connector pin 660b of the inner shield 600b can interact with the large holes 520b to maintain the passageway created by the small holes 510b and pogo pin holes 650b.

[0066] This connection can be further seen in **FIG. 7B**. **FIG. 7B** shows a bottom view of the inner shield 600b with the printed circuit board 500b aligned over it. The pogo pin holes 650b of the inner shield 600b can be larger in diameter than the small holes 510b of the printed circuit board 500b. In the embodiment shown in **FIG. 7B**, each of the small holes 510b can be coaxially aligned with each of the pogo pin holes 650b so as to allow a pogo pin 1000 to be retained and move within the passage (e.g. channel, pathway) created by the pogo pin hole 650b and small hole 510b.

[0067] As can be seen in **FIGS. 8C – D**, as was illustrated above in **FIGS. 8A – B**, the pogo pin holes 650b can be configured such that the plurality of pogo pins 1000 are positioned in the pogo pin holes 650b such that both ends of each of the pogo pins 1000 can protrude from the inner shield 600b. The distal end 1110 of the pogo pins 1000 contacts the printed circuit board 500b and allows for an electrical connection to be formed between the electrical contacts 545b of the printed circuit board 500b and the pogo pins 1000. As will be further discussed below, the small holes 510b of the printed circuit board 500b and the internal structure of each of the pogo pin holes 650b can help

to retain each of the pogo pins 1000 to prevent it from moving out of the pogo pin holes 650b of the inner shield 600b. Also, as will be discussed below, the pogo pins 1000 are retained in a staggered configuration that can accommodate sensors with a range of electrical contacts. This staggered configuration can help to reduce the profile of the connector 200 and allow the same connector 200 structure to be used in a large number of sensors. This is partly because the staggered configuration allows more separate connection points than would otherwise fit in the same space without a staggered configuration.

[0068] Each connector 200 contains a plurality of pogo pins 1000 that help to establish the electrical connection between the electrical contacts of the sensor assembly 800a and the connector 200 as seen in the complete assembly 100 of FIG. 1. Pogo pins can be made in a variety of shapes and sizes and usually take the form of a slender cylinder containing two spring loaded pins.

[0069] FIG. 9A – 9C illustrate multiple views of some embodiments of a pogo pin 1000. FIG. 9A shows a perspective view of a pogo pin 1000, FIG. 9B shows a cross section of the pogo pin 1000, and FIG. 9C shows the inside components of the pogo pins 1000. FIG. 9D – 9E illustrate two figures showing the pogo pins 1000 retained between the printed circuit board 500 and inner shield 600. FIG. 9D provides a cross-sectional example of the inner shield 600 with a plurality of pogo pins 1000 disposed within the pogo pin holes 650 of the inner shield 600. FIG. 9E provides a cross-sectional example of a plurality of pogo pins 1000 contained between the printed circuit board 500 and inner shield 600.

[0070] As can be seen in FIGS 9A – 9C, in one embodiment the pogo pin 1000 can include four structures – a plunger 1100, a hollow barrel 1140, a spring 1180, and a contact tip 1170. The hollow barrel 1140 houses the plunger 1100, spring 1180, and contact tip 1170. Further, the hollow barrel 1140 disposed about the spring 1180. The pogo pins 1000 can be made of a conductive material and are configured such that the spring 1180 can push against both the plunger 1100 and the contact tip 1170 to move both parts such that an electrical connection is established through the pogo pin 1000.

[0071] The hollow barrel 1140 has a distal opening 1150 and proximal opening 1160 to allow the plunger 1100 and contact tip 1170 to protrude from the hollow barrel 1140 respectively. As can be seen in FIG. 9A – 9B, the hollow barrel 1140 includes a distal edge 1142 and a proximal edge 1144 that helps to contain the pogo pins

1000 in the interior structure of the pogo pin holes 650 of the inner shield 600. As will be discussed further below, the interior structure of the pogo pin holes 650 along with the location of the small holes 510 of the printed circuit board 500 retain the pogo pins 1000 between the printed circuit board 500 and inner shield 600. The hollow barrel 1140 can also include an inner lip 1146 on the inside surface of the hollow barrel 1140 near the proximal opening 1160. As will be discussed in more detail, the inner lip 1146 can interact with the outer surface of the distal end of the contact tip 1170 to prevent the contact tip 1170 from exiting out from the proximal opening 1160 of the hollow barrel 1140.

[0072] The plunger 1100 includes a distal end 1110, stopper 1120, and cylindrical proximal end 1130. As is seen in FIG. 9B and 9C, the cylindrical proximal end 1130 is disposed within the coils of the spring 1180. The stopper 1120 is located distal to the cylindrical proximal end 1130 and has a cylindrical structure with a diameter that can be greater than the diameter of the coils of the spring 1180 but smaller than the diameter of the inside surface of the hollow barrel 1140. The diameter of the stopper 1120 allows the spring 1180 to collapse against the surface of the stopper 1120. The distal end 1110 of the plunger 1100 can have a cylindrical shape that has a diameter less than or equal to the diameter of the inside surface of the hollow barrel 1140. In one embodiment, the diameter and length of each of the distal ends 1110 of the pogo pins 1000 is configured to be coaxially disposed within one of the small holes 510 of the printed circuit board 500. In some embodiments, distal end 1110 is configured to engage with an electrical contact within the connector 200.

[0073] The spring 1180 can be disposed coaxially within the hollow barrel 1140 and assists in the driving of the plunger 1100 and the contact tip 1170. The spring 1180 can be made of a conductive material which allows the spring 1180 to connect the sensor with the electrical contacts on the printed circuit board 500. As seen in FIG. 9B, the spring 1180 is partially disposed within the hollow barrel 1140 and can extend past the proximal opening 1160 of the hollow barrel 1140. As discussed earlier, the cylindrical proximal end 1130 of the plunger 1100 is coaxially disposed within the coils of the spring 1180. The stopper 1120 of the plunger 1100 maintains the distal most position of the distal end of the spring 1180. A proximal portion of the spring 1180 extends out from the proximal opening 1160 of the hollow barrel 1140 and is coaxially disposed within the hollow center 1174 of the contact tip 1170. As will be discussed in

more detail, the contact tip 1170 can interact with the spring 1180 (e.g. compressing, shortening, extending, lengthening) as the contact tip 1170 moves axially along the inside surface of the hollow barrel 1140.

[0074] The contact tip 1170 can protrude from the proximal opening 1160 of the hollow barrel 1140. The contact tip 1170 has a distal end opening 1172, a hollow center 1174 with an internal surface, a proximal end 1176, and a distal lip 1178 on the outer surface of the distal end of the contact tip 1170. The contact tip 1170 can be made of a conductive material. The distal end opening 1172 of the contact tip 1170 allows the spring 1180 to extend coaxially into the hollow center 1174 of the contact tip 1170. As discussed above, the hollow center 1174 of the contact tip 1170 is disposed about the proximal end of the spring 1180 and movement of the contact tip 1170 within the hollow barrel 1140 causes the interaction of the inside surface of the contact tip 1170 with the proximal end of the spring 1180. This interaction causes the spring 1180 to either compress (e.g. shorten) or extend (e.g. lengthen). The proximal end 1176 of the contact tip 1170 can be configured such that it can interact with the electrical contact of the sensor assembly 800a. In some configurations, the proximal end 1176 can be tapered to provide a consistent connection with the electrical contact of the sensor assembly 800a. In other configurations, the proximal end 1176 has a rounded end in order to prevent damaging the surface of the electrical contact on the sensor assembly 800a. Finally, the distal lip 1178 can have a structure that retains the contact tip 1170 within the hollow barrel 1140. As seen in FIG. 9B, the distal lip 1178 of the distal end of the contact tip 1170 interacts with the inner distal lip 1178 of the hollow barrel 1140 such that a distal portion of the contact tip 1170 is retained in the hollow barrel 1140. In one embodiment, the diameter of the inner surface of the hollow barrel 1140 at the inner lip 1146 is configured to be narrower than the diameter of the distal lip 1178 but wide enough to allow the body of the contact tip 1170 to fit through. In this configuration, the interaction between the distal lip 1178 of the contact tip 1170 and the inner lip 1146 of the hollow barrel 1140 prevent the contact tip 1170 from fully exiting from the proximal opening 1160 of the hollow barrel 1140.

[0075] FIGS. 9D – 9E illustrate how the pogo pins 1000 are retained between the printed circuit board 500 and inner shield 600. As can be seen in FIG. 9D, each of the pogo pin holes 650 of the inner shield 600 has a distal opening 652 and a proximal opening 654. The diameter of the distal opening 652 is wider than the diameter of the

proximal opening 654 and the pogo pin holes 650 is configured to retain the hollow barrel 1140 of the pogo pin 1000. In one configuration, the distal opening 652 is configured to retain the distal edge 1142 of the hollow barrel 1140 and the proximal opening 654 is configured to retain the proximal body portion of the hollow barrel 1140. This configuration retains the pogo pin 1000 in the inner shield 600. To prevent the pogo pins 1000 from moving out of the inner shield 600 in a distal direction, the printed circuit board 500 is placed over inner shield 600. The small holes 510 of the printed circuit board 500 are configured to retain the distal end 1110 of the plunger 1100. This can serve a multitude of purposes. For example, because the small holes 510 have a diameter that accommodates the distal end 1110 but is not wide enough to accommodate the stopper 1120 of the plunger 1100, this retains the components of the pogo pins 1000 that are contained within the hollow barrel 1140. As well, the small holes 510 are configured to allow the plunger 1100 to come in contact with the electrical contacts on the printed circuit board 500.

[0076] In operation, the position of both the printed circuit board 500 and the inner shield 600 allow the establishment of a secure electric connection between the electrical contact on the printed circuit board 500 and the electrical contact on the sensor assembly 800a. As will be discussed in further detail below, as the sensor assembly 800a is positioned in the connector 200, the profile of the sensor assembly 800a pushes the contact tip 1170 in a distal direction such that the contact tip 1170 further retracts into the hollow barrel 1140. This movement causes the proximal end of the hollow center 1174 of the contact tip 1170 to compress the spring 1180. This compression force can then, in turn, force the stopper 1120 in a distal direction that brings the distal end 1110 of the plunger 1100 in contact with the electrical contacts on the printed circuit board 500. As the pogo pins 1000 are made of a conductive material, this ensures that an electrical connection is established between the electrical contacts on the printed circuit board 500 of the connector 200 and the electrical contact on the sensor assembly.

[0077] The connector and sensor of the complete assembly 100 are designed such that the same general assembly of the connector and sensor could be used for a number of different types of sensors. As discussed previously, the configuration of the plurality of pogo pins 1000 in the connector 200 allows the connector 200 to be adapted to accommodate a sensor with a wide range of electrical contacts. This design provides a manufacturing benefit as the general design of the complete assembly 100 does not need

to be redesigned to accommodate every individual sensor. Instead, the configuration of the small holes 510 and pogo pin holes 650 of the printed circuit board 500 and inner shield 600 can vary depending on the location of the electrical contacts on the sensor.

[0078] Because the same complete assembly 100 can be used for a number of different sensors, to assist a patient and/or medical practitioner in connecting the correct sensor with the correct connector, the connector and sensor of the complete assembly 100 can be configured with a number of helpful structures and/or characteristics. **FIGS. 10A – 10D** and **FIGS. 11A – 11E** illustrate two examples of corresponding connectors and sensors respectively that are configured to assist a user with properly connecting the correct connector to the correct sensor. **FIGS. 10A – 10D** illustrate two examples of connectors that are configured to only accept the proper sensor assembly. Similarly, **FIGS. 11A – 11E** illustrate two examples of corresponding sensor assemblies that are configured to only connect with the proper connector.

[0079] **FIGS. 10A – 10B** show a front and top view of the sensor assembly receiver 400a. As described above, the sensor assembly receiver (here the sensor assembly receiver 400a) has a body 490a to accommodate the male connector portion of the sensor assembly. As discussed above, the sensor assembly receiver 400a also has a plurality of arms – the first arm 465a, second arm 475a, and distal arm 485a – that help to retain the printed circuit board 500 and inner shield 600 as discussed above. The body 490a has a proximal end 410a with a tapered surface 430a that leads to the opening 420a of the body 490a. As discussed earlier, the tapered surface can help to guide the sensor into the opening 420a of the body 490a. The body 490a can include a receptor 445a that accommodates a key on the sensor. This is further shown in **FIG. 10B**, wherein the body 490a can only accommodate a sensor with a key in the shape of the receptor 445a. Further, the body 490a can also include a detent 440a that can interact with a similarly shaped detent on the sensor. As discussed below, the detent 440a and the detent located on the underside of the sensor can provide mechanical feedback to the user.

[0080] **FIGS. 11A – 11C** shows a front and bottom view of the sensor assembly 800a that is configured to fit into the body 490a of the sensor assembly receiver 400a. The sensor assembly 800a has a connector assembly 840a that can accommodate a sensor. As can be seen in **FIGS. 11A – 11B**, the connector assembly 840a includes a top connector assembly 842a and a bottom connector assembly 844a. The top connector assembly 842a can connect with the distal portion of the bottom connector assembly

844a. As the top connector assembly 842a and bottom connector assembly 844a are connected, the distal end 850a and the opening 880a can accommodate a sensor between the two parts of the connector assembly 840a. The proximal end of the top connector assembly 842a has a tapered surface 820a that is configured to fit against the tapered surface 430a of the sensor assembly receiver 400b. The top connector assembly 842a can accommodate a label 830a. As will be discussed further below, the label 830a can vary so as to indicate the type of sensor accommodated by the sensor assembly 800a. As can be seen in **FIGS. 11A – 11C**, the proximal end 870a of the bottom connector assembly 844a includes a sensor tab 810a that has a sensor side 812a, lip 814a, and a key 860a and a key detent 865a on the bottom of the sensor side 812a. The sensor side 812a has an opening that accommodates for the sensor and the lip 814a on the proximal end of the sensor tab 810a ensures the placement of the sensor on the sensor side 812a. On the reverse side of the sensor tab 810a is a key 860a. As will be discussed in further detail, the key 860a is configured to fit the detent 440a of the sensor assembly receiver 400a discussed above. As well, as will be discussed in further detail below, the key 860a is configured to engage with the receptor 445a of the sensor assembly receiver 400a.

[0081] In operation, as discussed earlier, the sensor assembly 800a can have a number of configurations to facilitate the connection between the sensor assembly 800a and the sensor assembly receiver 400a. Further, the sensor assembly 800a and sensor assembly receiver 400a can have a number of other configurations to ensure that the correct sensor assembly 800a is connected to the proper sensor assembly receiver 400a. As discussed above, the tapered surface 820a corresponds with the tapered surface 430a of the sensor assembly receiver 400a and can help to guide the sensor tab 810a into the opening 420a of the body 490a. As discussed above, each sensor assembly has a key that corresponds with the detent of the corresponding sensory assembly receiver of the connector 200. Here, the key 860a from **FIG. 11C** is configured to fit the receptor 445a of the sensor assembly receiver 400a. As can be seen in **FIGS. 10B** and **11C**, the shape of the receptor 445a is shaped to receive the key 860a of the sensor assembly 800a. The location of the key 860a and the receptor 445a also ensure that the sensor assembly 800a is inserted into the sensor assembly receiver 400a with the sensor side 812a up. Further, as discussed above, the underside of the sensor tab 810a includes a key detent 865a that can be engaged with the detent 440a located on the bottom surface of the sensor assembly receiver 400a. Once inserted, the sensor tab 810a and the detent 440a can engage to

provide mechanical feedback to the user. As will be discussed in further detail below, the sensor has a number of electrical contacts that will interact with the pogo pins 1000 shown in previous figures. This connection will ensure that an electrical connection is created between the connector 200 and the sensor assembly.

[0082] Finally, in some embodiments, the sensor assembly receiver 400a can have the same color as the label 830a of the sensor assembly 800a. For example, the sensor assembly receiver 400a and the label 830a of the sensor assembly 800a can both have a red color, a blue color, a black color, or a gray color. In this embodiment, when the sensor assembly receiver 400a is assembled inside the connector 200, the colored top tab 450a and the colored tapered surface 430a are visible from the outer jacket 210 of the connector 200. The matching colors of the visible portions of the sensor assembly receiver 400a and the label 830a allow the user to identify visually whether the correct connector 200 is attached to the correct sensor assembly. In some embodiments, the sensor assembly receiver 400a can have a color indicator on the tapered surface 430a and the top tab 450a. In some examples, this provides the user with a visual indicator as to what sensor assembly can be properly inserted into the connector. Because the tapered surface 430a of the sensor assembly receiver 400a is no longer visible once the sensor assembly 800a is inserted, in some embodiments, the top tab 450a can serve as a visual indicator to the user regarding the type of sensor the complete assembly 100 includes.

[0083] In order to prevent improper connections between different connectors and sensor assemblies, different connectors can have different detents. The corresponding sensor assemblies, in turn, will have keys that correspond with the connecting detent. FIGS. 10C – 10D and FIGS. 11D – 11E illustrate another example complete assembly 100 where the sensor assembly receiver 400b and sensor assembly 800b have corresponding receptor 445b and key 860b and corresponding detent 440b and key detent 865b. As seen in FIGS. 10C – 10D, the sensor assembly receiver 400b has the same construction as the sensor assembly receiver 400a except the receptor 445b and detent 440b of the body 490b have a different configuration than the receptor 445a and detent 440a of the sensor assembly receiver 400a. FIGS. 11D – 11E illustrate the sensor assembly 800b that has the same construction as the sensor assembly 800a except the key 860b has a different configuration than the key 860a. The key 860b is configured to interact with the receptor 445b. Therefore, the sensor assembly receiver 400b is configured such that it can only be inserted into a connector 200 with a sensor assembly

800b. Further, as discussed earlier, the label 830b has a different design than the label 830a and can help a user identify the sensor attached to the sensor assembly 800b. As well, the sensor assembly receiver 400b can have the same color as the label 830b of the sensor assembly 800b. As discussed earlier, the sensor assembly receiver 400b and label 830b of the sensor assembly 800b can both have a red color, a blue color, a black color, or a gray color. Because the top tab 450b and the 320b are visible from the outer jacket 210 of the connector 200, the user is readily able to identify that the sensor assembly 800b can be properly inserted into the connector 200 with a sensor assembly receiver 400b.

[0084] As discussed above, the detent can provide the user with a mechanical “locking” feel as the proximal end of the sensor assembly is inserted into the connector. In addition to the interaction between the detent located on the sensor assembly and sensor assembly receiver, this is accomplished by the interaction between the pogo pins 1000 and the sensor side 812a of the sensor tab 810a. In the connector 200, as seen in **FIG. 2B**, the pogo pins 1000 extend from the inner shield 600 into the body 490a of the sensor assembly receiver 400a. As the sensor tab 810a is inserted into the body 490a the key detent 865a of the sensor assembly 800a begins to engage with the detent 440a of the sensor assembly receiver 400a. The insertion of the sensor tab 810a causes the surface of the sensor side 812a to contact the proximal end 1176 and retract the contact tip 1170 distally into the hollow barrel 1140. Once the proximal end of the sensor assembly 800a is fully inserted into the body 490a, the spring force of the springs 1180 in the plurality of pogo pins 1000 can push the contact tip 1170 in a proximal direction – causing the contact tip 1170 to extend out of the proximal opening 1160 of the hollow barrel 1140. As the contact tip 1170 of the plurality of pogo pins 1000 extend outwards, the proximal end of the sensor assembly receiver 400a will be pushed downward such that the key detent 865a and detent 440a are activated (e.g. fully engaged). This interaction can further provide the user with a mechanical “locking” feel which provides a tactile indication to the user that the sensor assembly has been properly inserted into the connector 200.

[0085] **FIGS. 10E – K** and **FIGS. 11F – H** provide an alternative embodiment of the engagement between the sensor assembly and sensor assembly receiver. In some embodiments, the sensor assembly receiver and sensor assembly can engage to reduce the wear on the electrical contacts on the surface of the sensor assembly.

In some embodiments, the sensor assembly includes a structure on the proximal end to prevent jamming and to ensure that the sensor assembly enters the sensor assembly receiver at the correct angle.

[0086] In some embodiments, the sensor assembly receiver and sensor assembly can be configured to reduce the wear on the surface of the sensor assembly. As discussed above, as the sensor assembly is inserted into the sensor assembly receiver, the pogo pins can contact the traces located on the surface of the sensor assembly. As will be discussed below, because the pogo pins can be spring loaded in order to better contact the traces located on the surface of the sensor assembly, repeated insertions of the sensor assembly can cause significant wear on the surface of the sensor assembly receiver. **FIGS. 10E – K, 11F – I, and 14A – I** illustrate an embodiment of the sensor assembly and sensor assembly receiver that can be configured to reduce the wear on the sensor surface of the sensor assembly.

[0087] **FIGS. 10E – G** illustrates one embodiment of a sensor assembly receiver configured to reduce the wear of the sensor surface of the sensor assembly. As can be seen, in some embodiments, the sensor assembly receiver 400c is very similar to the sensor assembly receiver illustrated in **FIGS. 10A – D**. The sensor assembly receiver 400c can include a proximal end 410c and a body 490c. In some embodiments, the proximal end 410c can include a tapered surface 430c and an opening 420c. In some embodiments, the proximal end 410c includes a top tab 450c. As discussed above, the top tab 450c and the tapered surface 430c of the proximal end 410c can have a color that corresponds with a portion of the sensor assembly in order to provide a visual indication to the user that the correct sensor assembly has been attached to the property connector with the corresponding sensor assembly receiver. In some embodiments, as discussed above, the sensor assembly receiver 400c can include a plurality of arms that allow the sensor assembly receiver 400c to be secured within the connector 200. Like the sensor assembly receivers discussed above, the sensor assembly receiver 400c can include a first arm 460c, a second arm 470c, distal arm 480c, and distal tab 485c. **FIGS. 10H – K** illustrates two additional embodiments of sensor assembly receivers configured to reduce the wear of the sensor surface of the sensor assembly. **FIGS. 10H – I** illustrates the sensor assembly receiver 400d and **FIGS. 10J – K** illustrates the sensor assembly receiver 400e. The sensor assembly receiver 400d and sensor assembly receiver 400e can

similarly include the parts described with regard to sensor assembly receiver 400a, sensor assembly receiver 400b, and sensor assembly receiver 400c described above.

[0088] The sensor assembly receiver embodiments illustrated in **FIGS. 10E – K**, like the sensor assembly receivers illustrated in **FIGS. 10A – D**, is configured to receive a key from a corresponding sensor assembly. In some embodiments, the sensor assembly receiver embodiments are also configured to include a detent structure that can interact with a corresponding detent structure on the underside of the sensor assembly to provide mechanical feedback. In some embodiments, the sensor assembly receiver includes a ramp that can raise the sensor assembly within the sensor assembly receiver.

[0089] **FIGS. 10E – G**, illustrates a sensor assembly receiver 400c that can include a receptor 445c and a detent 440c. As can be better seen in **FIGS. 10F – G**, the sensor assembly receiver 400c includes a receptor 445c that is located on two sides of the bottom surface 443c of the sensor assembly receiver 400c. The receptor 445c of the sensor assembly receiver 400c can include receptor protrusions 447c near the distal end of the sensor assembly receiver 400c. The receptor protrusion 447c creates a raised portion from the receptor 445c. The receptor 445c can also include a receptor end 449c located at the distal end of the sensor assembly receiver 400c that is no longer elevated. The sensor assembly receiver 400c can also include a detent 440c. As can be seen in **FIG. 10F**, the detent 440c can be located near the proximal end of the sensor assembly receiver 400c and form a groove in the bottom surface 443c of the sensor assembly receiver 400c. As well, in some embodiments, the sensor assembly receiver 400c can include an angled surface 441c. As can be seen in **FIG. 10G**, the angled surface 441c raises the bottom surface 443c.

[0090] The two embodiments illustrated in **FIGS. 10H – K** provide similar structures as discussed above. **FIGS. 10H – I** illustrates a sensor assembly receiver 400d that has a receptor 445d that is located at the center of the bottom surface 443d of the sensor assembly receiver 400d. The receptor 445d of the sensor assembly receiver 400d can include receptor protrusion 447d near the distal end of the sensor assembly receiver 400d. The receptor protrusion 447d creates a raised portion from the receptor 445d. The receptor 445d can also include a receptor end 449d located at the distal end of the sensor assembly receiver 400d that is not elevated. The sensor assembly receiver 400d can also include a detent 440d. As can be seen in **FIG. 10H**, the detent 440d is composed of two portions that are located on either side of the proximal end of the receptor 445d and form

grooves in the bottom surface 443d of the sensor assembly receiver 400d. As well, in some embodiments, the sensor assembly receiver 400d can include an angled surface angled surface 441d. As can be seen in **FIG. I**, the angled surface 441d raises the bottom surface 443c. **FIGS. 10J – K** illustrates a sensor assembly receiver 400e that has a similar configuration to the sensor assembly receiver 400d described above. In the embodiment illustrated in sensor assembly receiver 400e, compared to the sensor assembly receiver 400d, the receptor 445e is narrower and the two detents 440e are longer.

[0091] As discussed above, the sensor assembly can be configured to include a key and detent structures that are structured to engage with the sensor assembly receiver that the sensor on the sensor assembly is configured to form an electrical connection with. **FIGS. 11F – H** illustrate three embodiments of the sensor assembly. **FIG 11F** illustrates a sensor assembly 800c that is configured to be inserted into a connector 200 with a sensor assembly receiver 400c as illustrated in **FIGS. 10E – G**. **FIG. 11G** illustrates a sensor assembly 800d that is configured to be inserted into a connector 200 with a sensor assembly receiver 400d as illustrated in **FIGS. 10H – I**. **FIG. 11H** illustrates a sensor assembly 800e that is configured to be inserted into a connector 200 with a sensor assembly receiver 400e as illustrated in **FIGS. 10J – K**.

[0092] **FIG. 11F** illustrates the underside of the sensor tab 810c of the sensor assembly 800c. The sensor assembly 800c can include a key 860c. In this embodiment, the key 860c is composed of two rectangular structures on the underside of the sensor tab 810c. As will be discussed in more detail below, the key 860c is configured to engage with the receptor 445c of the sensor assembly receiver 400c. On the proximal end 870c of the key 860c, the key 860c can include a curved bottom receptor 876c and a protruding bottom protrusion 874c. The bottom receptor 876c and bottom protrusion 874c can be configured to engage with the receptor protrusion 447c and the receptor end 449c respectively. The sensor assembly 800c can also include a key detent 865c. In some embodiments, the key detent 865c is located near the distal end of the sensor tab 810c between the two structures making up the key 860c. As will be discussed in more detail below, the key detent 865c is configured to engage with the detent 440c of the sensor assembly receiver 400c.

[0093] **FIG. 11G** illustrates sensor assembly 800d, another embodiment of the underside of the sensor tab of a sensor assembly and **FIG. 11M** illustrates a perspective

view of the sensor tab 810d. The sensor assembly 800d can also include a key 860d. In this embodiment, the key 860d is composed of a rectangular structure centered on the underside of the sensor tab 810d. As will be discussed in more detail below, the key 860d is configured to engage with the receptor 445d of the sensor assembly receiver 400d. On the proximal end 870d of the key 860d, the key 860d can include a curved bottom receptor 876d and a protruding bottom protrusion 874d. The bottom receptor 876d and bottom protrusion 874d can be configured to engage with the receptor protrusion 447d and the receptor end 449d respectively. The sensor assembly 800d can also include two key detents 865d. In some embodiments, the two key detents 865d are located near the distal end of the sensor tab 810d on either side of the key 860d. As will be discussed in more detail below, the two key detents 865d is configured to engage with the detents 440d of the sensor assembly receiver 400d. **FIG. 11H** illustrates a sensor assembly 800e that has a similar configuration to the sensor assembly 800d described above. In the embodiment illustrated in sensor assembly 800e, compared to the sensor assembly 800d, the key 860e is wider and the two key detents 865e are longer in order to engage with the receptor 445e and detents 440e of sensor assembly receiver 400e. As well, the bottom receptor 876d and bottom protrusion 874d are configured to engage with the receptor protrusion 447e and receptor end 449e respectively.

[0094] In some embodiments, the sensor assemblies can include additional structures that allow the sensor assemblies to be further secured within the connector 200. For example, **FIGS. 11I – L** illustrates embodiments of sensor assemblies from **FIGS. 11F – H** that further include structures on either side of the sensor tab that can be secured by the connector 200. In some embodiments, the structures on either side of the sensor tab can be configured to serve as a locking structure that secures the sensor tab to the connector exhaust line 200. **FIG. 11I** illustrates the sensor assembly 800c with a sensor tab 810c that includes an indentation 890c on either side of the sensor tab 810c. As noted above, in some embodiments, the indentations 890c can serve as a locking structure that engages the connector 200. **FIG. 11J** illustrates the sensor assembly 800d with a sensor tab 810d that includes an indentation 890d on either side of the sensor tab 810d. In some embodiments, the indentations 890d can serve as a locking structure that engages the connector 200. **FIG. 11K** illustrates the sensor assembly 800e with a sensor tab 810e that includes an indentation 890e on either side of the sensor tab 810e. In some embodiments, the indentations 890e can serve as a locking structure that engages the connector 200.

[0095] In operation, the connector 200 can include a locking structure that can be configured to interact with the indentations on either side of the sensor tab. In some embodiments, this locking structure prevents movement within the connector 200. In some variants, the connector 200 further includes an unlocking mechanism that releases the locking structure from the sensor tab. In some examples, the sensor assembly cannot be removed from the connector 200 without first actuating the unlocking mechanism. In other embodiments, the sensor tab can include other structures that allow the connector 200 to secure the sensor assembly within the connector 200.

[0096] In some embodiments, the sensor assembly can include a sensor tab with protrusions located on either side of the proximal end. In some variants, the protrusion can ensure that the sensor assembly is inserted into the sensor assembly receiver parallel to the pogo pins 1000 that extend through the sensor assembly receiver. In some embodiments, this can prevent the sensor assembly from being inserted at an angle and jamming the pogo pins 1000. **FIG. 11L** illustrates an example of the proximal end 870c of the sensor assembly 800c. As illustrated, in some embodiments, the proximal end 870c of the sensor assembly 800c includes a proximal protrusion 872c on either side of the top surface of the proximal end 870c of the sensor tab 810c. In some embodiments, the height of the proximal protrusion 872c ensures that the sensor tab 810c is inserted through the opening 420c at a distance from the top of the opening 420c and therefore at a distance from the pogo pins 1000.

[0097] The sensor assembly receiver embodiments illustrated in **FIGS. 10E – K** can reduce the wear on the surface sensor assembly through the configuration of the receptor and detent located on the insides surface of the sensor assembly receiver. As discussed above, the sensor assembly receiver includes a receptor that is configured to receive a key located on the underside of the sensor assembly. As discussed above, this ensures that the sensor assembly receiver can only receive certain sensor assemblies. As well, it ensures that the sensor assembly is attached to the sensor assembly receiver with the sensor side facing up so as to properly form an electrical connection with the pogo pins located inside the connector. In some embodiments, the detent located inside the sensor assembly receiver can engage with a corresponding detent located on the underside of the sensor assembly. As discussed above, the detent provides the user with a tactile or mechanical feedback to indicate to the user that the sensor assembly has been properly inserted. In the embodiments of the sensor assembly receivers illustrated in

FIGS. 10E – K, the sensor assembly receiver includes a ramp that brings the surface of the sensor assembly receiver

[0098] **FIGS. 14A – I** illustrate the interaction between the sensor assembly receiver and sensor assembly discussed above in **FIGS. 10E – K** and **11F – I** respectively. **FIGS. 14A – C** illustrate the sensor assembly 800c as it is inserted into the sensor assembly receiver 400c. **FIGS. 14A – B** provide a side cross-sectional view of the sensor assembly 800c as it is incrementally inserted into the sensor assembly receiver 400c. **FIG. 14C** provides a top perspective two-thirds cross-sectional view of the sensor assembly 800c as it is partially inserted into the sensor assembly receiver 400c. **FIGS. 14D – F** illustrate the sensor assembly 800d as it is inserted into the sensor assembly receiver 400d. **FIGS. 14D – E** provide a side cross-sectional view of the sensor assembly 800d as it is incrementally inserted into the sensor assembly receiver 400d. **FIG. 14F** provides a top perspective two-thirds cross-sectional view of the sensor assembly 800e as it is partially inserted into the sensor assembly receiver 400e. **FIGS. 14G – I** illustrate the sensor assembly 800e as it is inserted into the sensor assembly receiver 400e. **FIGS. 14G – H** provide a side cross-sectional view of the sensor assembly 800e as it is incrementally inserted into the sensor assembly receiver 400e. **FIG. 14I** provides a top perspective two-thirds cross-sectional view of the sensor assembly 800c as it is partially inserted into the sensor assembly receiver 400e.

[0099] In operation, as discussed above, in some embodiments the sensor assembly and sensor assembly receiver can interact to reduce the wear on the top surface of the sensor assembly as its received in the sensor assembly receiver. As illustrated in **FIG. 14A**, as the sensor assembly 800c is inserted into the sensor assembly receiver 400c, the sensor side 812c of the sensor tab 810c can interact with the plurality of pogo pins 1000 that extend downward into the sensor assembly receiver 400c. Because each of the plurality of pogo pins 1000 can be spring loaded, the closer the sensor side 812c is to the pogo pins 1000, the greater the pressure is exerted on the sensor side 812c of the sensor tab 810c as the sensor assembly 800c is inserted. In some embodiments, this can cause increased wear of the sensor on the sensor assembly 800c. In some examples, as illustrated in **FIGS. 14A – B**, wear on the sensor side 812c of the sensor tab 810c is reduced by creating two levels on the bottom surface 443c of the sensor assembly receiver 400c for the sensor assembly 800c to move against. As is illustrated in **FIG. 14A**, when the sensor assembly 800c is first inserted into the sensor assembly receiver

400c, the sensor tab 810c moves adjacent to the bottom surface 443c. In some embodiments, the bottom surface 443c is configured such that it reduces the interaction and pressure placed on the sensor side 812c by the plurality of pogo pins 1000. Then, as illustrated in **FIG. 14B**, as the sensor tab 810c of the sensor assembly 800c is further inserted into sensor assembly 800c, an angled surface 441c of the bottom surface 443c serves as a ramp to move the sensor tab 810c to an elevated level. In some embodiments, the sensor tab 810c further includes a ramp 815c on the distal end that can also serve to move the sensor tab 810c to an elevated level. This elevated level brings the sensor tab 810c closer against the plurality of pogo pins 1000 in order to provide a more secure electrical connection with the sensor assembly receiver 400c. In some embodiments, the key detent 865c and detent 440c, in addition to providing the user with a mechanical feedback, can serve to lock the sensor tab 810c of the sensor assembly 800c in the elevated configuration. In addition, in some examples, as illustrated in **FIG. 14C**, the bottom receptor 876c and bottom protrusion 874c located at the proximal end 870c of the sensor tab 810c can interact with the receptor protrusion 447c and receptor end 449c of the sensor assembly receiver 400c to secure the sensor assembly 800c in the sensor assembly receiver 400c. As illustrated in **FIGS. 14D – F** and **14G – I**, the sensor assembly 800d and sensor assembly receiver 400d and sensor assembly 800e and sensor assembly receiver 400e interact in a similar or identical manner as discussed above. These embodiments further illustrate the goal of reducing wear on the sensor side of the sensor tab in various embodiments. The numbering convention of **FIGS. 14A – C** applies to **FIGS. 14D – F** except the “c” is replaced with a “d” and **FIGS. 14G – I** except the “c” is replaced with an “e.”

[0100] As discussed above, one of the advantages of the present design is the ability of the connector and sensor assembly to accommodate various sensors with a wide range of electrical contacts. This is accomplished through the use of pogo pins 1000 and a sensor with a plurality of electrical contacts on its surface. As will be discussed more fully below, because the connector 200 can accommodate a large number of electrical contacts, the configuration of the pogo pins 1000 in the connector 200 is important to prevent short circuiting.

[0101] As discussed above, the sensor assembly can accommodate different sensors. For example, as shown in **FIGS. 11A – 11C**, the sensor assembly 800a has a connector assembly 840a has a top connector assembly 842a and bottom connector

assembly 844a that can accommodate and retain the sensor. The proximal end of the sensor has a plurality of electrical contacts on the sensor that are located on the sensor side 812a of the sensor tab 810a. **FIG. 12A** illustrates an example of a sensor assembly proximal end 900 with the sensor placed on the sensor tab. The sensor assembly proximal end 900 includes the connector assembly 970 with a sensor tab 910 and lip 930 on the proximal end. The sensor 940 is retained between the two parts of the connector assembly 970 such that the sensor 940 protrudes from both the opening 990 of the top connector assembly 960 and also from the distal end 980 of the connector assembly 970. The proximal end of the sensor 940 has a plurality of electrical contacts on its surface (e.g. electrical contact 900a1, electrical contact 900b1, electrical contact 900c1, electrical contact 900c2, electrical contact 900d1, electrical contact 900d2, electrical contact 900e1, electrical contact 900f1, electrical contact 900g1, electrical contact 900g2) that are configured to engage the contact tips 1170 of the plurality of pogo pins 1000.

[0102] As can be seen in **FIG. 12A**, the staggered electrical contacts on the surface of the sensor 940 are arranged in a plurality of rows. In the example shown in **FIG. 12A**, electrical contact 900a1 is in one row, electrical contact 900b1 is in a second row, electrical contact 900c1 and electrical contact 900c2 are in a third row, electrical contact 900d1 and electrical contact 900d2 are in a fourth row, electrical contact 900e1 is in a fifth row, electrical contact 900f1 is in a sixth row, and sensor assembly proximal end 900 electrical contact g1 and electrical contact 900g2 is in a seventh row. As will be further shown below, the plurality of pogo pins 1000 are arranged and retained in a similar configuration in the inner shield 600.

[0103] **FIG. 12B** illustrates an embodiment of the sensor assembly proximal end 900 wherein the plurality of traces 950 includes a ground trace 955. As seen in **FIG. 12B**, the ground trace 955 – labeled as trace 950 “3” – has portions that extend from the proximal end of the sensor tab to the proximal end of the lip 930. As illustrated in **FIG. 12C**, in some embodiments, the ground trace 955b is electrically connected entirely on the surface of the sensor tab. In other embodiments, as illustrated in **FIG. 12B**, the ground trace 955 has portions that are electrically connected beneath the surface of the sensor. In other embodiments, the ground trace 955 is intermittently connected across the surface of the sensor.

[0104] In some embodiments, the ground trace 955 can serve as a grounding line to discharge any buildup of static electricity in the sensor assembly. In some

embodiments, to prevent damage to the connector 200 or the sensor assembly, the sensor assembly can be discharged before certain electrical connections are formed between the plurality of pogo pins 1000 and the traces 950 (e.g. whether some or all of the traces 950). In some examples, in order to ground the sensor assembly before any of the plurality of pogo pins 1000 contacts any of the plurality of traces 950, the ground trace 955 can be configured such that a portion of the connector 200 will contact the ground trace 955 before any of the other traces 950. For example, as illustrated in **FIG. 12B**, in some embodiments, the ground trace 955 extends further in a proximal direction than the other traces in the same row (e.g. trace “10”, trace “11”, and trace “12”). In this way, as the sensor side 920 of the sensor assembly proximal end 900 is inserted into the connector 200, a structure within the connector 200 will contact the ground trace 955 to first discharge the sensor assembly before the plurality of pogo pins 1000 contact the remaining traces 950 on the sensor side 920.

[0105] In order to ground the sensor assembly, a portion of the connector 200 can be grounded. In some embodiments the outer shield 300 is connected to ground. In other embodiments, the inner shield 600 is connected to ground. As discussed above, in some examples, a portion of the connector 200 that is configured to contact the sensor side 920 of the sensor assembly is connected to the grounded portion of the connector 200 (for example, the outer shield 300 or the inner shield 600). In some examples, one of the plurality of pogo pins 1000 is connected to ground and can be configured to contact the ground trace 955. In other examples, the inside surface of the connector 200 includes a structure (for example, a protrusion or extended piece such as a flexible wire or contact) near the opening of the connection which is configured to contact the ground trace 955 to ground the sensor assembly before contact is made with any other electrically conductive portion of the connector 200.

[0106] **FIGS. 13A – 13B** show an example of a connector with pogo pins 1000 that correspond with the electrical contacts on the sensor of the corresponding sensor assembly. The sensor assembly proximal end 1300 shown in **FIG. 13A** has a connector assembly 1310 with a top connector assembly 1320 that has an opening 1360 from which the sensor 1340 protrudes from. The sensor 1340 is contained on the sensor tab 1330 and has a plurality of electrical contacts 1350. **FIG. 13B** shows a cross-sectional view of the connector 1400 with a plurality of pogo pins 1000. In the example sensor assembly and connector shown in **FIGS. 13A – 13B**, the configuration of the

electrical contacts on the sensor 1340 and pogo pins 1000 in the connector 1400 are arranged to establish a plurality of electrical connections between the sensor 1340 and the connector 1400. The sensor 1340 has a plurality of electrical contacts – electrical contact a, electrical contact b1, electrical contact b2, electrical contact c1, electrical contact c2, electrical contact d1, electrical contact d2, electrical contact e1, electrical contact e2, electrical contact e3, electrical contact e4, electrical contact f1, electrical contact f2, electrical contact g1, and electrical contact g2. The connector 1400 has a plurality of pogo pins 1000 – pogo pin contact a', pogo pin contact b1', pogo pin contact b2', pogo pin contact c1', pogo pin contact c2', pogo pin contact d1', pogo pin contact d2', pogo pin contact e1', pogo pin contact e2', pogo pin contact e3', pogo pin contact e4', pogo pin contact f1', pogo pin contact f2', pogo pin contact g1', and pogo pin contact g2'. These pogo pins 1000 contact the plurality of electrical contacts 1350 to establish a plurality of electrical connections. In the present example, once the sensor tab 1330 is fully inserted into the connector 1400, the following pogo pins contact the following electrical contacts: pogo pin contact a' with electrical contact a, pogo pin contact b1' with electrical contact b1, pogo pin contact b2' with electrical contact b2, pogo pin contact c1' with electrical contact c1, pogo pin contact c2' with electrical contact c2, pogo pin contact d1' with electrical contact d1, pogo pin contact e1' with electrical contact e1, pogo pin contact f1' with electrical contact f1, pogo pin contact f2' with electrical contact f2, pogo pin contact g1' with electrical contact g1, and pogo pin contact g2' with electrical contact g2.

[0107] As the sensor tab 1330 is inserted into the opening 1410 of the sensory assembly receiver 1420, the pogo pins 1000 proximal to the opening 1410 will contact the length of the sensor 1340 before connecting with its corresponding electrical contacts. For example, pogo pin contact a1' will contact the proximal end of the sensor 1340 before reaching the electrical contact a. Therefore, in one configuration, to prevent short circuiting, the electrical contacts on the sensor 1340 and the corresponding pogo pins 1000 in the connector 1400 are arranged in staggered rows to minimize the electrical contacts that the proximal end of each of the pogo pins 1000 will touch as the sensor tab 1330 is inserted into the connector 1400. For example, as seen in **FIG. 13A**, the electrical contact b1 is located proximal and between the electrical contact a and electrical contact c1. In this way, the pogo pin contact a1' and pogo pin contact c1' on either side of the pogo pin contact b1' will not contact the electrical contact b1 as the sensor tab 1330 is inserted.

[0108] Another potential benefit of the staggering of the electrical contacts on the sensor tab 1330 and the pogo pins 1000 in the connector 1400 is the increase in electrical connections that a sensor can have given the configuration of the sensor tab 1330 and the inner shield 600 of the connector 1400. As discussed earlier, because of the configuration of the pogo pins 1000 and the electrical contacts on the sensor tab 1330, the disclosed configuration of the sensor assembly and connector can accommodate sensors requiring a large number of electrical contacts.

[0109] Although this disclosure has been disclosed in the context of certain preferred embodiments and examples, it will be understood by those skilled in the art that the present disclosure extends beyond the specifically disclosed embodiments to other alternative embodiments and/or uses of the disclosure and obvious modifications and equivalents thereof. In addition, while a number of variations of the disclosure have been shown and described in detail, other modifications, which are within the scope of this disclosure, will be readily apparent to those of skill in the art based upon this disclosure. It is also contemplated that various combinations or sub-combinations of the specific features and aspects of the embodiments may be made and still fall within the scope of the disclosure. Accordingly, it should be understood that various features and aspects of the disclosed embodiments can be combined with or substituted for one another in order to form varying modes of the disclosed

EMBODIMENTS IN WHICH AN EXCLUSIVE PROPERTY OR PRIVILEGE IS CLAIMED ARE DEFINED AS FOLLOWS:

1. A connector and sensor assembly, the assembly including:

a connector including:

an opening with an internal surface, and

a plurality of retractable electrical connectors extending from the internal surface;

a sensor assembly including:

a body portion, and

a proximal end with a top side including a plurality of electrical contacts, wherein the proximal end is configured to be removably inserted into the opening of the connector and wherein the plurality of electrical contacts include an electrical contact which serves as a grounding line,

wherein any of the plurality of retractable electrical connectors contacts the grounding line first before contacting any of the remaining plurality of electrical contacts, and

wherein the grounding line is electrically connected entirely on a top side of the proximal end of the sensor assembly.

2. The connector and sensor assembly according to Claim 1 wherein the plurality of retractable electrical connectors are pogo pins.

3. The connector and sensor assembly according to Claim 1 or 2 wherein the plurality retractable electrical connectors are in a staggered configuration.
4. The connector and sensor assembly according to Claim 3 wherein the plurality of retractable electrical connectors are configured into a plurality of rows, wherein each row can include one or more of the plurality of retractable electrical connectors.
5. The connector and sensor assembly according to any one of Claims 1-4 wherein the plurality of electrical contacts on the sensor assembly are in a staggered configuration.
6. The connector and sensor assembly according to Claim 5 wherein the plurality of electrical contacts are configured into a plurality of rows, wherein each row can include one or more of the plurality of electrical contacts.
7. The connector and sensor assembly according to any one of Claims 1-6 wherein the connector includes a first color indicator and the sensor assembly includes a second color indicator, wherein the first color indicator and second color indicator are the same colors.
8. The connector and sensor assembly according to any one of Claims 1-7 wherein the sensor assembly includes a visual indicator that indicates the type of sensor assembly to a user.
9. The connector and sensor assembly according to any one of Claims 1-8 further including a first tapered surface on a proximal end of the connector and a second tapered surface on the proximal end of the sensor assembly, and wherein the first tapered surface tapers into the opening of the connector and the second tapered surface tapers outward.
10. The connector and sensor assembly according to Claim 9 wherein the first tapered surface of the connector is configured to interact with the second tapered surface of the sensor assembly.

11. The connector and sensor assembly according to Claim 9 wherein the tapered surface of the sensor assembly is configured to raise each of the plurality of retractable electrical connectors as the sensor assembly is inserted into the opening of the connector, wherein the second tapered surface of the sensor assembly is configured to reduce wear of the plurality of electrical contacts.
12. The connector and sensor assembly according to any one of Claims 1-11 wherein the grounding line is located near the proximal end of the sensor assembly.
13. The connector and sensor assembly according to any one of Claims 1-12 wherein the grounding line is located entirely on a surface of the sensor assembly.
14. The connector and sensor assembly according to any one of Claims 1-12 wherein the grounding line is partially located above a surface of the sensor assembly and partially located below the surface of the sensor assembly.
15. The connector and sensor assembly according to any one of Claims 1-12 wherein the grounding line is intermittently connected across a surface of the sensor assembly.
16. A male connector assembly which physically connects to and electrically communicates with corresponding female connector, the male connector comprising:

a flat board portion; and

a plurality of electrical contacts arranged on the flat board portion in a staggered configuration, wherein at least one of the electrical contacts is a ground contact, the ground contact is arranged to physically contact and electrically communicate with a corresponding electrical contact of a female connector before any other contact of the electrical contacts comes into electrical communication with a corresponding electrical contact of the female connector, and

wherein the ground contact is electrically connected entirely on a surface of the flat board portion.

17. The male connector according to Claim 16 wherein the electrical contacts are configured into a plurality of rows, wherein each row can include one or more of the electrical contacts.
18. The male connector according to Claim 16 or 17 wherein the male connector includes a color indicator that corresponds with a color indicator of the female connector.
19. The male connector according to any one of Claims 16-18 wherein the male connector includes a visual indicator that indicates the type of male connector to a user.
20. The male connector according to any one of Claims 16-19 further including a tapered surface on a proximal end of the flat board portion of the male connector that is configured to engage with a tapered surface on a proximal end of the female connector.
21. The male connector according to Claim 20 wherein the tapered surface on the male connector tapers outward and the tapered surface on the female connector tapers into the opening of the female connector.
22. The male connector according to any one of Claims 16-21 wherein the ground contact is located near a proximal end of the male connector.
23. The male connector according to any one of Claims 16-22 wherein the ground contact is located entirely on the surface of the flat board portion.
24. The male connector according to any one of Claims 16-22 wherein the ground contact is partially located above and partially located below the surface of the flat board portion.

- 25.** The male connector according to any one of Claims **16-22** wherein the ground contact is intermittently connected across the surface of the flat board portion.
- 26.** The male connector according to any one of Claims **16-19** further comprising a key structure located on an opposite surface of the electrical contacts and configured to engage a lock structure of the female connector.
- 27.** The male connector according to Claim **26** wherein the key structure is a protrusion in the shape of a rectangle.
- 28.** The male connector according to Claim **26** wherein the key structure includes a first detent that is configured to interact with a second detent on the female connector to provide a tactile feedback to the user.
- 29.** The male connector according to Claim **26** wherein the key structure is configured to only engage the lock structure of the corresponding female connector.
- 30.** The male connector according to Claim **26** wherein the key structure is a plurality of indentations located on either side of a proximal end of the flat board portion that can be secured by the lock structure of the female connector.
- 31.** The male connector according to Claim **26** wherein the key structure is a centered rectangular structure with a curved indentation at a proximal end of the flat board portion and a proximal lip.




FIG. 1A




FIG. 1B




FIG. 1C




FIG. 1D




FIG. 2A




FIG. 2B




FIG. 3




FIG. 4A




FIG. 4B




FIG. 4C




FIG. 4D




FIG. 5A





FIG. 5B







FIG. 6B

**FIG. 6C**




FIG. 7A




FIG. 8A





FIG. 8B






FIG. 8D




FIG. 9A




FIG. 9B




FIG. 9C




FIG. 9D




FIG. 9E




FIG. 10A






FIG. 10B

**FIG. 10C****FIG. 10D**




FIG. 10E




FIG. 10F




FIG. 10G




FIG. 10H




FIG. 10I




FIG. 10J




FIG. 10K




FIG. 11A




FIG. 11B




FIG. 11C




FIG. 11D




FIG. 11E




FIG. 11F




FIG. 11G




FIG. 11H




FIG. 11I




FIG. 11J




FIG. 11K





FIG. 11L






FIG. 12A




FIG. 12B




FIG. 12C




FIG. 13A




FIG. 13B




FIG. 14A




FIG. 14B




FIG. 14C




FIG. 14D




FIG. 14E




FIG. 14F




FIG. 14G




FIG. 14H




FIG. 14I

