




(86) Date de dépôt PCT/PCT Filing Date: 2009/09/29
(87) Date publication PCT/PCT Publication Date: 2010/04/08
(85) Entrée phase nationale/National Entry: 2010/05/28
(86) N° demande PCT/PCT Application No.: JP 2009/004991
(87) N° publication PCT/PCT Publication No.: 2010/038427
(30) Priorité/Priority: 2008/10/02 (JP2008-257679)

(51) Cl.Int./Int.Cl. *G11B 20/18* (2006.01),
G11B 20/14 (2006.01), *G11B 7/005* (2006.01)
(71) Demandeur/Applicant:
PANASONIC CORPORATION, JP
(72) Inventeurs/Inventors:
ITO, KIYOTAKA, JP;
HINO, YASUMORI, JP;
MIYASHITA, HARUMITSU, JP;
KOBAYASHI, ISAO, JP
(74) Agent: OSLER, HOSKIN & HARCOURT LLP

(54) Titre : PROCEDE D'EVALUATION D'UN SIGNAL REPRODUIT, SUPPORT D'ENREGISTREMENT
D'INFORMATIONS, DISPOSITIF DE REPRODUCTION, ET DISPOSITIF D'ENREGISTREMENT
(54) Title: REPRODUCED SIGNAL EVALUATING METHOD, INFORMATION RECORDING MEDIUM, REPRODUCING
DEVICE, AND RECORDING DEVICE



(57) Abrégé/Abstract:

A reproduction signal evaluation method according to the present invention includes a step of generating a binary signal from an information recording medium on which a data sequence including marks and spaces in combination is recordable, using a PRML

(57) Abrégé(suite)/Abstract(continued):

signal processing method from a signal obtained by reproducing the data sequence; and a differential calculation step of calculating a differential metric using a first state transition path having a maximum likelihood and a second state transition path having a second maximum likelihood, and a reproduction signal, the first state transition path and the second state transition path being obtained based on the binary signal. In a pattern including a shortest mark and a shortest space adjacent before or after the shortest mark, a shift amount of an edge of the shortest mark is obtained from a differential metric calculated regarding one of a first pattern in which a space adjacent to the shortest mark and not adjacent to the shortest space is longer than the shortest space; and a second pattern in which a mark adjacent to the shortest space and not adjacent to the shortest mark is longer than the shortest mark.

ABSTRACT

A reproduction signal evaluation method according to the present invention includes a step of generating a binary signal from an information recording medium on which a data sequence including marks and spaces in combination is recordable, using a PRML signal processing method from a signal obtained by reproducing the data sequence; and a differential calculation step of calculating a differential metric using a first state transition path having a maximum likelihood and a second state transition path having a second maximum likelihood, and a reproduction signal, the first state transition path and the second state transition path being obtained based on the binary signal. In a pattern including a shortest mark and a shortest space adjacent before or after the shortest mark, a shift amount of an edge of the shortest mark is obtained from a differential metric calculated regarding one of a first pattern in which a space adjacent to the shortest mark and not adjacent to the shortest space is longer than the shortest space; and a second pattern in which a mark adjacent to the shortest space

and not adjacent to the shortest mark is longer than the
shortest mark.

DESCRIPTION

REPRODUCED SIGNAL EVALUATING METHOD, INFORMATION RECORDING
MEDIUM, REPRODUCING DEVICE, AND RECORDING DEVICE

TECHNICAL FIELD

[0001] The present invention relates to a signal processing method using maximum likelihood decoding and a method for evaluating an information recording medium using maximum likelihood decoding.

BACKGROUND ART

[0002] Recently, as the recording density for information recording mediums is being improved, the shortest mark length of recording marks is approaching the limit of the resolving power, which relies on a detection system.

[0003] In the case where, for example, an information recording medium is an optical disc medium, the "resolving power, which relies on a detection system" means an optical resolving power, which relies on the size of an optical spot generated by collecting laser light.

[0004] Due to the limit of the resolving power, increase of the inter-code interference and deterioration of SNR (Signal to Noise Ratio) are more conspicuous. As a result, a PRML (Partial Response Maximum Likelihood) method or the like is now used generally as a signal processing method.

[0005] The PRML method is a technology generated by combining partial response (PR) and maximum likelihood (ML). By the PRML method, with a premise that known inter-code interference occurs, a signal sequence having the maximum likelihood is selected from a reproduction waveform.

[0006] Owing to this, the PRML method is known to improve the decoding capability than a conventional level determination method (e.g., Non-Patent Document No. 1).

[0007] In the meantime, because the signal processing method is now changed from the level determination method to the PRML method, problems occur in the evaluation method of a reproduction signal.

[0008] Jitter, which is a conventionally used reproduction signal evaluation index, is used with a premise that signal processing is performed by the level determination method.

Therefore, occasionally, jitter may not be correlated with the decoding capability of the PRML method, which is based on a different signal processing algorithm from the level determination method.

[0009] Under the circumstances, new indices which are correlated with the decoding capability of the PRML method has been proposed (e.g., Patent Document No. 1 and Patent Document No. 2).

[0010] Now, a case where the recording and reproduction quality is detected as distributions shown in FIG. **25** will be discussed.

[0011] FIG. **25** shows four distributions of differential metrics classified by the length of the space of 2T, 3T, 4T or 5T combined with a 3T-long mark, and the total of the four distributions. T represents a channel clock.

[0012] In FIG. **25**, only 3T-long marks are classified as an example, but usually marks of other lengths are also classified.

[0013] In the case where classification is made by the length of the mark and the length of the space, there are the

following two cases. In the case of FIG. **25(a)**, an SN component, which is the distribution width, is dominant in the distributions of in all the mark-space combinations. In the case of FIG. **25(b)**, an SN component of each pattern is good, but a shift component from the center of the distribution is different among the patterns. When the distributions are summed up, it appears that the SN component is poor.

[0014] The index described in Patent Document No. 1 cannot distinguish whether each distribution of differential metric is caused by an SN component or by a shift component.

[0015] Patent Document No. 3 solves this problem.

[0016] The index proposed in Patent Document No. 3 can detect a positional shift between a mark and a space (edge shift) by a combination of a mark length and a space length.

[0017] Namely, the level of the recording and reproduction quality obtained by the index proposed in Patent Document No. 1 can be distinguished as corresponding to an SN component or as corresponding to a shift component.

[0018] Owing to such distinguishing between an SN

component and a shift component, it is now possible to analyze which type of error occurs in which pattern.

[0019] As described above, as the recording density of information recording mediums is more improved, the problems of the inter-code interference and SN deterioration will be more serious.

[0020] It is described in Non-Patent Document No. 1 that the system margin of an information recording and reproduction apparatus can be maintained by using a higher-order PRML method.

[0021] For example, when the recording capacity of one recording layer of a 12-cm optical disc medium is 25 GB, the system margin can be maintained by adopting the PR1221ML method.

[0022] The above-mentioned book describes that when the recording capacity of one recording layer is 33.3 GB, the PR12221ML method needs to be adopted.

CITATION LIST

PATENT LITERATURE

[0023]

Patent Document No. 1: Japanese Laid-Open Patent

Publication No. 2003-141823

Patent Document No. 2: Japanese Laid-Open Patent

Publication No. 2004-213862

Patent Document No. 3: Japanese Laid-Open Patent

Publication No. 2004-335079

NON PATENT LITERATURE

[0024]

Non-Patent Document No. 1: "Illustrated Blu-ray Disc Reader" ("Zukai Blu-ray Disc Dokuhon") published by Ohmsha, Ltd.

Non-Patent Document No. 2: "Adaptive Signal Processing Algorithm ("Tekioh Shingoshori Algorithm") published by Baifukan, Co., Ltd.

SUMMARY OF INVENTION

TECHNICAL PROBLEM

[0025] Patent Document No. 3 proposes an index capable of

detecting a positional shift of a combination of one mark and one space (edge shift). The positional shift represents the recording and reproduction quality of an information recording medium.

[0026] However, in an information recording medium having a higher recording density, there are marks and spaces which are much shorter than the length detectable by the resolving power of the detection system. Therefore, it is necessary to consider a positional shift including a plurality of edges provided by a combination of one or more marks and one or more spaces.

[0027] Hereinafter, a positional shift including a plurality of edges will be described.

[0028] The description will be given with a 12-cm optical disc medium for blue laser having a wavelength of 405 nm as an example.

[0029] According to Non-Patent Document No. 1, when blue laser is collected on an optical disc medium, the size of an optical spot is 390 nm. When the recording capacity of one recording layer using RLL(1,7) as a recording code is 25 GB,

the length of the shortest mark is 149 nm.

[0030] When the recording capacity of one recording layer of this optical disc medium is 33.3 GB, the length of the shortest mark is 112 nm. When the recording density is further improved, the length of the shortest mark is shorter.

[0031] Even where an identical detection system is used, when the recording density is 25 GB as shown in FIG. **26(a)**, the number of the shortest marks encompassed in an optical spot **201** is 2.6; whereas when the recording density is 33.3 GB as shown in FIG. **26(b)**, the number of the shortest marks encompassed in the optical spot **201** is 3.5. The length of the marks in the size of optical spot, which acts as the detection system for the optical disc medium, is shorter.

[0032] Therefore, an optical spot size may occasionally encompass a combination of a plurality of marks and spaces, instead of a combination of one mark and one space.

[0033] As a result, a signal influenced by a positional shift of a plurality of edges is detected, depending on the number of the marks and spaces encompassed in the optical spot size.

[0034] For example, a pattern in FIG. **27(a)** in which one mark is sandwiched by two spaces, and a pattern in FIG. **27(b)** in which one space is sandwiched by two marks, both include two edges. A pattern in FIG. **27(c)**, which include two marks and two spaces, includes three edges.

[0035] The index for evaluating the recording and reproduction quality of an information recording medium described in Patent Document No. 3 considers only the case where one edge shift of a combination of a mark length and a space length is included, and does not consider evaluating the recording and reproduction quality regarding a positional shift including a plurality of edges.

[0036] Non-Patent Document No. 1 describes that for a 12-cm optical disc medium for blue laser having a recording capacity per layer of 33.3 GB, the PR12221ML method needs to be adopted. Patent Document No. 3 describes that the proposed index is applicable to the PR12221ML method.

[0037] When the PR12221ML method is used for an optical disc medium using RLL(1,7) as a recording code, the shortest marks are present in succession, and there is a pattern in

which the square of the Euclidean distance between two ideal signals, i.e., a state transition path having the maximum likelihood and a state transition path having the second maximum likelihood, is 12.

[0038] The pattern in which the square of the Euclidean distance is 12 will be described later in detail.

[0039] The pattern in which the square of the Euclidean distance is 12 includes the shortest marks which are detected as a pattern including a plurality of edges as shown in FIG 27.

[0040] It is now possible to provide an index representing a detection signal including information on a plurality of edge shifts which are detected by the PRML signal processing. However, provision of an index representing how each edge is shifted has not considered so far.

[0041] The present invention for solving the above-described problems of the conventional art has an object of providing a method and an apparatus for evaluating a recording and reproduction quality by classifying detection signals including a plurality of edges into patterns and

providing an index for evaluating various positional shifts caused in a high density information recording medium by inter-code interference of recording marks or interference of heat which is used for recording information on the information recording medium.

SOLUTION TO PROBLEM

[0042] A reproduction signal evaluation method according to the present invention includes a step of generating a binary signal from an information recording medium on which a data sequence including marks and spaces in combination is recordable, using a PRML signal processing method from a signal obtained by reproducing the data sequence; and a differential calculation step of calculating a differential metric using a first state transition path having a maximum likelihood and a second state transition path having a second maximum likelihood, and a reproduction signal, the first state transition path and the second state transition path being obtained based on the binary signal. In a pattern including a shortest mark and a shortest space adjacent

before or after the shortest mark, a shift amount of an edge of the shortest mark is obtained from a differential metric calculated regarding one of a first pattern in which a space adjacent to the shortest mark and not adjacent to the shortest space is longer than the shortest space; and a second pattern in which a mark adjacent to the shortest space and not adjacent to the shortest mark is longer than the shortest mark.

[0043] In an embodiment, where a reference cycle of the data sequence is T , the shortest mark and the shortest space each have a length of $2T$; and where binary data of a pattern including the shortest mark and the shortest space adjacent to each other is represented by "0" and "1", the shift amount of the edge of the shortest mark is obtained from a differential metric calculated regarding a pattern, the binary data of which is "x000110011x" or "x001100111x" ("x" is "0" or "1").

[0044] In an embodiment, where a reference cycle of the data sequence is T , the shortest mark and the shortest space each have a length of $2T$; and where binary data of a pattern

including the shortest mark and the shortest space adjacent to each other is represented by "0" and "1", the shift amount of the edge of the shortest mark is obtained from a differential metric calculated regarding a pattern, the binary data of which is "x110011000x" or "x111001100x" ("x" is "0" or "1").

[0045] An information recording medium according to the present invention is an information recording medium on which a data sequence including marks and spaces in combination is recordable. The information recording medium has a track on which the data sequence is recordable. A reproduction signal from the information recording medium is evaluated using a prescribed method. The prescribed method includes a step of generating a binary signal using a PRML signal processing method from a signal obtained by reproducing the data sequence from the information recording medium; and a differential calculation step of calculating a differential metric using a first state transition path having a maximum likelihood and a second state transition path having a second maximum likelihood, and a reproduction signal, the first

state transition path and the second state transition path being obtained based on the binary signal. In a pattern including a shortest mark and a shortest space adjacent before or after the shortest mark, a shift amount of an edge of the shortest mark is obtained from a differential metric calculated regarding one of a first pattern in which a space adjacent to the shortest mark and not adjacent to the shortest space is longer than the shortest space; and a second pattern in which a mark adjacent to the shortest space and not adjacent to the shortest mark is longer than the shortest mark.

[0046] A reproduction apparatus according to the present invention is a reproduction apparatus for reproducing information from the above-described information recording medium. The reproduction apparatus includes an irradiation section for irradiating the track with laser light; a light receiving section for receiving reflected light of the laser light used for the irradiation; and a reproduction section for reproducing the data sequence based on a signal obtained by the received light.

[0047] A recording apparatus according to the present invention is a recording apparatus for recording information on the above-described information recording medium. The recording apparatus includes an irradiation section for irradiating the track with laser light; and a recording section for forming marks on the track by the irradiation to record a data sequence including marks and spaces between the marks arranged alternately.

[0048] A reproduction signal evaluation method according to the present invention is a method for evaluating a reproduction signal obtained from an information recording medium on which a data sequence including marks and spaces in combination is recordable. The method includes a recognition step of recognizing a prescribed pattern from the data sequence; and an evaluation step of evaluating a reproduction signal corresponding to the recognized pattern. The recognition step includes the steps of recognizing a pattern, included in the data sequence, including a first mark, a first space adjacent before or after the first mark, and a second mark not adjacent to the first mark and adjacent to

the first space; and recognizing, when the first space and the second mark each have a length equal to or shorter than a prescribed length, whether or not a second space not adjacent to the first mark and adjacent to the second mark is longer than the prescribed length.

[0049] An information recording medium according to the present invention is an information recording medium on which a data sequence including marks and spaces in combination is recordable. The information recording medium has a track on which the data sequence is recordable. A reproduction signal from the information recording medium is evaluated using a prescribed method. The prescribed method includes a recognition step of recognizing a prescribed pattern from the data sequence; and an evaluation step of evaluating a reproduction signal corresponding to the recognized pattern. The recognition step includes the steps of recognizing a pattern, included in the data sequence, including a first mark, a first space adjacent before or after the first mark, and a second mark not adjacent to the first mark and adjacent to the first space; and recognizing, when the first space and

the second mark each have a length equal to or shorter than a prescribed length, whether or not a second space not adjacent to the first mark and adjacent to the second mark is longer than the prescribed length.

[0050] A reproduction apparatus according to the present invention is a reproduction apparatus for reproducing information from the above-described information recording medium. The reproduction apparatus includes an irradiation section for irradiating the track with laser light; a light receiving section for receiving reflected light of the laser light used for the irradiation; and a reproduction section for reproducing the data sequence based on a signal obtained by the received light.

[0051] A recording apparatus according to the present invention is a recording apparatus for recording information on the above-described information recording medium. The recording apparatus includes an irradiation section for irradiating the track with laser light; and a recording section for forming marks on the track by the irradiation to record a data sequence including marks and spaces between the

marks arranged alternately.

[0052] A reproduction signal evaluation method according to the present invention is a method for evaluating a reproduction signal obtained from an information recording medium on which a data sequence including marks and spaces in combination is recordable. The method includes a recognition step of recognizing a prescribed pattern from the data sequence; and an evaluation step of evaluating a reproduction signal corresponding to the recognized pattern. The recognition step includes the steps of recognizing a pattern, included in the data sequence, including a first mark, a first space adjacent before or after the first mark, and a third space not adjacent to the first space and adjacent to the first mark; and recognizing, when the first mark and the third space each have a length equal to or shorter than a prescribed length, whether or not a third mark not adjacent to the first space and adjacent to the third space is longer than the prescribed length.

[0053] An information recording medium according to the present invention is an information recording medium on which

a data sequence including marks and spaces in combination is recordable. The information recording medium has a track on which the data sequence is recordable. A reproduction signal from the information recording medium is evaluated using a prescribed method. The prescribed method includes a recognition step of recognizing a prescribed pattern from the data sequence; and an evaluation step of evaluating a reproduction signal corresponding to the recognized pattern. The recognition step includes the steps of recognizing a pattern, included in the data sequence, including a first mark, a first space adjacent before or after the first mark, and a third space not adjacent to the first space and adjacent to the first mark; and recognizing, when the first mark and the third space each have a length equal to or shorter than a prescribed length, whether or not a third mark not adjacent to the first space and adjacent to the third space is longer than the prescribed length.

[0054] A reproduction apparatus according to the present invention is a reproduction apparatus for reproducing information from the above-described information recording

medium. The reproduction apparatus includes an irradiation section for irradiating the track with laser light; a light receiving section for receiving reflected light of the laser light used for the irradiation; and a reproduction section for reproducing the data sequence based on a signal obtained by the received light.

[0055] A recording apparatus according to the present invention is a recording apparatus for recording information on the above-described information recording medium. The recording apparatus includes an irradiation section for irradiating the track with laser light; and a recording section for forming marks on the track by the irradiation to record a data sequence including marks and spaces between the marks arranged alternately.

ADVANTAGEOUS EFFECTS OF INVENTION

[0056] According to the present invention, a shift amount of the edge of the shortest mark of a 2T/2T portion, which is a 2T-continuous pattern, is obtained by calculating a differential metric of a pattern including a 3T or longer

mark or space provided before or after the 2T/2T portion. Owing to this, even where a sufficient signal fluctuation of the 2T/2T portion is not obtained, the shift amount of the edge of the shortest mark of the 2T/2T portion can be detected.

[0057] The present invention is directed to a signal evaluation method, usable for an information recording medium having a data sequence including a mark and a space located alternately, for generating a binary signal from a signal obtained by reproducing the data sequence using a PRML signal processing method and evaluating a likelihood of the binary signal. From the binary signal, a differential metric which is a difference of a reproduction signal from a first state transition path having a maximum likelihood and a second state transition path having a second maximum likelihood is calculated. The differential metric is classified to any of a plurality of data patterns each including at least one mark and at least one space. The data pattern classification to any of a plurality of data patterns is performed using a combination of a length of a first mark included in the data

sequence and a length of a first space adjacently located immediately previous or immediately subsequent to the first mark, and is further performed using a length of a second mark which is not adjacent to the first mark and located adjacent to the first space. Thus, a reproduction signal quality of the information recording medium is evaluated, and an index for an edge shift of each data pattern including at least one edge can be provided.

[0058] The present invention is also directed to a signal evaluation method, usable for an information recording medium having a data sequence including a mark and a space located alternately, for generating a binary signal from a signal obtained by reproducing the data sequence using a PRML signal processing method and evaluating a likelihood of the binary signal. From the binary signal, a differential metric which is a difference of a reproduction signal from a first state transition path having a maximum likelihood and a second state transition path having a second maximum likelihood is calculated. The differential metric is classified to any of a plurality of data patterns each including at least one mark

and at least one space. The data pattern classification to any of a plurality of data patterns is performed using a combination of a length of a first mark included in the data sequence and a length of a first space adjacently located immediately previous or immediately subsequent to the first mark, and is further performed using a length of a third space which is not adjacent to the first space and located adjacent to the first mark. Thus, a reproduction signal quality of the information recording medium is evaluated, and an index for an edge shift of each data pattern including at least one edge can be provided.

BRIEF DESCRIPTION OF DRAWINGS

[0059]

FIG. 1 shows an optical disc apparatus according to an embodiment of the present invention.

FIG. 2 shows a state transition rule defined by the RLL(1,7) recording code and the equalization method PR(1,2,2,2,1) according to the embodiment of the present invention.

FIG. 3 is a trellis diagram corresponding to the state transition rule shown in FIG. 2.

FIG. 4 shows PR equalization ideal waveforms shown in Table 1 according to the embodiment of the present invention.

FIG. 5 is PR equalization ideal waveforms shown in Table 2 according to the embodiment of the present invention.

FIG. 6 is PR equalization ideal waveforms shown in Table 3 according to the embodiment of the present invention.

FIG. 7 shows classification into detailed patterns of differential metrics having a 14-detection pattern by PR(1,2,2,2,1)ML according to the embodiment of the present invention.

FIG. 8 shows classification into detailed patterns of differential metrics having a 12A-detection pattern by PR(1,2,2,2,1)ML according to the embodiment of the present invention.

FIG. 9 shows classification into detailed patterns of differential metrics having a 12B-detection pattern by PR(1,2,2,2,1)ML according to the embodiment of the present invention.

FIG. **10** shows a differential metric distribution by PR(1,2,2,2,1)ML according to the embodiment of the present invention.

FIG. **11** shows a differential metric distribution of each Euclidean distance pattern by PR(1,2,2,2,1)ML according to the embodiment of the present invention.

FIG. **12** shows examples of correlation of PR equalization ideal waveforms/reproduction waveform and a shift of marks regarding the 14-detection pattern shown in Table 1 according to the embodiment of the present invention.

FIG. **13** shows an example of correlation between PR equalization ideal waveforms/reproduction waveform and a shift of marks regarding the 12A-detection pattern shown in Table 2 according to the embodiment of the present invention.

FIG. **14** shows an example of correlation between PR equalization ideal waveforms/reproduction waveform and a shift of marks regarding the 12B-detection pattern shown in Table 3 according to the embodiment of the present invention.

FIG. **15** shows an example of a structure of a multi-layer disc according to an embodiment of the present invention.

FIG. **16** shows an example of a structure of a single layer disc according to an embodiment of the present invention.

FIG. **17** shows an example of a structure of a two-layer disc according to an embodiment of the present invention.

FIG. **18** shows an example of a structure of a three-layer disc according to an embodiment of the present invention.

FIG. **19** shows an example of a structure of a four-layer disc according to an embodiment of the present invention.

FIG. **20** shows a physical structure of an optical disc according to an embodiment of the present invention.

FIG. **21 (a)** shows an example of a 25 GB BD, and FIG. **21 (b)** shows an example of an optical disc having a higher recording density than that of the 25 GB BD according to an embodiment of the present invention.

FIG. **22** shows how a mark sequence recorded on a track is irradiated with a light beam according to an embodiment of the present invention.

FIG. **23** shows the relationship between the OTF and the shortest recording mark when the recording capacity is 25 GB

according to an embodiment of the present invention.

FIG. 24 shows an example in which the spatial frequency of the shortest mark (2T) is higher than the OTF cutoff frequency and the amplitude of a 2T reproduction signal is 0 according to an embodiment of the present invention.

FIG. 25 shows an example of distributions of differential metrics of different patterns.

FIG. 26 shows examples of relationship between an optical spot size and the mark length.

FIG. 27 shows examples of relationship between an optical spot size and a pattern including a plurality of edges.

DESCRIPTION OF EMBODIMENTS

[0060] Hereinafter, embodiments of the present invention will be described with reference to the drawings. Identical elements bear identical reference numerals, and identical descriptions thereof will be omitted.

[0061] With reference to FIG. 1, an optical disc apparatus (signal evaluation apparatus) using a PRML method according

to an embodiment of the present invention will be described. The optical disc apparatus evaluates a signal obtained, from an information recording medium on which a data sequence including marks and spaces in combination can be recorded, by reproducing the data sequence using a PRML signal processing method. In the optical disc apparatus, a PR12221ML method is adopted for signal processing of a reproduction system, and an RLL (Run Length Limited) code such as an RLL(1,7) code is used as a recording code. First, with reference to FIG. 2 and FIG. 3, PR12221ML will be described briefly. FIG. 2 is a state transition diagram showing a state transition rule defined by the RLL(1,7) recording code and the equalization method PR(1,2,2,2,1). FIG. 3 is a trellis diagram corresponding to the state transition diagram shown in FIG. 2.

[0062] By the combination of PR12221ML and RLL(1,7), the number of states in a decoding section is limited to 10, the number of state transition paths is 16, and the number of reproduction levels are 9.

[0063] Referring to the state transition rule of PR12221 shown in FIG. 2, ten states at a certain time are represented

as follows. State $S(0,0,0,0)$ is represented as "0", state $S(0,0,0,1)$ is represented as S1, state $S(0,0,1,1)$ is represented as S2, state $S(0,1,1,1)$ is represented as S3, state $S(1,1,1,1)$ is represented as S4, state $S(1,1,1,0)$ is represented as S5, state $S(1,1,0,0)$ is represented as S6, state $S(1,0,0,0)$ is represented as S7, state $S(1,0,0,1)$ is represented as S8, and state $S(0,1,1,0)$ is represented as S9. "0" or "1" in parentheses represents a signal on the time axis, and represents which state will possibly occur at the next time by a state transition from one state. The trellis diagram is obtained by developing this state transition diagram along the time axis.

[0064] In the state transition of PR12221ML shown in FIG. 3, there are numerous state transition path patterns (state combinations) by which a prescribed state at one time is changed to another prescribed state at the next time via either one of two state transitions. However, the patterns which are highly likely to cause an error are limited to specific patterns which are difficult to be distinguished. Focusing on such patterns which are likely to cause an error,

the state transition path patterns of PR12221 can be summarized as Tables 1, 2 and 3.

[0065]

[Table 1]

[0066]

[Table 2]

[0067]

[Table 3]

[0068] In Tables 1 through 3, the first column represents the state transition ($S_{m_{k-9}} \rightarrow S_{n_k}$) by which two state transitions which are likely to cause an error are branched and rejoin.

[0069] The second column represents the state data sequence ($b_{k-1}, \dots, b_k$) which causes the corresponding state transition.

[0070] "X" in the demodulated data sequence represents a bit which is likely to cause an error in such data. When the corresponding state transition is determined to be an error, the number of X (also the number of !X) is the number of errors.

[0071] Among a transition data sequence in which X is 1 and a transition data sequence in which X is 0, one corresponds to a first state transition path having the maximum likelihood, and the other corresponds to a second state transition path having the second maximum likelihood.

[0072] In Tables 2 and 3, "!X" represents an inverted bit of X.

[0073] From the demodulated data sequences obtained by

demodulation performed by a Viterbi decoding section, the first state transition path having the maximum likelihood of causing an error and the second state transition path having the second maximum likelihood of causing an error can be extracted by comparing each demodulated data sequence and the transition data sequence (X: Don't care).

[0074] The third column represents the first state transition path and the second state transition path.

[0075] The fourth column represents two ideal reproduction waveforms (PR equalization ideal values) after the respective state transitions. The fifth column represents the square of the Euclidean distance between the two ideal signals (inter-path Euclidean distance).

[0076] Among combination patterns of two possible state transitions, Table 1 shows 18 patterns by which the square of the Euclidean distance between the two possible state transitions is 14.

[0077] These patterns correspond to a portion of an optical disc medium at which a mark is switched to a space (edge of a waveform).

[0078] In other words, these patterns are 1-bit edge shift error patterns.

[0079] As an example, state transition paths from $S0(k-5)$ to $S6(k)$ in the state transition rule in FIG. 3 will be described.

[0080] In this case, one path in which the recording sequence is changed as "0,0,0,0,1,1,1,0,0" is detected. Considering that "0" of the reproduction data is a space and "1" of the reproduction data is a mark, this state transition path corresponds to a 4T or longer space, a 3T mark, and a 2T or longer space.

[0081] FIG. 4 shows an example of the PR equalization ideal waveforms in the recording sequence shown in Table 1. In FIG. 4, "A path waveform" represents the PR equalization ideal waveform of the above-mentioned recording sequence.

[0082] Similarly, FIG. 5 shows an example of the PR equalization ideal waveforms shown in Table 2.

[0083] FIG. 6 shows an example of the PR equalization ideal waveforms shown in Table 3.

[0084] In FIGS. 4, 5 and 6, the horizontal axis represents

the sampling time (sampled at one time unit of the recording sequence), and the vertical axis represents the reproduction signal level.

[0085] As described above, in PR12221ML, there are 9 ideal reproduction signal levels (level 0 through level 8).

[0086] In the state transition rule shown in FIG. 3, there is another path from $S0(k-5)$ to $S6(k)$, in which the recording sequence is changed as "0,0,0,0,0,1,1,0,0". Considering that "0" of the reproduction data is a space and "1" of the reproduction data is a mark, this state transition path corresponds to a 5T or longer space, a 2T mark, and a 2T or longer space.

[0087] In FIG. 4, "B path waveform" represents the PR equalization ideal waveform of this path.

[0088] The patterns shown in Table 1 corresponding to the square of the Euclidean distance of 14 have a feature of necessarily including one piece of edge information.

[0089] Table 2 shows 18 patterns by which the square of the Euclidean distance between the two possible state transitions is 12.

[0090] These patterns correspond to a shift error of a 2T mark or a 2T space; namely, are 2-bit shift error patterns.

[0091] As an example, state transition paths from $S0(k-7)$ to $S0(k)$ in the state transition rule in FIG. 3 will be described.

[0092] In this case, one path in which the recording sequence is changed as "0,0,0,0,1,1,0,0,0,0" is detected. Considering that "0" of the reproduction data is a space and "1" of the reproduction data is a mark, this state transition path corresponds to a 4T or longer space, a 2T mark, and a 5T or longer space.

[0093] In FIG. 5, "A path waveform" represents the PR equalization ideal waveform of this path.

[0094] There is another path in which the recording sequence is changed as "0,0,0,0,0,1,1,0,0,0". Considering that "0" of the reproduction data is a space and "1" of the reproduction data is a mark, this state transition path corresponds to a 5T or longer space, a 2T mark, and a 4T or longer space.

[0095] In FIG. 5, "B path waveform" represents the PR

equalization ideal waveform of this path.

[0096] The patterns shown in Table 2 corresponding to the square of the Euclidean distance of 12 have a feature of necessarily including two pieces of edge information on a 2T rise and a 2T fall.

[0097] Table 3 also shows 18 patterns by which the square of the Euclidean distance between two possible state transitions is 12. The patterns in Table 3 is of a different type from the patterns in Table 2.

[0098] These patterns correspond to a portion at which a 2T mark is continuous to a 2T space; namely, are 3-bit error patterns.

[0099] As an example, state transition paths from $S_0(k-9)$ to $S_6(k)$ in the state transition rule in FIG. 3 will be described.

[0100] In this case, one path in which the recording sequence is changed as "0,0,0,0,1,1,0,0,1,1,1,0,0" is detected. Considering that "0" of the reproduction data is a space and "1" of the reproduction data is a mark, this state transition path corresponds to a 4T or longer space, a 2T

mark, a 2T space, a 3T mark, and a 2T or longer space.

[0101] In FIG. 6, "A path waveform" represents the PR equalization ideal waveform of this path.

[0102] There is another path in which the recording sequence is changed as "0,0,0,0,0,1,1,0,0,1,1,0,0".

Considering that "0" of the reproduction data is a space and "1" of the reproduction data is a mark, this state transition path corresponds to a 5T or longer space, a 2T mark, a 2T space, a 2T mark, and a 2T or longer space.

[0103] In FIG. 6, "B path waveform" represents the PR equalization ideal waveform of this path.

[0104] The patterns shown in Table 3 corresponding to the square of the Euclidean distance of 12 have a feature of including at least three pieces of edge information.

[0105] Even where the state transition path pattern includes 2T/2T ("shortest mark/shortest space" or "shortest space/shortest mark"), which is a 2T-continuous pattern, in a recording layer having a recording capacity of 25 GB, a signal amplitude fluctuation which is sufficient to distinguish an edge is obtained. However, in a high density

recording layer having a recording capacity of 33.3 GB, as is clear from FIG. 6, the wavelength is almost flat in a 2T/2T portion. This indicates that a sufficient signal amplitude fluctuation is not obtained. As a result of accumulated studies, the present inventors found that in order to calculate a shift amount of the edge of the shortest mark of the 2T/2T portion, it is effective to provide, before or after the 2T/2T portion, a pattern including a 3T or longer mark or space to find a differential metric. Such a pattern is:

"shortest mark/shortest space/second shortest or longer mark" or

"second shortest or longer space/shortest mark/shortest space" or

"shortest space/shortest mark/second shortest or longer space" or

"second shortest or longer mark/shortest space/shortest mark".

[0106] Each of the above patterns, in other words, are one of the following: a pattern in which a shortest space is

adjacent before or after a shortest mark and a space adjacent to the shortest mark and not adjacent to the shortest space is longer than the shortest space; or a pattern in which a shortest space is adjacent before or after a shortest mark and a mark adjacent to the shortest space and not adjacent to the shortest mark is longer than the shortest mark. Such a feature of the present invention will be further described later with reference to FIG. **14**.

[0107] In this specification, the "shortest mark" or the "shortest space" may be occasionally referred to as the "shortest". For example, the expression "shortest/shortest" means that a "shortest space" is adjacent after a "shortest mark", or a "shortest mark" is adjacent after a "shortest space".

[0108] In addition, for example, the expression " $\bigcirc$ /second shortest or longer/shortest/shortest/ Δ " means a data sequence in which the marks and/or spaces are sequentially arranged as follows:

- a mark (or space) of any length,
- a second shortest or longer space (or mark),

a shortest mark (or space),
a shortest space (or mark), and
a mark (or space) of any length.

The expression "second shortest" means a length which is shortest next to the "shortest", and is 3T herein. For example, a "second shortest or longer space" means a "3T or longer space".

(EMBODIMENT 1)

[0109] Now, an optical disc apparatus according to an embodiment of the present invention will be described.

[0110] FIG. **1** shows an optical disc apparatus **100** according to Embodiment 1 of the present invention.

[0111] The optical disc apparatus **100** reproduces information from an information recording medium **1** mounted thereon or records information to the information recording medium **1**.

[0112] The information recording medium **1** is, for example, an optical disc medium.

[0113] The optical disc apparatus **100** includes an optical

head section **2**, a preamplifier section **3**, an AGC (Automatic Gain Controller) section **4**, a waveform equalization section **5**, an A/D conversion section **6**, a PLL section **7**, a PR equalization section **8**, a maximum likelihood decoding section **9**, a signal evaluation index detection section **10**, and an optical disc controller section **15**.

[0114] The optical head section **2** includes an irradiation section for irradiating a track of the information recording medium with laser light and a light receiving section for receiving light reflected from the track. The preamplifier section **3**, the AGC section **4**, the waveform equalization section **5**, the A/D conversion section **6**, the PLL section **7**, the PR equalization section **8**, and the maximum likelihood decoding section **9** together act as a reproduction section for reproducing a data sequence based on the signal obtained by the received light.

[0115] The signal evaluation index detection section **10** includes a 14-pattern detection section **101**, a 12A-pattern detection section **104** and a 12B-pattern detection section **107** for respectively detecting patterns corresponding to Table 1

(14-patterns), Table 2 (12A-patterns) and Table 3 (12B-patterns); differential metric calculation sections **102**, **105** and **108** for calculating a metric difference of each pattern; and memory sections **103**, **106** and **109** for accumulating and storing a positional shift index of each pattern calculated by the differential metric calculation sections **102**, **105** and **108**.

[0116] The optical head section **2** converges laser light transmitted through an objective lens on a recording layer of the information recording medium **1**, receives the reflected light, and generates an analog reproduction signal representing information recorded on the information recording medium **1**. The numerical aperture of the objective lens is 0.7 to 0.9, and preferably is 0.85.

[0117] The laser light has a wavelength of 410 nm or shorter, preferably of 405 nm.

[0118] The preamplifier section **3** amplifies the analog reproduction signal at a prescribed gain and outputs the amplified analog reproduction signal to the AGC section **4**.

[0119] The AGC section **4** amplifies the reproduction signal

using a preset target gain, such that a reproduction signal output from the A/D conversion section **6** has a constant level, and outputs the reproduction signal to the waveform equalization section **5**.

[0120] The waveform equalization section **5** has an LPF characteristic of shielding a high region of a reproduction signal and a filter characteristic of amplifying a prescribed frequency region of a reproduction signal, shapes the reproduction signal so as to have a desired characteristic and outputs the reproduction signal to the A/D conversion section **6**.

[0121] The PLL circuit **7** generates a reproduction clock synchronized with the reproduction signal processed with waveform equalization and outputs the reproduction clock to the A/D conversion section **6**.

[0122] The A/D conversion section **6** samples the reproduction signal in synchronization with the reproduction clock which is output from the PLL circuit **7**, converts the analog reproduction signal to a digital reproduction signal, and outputs the digital reproduction signal to the PR

equalization section **8**, the PLL section **7** and the AGC section **4**.

[0123] The PR equalization section **8** has, as a frequency characteristic of the reproduction system, a frequency characteristic which is set to be assumed by the maximum likelihood decoding section **9** (for example, PR(1,2,2,2,1) equalization characteristic), executes PR equalization processing of suppressing noise in a high region and adding an intentional inter-code interference on the reproduction signal, and outputs the resultant signal to the maximum likelihood decoding section **9**.

[0124] The PR equalization section **8** may include an FIR (Finite Impulse Response) filter structure and adaptably control the tap coefficient using an LMS (The Least-Mean Square) algorithm (see Non-Patent Document No. 2).

[0125] The maximum likelihood decoding section **9** is, for example, a Viterbi decoder, and decodes the reproduction signal processed with PR equalization by the PR equalization section **8** using a maximum likelihood decoding method for estimating a path having the maximum likelihood based on the

code rule intentionally added in accordance with the form of partial response, and outputs binary data.

[0126] The binary data is output to the optical disc controller **15** on a later stage as a demodulated binary signal and processed as prescribed. Thus, the information recorded on the information recording medium **1** is reproduced.

[0127] To the signal evaluation index detection section **10**, the waveform-shaped digital reproduction signal output from the PR equalization section **8** and the binary signal output from the maximum likelihood decoding section **9**.

[0128] The pattern detection sections **101**, **104** and **107** compare the transition data sequences in Tables 1, 2 and 3 with the binary data. When the binary data matches the transition data sequences in Tables 1, 2 and 3, the pattern detection sections **101**, **104** and **107** select a state transition path 1 having the maximum likelihood and a state transition path 2 having the second maximum likelihood based on Tables 1, 2 and 3.

[0129] Based on the selection results, the differential metric calculation sections **102**, **105** and **108** calculate a

metric, which is a distance between an ideal value of each state transition path (PR equalization ideal value; see Tables 1, 2 and 3) and the digital reproduction signal, and also calculate a difference between the metrics calculated on the two state transition matrices. Such a metric difference has a positive or a negative value, and therefore is subjected to absolute value processing.

[0130] Based on the binary data, the pattern detection sections **101**, **104** and **107** generate a pulse signal to be assigned to each of start edge/end edge patterns of the mark shown in FIGS. **7**, **8** and **9**, and output the pulse signal to the memory sections **103**, **106** and **109**.

[0131] Based on the pulse signal output from the pattern detection sections **101**, **104** and **107**, the memory sections **103**, **106** and **109** accumulatively add the metric differences obtained by the differential metric calculation sections **102**, **105** and **108** for each pattern shown in FIGS. **7**, **8** and **9**.

[0132] Now, the detailed pattern classification in FIGS. **7**, **8** and **9** will be described in detail.

[0133] In FIGS. **7**, **8** and **9**, "M" represents a mark and "S"

represents a space.

[0134] "i" represents time. For example, $(2S(i-1), 3M(i), 4S(i+1))$ means a 2T space is present before a 3T mark as the reference and a 4T space is present after the 3T mark.

[0135] In FIGS. **7**, **8** and **9**, pattern numbers correspond to the pattern numbers in Tables 1, 2 and 3.

[0136] For example, referring to Table 1, data sequence [14]1A has a transition data sequence $(0,0,0,0,1,1,1,0,0)$. Where 0 represents a space and 1 represents a mark, this transition data sequence has a pattern of (4T or longer space, 3T mark, 2T or longer space).

[0137] This pattern corresponds to the cell of $(wS(i-3), xM(i-2), 4S(i-1), 3M(i), yS(i+1), zM(i+2))$ in FIG **7**.

[0138] Each of w, x, y and z may be any numerical value representing the length which a mark or a space can have.

[0139] For example, in the case of the RLL(1,7) recording code, each of w, x, y and z may be any value of 2 to 9.

[0140] By the detailed pattern classification of the 14-detection patterns in FIG. **7**, one edge shift of one space and one mark is classified. The "start" of a 14-detection

pattern indicates an edge shift of a mark at time i and a space at time $i-1$. The "end" of a 14-detection pattern indicates an edge shift of a mark at time i and a space at time $i+1$.

[0141] By the detailed pattern classification of the 12A-detection patterns in FIG. 8, a shift of a 2T mark or a 2T space in a 14-detection pattern shown in FIG. 7 is further classified by the mark or space at the immediately previous time or the immediately subsequent time.

[0142] In the "start" of the 12A-detection pattern, a shift of a 2T mark at time i sandwiched between a space at time $i-1$ and a space at time $i+1$ is classified by the length of the space at time $i+1$, or a shift of a 2T space at time $i-1$ sandwiched between a mark at time i and a mark at time $i-2$ is classified by the length of the mark at time $i-2$.

[0143] In the "end" of the 12A-detection pattern, a shift of a 2T mark at time i sandwiched between a space at time $i-1$ and a space at time $i+1$ is classified by the length of the space at time $i-1$, or a shift of a 2T space at time $i+1$ sandwiched between a mark at time i and a mark at time $i+2$ is

classified by the length of the mark at time $i+2$.

[0144] Finally, by the detailed pattern classification of the 12A-detection patterns in FIG. 9, a shift of continuous 2T mark and 2T space in a 12A-detection pattern shown in FIG. 8 is further classified by the mark or space at the further immediately previous time or the further immediately subsequent time. Namely, a shift of a 2T mark and a 2T space located in succession and sandwiched between one mark and one space is classified.

[0145] In the "start" of the 12B-detection pattern, a shift of a 2T mark at time i and a 2T space at time $i+1$ sandwiched between a mark at time $i+2$ and a space at time $i-1$ is classified by the length of the mark at time $i+2$, or a shift of a 2T mark at time $i-2$ and a 2T space at time $i-1$ sandwiched between a space at time $i-3$ and a mark at time i is classified by the length of the space at time $i-3$.

[0146] In the "end" of the 12B-detection pattern, a shift of a 2T mark at time i and a 2T space at time $i-1$ sandwiched between a space at time $i+1$ and a mark at time $i-2$ is classified by the length of the mark at time $i-2$, or a shift

of a 2T space at time $i+1$ and a 2T mark at time $i+2$ sandwiched between a mark at time i and a space at time $i+3$ is classified by the length of the space at time $i+3$.

[0147] In FIG. 7, FIG. 8 and FIG. 9, the bit sequence represented by "x", "0" and "1" below each classification pattern represents the data sequence corresponding to the respective pattern. Herein, "0" represents binary data corresponding to a space in the data sequence, and "1" represents binary data corresponding to a mark in the data sequence. Where the reference cycle of the data sequence is T , one "0" represents binary data corresponding to a 1T space, and one "1" represents binary data corresponding to a 1T mark. "x" represents "0" or "1".

[0148] The binary data of the above-described pattern (pattern in which a shortest space is adjacent before or after a shortest mark and a space adjacent to the shortest mark and not adjacent to the shortest space is longer than the shortest space) is represented as, for example, "x000110011x" or "x110011000x".

[0149] The binary data of the above-described pattern

(pattern in which a shortest space is adjacent before or after a shortest mark and a mark adjacent to the shortest space and not adjacent to the shortest mark is longer than the shortest mark) is represented as, for example, "x001100111x" or "x111001100x".

[0150] The operation of recognizing a prescribed pattern from binary data in this manner is executed by the pattern detection sections **101**, **104** and **107**. For example, for detecting the 12B-detection pattern, the pattern detection section **107** recognizes, based on the binary data, a pattern, included in the data sequence, including a first mark, a first space adjacent before or after the first mark, and a second mark not adjacent to the first mark and adjacent to the first space. When the first space and the second mark each have a length equal to or shorter than a prescribed length, the pattern detection section **107** recognizes whether or not a second space not adjacent to the first mark and adjacent to the second mark is longer than the prescribed length. When the second space is longer than the prescribed length, the pattern detection section **107** detects the 12B-

detection pattern. The prescribed length is, for example, $2T$, but is not limited to this.

[0151] In another example, for detecting the 12B-detection pattern, the pattern detection section **107** recognizes, based on the binary data, a pattern, included in the data sequence, including a first mark a first space adjacent before or after the first mark, and a third space not adjacent to the first space and adjacent to the first mark. When the first mark and the third space each have a length equal to or shorter than a prescribed length, the pattern detection section **107** recognizes whether or not a third mark not adjacent to the first space and adjacent to the third space is longer than the prescribed length. When the third mark is longer than the prescribed length, the pattern detection section **107** detects the 12B-detection pattern.

[0152] When the 12B-detection pattern is detected based on the binary signal as in this example, a first state transition path having the maximum likelihood and a second state transition path having the second maximum likelihood are selected from the 12B-detection pattern. The

differential metric calculation section **108** calculates a differential metric using the first and second state transition matrices and a digital reproduction signal. Using the calculation result of the differential metric, the quality of the reproduction signal can be evaluated. For example, the quality of the digital reproduction signal can be evaluated by calculating a shift amount of the edge of the shortest mark of the 2T/2T portion described above.

[0153] Hereinafter, a process for evaluating the quality of a reproduction signal (recording quality) will be described in detail.

[0154] In order to provide a signal evaluation index having a higher correlation with an error rate, an evaluation method considering all the patterns having a high likelihood of causing an error in the PR12221ML signal processing is required.

[0155] FIG. **10** shows a distribution of differential metrics in the PR12221ML signal processing.

[0156] The horizontal axis represents the square of the Euclidean distance, and the vertical axis represents the

frequency.

[0157] FIG. **10** shows that as the square of the Euclidean distance of the distribution is smaller, the likelihood of causing an error in the PR12221ML signal processing is higher.

[0158] It is seen from this figure that the distribution has highly dense groups at the square of the Euclidean distance of 12 and 14, and in the range of the square of the Euclidean distance above 14, the differential metrics are present only at 30 or higher.

[0159] Namely, it is appreciated that in order to provide a signal index having a high correlation with the error rate, it is sufficient to pay attention to the groups at the square of the Euclidean distance of 12 and 14.

[0160] These groups correspond to the patterns shown in Table 1 and Tables 2 and 3.

[0161] The pattern detection sections **101**, **104** and **107** identify these patterns.

[0162] Hereinafter, an operation of the differential metric calculation sections for calculating a metric difference from the identified patterns will be described in

further detail.

[0163] A binary signal is generated from a reproduction signal reproduced from the disc by the PRML processing.

[0164] From the binary signal, any of the patterns of the transition data sequences in Table 1 is detected. Thus, the PR equalization ideal values of the state transition matrices 1 and 2 are determined.

[0165] For example, it is assumed that in Table 1, (0,0,0,0,X,1,1,0,0) is demodulated as a binary signal. In this case, as the state transition path 1 having the maximum likelihood, data sequence [14]1A(S0, S1, S2, S3, S5, S6) is selected. As the state transition path 2 having the second maximum likelihood, data sequence [14]1B(S0, S0, S1, S2, S9, S6) is selected.

[0166] The PR equalization ideal value for the state transition path 1 is (1,3,5,6,5).

[0167] The PR equalization ideal value for the state transition path 2 is (0,1,3,4,4).

[0168] Next, the square of the difference between the reproduction signal sequence and the PR equalization ideal

value for the state transition path 1 is found and labeled Pa. Similarly, the square of the difference between the reproduction signal sequence and the PR equalization ideal value for the state transition path 2 is found and labeled Pb. The absolute value of the difference between Pa and Pb is the differential metric $D_{14}=|Pa_{14}-Pb_{14}|$.

[0169] This processing is performed by the differential metric calculation sections.

[0170] The calculation of Pa_{14} is represented by expression (1). The calculation of Pb_{14} is represented by expression (2).

In the expressions, a_k is the PR equalization ideal value for the state transition path 1, b_k is the PR equalization ideal value for the state transition path 2, and y_k is the reproduction signal sequence.

$$Pa_{14} = \sum_{k=k-5}^k (y_k - a_k)^2 \quad \text{expression (1)}$$

$$Pb_{14} = \sum_{k=k-5}^k (y_k - b_k)^2 \quad \text{expression (2)}$$

$$D_{14} = |Pa_{14} - Pb_{14}| \quad \text{expression (3)}$$

[0171] In FIG. 11, (A) represents an output frequency distribution of the differential metric calculation section

102.

[0172] Similarly, outputs from the differential metric calculation section **105** are represented by expressions (4) through (6), and outputs from the differential metric calculation section **108** are represented by expressions (7) through (9).

$$Pa_{12A} = \sum_{k=k-7}^k (y_k - a_k)^2 \quad \text{expression (4)}$$

$$Pb_{12A} = \sum_{k=k-7}^k (y_k - b_k)^2 \quad \text{expression (5)}$$

$$D_{12A} = |Pa_{12A} - Pb_{12A}| \quad \text{expression (6)}$$

$$Pa_{12B} = \sum_{k=k-9}^k (y_k - a_k)^2 \quad \text{expression (7)}$$

$$Pb_{12B} = \sum_{k=k-9}^k (y_k - b_k)^2 \quad \text{expression (8)}$$

$$D_{12B} = |Pa_{12B} - Pb_{12B}| \quad \text{expression (9)}$$

[0173] In FIG. **11**, (B) represents an output frequency distribution of the differential metric calculation section **105**, and (C) represents an output frequency distribution of the differential metric calculation section **108**.

[0174] The distributions represented by (A), (B) and (C) in FIG. **11** are different in the frequency and the center position as well as in the number of error bits generated when the respective pattern causes an error.

[0175] In the patterns in Table 1 corresponding to the square of the Euclidean distance of 14, a 1-bit error is generated. In the patterns in Table 2 corresponding to the square of the Euclidean distance of 12, a 2-bit error is generated. In the patterns in Table 3 corresponding to the square of the Euclidean distance of 12, a 3- or greater bit error is generated.

[0176] Especially, the number of error bits of the patterns in Table 3 depends on the number of successive 2T marks/spaces. For example, in the case of a recording modulation code permitted to include 6 successive marks/spaces at the maximum, a 6-bit error is generated at the maximum.

[0177] Table 3 does not show 6-bit errors, but a pattern causing a 6-bit error may be obtained by expanding the pattern including successive 2T marks/spaces.

[0178] The pattern causing a 6-bit error is omitted in this embodiment.

[0179] Now, a method for classifying each detection pattern into a detailed pattern using the above-described

differential metric calculation will be described.

[0180] FIG. **12** shows the correlation between the reproduction waveform and the shift of the mark of a pattern shown in FIG. **4**, which are provided as an example of the 14-pattern.

[0181] In FIG. **12(a)**, a path **A21** is a state transition path having the maximum likelihood, and a path **B22** is a state transition path having the second maximum likelihood.

[0182] A reproduction waveform **23** represented by the dashed line with white triangles represents a waveform of data, of the information recording medium, having a signal which is slightly closer to the path **B22** with respect to the path **A21** as the reference.

[0183] A space **24** and a mark **25** respectively represent the ideal positions of the space and the mark of path **A21**, which is the state transition path having the maximum likelihood. A space **26** and a mark **27** respectively represent the positions of the space and the mark at which the reproduction waveform **23** is obtained.

[0184] The signal levels of the reproduction waveform **23**

at sampling points $(y_{k-4}, y_{k-3}, y_{k-2}, y_{k-1}, y_k)$ are $(0.7, 2.7, 4.7, 5.7, 4.7)$.

[0185] At this point, the signal levels of the path **A21** and the path **B22** are $a_k=(1, 3, 5, 6, 5)$ and $b_k=(0, 1, 3, 4, 4)$.

[0186] From the above-mentioned signal levels and expressions (1) and (2), the distance Pa_{14} between the reproduction waveform **23** and the path **A21** and the distance Pb_{14} between the reproduction waveform **23** and the path **B22** are found as expressions (10) and (11).

$$Pa_{14} = (0.7-1)^2 + (2.7-3)^2 + (4.7-5)^2 + (5.7-6)^2 + (4.7-5)^2 = 0.45$$

expression (10)

$$Pb_{14} = (0.7-0)^2 + (2.7-1)^2 + (4.7-3)^2 + (5.7-4)^2 + (4.7-4)^2 = 9.65$$

expression (11)

[0187] From expression (3), the differential metric D_{14} is found as expression (12).

$$D_{14} = |Pa_{14} - Pb_{14}| = |0.45 - 9.65| = 9.2$$

expression (12)

Where the distance between the path **A** and the path **B** is $Pstd_{14}$, $Pstd_{14}$ is the value of Pb_{14} at which $Pa_{14}=0$, i.e.,

$Pstd_{14}$ is 14.

[0188] A shift amount E_{14} of the reproduction waveform from the path **A21**, which is the state transition path having the maximum likelihood, is obtained by expression (13) below.

$$E_{14} = D_{14} - Pstd_{14} = 9.2 - 14 = -4.8 \quad \text{expression (13)}$$

[0189] The absolute value of E_{14} obtained from expression (13) is the shift amount, and the sign thereof is the shifting direction.

[0190] Now, the shifting direction represented by the sign of E_{14} will be described.

[0191] Similarly to the above, in FIG. **12(b)**, a reproduction waveform **29** represented by the dashed line with white triangles has a signal level which is farther from the path **B22** with respect to the path **A21** as the reference.

[0192] Where the signal levels of the reproduction waveform **29** ($y_{k-4}, y_{k-3}, y_{k-2}, y_{k-1}, y_k$) are (1.3, 3.3, 5.3, 6.3, 5.3), $E_{14}(32) = 4.8$.

[0193] FIGS. **12(c)** and **(d)** each show a case where the path **B22** represents the state transition path having the maximum likelihood.

[0194] In FIG. **12(c)**, a reproduction waveform **33** represented by the dashed line with white triangles has a signal level which is farther from the path **A21** with respect to the path **B22** as the reference. In FIG. **12(d)**, a reproduction waveform **39** represented by the dashed line with white triangles has a signal level which is slightly closer to the path **A21** with respect to the path **B22** as the reference.

[0195] Where the signal levels of the reproduction waveforms **33** and **39** $(Y_{k-4}, Y_{k-3}, Y_{k-2}, Y_{k-1}, Y_k)$ are $(0, 0.7, 2.7, 3.7, 3.7)$ and $(0.3, 1.3, 3.3, 4.3, 4.3)$, $E_{14}(38)=4.2$ and $E_{14}(42)=-4.8$.

[0196] From the above, when the reproduction waveform has a signal level which is closer to the state transition path having the second maximum likelihood with respect to the state transition path having the maximum likelihood, the sign of the E_{14} value is negative. When the reproduction waveform has a signal level which is farther from the state transition path having the second maximum likelihood with respect to the state transition path having the maximum likelihood, the sign of the E_{14} value is positive.

[0197] FIG. **13** shows the correlation between the reproduction waveform and the shift of the mark of a pattern shown in FIG. **5**, which is provided as an example of the 12A-pattern.

[0198] In FIG. **13**, a path **A51** is a state transition path having the maximum likelihood, and a path **B52** is a state transition path having the second maximum likelihood.

[0199] A reproduction waveform **53** represented by the dashed line with white triangles represents a waveform of data, of the information recording medium, having a signal which is slightly closer to the path **B52** with respect to the path **A51** as the reference.

[0200] Spaces **54** and **56** and a mark **55** respectively represent the ideal positions of the spaces and the mark of path **A51**, which is the state transition path having the maximum likelihood. Spaces **57** and **59** and a mark **58** respectively represent the positions of the spaces and the mark at which the reproduction waveform **53** is obtained.

[0201] The signal levels of the reproduction waveform **53** at sampling points $(Y_{k-6}, Y_{k-5}, Y_{k-4}, Y_{k-3}, Y_{k-2}, Y_{k-1}, Y_k)$ are

$(0.7, 2.7, 3.7, 4, 3.3, 1.3, 0.3)$.

[0202] At this point, the signal levels of the path **A51** and the path **B52** are $a_k = (1, 3, 4, 4, 3, 1, 0)$ and $b_k = (0, 1, 3, 4, 4, 3, 1)$.

[0203] From the above-mentioned signal levels and expressions (1) and (2), the distance Pa_{12A} between the reproduction waveform **53** and the path **A51** and the distance Pb_{12A} between the reproduction waveform **53** and the path **B52** are found as expressions (14) and (15).

$$\begin{aligned} Pa_{12A} = & (0.7-1)^2 + (2.7-3)^2 + (3.7-4)^2 + (4-4)^2 \\ & + (3.3-3)^2 + (1.3-1)^2 + (0.3-0)^2 = 0.54 \end{aligned}$$

expression (14)

$$\begin{aligned} Pb_{12A} = & (0.7-0)^2 + (2.7-1)^2 + (3.7-3)^2 + (4-4)^2 \\ & + (3.3-4)^2 + (1.3-3)^2 + (0.3-1)^2 = 7.74 \end{aligned}$$

expression (15)

[0204] From expression (3), the differential metric D_{12A} is found as expression (16).

$$D_{12A} = |Pa_{12A} - Pb_{12A}| = |0.54 - 7.74| = 7.2 \quad \text{expression (16)}$$

Where the distance between the path **A** and the path **B** is $Pstd_{12A}$, $Pstd_{12A}$ is the value of Pb_{12A} at which $Pa_{12A} = 0$, i.e., $Pstd_{12A}$ is 12.

[0205] A shift amount E_{12A} of the reproduction waveform from the path **A51**, which is the state transition path having the maximum likelihood, is obtained by expression (17) below.

$$E_{12A} = D_{12A} - Pstd_{12A} = 7.2 - 12 = -4.8 \quad \text{expression (17)}$$

[0206] In the case of the 12A-pattern, as in the case of the 14-pattern, when the reproduction waveform has a signal level which is closer to the state transition path having the second maximum likelihood with respect to the state transition path having the maximum likelihood, the sign of the E_{12A} value is negative. When the reproduction waveform has a signal level which is farther from the state transition path having the second maximum likelihood with respect to the state transition path having the maximum likelihood, the sign of the E_{12A} value is positive.

[0207] In the example of FIG. **13**, the mark **55** and the mark **58** are described as having the same length. The shift in the 12A-pattern is also applicable to a case where the ideal mark and the mark of the reproduction waveform have different lengths.

[0208] FIG. **14** shows the correlation between the

reproduction waveform and the shift of the mark of a pattern shown in FIG. **6**, which are provided as an example of the 12B-pattern.

[0209] In FIG. **14**, a path **A71** is a state transition path having the maximum likelihood, and a path **B72** is a state transition path having the second maximum likelihood.

[0210] A reproduction waveform **73** represented by the dashed line with white triangles represents a waveform of data, of the information recording medium, having a signal which is slightly closer to the path **B72** with respect to the path **A71** as the reference.

[0211] Spaces **74** and **76** and marks **75** and **77** respectively represent the ideal positions of the spaces and the marks of path **A71**, which is in the state transition path having the maximum likelihood. Spaces **78** and **80** and marks **79** and **81** respectively represent the positions of the spaces and the marks at which the reproduction waveform **73** is obtained.

[0212] The signal levels of the reproduction waveform **73** at sampling points $(y_{k-8}, y_{k-7}, y_{k-6}, y_{k-5}, y_{k-4}, y_{k-3}, y_{k-2}, y_{k-1}, y_k)$ are $(0.7, 2.7, 3.7, 4, 4, 4, 4.7, 5.7, 4.7)$.

[0213] At this point, the signal levels of the path **A71** and the path **B72** are $a_k=(1,3,4,4,4,4,5,6,5)$ and $b_k=(0,1,3,4,4,4,4,4,4)$.

[0214] From the above-mentioned signal levels and expressions (1) and (2), the distance Pa_{12B} between the reproduction waveform **73** and the path **A71** and the distance Pb_{12B} between the reproduction waveform **73** and the path **B72** are found as expressions (18) and (19).

$$Pa_{12b} = (0.7-1)^2 + (2.7-3)^2 + (3.7-4)^2 + (4-4)^2 + (4-4)^2 + (4-4)^2 + (4.7-5)^2 + (5.7-6)^2 + (4.7-5)^2 = 0.54$$

expression (18)

$$Pb_{12b} = (0.7-0)^2 + (2.7-1)^2 + (3.7-3)^2 + (4-4)^2 + (4-4)^2 + (4-4)^2 + (4.7-4)^2 + (5.7-4)^2 + (4.7-4)^2 = 7.74$$

expression (19)

[0215] From expression (3), the differential metric D_{12B} is found as expression (20).

$$D_{12B} = |Pa_{12B} - Pb_{12B}| = |0.54 - 7.74| = 7.2 \quad \text{expression (20)}$$

Where the distance between the path **A** and the path **B** is $Pstd_{12B}$, $Pstd_{12B}$ is the value of Pb_{12B} at which $Pa_{12B}=0$, i.e., $Pstd_{12B}$ is 12.

[0216] A shift amount E_{12B} of the reproduction waveform

from the path **A71**, which is the state transition path having the maximum likelihood, is obtained by expression (21) below.

$$E_{12B} = D_{12B} - Pstd_{12B} = 7.2 - 12 = -4.8 \quad \text{expression (21)}$$

[0217] In the case of the 12B-pattern, as in the case of the 14-pattern, when the reproduction waveform has a signal level which is closer to the state transition path having the second maximum likelihood with respect to the state transition path having the maximum likelihood, the sign of the E_{12B} value is negative. When the reproduction waveform has a signal level which is farther from the state transition path having the second maximum likelihood with respect to the state transition path having the maximum likelihood, the sign of the E_{12B} value is positive.

[0218] In the example of FIG. **14**, the mark **75** and the space **76** are described as having the same lengths as the mark **79** and the space **80**. The shift in the 12B-pattern is also applicable to a case where the ideal mark or space and the mark or space of the reproduction waveform have different lengths.

[0219] As described above with reference to FIG. **6** and

also understood from FIG. **14**, where the state transition path includes a 2T/2T portion, which is a 2T-continuous pattern, a sufficient signal amplitude fluctuation is not obtained in the 2T/2T portion. In order to calculate a shift amount of the edge of the shortest mark of 2T/2T portion, it is effective to provide, before or after the 2T/2T portion, a pattern including a 3T or longer mark or space to find a differential metric. Such a pattern is:

"shortest mark/shortest space/second shortest or longer mark" or

"second shortest or longer space/shortest mark/shortest space" or

"shortest space/shortest mark/second shortest or longer space" or

"second shortest or longer mark/shortest space/shortest mark".

[0220] More specifically, the path **A** is represented as "4T or longer space (**74**)/2T mark (**75**)/2T space (**76**)/3T mark (**77**)/2T or longer space", which includes a 2T-continuous portion. In such a path **A**, the shift amount of the edge of

the shortest mark (2T mark (**75**)) can be obtained by calculating a differential metric of the pattern of "4T or longer space (**74**)/2T mark (**75**)/2T space (**76**)". The "pattern of 4T or longer space (**74**)/2T mark (**75**)/2T space (**76**)" corresponds to a "pattern including a 3T or longer mark or space before or after 2T/2T".

[0221] The path **B** is represented as "5T or longer space/2T mark/2T space/2T mark/2T or longer space", which includes a 2T-continuous portion. In such a path **B**, the shift amount of the edge of the shortest mark (2T mark) can be obtained by calculating a differential metric of the pattern of "5T or longer space/2T mark/2T space". The "pattern of 5T or longer space/2T mark/2T space" corresponds to a "pattern including a 3T or longer mark or space before or after 2T/2T".

[0222] As described above with reference to FIG. **6**, a pattern corresponding to the square of the Euclidean distance of 12 includes at least three pieces of edge information. Namely, calculating the shift amount of the edge of the shortest mark using the pattern of " $\bigcirc$ /second shortest or longer/shortest/shortest/ Δ " or " $\bigcirc$ /shortest/shortest/second

shortest or longer/ Δ " is applicable to the 12A pattern in substantially the same manner as to the 12B pattern.

[0223] In the above example, a pattern including a shortest-continuous (e.g., 2T-continuous) portion is described as an example of a pattern by which a sufficient signal amplitude fluctuation is not obtained. Depending on the relationship with the recording density or the size of a spot diameter described later, a 2T-continuous pattern may not necessarily be the only pattern by which a sufficient signal amplitude fluctuation is not obtained. In such a case, it may be recognized whether or not the data sequence of interest includes a portion including a mark and a space continuously both having a length equal to or shorter than the length at which a sufficient signal amplitude fluctuation is not obtained (a portion having a mark of a prescribed length or shorter and a space of the prescribed length or shorter continuously), and then it may be identified whether or not a mark or space adjacent to the portion is longer than the prescribed length.

[0224] As described above, according to Embodiment 1, it

is made possible to calculate, using the PR12221ML signal processing, a differential metric of a pattern by which the square of the Euclidean distance between two ideal signals, i.e., the state transition path having the maximum likelihood and the state transition path having the second maximum likelihood, is 12 or 14. Thus, it is made possible to represent how each edge is shifted in a detection signal including a plurality of edges, with an index correlating with the error rate. As a result, the recording and reproduction quality of a high density information recording medium can be evaluated.

[0225] Using such an evaluation index, it is made possible to feedback the results of the recording quality evaluation to a reproduction compensation section or a recording compensation section at the time of information recording to or reproduction from a high density information recording medium. Thus, the reproduction errors can be reduced, and high quality recording with few errors can be performed.

[0226] The preamplifier section **3**, the AGC section **4** and the waveform equalization section **5** shown in FIG. **1** in this

embodiment may be structured as one analog integrated circuit (LSI).

[0227] The preamplifier section **3**, the AGC section **4**, the waveform equalization section **5**, the A/D conversion section **6**, the PLL section **7**, the PR equalization section **8**, the maximum likelihood decoding section **9**, the signal evaluation index detection section **10** and the optical disc controller section **15** may be structured as one integrated circuit (LSI) having both analog and digital elements mounted thereon.

[0228] The above-described optical disc apparatus **100** is a reproduction apparatus for reproducing information from an information recording medium, but may be a recording and reproduction apparatus or a recording apparatus.

[0229] In such a case, a circuit for recording is added, but the description thereof will be omitted in this example. For example, the optical disc apparatus **100** includes a recording section for recording information on the information recording medium **1**. The recording section forms marks on the track by irradiation with laser light to record a data sequence in which marks and spaces between the marks

are arranged alternately. The recording section includes, for example, a pattern generation section, a recording compensation section and a laser driving section. The pattern generation section outputs a recording pattern for adjusting the edge of the recording mark. The recording compensation section receives a recording parameter from the optical disc controller section and generates a laser emission waveform pattern in accordance with the recording parameter and the recording pattern. The laser driving section controls the laser emission operation of the optical head section **2** in accordance with the generated laser emission waveform pattern. The optical head section **2** irradiates the track with laser light to record marks on the track and thus to record a data sequence in which marks and spaces are arranged alternately.

[0230] These examples of the structure of the optical disc apparatus do not limit the present invention, and other structures are usable.

[0231] In the above embodiment, maximum likelihood decoding is performed using a state transition rule defined

by a code having a shortest mark length of 2 and the equalization method $PR(1,2,2,2,1)$, but the present invention is not limited to this.

[0232] For example, the present invention is also applicable to a case where a code having a shortest mark length of 2 or 3 and the equalization method $PR(C0, C1, C1, C0)$ are used, or to a case where a code having a shortest mark length of 3 and the equalization method $PR(C0, C1, C2, C1, C0)$ are used. $C0$, $C1$ and $C2$ may each be any positive numeral.

[0233] In the above embodiment, only the marks and spaces having the shortest length are classified in detail, but the present invention is not limited to this.

[0234] For example, the present invention is applicable to marks or spaces having the second shortest length, or marks or spaces which are shorter than a prescribed length, instead of marks having the shortest length.

[0235] Now, the information recording medium according to the present invention will be described in more detail.

(Main parameters)

[0236] Examples of the recording mediums to which the present invention is applicable include Blu-ray disc (BD) and optical discs of other formats. Herein, BDs will be described. There are the following types of BD in accordance with the characteristics of the recording layers: reproduction-only BD-ROM, write once BD-R, rewritable BD-RE and the like. The present invention is applicable to any of the ROM (reproduction only) type, the R (write once) type and the RE (rewritable) type of BDs and other format recording mediums. The main optical constants and physical formats of the Blu-ray disc are disclosed in "Illustrated Blu-ray Disc Reader" published by Ohmsha, Ltd. or the white papers put on the web site of the Blu-ray Association (<http://www.blu-raydisc.com/>).

[0237] For the BD, laser light having a wavelength of about 405 nm (where the tolerable error range is ± 5 nm with respect to the standard value of 405 nm, 400 to 410 nm) and an objective lens having a numerical aperture (NA) of about 0.85 (where the tolerable error range is ± 0.01 nm with

respect to the standard value of 0.85, 0.84 to 0.86) are used. The track pitch of the BD is about 0.32 μm (where the tolerable error range is 0.010 μm with respect to the standard value of 0.320 μm , 0.310 to 0.330 μm), and one or two recording layers are provided. One or two recording layers each having a recording surface are provided on the side on which the laser light is incident. The distance from the surface of a protective layer of the BD to the recording surface is 75 μm to 100 μm .

[0238] As the modulation system for a recording signal, 17PP modulation is used. The length of the shortest mark to be recorded (2T mark; T is a cycle of the reference clock (the reference cycle of modulation in the case where a mark is recorded by a prescribed modulation rule)) is 0.149 μm (or 0.138 μm) (channel bit length T is 74.50 nm (or 69.00 nm)). The recording capacity is 25 GB (or 27 GB) (more precisely, 25.025 GB (or 27.020 GB) where one layer is provided on one side, or 50 GB (or 54 GB) (more precisely, 50.050 GB (or 54.040 GB) where two layers are provided on one side.

[0239] The channel clock frequency is 66 MHz (channel bit

rate: 66.000 Mbits/s) at the standard transfer rate (BD1x), 264 MHz (channel bit rate: 264.000 Mbits/s) at the 4x transfer rate (BD4x), 396 MHz (channel bit rate: 396.000 Mbits/s) at the 6x transfer rate (BD6x) rate, and 528 MHz (channel bit rate: 528.000 Mbits/s) at the 8x transfer rate (BD8x).

[0240] The standard linear velocity (reference linear velocity, 1x) is 4.917 m/sec. (or 4.554 m/sec.). The linear velocity at 2x, 4x, 6x and 8x is respectively 9.834 m/sec., 19.668 m/sec., 29.502 m/sec., and 39.336 m/sec. A linear velocity higher than the reference linear velocity is generally a positive integral multiple of the reference linear velocity, but is not limited to an integral multiple and may be a positive real number multiple of the reference linear velocity. A linear velocity lower than the reference linear velocity, such as 0.5 times (0.5x), may also be defined.

[0241] The above description is regarding BDs already developed into commercial products, which include one layer or two layers and have a recording capacity per layer of,

mainly, about 25 GB (or about 27 GB). For realizing a higher capacity, a high density BD having a recording capacity per layer of about 32 GB or about 33.4 GB and a BD including three or four layers are also under research, and these BDs will also be described below.

(Multiple layers)

[0242] In the case of a one-sided disc used for information reproduction and/or recording with laser light incident on the side of the protective layer, where there are two or more recording layers, there are a plurality of recording layers between the substrate and the protective layer. An example of a general structure of such a multi-layer disc is shown in FIG. **15**. The disc shown here includes (n+1) information recording layers **502** (n is an integer of 0 or greater). A specific structure of the optical disc is as follows. A cover layer **501**, the (n+1) information recording layers (Ln through L0 layers) **502**, and a substrate **500** are sequentially stacked from a surface on which laser light **505** is incident. Between each two adjacent layers of the (n+1)

information recording layers **502**, an intermediate layer **503** acting as an optical buffer member is inserted. The reference layer (L0) is provided at a deepest position which is away from the light incidence surface by a prescribed distance (a position farthest from the light source), and the other layers (L1, L2, ... Ln) are stacked on the reference layer (L0) toward the light incidence surface.

[0243] The distance from the light incidence surface to the reference layer L0 of the multi-layer disc may be substantially the same as the distance from the light incidence surface to the recording layer of a single layer disc (e.g., about 0.1 mm). By keeping the distance to the deepest (farthest) layer the same regardless of the number of layers in this manner (i.e., by making the distance the same as the distance in the single layer disc), the following effects are provided. The compatibility can be maintained between a single layer disc and a multi-layer disc regarding the access to the reference layer. In addition, the influence of the tilt is prevented from being increased even when the number of layers increases, for the following reason.

The deepest layer is most influenced by the tilt. However, in the case where the distance to the deepest layer is made the same as the distance in the single layer disc, the distance to the deepest layer is not increased even if the number of layers increases.

[0244] Regarding the spot advancing direction (also referred to as the "track direction or spiral direction"), either the parallel path or the opposite path is usable.

[0245] By the parallel path, the reproduction direction is the same in all the layers. Namely, the spot advancing direction is from the innermost end toward the outermost end in all the layers, or from the outermost end toward the innermost end in all the layers.

[0246] By the opposite path, the reproduction direction in one layer is opposite to the reproduction direction in a layer adjacent thereto. Specifically, where the spot advancing direction is from the innermost end toward the outermost end in the reference layer (L0), the reproduction direction is from the outermost end toward the innermost end in the recording layer L1 and is from the innermost end

toward the outermost end in the recording layer L2. Namely, the reproduction direction is from the innermost end toward the outermost end in the recording layer L_m (m is 0 or an even number) and is from the outermost end toward the innermost end in the recording layer L_{m+1}. Alternatively, the reproduction direction is from the outermost end toward the innermost end in the recording layer L_m (m is 0 or an even number) and is from the innermost end toward the outermost end in the recording layer L_{m+1}.

[0247] The thickness of the protective layer (cover layer) is set to be smaller because the numerical aperture (NA) is higher and so the focal distance is shorter, and also in order to suppress the influence of the distortion of the spot caused by the tilt. The numerical aperture NA is set to about 0.85 for the BD whereas the numerical aperture NA is set to 0.45 for the CD and 0.65 for the DVD. For example, among the total thickness of the recording medium of about 1.2 mm, the thickness of the protective layer may be 10 to 200 μm . More specifically, on a substrate having a thickness of about 1.1 mm, a transparent protective layer having a

thickness of about 0.1 mm may be provided in the case of a single layer disc, and a protective layer having a thickness of about 0.075 mm and an intermediate layer (spacer layer) having a thickness of about 0.025 mm may be provided in the case of a two-layer disc. For a disc including three or more layers, the thickness of the protective layer and/or space layer may be thinner.

(Structural examples of discs having one through four layers)

[0248] Now, FIG. **16** shows an example of a structure of a single layer disc, FIG. **17** shows an example of a structure of a two-layer disc, FIG. **18** shows an example of a structure of a three-layer disc, and FIG. **19** shows an example of a structure of a four-layer disc. As described above, where the distance from the light incidence surface to the reference layer L0 is made the same, the total thickness of the disc is about 1.2 mm (it is preferable that the total thickness is equal to or less than 1.40 mm including label printing or the like), the thickness of the substrate **500** is about 1.1 mm, and the distance from the light incidence

surface to the reference layer L0 is about 0.1 mm in any of the discs shown in FIG. **17** through FIG. **19**. In the single layer disc shown in FIG. **16** ($n = 0$ in FIG. **15**), the thickness of a cover layer **5011** is about 0.1 mm. In the two-layer disc shown in FIG. **17** ($n = 1$ in FIG. **15**), the thickness of a cover layer **5012** is about 0.075 mm and the thickness of a space layer **5032** is about 0.025 mm. In the three-layer disc shown in FIG. **18** ($n = 2$ in FIG. **15**) and the four-layer disc shown in FIG. **19** ($n = 3$ in FIG. **15**), the thickness of cover layers **5013** and **5014** and/or the thickness of space layers **5033** and **5034** are still thinner.

(Production method of the optical disc)

[0249] These single layer or multi-layer discs (disc having k number of recording layers; k is an integer of 1 or greater) can be each produced by the following process.

[0250] A substrate having a thickness of about 1.1 mm is irradiated with laser light having a wavelength of 400 nm or greater and 410 nm or less via an objective lens having a numerical aperture of 0.84 or greater and 0.86 or less. Thus,

k number of recording layers from which information is reproduceable is formed.

[0251] Next, $(k-1)$ number of space layers are formed between a recording layer and another recording layer. In the case of a single layer disc, $k = 1$. Since $k - 1 = 0$, no space layer is formed.

[0252] Next, on the k 'th recording layer counted from the substrate side (in the case of a multi-layer disc, the recording layer farthest from the substrate), a protective layer having a thickness of 0.1 mm or less is formed.

[0253] During the step of forming the recording layers, when an i 'th recording layer counted from the substrate side (i is an odd number of 1 or greater and k or less) is formed, a concentric or spiral track is formed such that the reproduction direction is from the innermost end toward the outermost end of the disc. When a j 'th recording layer counted from the substrate side (j is an even number of 1 or greater and k or less) is formed, a concentric or spiral track is formed such that the reproduction direction is from the outermost end toward the innermost end of the disc. In

the case of a single layer disc, $k = 1$. In the case where $k = 1$, i , which is an odd number that is 1 or greater and k or less, is only "1". Therefore, only one recording layer is formed as the i 'th recording layer. In the case where $k = 1$, j , which is an even number that is 1 or greater and k or less, does not exist. Therefore, no layer is formed as the j 'th recording layer.

[0254] In the track of the recording layers, various types of areas can be assigned.

(Reproduction apparatus of the optical disc)

[0255] Reproduction from such a single layer or multi-layer disc (disc having k number of recording layers; k is an integer of 1 or greater) is performed by a reproduction apparatus having the following structure.

[0256] The disc has a structure of including a substrate having a thickness of about 1.1 mm, k number of recording layers provided on the substrate, $(k-1)$ number of space layers provided between a recording layer and another recording layer (in the case of a single layer disc, $k = 1$,

and since $k - 1 = 0$, no space layer is formed), and a protective layer having a thickness of 0.1 mm or less and provided on the k 'th recording layer counted from the substrate side (in the case of a multi-layer disc, the recording layer farthest from the substrate). A track is formed on each of the k number of recording layers, and in at least one of the tracks, various types of areas can be assigned.

[0257] An optical head irradiates the k number of recording layers with laser light having a wavelength of 400 nm or greater and 410 nm or less via an objective lens having a numerical aperture of 0.84 or greater and 0.86 or less from the side of a surface of the protective layer. Thus, information is made reproduceable from each of the k number of recording layers.

[0258] On the i 'th recording layer counted from the substrate side (i is an odd number of 1 or greater and k or less), a concentric or spiral track is formed. A control section for reproducing information from the innermost end toward the outermost end of the disc controls the

reproduction direction, so that information can be reproduced from the i'th recording layer.

[0259] On the j'th recording layer counted from the substrate side (j is an odd number of 1 or greater and k or less), a concentric or spiral track is formed. The control section for reproducing information from the outermost end toward the innermost end of the disc controls the reproduction direction, so that information can be reproduced from the j'th recording layer.

(Modulation)

[0260] Now, the modulation system of the recording signal will be described. For recording data (original source data/pre-modulation binary data) on a recording medium, the data is divided into parts of a prescribed size, and the data divided into parts of the prescribed size is further divided into frames of a prescribed length. For each frame, a prescribed sync. code/synchronization code stream is inserted (frame sync. area). The data divided into the frames is recorded as a data code stream modulated in accordance with a

prescribed modulation rule matching the recording/reproduction signal characteristic of the recording medium (frame data area).

[0261] The modulation rule may be, for example, an RLL (Run Length Limited) coding system by which the mark length is limited. The notation "RLL(d,k)" means that the number of 0's appearing between 1 and 1 is d at the minimum and k at the maximum (d and k are natural numbers fulfilling $d < k$). For example, when $d = 1$ and $k = 7$, where T is the reference cycle of modulation, the length of the mark or space is 2T at the shortest and 8T at the longest. Alternatively, the modulation rule may be 1-7PP modulation, in which the following features [1] and [2] are added to the RLL(1,7) modulation. "PP" of 1-7PP is an abbreviation of Parity preserve/Prohibit Repeated Minimum Transition Length.

[1] "Parity preserve" represented by the first "P" means that whether the number of 1's of the pre-modulation source data bits is an odd number or an even number (i.e., Parity) matches whether the number of 1's of the corresponding post-modulation bit pattern is an odd number or an even number.

[2] "Prohibit Repeated Minimum Transition Length" represented by the second "P" means a mechanism for limiting the number of times the shortest marks and spaces are repeated on the post-modulation recording wave (specifically, a mechanism for limiting the number of times 2T is repeated to 6).

[0262] When the recording density increases, a plurality of recording densities may be possibly provided for optical disc mediums. In such a case, only a part of the various formats and methods described above may be adopted, or a part thereof may be replaced with another format or method.

[0263] Now, a physical structure of an optical disc will be described.

[0264] FIG. **20** shows a physical structure of an optical disc **1** according to this embodiment. On the disc-shaped optical disc **1**, a great number of tracks **2A** are formed concentrically or in a spiral, for example. In each track **2A**, a great number of tiny sectors are formed. As described later, data is recorded on each track **2A** in units of blocks **3A** each having a predetermined size.

[0265] The optical disc **1** according to this embodiment has

an expanded recording capacity per information recording layer as compared with a conventional optical disc (for example, a BD of 25 GB). The recording capacity is expanded by raising the recording linear density, for example, by decreasing the length of a recording mark to be recorded on the optical disc. Here, the expression "raising the recording linear density" means to decrease the channel bit length. The "channel bit length" refers to a length corresponding to cycle T of the reference clock (the reference cycle T of modulation in the case where a mark is recorded by a prescribed modulation rule). The optical disc **1** may include a plurality of layers. In the following, only one information recording layer will be described for the convenience of explanation. Even where the width of the track is the same among a plurality of layers provided in the optical disc, the recording linear density may be varied on a layer-by-layer basis by making the mark length different among different layers while making the mark length the same in the same layer.

[0266] The track **2A** is divided into blocks by a data

recording unit of 64 kB (kilobytes), and the blocks are sequentially assigned block address values. Each block is divided into sub blocks each having a prescribed length. Three sub blocks form one block. The sub blocks are assigned sub block numbers of 0 through 2 from the first sub block.

(Recording density)

[0267] Now, the recording density will be described with reference to FIG. **21**, FIG. **22** and FIG. **23**.

[0268] FIG. **21(a)** shows an example of a 25 GB BD. For the BD, the wavelength of laser light **123** is 405 nm and the numerical aperture (NA) of an objective lens **220** is 0.85.

[0269] Like in the case of a DVD, also in the case of a BD, the recording data is recorded as marks **120** and **121** formed by a physical change on the track **2A** of the optical disc. A mark having the shortest length among these marks is referred to as the "shortest mark". In the figure, the mark **121** is the shortest mark.

[0270] When the recording capacity is 25 GB, the physical length of the shortest mark **121** is 0.149 μm . This

corresponds to about $1/2.7$ of that of a DVD. Even if the resolving power of the laser light is raised by changing the wavelength parameter (405 nm) and the NA parameter (0.85) of the optical system, the physical length of the shortest mark is close to the limit of the optical resolving power, i.e., the limit at which a light beam can identify a recording mark.

[0271] FIG. **22** shows how a mark sequence recorded on the track is irradiated with a light beam. In the case of a BD, an optical spot **30A** has a diameter of about $0.39\ \mu\text{m}$ because of the above-mentioned parameters of the optical system. When the recording linear density is raised without changing the structure of the optical system, the recording mark becomes smaller with respect to the diameter of the optical spot **30A**, and therefore the resolving power for reproduction is declined.

[0272] For example, FIG. **21 (b)** shows an example of an optical disc having a recording density higher than that of the 25 GB BD. For this disc also, the wavelength of the laser light **123** is 405 nm and the numerical aperture (NA) of the objective lens **220** is 0.85. A mark shortest among the

marks **125** and **124** of the disc, namely, the mark **125**, has a physical length of $0.1115\ \mu\text{m}$. In the disc in FIG. **21(b)**, as compared with the disc shown in FIG. **21(a)**, the diameter of the spot is the same at about $0.39\ \mu\text{m}$ but the recording mark is smaller and the inter-mark gap is narrower. Therefore, the resolving power for reproduction is declined.

[0273] An amplitude of a reproduction signal obtained by reproducing a recording mark using a light beam decreases as the recording mark is shortened, and becomes almost zero at the limit of the optical resolving power. The inverse of the cycle of the recording mark is called "spatial frequency", and the relationship between the spatial frequency and the signal amplitude is called OTF (Optical Transfer Function). The signal amplitude decreases almost linearly as the spatial frequency increases. The critical frequency for reproduction at which the signal amplitude becomes zero is called "OTF cutoff".

[0274] FIG. **23** is a graph showing the relationship between the OTF and the shortest recording mark when the recording capacity is 25 GB. The spatial frequency of the shortest

recording mark of the BD is about 80% with respect to the OTF cutoff, which is close to the OTF cutoff. It is also seen that the amplitude of the reproduction signal of the shortest mark is very small at about 10% of the maximum detectable amplitude. For the BD, the recording capacity at which the spatial frequency of the shortest recording mark is very close to the OTF cutoff, i.e., the recording capacity at which the reproduction amplitude of the shortest mark is almost zero, is about 31 GB. When the frequency of the reproduction signal of the shortest mark is around, or exceeds, the OFF cutoff frequency, the resolving power of the laser light is close to the limit or may exceed the limit. In such an area, the amplitude of the reproduction signal decreases and the S/N ratio is drastically deteriorated.

[0275] Therefore, with the recording linear density which is assumed for the high density optical disc shown in FIG. **21 (b)**, the frequency of the shortest mark of the reproduction signal is in the vicinity of the OTF cutoff (including a case where the frequency is equal to or lower than the OTF cutoff, but is not significantly lower than the

OTF cutoff) or equal to or higher than the OTF cutoff.

[0276] FIG. **24** is a graph showing an example the relationship between the signal amplitude and the spatial frequency when the spatial frequency of the shortest mark (2T) is higher than the OTF cutoff frequency and the amplitude of a 2T reproduction signal is 0. In FIG. **24**, the spatial frequency of the shortest mark (2T) is 1.12 times of the OTF cutoff frequency.

(Relationship among the wavelength, numerical aperture and mark length)

[0277] The relationship among the wavelength, numerical aperture and length of a mark/space of a higher recording density disc B is as follows.

[0278] Where the shortest mark length is T_M nm and the shortest space length is T_S nm, (shortest mark length + shortest space length) P is represented as $(T_M + T_S)$ nm. In the case of 17 modulation, $P = 2T + 2T = 4T$. Where the three parameters, i.e., the laser light wavelength λ ($405 \text{ nm} \pm 5 \text{ nm}$, i.e., 400 to 410 nm), the numerical aperture (NA) ($0.85 \pm$

0.01, i.e., 0.84 to 0.86), and the length P of the shortest mark + the shortest space (in the case of 17 modulation, $P = 2T + 2T = 4T$ because the shortest length is $2T$) are used, when the reference T decreases to fulfill $P \leq \lambda/2NA$, the spatial frequency of the shortest mark exceeds the OTF cutoff frequency.

[0279] The reference T corresponding to the OTF cutoff frequency when $NA = 0.85$ and $\lambda = 405$ nm is:

$$T = 405 / (2 \times 0.85) / 4 = 59.558 \text{ nm.}$$
 (When $P > \lambda/2NA$, the spatial frequency of the shortest mark is lower than the OTF cutoff frequency.)

[0280] In this manner, merely by increasing the recording linear density, the S/N ratio is deteriorated by the limit of the optical resolution. The deterioration of the S/N ratio caused by increasing the number of information recording layers may be occasionally intolerable from the viewpoint of the system margin. As described above, the deterioration of the S/N ratio is conspicuous especially where the frequency of the shortest mark is higher than the OTF cutoff frequency.

[0281] In the above, the frequency of the reproduction

signal of the shortest mark and the OTF cutoff frequency are compared in relation with the recording density. When the density improvement is more advanced, a recording density (recording linear density, recording capacity) corresponding to each case can be set by the principle described above based on the relationship between the frequency of the reproduction signal of the second shortest mark (also the third shortest mark (also the second shortest or longer mark) and the OTF cutoff frequency.

(Recording density and the number of layers)

[0282] For a BD usable with laser light having a wavelength of 405 nm and an objective lens having a numerical aperture of 0.85, the following can be considered as a specific recording capacity per layer in the case where the spatial frequency of the shortest mark is in the vicinity of the OTF cutoff: about 29 GB (e.g., $29.0 \text{ GB} \pm 0.5 \text{ GB}$ or $29 \text{ GB} \pm 1 \text{ GB}$, etc.) or larger, about 30 GB (e.g., $30.0 \text{ GB} \pm 0.5 \text{ GB}$ or $30 \text{ GB} \pm 1 \text{ GB}$, etc.) or larger, about 31 GB (e.g., $31.0 \text{ GB} \pm 0.5 \text{ GB}$ or $31 \text{ GB} \pm 1 \text{ GB}$, etc.) or larger, about 32 GB (e.g.,

32.0 GB $\pm$ 0.5 GB or 32 GB $\pm$ 1 GB, etc.) or larger, and the like.

[0283] In the case where the spatial frequency of the shortest mark is equal to or higher than the OTF cutoff, the following can be considered as a recording capacity per layer: about 32 GB (e.g., 32.0 GB $\pm$ 0.5 GB or 32 GB $\pm$ 1 GB, etc.) or larger, about 33 GB (e.g., 33.0 GB $\pm$ 0.5 GB or 33 GB $\pm$ 1 GB, etc.) or larger, about 33.3 GB (e.g., 33.3 GB $\pm$ 0.5 GB or 33.3 GB $\pm$ 1 GB, etc.) or larger, about 33.4 GB (e.g., 33.4 GB $\pm$ 0.5 GB or 33.4 GB $\pm$ 1 GB, etc.) or larger, about 34 GB (e.g., 34.0 GB $\pm$ 0.5 GB or 34 GB $\pm$ 1 GB, etc.) or larger, about 35 GB (e.g., 35.0 GB $\pm$ 0.5 GB or 35 GB $\pm$ 1 GB, etc.) or larger, and the like.

[0284] Especially where the recording density is about 33.3 GB, a recording capacity of about 100 GB (99.9 GB) is realized with three layers. Where the recording density is about 33.4 GB, a recording capacity of 100 GB or greater (100.2 GB) is realized with three layers. This generally matches the recording capacity of a BD including four layers each having a recording density of 25 GB. For example, where

the recording density is 33 GB, $33 \times 3 = 99$ GB, which is different from 100 GB by 1 GB (equal to or less than 1 GB).

Where the recording density is 34 GB, $34 \times 3 = 102$ GB, which is different from 100 GB by 2 GB (equal to or less than 2 GB).

Where the recording density is 33.3 GB, $33.3 \times 3 = 99.9$ GB, which is different from 100 GB by 0.1 GB (equal to or less than 0.1 GB). Where the recording density is 33.4 GB, $33.4 \times 3 = 100.2$ GB, which is different from 100 GB by 0.2 GB (equal to or less than 0.2 GB).

[0285] As described above, when the recording density is significantly expanded, precise reproduction becomes difficult because of the influence of the reproduction characteristic of the shortest mark. As a recording density which is suppressed from being expanded significantly but realizes a recording capacity of 100 GB or greater, about 33.4 GB is realistically usable.

[0286] In this situation, there are the following alternatives for the disc structure: including four layers each having 25 GB, or including three layers each having 33 to 34 GB. When the number of layers increases, the

reproduction signal amplitude of each recording layer is decreased (the S/N ratio is deteriorated) or the influence of multi-layer stray light (signal from an adjacent recording layer) is exerted, for example. A disc including three layers each having 33 to 34 GB, as opposed to a disc including four layers each having 25 GB, can realize a recording capacity of about 100 GB while suppressing the influence of the stray light as much as possible, i.e., with a smaller number of layers (with three layers as opposed to four layers). Thus, a disc manufacture wishing to realize about 100 GB while avoiding the increase of the number of the layers as much as possible can choose a disc including three layers each having 33 to 34 GB. By contrast, a disc manufacturer wishing to realize about 100 GB while keeping the conventional format (the recording density of 25 GB) can choose a disc including four layers each having 25 GB. In this manner, manufacturers with different purposes can realize the respective purposes with different structures. This provides a certain degree of freedom in disc designing.

[0287] Where the recording density per layer is about 30

to 32 GB, a recording capacity of 120 GB or greater is realized with a four-layer disc although 100 GB is not reached by a three-layer disc (about 90 to 96 GB). Where the recording density is about 32 GB, a four-layer disc realizes a recording capacity of about 128 GB. The numerical value of 128 matches a power of 2 (seventh power of 2) which is convenient to be processed by a computer. As compared to the disc realizing about 100 GB with three layers, the disc realizing about 128 GB with four layers has less influence on the reproduction characteristic of the shortest mark.

[0288] Based on this, for expanding the recording density, a plurality of recording densities may be provided (for example, about 32 GB and about 33.4 GB) and combined with a plurality of numbers of layers. In this manner, the disc manufacturers can be provided with a certain degree of freedom in designing. For example, a manufacturer wishing to increase the capacity while suppressing the influence of a larger number of layers can choose to produce a three-layer disc of about 100 GB in which each of three layers has 33 to 34 GB. A manufacture wishing to increase the capacity while

suppressing the influence on the reproduction characteristic can choose to produce a four-layer disc of about 120 GB in which each of four layers has 30 to 32 GB.

[0289] As described above, a reproduction signal evaluation method according to the present invention includes a step of generating a binary signal from an information recording medium on which a data sequence including marks and spaces in combination is recordable, using a PRML signal processing method from a signal obtained by reproducing the data sequence; and a differential calculation step of calculating a differential metric using a first state transition path having a maximum likelihood and a second state transition path having a second maximum likelihood, and a reproduction signal, the first state transition path and the second state transition path being obtained based on the binary signal. In a pattern including a shortest mark and a shortest space adjacent before or after the shortest mark, a shift amount of an edge of the shortest mark is obtained from a differential metric calculated regarding one of a first pattern in which a space adjacent to the shortest mark and

not adjacent to the shortest space is longer than the shortest space; and a second pattern in which a mark adjacent to the shortest space and not adjacent to the shortest mark is longer than the shortest mark.

[0290] In an embodiment, where a reference cycle of the data sequence is T , the shortest mark and the shortest space each have a length of $2T$; and where binary data of a pattern including the shortest mark and the shortest space adjacent to each other is represented by "0" and "1", the shift amount of the edge of the shortest mark is obtained from a differential metric calculated regarding a pattern, the binary data of which is "x000110011x" or "x001100111x" ("x" is "0" or "1").

[0291] In an embodiment, where a reference cycle of the data sequence is T , the shortest mark and the shortest space each have a length of $2T$; and where binary data of a pattern including the shortest mark and the shortest space adjacent to each other is represented by "0" and "1", the shift amount of the edge of the shortest mark is obtained from a differential metric calculated regarding a pattern, the

binary data of which is "x110011000x" or "x111001100x" ("x" is "0" or "1").

[0292] An information recording medium according to the present invention is an information recording medium on which a data sequence including marks and spaces in combination is recordable. The information recording medium has a track on which the data sequence is recordable. A reproduction signal from the information recording medium is evaluated using a prescribed method. The prescribed method includes a step of generating a binary signal using a PRML signal processing method from a signal obtained by reproducing the data sequence from the information recording medium; and a differential calculation step of calculating a differential metric using a first state transition path having a maximum likelihood and a second state transition path having a second maximum likelihood, and a reproduction signal, the first state transition path and the second state transition path being obtained based on the binary signal. In a pattern including a shortest mark and a shortest space adjacent before or after the shortest mark, a shift amount of an edge

of the shortest mark is obtained from a differential metric calculated regarding one of a first pattern in which a space adjacent to the shortest mark and not adjacent to the shortest space is longer than the shortest space; and a second pattern in which a mark adjacent to the shortest space and not adjacent to the shortest mark is longer than the shortest mark.

[0293] A reproduction apparatus according to the present invention is a reproduction apparatus for reproducing information from the above-described information recording medium. The reproduction apparatus includes an irradiation section for irradiating the track with laser light; a light receiving section for receiving reflected light of the laser light used for the irradiation; and a reproduction section for reproducing the data sequence based on a signal obtained by the received light.

[0294] A recording apparatus according to the present invention is a recording apparatus for recording information on the above-described information recording medium. The recording apparatus includes an irradiation section for

irradiating the track with laser light; and a recording section for forming marks on the track by the irradiation to record a data sequence including marks and spaces between the marks arranged alternately.

[0295] A reproduction signal evaluation method according to the present invention is a method for evaluating a reproduction signal obtained from an information recording medium on which a data sequence including marks and spaces in combination is recordable. The method includes a recognition step of recognizing a prescribed pattern from the data sequence; and an evaluation step of evaluating a reproduction signal corresponding to the recognized pattern. The recognition step includes the steps of recognizing a pattern, included in the data sequence, including a first mark, a first space adjacent before or after the first mark, and a second mark not adjacent to the first mark and adjacent to the first space; and recognizing, when the first space and the second mark each have a length equal to or shorter than a prescribed length, whether or not a second space not adjacent to the first mark and adjacent to the second mark is longer

than the prescribed length.

[0296] An information recording medium according to the present invention is an information recording medium on which a data sequence including marks and spaces in combination is recordable. The information recording medium has a track on which the data sequence is recordable. A reproduction signal from the information recording medium is evaluated using a prescribed method. The prescribed method includes a recognition step of recognizing a prescribed pattern from the data sequence; and an evaluation step of evaluating a reproduction signal corresponding to the recognized pattern. The recognition step includes the steps of recognizing a pattern, included in the data sequence, including a first mark, a first space adjacent before or after the first mark, and a second mark not adjacent to the first mark and adjacent to the first space; and recognizing, when the first space and the second mark each have a length equal to or shorter than a prescribed length, whether or not a second space not adjacent to the first mark and adjacent to the second mark is longer than the prescribed length.

[0297] A reproduction apparatus according to the present invention is a reproduction apparatus for reproducing information from the above-described information recording medium. The reproduction apparatus includes an irradiation section for irradiating the track with laser light; a light receiving section for receiving reflected light of the laser light used for the irradiation; and a reproduction section for reproducing the data sequence based on a signal obtained by the received light.

[0298] A recording apparatus according to the present invention is a recording apparatus for recording information on the above-described information recording medium. The recording apparatus includes an irradiation section for irradiating the track with laser light; and a recording section for forming marks on the track by the irradiation to record a data sequence including marks and spaces between the marks arranged alternately.

[0299] A reproduction signal evaluation method according to the present invention is a method for evaluating a reproduction signal obtained from an information recording

medium on which a data sequence including marks and spaces in combination is recordable. The method includes a recognition step of recognizing a prescribed pattern from the data sequence; and an evaluation step of evaluating a reproduction signal corresponding to the recognized pattern. The recognition step includes the steps of recognizing a pattern, included in the data sequence, including a first mark, a first space adjacent before or after the first mark, and a third space not adjacent to the first space and adjacent to the first mark; and recognizing, when the first mark and the third space each have a length equal to or shorter than a prescribed length, whether or not a third mark not adjacent to the first space and adjacent to the third space is longer than the prescribed length.

[0300] An information recording medium according to the present invention is an information recording medium on which a data sequence including marks and spaces in combination is recordable. The information recording medium has a track on which the data sequence is recordable. A reproduction signal from the information recording medium is evaluated using a

prescribed method. The prescribed method includes a recognition step of recognizing a prescribed pattern from the data sequence; and an evaluation step of evaluating a reproduction signal corresponding to the recognized pattern. The recognition step includes the steps of recognizing a pattern, included in the data sequence, including a first mark, a first space adjacent before or after the first mark, and a third space not adjacent to the first space and adjacent to the first mark; and recognizing, when the first mark and the third space each have a length equal to or shorter than a prescribed length, whether or not a third mark not adjacent to the first space and adjacent to the third space is longer than the prescribed length.

[0301] A reproduction apparatus according to the present invention is a reproduction apparatus for reproducing information from the above-described information recording medium. The reproduction apparatus includes an irradiation section for irradiating the track with laser light; a light receiving section for receiving reflected light of the laser light used for the irradiation; and a reproduction section

for reproducing the data sequence based on a signal obtained by the received light.

[0302] A recording apparatus according to the present invention is a recording apparatus for recording information on the above-described information recording medium. The recording apparatus includes an irradiation section for irradiating the track with laser light; and a recording section for forming marks on the track by the irradiation to record a data sequence including marks and spaces between the marks arranged alternately.

[0303] A reproduction signal evaluation method according to the present invention is a signal evaluation method, usable for an information recording medium having a data sequence including a mark and a space located alternately, for generating a binary signal from a signal obtained by reproducing the data sequence using a PRML signal processing method and evaluating a likelihood of the binary signal. The signal evaluation method comprises a differential metric calculation step of calculating, from the binary signal, a differential metric which is a difference of a reproduction

signal from a first state transition path having a maximum likelihood and a second state transition path having a second maximum likelihood; and a step of classifying the differential metric to any of a plurality of data patterns each including at least one mark and at least one space. The data pattern classification to any of a plurality of data patterns is performed using a combination of a length of a first mark included in the data sequence and a length of a first space adjacently located immediately previous or immediately subsequent to the first mark, and is further performed using a length of a second mark which is not adjacent to the first mark and located adjacent to the first space; and thus a reproduction signal quality of the information recording medium is evaluated.

[0304] In an embodiment, the classification using the length of the second mark is performed only when the length of the first mark is equal to or shorter than a prescribed length.

[0305] In an embodiment, the data pattern classification is further performed using a length of a second space which

is located adjacent to neither the first mark nor the first space and located adjacent to the second mark.

[0306] In an embodiment, the classification using the length of the second space is performed only when the length of the second mark is equal to or shorter than the prescribed length.

[0307] A reproduction signal evaluation method according to the present invention is a signal evaluation method, usable for an information recording medium having a data sequence including a mark and a space located alternately, for generating a binary signal from a signal obtained by reproducing the data sequence using a PRML signal processing method and evaluating a likelihood of the binary signal. The signal evaluation method comprises a differential metric calculation step of calculating, from the binary signal, a differential metric which is a difference of a reproduction signal from a first state transition path having a maximum likelihood and a second state transition path having a second maximum likelihood; and a step of classifying the differential metric to any of a plurality of data patterns

each including at least one mark and at least one space. The data pattern classification to any of a plurality of data patterns is performed using a combination of a length of a first mark included in the data sequence and a length of a first space adjacently located immediately previous or immediately subsequent to the first mark, and is further performed using a length of a third space which is not adjacent to the first space and located adjacent to the first mark; and thus a reproduction signal quality of the information recording medium is evaluated.

[0308] In an embodiment, the classification using the length of the third space is performed only when the length of the first mark is equal to or shorter than a prescribed length.

[0309] In an embodiment, the data pattern classification is further performed using a length of a third mark which is located adjacent to neither the first mark nor the first space and located adjacent to the third space.

[0310] In an embodiment, the classification using the length of the third mark is performed only when the length of

the third space is equal to or shorter than the prescribed length.

[0311] In an embodiment, the prescribed length is a shortest mark length in the data sequence.

[0312] An information reproduction apparatus according to the present invention is an information reproduction apparatus, usable for an information recording medium having a data sequence including a mark and a space located alternately, for generating a binary signal from a signal obtained by reproducing the data sequence using a PRML signal processing method and evaluating a likelihood of the binary signal. The information reproduction apparatus comprises a differential metric calculation section for calculating, from the binary signal, a differential metric which is a difference of a reproduction signal from a first state transition path having a maximum likelihood and a second state transition path having a second maximum likelihood; and a pattern detection section for classifying the differential metric to any of a plurality of data patterns each including at least one mark and at least one space. The data pattern

classification to any of a plurality of data patterns is performed using a combination of a length of a first mark included in the data sequence and a length of a first space adjacently located immediately previous or immediately subsequent to the first mark, and is further performed using a length of a second mark which is not adjacent to the first mark and located adjacent to the first space; and thus a reproduction signal quality of the information recording medium is evaluated.

[0313] In an embodiment, the classification using the length of the second mark is performed only when the length of the first mark is equal to or shorter than a prescribed length.

[0314] In an embodiment, the data pattern classification is further performed using a length of a second space which is located adjacent to neither the first mark nor the first space and located adjacent to the second mark.

[0315] In an embodiment, the classification using the length of the second space is performed only when the length of the second mark is equal to or shorter than the prescribed

length.

[0316] An information reproduction apparatus according to the present invention is an information reproduction apparatus, usable for an information recording medium having a data sequence including a mark and a space located alternately, for generating a binary signal from a signal obtained by reproducing the data sequence using a PRML signal processing method and evaluating a likelihood of the binary signal. The information reproduction apparatus comprises a differential metric calculation section for calculating, from the binary signal, a differential metric which is a difference of a reproduction signal from a first state transition path having a maximum likelihood and a second state transition path having a second maximum likelihood; and a pattern detection section for classifying the differential metric to any of a plurality of data patterns each including at least one mark and at least one space. The data pattern classification to any of a plurality of data patterns is performed using a combination of a length of a first mark included in the data sequence and a length of a first space

adjacently located immediately previous or immediately subsequent to the first mark, and is further performed using a length of a third space which is not adjacent to the first space and located adjacent to the first mark; and thus a reproduction signal quality of the information recording medium is evaluated.

[0317] In an embodiment, the classification using the length of the third space is performed only when the length of the first mark is equal to or shorter than a prescribed length.

[0318] In an embodiment, the data pattern classification is further performed using a length of a third mark which is located adjacent to neither the first mark nor the first space and located adjacent to the third space.

[0319] In an embodiment, the classification using the length of the third mark is performed only when the length of the third space is equal to or shorter than the prescribed length.

[0320] In an embodiment, the prescribed length is a shortest mark length in the data sequence.

INDUSTRIAL APPLICABILITY

[0321] The present invention is especially useful in the technical field of performing signal processing using a maximum likelihood decoding method.

REFERENCE SIGNS LIST

[0322]

- 1 information recording medium
- 2 optical head section
- 3 preamplifier section
- 4 AGC section
- 5 waveform equalization section
- 6 A/D conversion section
- 7 PLL section
- 8 PR equalization section
- 9 maximum likelihood decoding section
- 10 signal evaluation index detection section
- 15 optical disc controller section
- 100 optical disc apparatus

101, 104, 107 pattern detection section

102, 105, 108 differential metric calculation section

103, 106, 109 memory section

21, 22 PR equalization ideal waveforms of 14-detection
pattern

23, 29, 33, 39 reproduction waveform of 14-detection pattern

24, 34 space of PR equalization ideal waveforms of 14-
detection pattern

25, 35 mark of PR equalization ideal waveforms of 14-
detection pattern

26, 30, 36, 40 space of reproduction waveform of 14-detection
pattern

27, 31, 37, 41 mark of reproduction waveform of 14-detection
pattern

28, 32, 38, 42 shift amount of 14-detection pattern

51, 52 PR equalization ideal waveforms of 12A-detection
pattern

53 reproduction waveform of 12A-detection pattern

54, 56 space of PR equalization ideal waveforms of 12A-
detection pattern

55 mark of PR equalization ideal waveforms of 12A-detection pattern

57, 59 space of reproduction waveform of 12A-detection pattern

58 mark of reproduction waveform of 12A-detection pattern

60 shift amount of 12A-detection pattern

71, 72 PR equalization ideal waveforms of 12B-detection pattern

73 reproduction waveform of 12B-detection pattern

74, 76 space of PR equalization ideal waveforms of 12B-detection pattern

75, 77 mark of PR equalization ideal waveforms of 12B-detection pattern

78, 80 space of reproduction waveform of 12B-detection pattern

79, 81 mark of reproduction waveform of 12B-detection pattern

82 shift amount of 12B-detection pattern

201 optical spot size

CLAIMS

1. A reproduction signal evaluation method, comprising:

a step of generating a binary signal from an information recording medium on which a data sequence including marks and spaces in combination is recordable, using a PRML signal processing method from a signal obtained by reproducing the data sequence; and

a differential calculation step of calculating a differential metric using a first state transition path having a maximum likelihood and a second state transition path having a second maximum likelihood, and a reproduction signal, the first state transition path and the second state transition path being obtained based on the binary signal;

wherein in a pattern including a shortest mark and a shortest space adjacent before or after the shortest mark, a shift amount of an edge of the shortest mark is obtained from a differential metric calculated regarding one of:

a first pattern in which a space adjacent to the shortest mark and not adjacent to the shortest space is longer than the shortest space; and

a second pattern in which a mark adjacent to the shortest space and not adjacent to the shortest mark is longer than the shortest mark.

2. The reproduction signal evaluation method of claim 1, wherein:

where a reference cycle of the data sequence is T , the shortest mark and the shortest space each have a length of $2T$; and

where binary data of a pattern including the shortest mark and the shortest space adjacent to each other is represented by "0" and "1", the shift amount of the edge of the shortest mark is obtained from a differential metric calculated regarding a pattern, the binary data of which is "x000110011x" or "x001100111x" ("x" is "0" or "1").

3. The reproduction signal evaluation method of claim 1, wherein:

where a reference cycle of the data sequence is T , the shortest mark and the shortest space each have a length of

2T; and

where binary data of a pattern including the shortest mark and the shortest space adjacent to each other is represented by "0" and "1", the shift amount of the edge of the shortest mark is obtained from a differential metric calculated regarding a pattern, the binary data of which is "x110011000x" or "x111001100x" ("x" is "0" or "1").

4. An information recording medium on which a data sequence including marks and spaces in combination is recordable, wherein:

the information recording medium has a track on which the data sequence is recordable;

a reproduction signal from the information recording medium is evaluated using a prescribed method;

the prescribed method includes:

a step of generating a binary signal using a PRML signal processing method from a signal obtained by reproducing the data sequence from the information recording medium; and

a differential calculation step of calculating a differential metric using a first state transition path having a maximum likelihood and a second state transition path having a second maximum likelihood, and a reproduction signal, the first state transition path and the second state transition path being obtained based on the binary signal; and

in a pattern including a shortest mark and a shortest space adjacent before or after the shortest mark, a shift amount of an edge of the shortest mark is obtained from a differential metric calculated regarding one of:

a first pattern in which a space adjacent to the shortest mark and not adjacent to the shortest space is longer than the shortest space; and

a second pattern in which a mark adjacent to the shortest space and not adjacent to the shortest mark is longer than the shortest mark.

5. A reproduction apparatus for reproducing information from the information recording medium of claim 4, the

reproduction apparatus comprising:

an irradiation section for irradiating the track with laser light;

a light receiving section for receiving reflected light of the laser light used for the irradiation; and

a reproduction section for reproducing the data sequence based on a signal obtained by the received light.

6. A recording apparatus for recording information on the information recording medium of claim 4, the recording apparatus comprising:

an irradiation section for irradiating the track with laser light; and

a recording section for forming marks on the track by the irradiation to record a data sequence including marks and spaces between the marks arranged alternately.

7. A method for evaluating a reproduction signal obtained from an information recording medium on which a data sequence including marks and spaces in combination is

recordable, the method comprising:

a recognition step of recognizing a prescribed pattern from the data sequence; and

an evaluation step of evaluating a reproduction signal corresponding to the recognized pattern;

wherein the recognition step includes the steps of:

recognizing a pattern, included in the data sequence, including a first mark, a first space adjacent before or after the first mark, and a second mark not adjacent to the first mark and adjacent to the first space; and

recognizing, when the first space and the second mark each have a length equal to or shorter than a prescribed length, whether or not a second space not adjacent to the first mark and adjacent to the second mark is longer than the prescribed length.

8. An information recording medium on which a data sequence including marks and spaces in combination is recordable, wherein:

the information recording medium has a track on which the data sequence is recordable;

a reproduction signal from the information recording medium is evaluated using a prescribed method;

the prescribed method includes:

a recognition step of recognizing a prescribed pattern from the data sequence; and

an evaluation step of evaluating a reproduction signal corresponding to the recognized pattern; and

the recognition step includes the steps of:

recognizing a pattern, included in the data sequence, including a first mark, a first space adjacent before or after the first mark, and a second mark not adjacent to the first mark and adjacent to the first space; and

recognizing, when the first space and the second mark each have a length equal to or shorter than a prescribed length, whether or not a second space not adjacent to the first mark and adjacent to the second mark is longer than the prescribed length.

9. A reproduction apparatus for reproducing information from the information recording medium of claim 8, the reproduction apparatus comprising:

an irradiation section for irradiating the track with laser light;

a light receiving section for receiving reflected light of the laser light used for the irradiation; and

a reproduction section for reproducing the data sequence based on a signal obtained by the received light.

10. A recording apparatus for recording information on the information recording medium of claim 8, the recording apparatus comprising:

an irradiation section for irradiating the track with laser light; and

a recording section for forming marks on the track by the irradiation to record a data sequence including marks and spaces between the marks arranged alternately.

11. A method for evaluating a reproduction signal obtained from an information recording medium on which a data sequence including marks and spaces in combination is recordable, the method comprising:

a recognition step of recognizing a prescribed pattern from the data sequence; and

an evaluation step of evaluating a reproduction signal corresponding to the recognized pattern;

wherein the recognition step includes the steps of:

recognizing a pattern, included in the data sequence, including a first mark, a first space adjacent before or after the first mark, and a third space not adjacent to the first space and adjacent to the first mark; and

recognizing, when the first mark and the third space each have a length equal to or shorter than a prescribed length, whether or not a third mark not adjacent to the first space and adjacent to the third space is longer than the prescribed length.

12. An information recording medium on which a data sequence including marks and spaces in combination is recordable, wherein:

the information recording medium has a track on which the data sequence is recordable;

a reproduction signal from the information recording medium is evaluated using a prescribed method;

the prescribed method includes:

a recognition step of recognizing a prescribed pattern from the data sequence; and

an evaluation step of evaluating a reproduction signal corresponding to the recognized pattern; and

the recognition step includes the steps of:

recognizing a pattern, included in the data sequence, including a first mark, a first space adjacent before or after the first mark, and a third space not adjacent to the first space and adjacent to the first mark; and

recognizing, when the first mark and the third space each have a length equal to or shorter than a

prescribed length, whether or not a third mark not adjacent to the first space and adjacent to the third space is longer than the prescribed length.

13. A reproduction apparatus for reproducing information from the information recording medium of claim 12, the reproduction apparatus comprising:

an irradiation section for irradiating the track with laser light;

a light receiving section for receiving reflected light of the laser light used for the irradiation; and

a reproduction section for reproducing the data sequence based on a signal obtained by the received light.

14. A recording apparatus for recording information on the information recording medium of claim 12, the recording apparatus comprising:

an irradiation section for irradiating the track with laser light; and

a recording section for forming marks on the track by

the irradiation to record a data sequence including marks and spaces between the marks arranged alternately.

FIG. 1

1/18






FIG.2STATE $(b_{k-3}, b_{k-2}, b_{k-1}, b_k)$ 

FIG. 3

4/18




FIG. 4*FIG. 5**FIG. 6*

FIG. 7

START										
		M (i)	2M			3M	4M	≥5M		
		S (i+1)	2S		(≥3S)	xS	xS	xS		
S(i-3)	M(i-2)	M(i+2) S(i-1)	2M	(≥3M)	xM	xM	xM	xM		
	2S						[14]13A X110011100X	[14]14A X1100111100X	[14]15A X110011111X	
	(≥3S)									
xS	xM	2S	[14]13B X110001100X		[14]10A, [14]14B X1100011100X	[14]11A, [14]15B X11000111100X	[14]12A X1100011111X	[14]12A X1100011111X		
			[14]10B X1100001100X		[14]1A, [14]11B X11000011100X	[14]2A, [14]12B X110000111100X	[14]3A X11000011111X	[14]3A X11000011111X		
			[14]1B X000001100X		[14]2B X0000011100X	[14]3B X00000111100X	[14]3A, [14]3B X0000011111X	[14]3A, [14]3B X0000011111X		
END										
		M (i)	2M			3M	4M	≥5M		
		S (i-1)	2S		(≥3S)	xS	xS	xS		
S(i+3)	M(i+2)	M(i-2) S(i+1)	2M	(≥3M)	xM	xM	xM	xM		
	2S						[14]6A X001110011X	[14]9A X0011110011X	[14]18A X111110011X	
	(≥3S)									
xS	xM	2S	[14]6B X001100011X		[14]5A, [14]9B X0011100011X	[14]8A, [14]18B X00111100011X	[14]17A X1111100011X	[14]17A X1111100011X		
			[14]5B X0011000011X		[14]4A, [14]8B X00111000011X	[14]7A, [14]17B X001111000011X	[14]16A X11111000011X	[14]16A X11111000011X		
			[14]4B X001100000X		[14]7B X0011100000X	[14]16B X00111100000X	[14]16A, [14]16B X1111100000X	[14]16A, [14]16B X1111100000X		



FIG. 8

START															
S(i-3)	M(i-2)	M(i)	2M		S(i-1)	M(i+2)	2M	(≥3M)	xM	3M	4M	≥5M			
	2S (≥3S)	S(i+1)	2S	(≥3S)						xS	xS	xS			
		2S													
xS	xM	3S	[12A]15B X11000110011X	[12A]13B, [12A]14B X1100011000X											
		4S	[12A]12B X110000110011X	[12A]10B, [12A]11B X11000011000X											
		≥5S	[12A]3B X00000110011X	[12A]1B, [12A]2B X0000011000X											
END															
S(i+3)	M(i+2)	M(i)	2M		S(i+1)	M(i-2)	2M	(≥3M)	xM	3M	4M	≥5M			
	2S (≥3S)	S(i-1)	2S	(≥3S)						xS	xS	xS			
		2S													
xS	xM	3S	[12A]15A X11001100011X	[12A]3A, [12A]12A X0001100011X											
		4S	[12A]14A X110011000011X	[12A]2A, [12A]11A X00011000011X											
		≥5S	[12A]13A X11001100000X	[12A]1A, [12A]10A X0001100000X											

FIG.9


START									
		M (i)	2M			3M	4M	$\geq 5M$	
		S (i+1)	2S	($\geq 3S$)	xS	xS	xS		
S(i-3)	M(i-2)	M(i+2) S(i-1)	2M	($\geq 3M$)	xM	xM	xM	xM	
2S	2M	2S			[12B]13A X1100110011100X	[12B]14A X11001100111100X	[12B]15A X11001100111111X		
					[12B]10A X0001100111100X	[12B]11A, [12B]10A X0001100111100X	[12B]12A, [12B]11A X0001100111100X		
$(\geq 3S)$	$(\geq 3M)$	3S	[12B]13B X1100011001100X	[12B]14B, [12B]15B X1100011001111X					
			[12B]10B X11000011001100X	[12B]11B, [12B]12B X1100001100111X					
			[12B]1B X0000011001100X	[12B]2B, [12B]3B X0000011001111X					
xS	xM	$\geq 5S$							
END									
		M (i)	2M			3M	4M	$\geq 5M$	
		S (i-1)	2S	($\geq 3S$)	xS	xS	xS		
S(i+3)	M(i+2)	M(i-2) S(i+1)	2M	($\geq 3M$)	xM	xM	xM	xM	
2S	2M	2S				[12B]6A X0011100110011X	[12B]9A X00111100110011X	[12B]18A X11111100110011X	
						[12B]5A X001110011000X	[12B]7A, [12B]8A X0011110011000X	[12B]16A, [12B]17A X111110011000X	
$(\geq 3S)$	$(\geq 3M)$	3S							
xS	xM	$\geq 5S$	[12B]6B X0011001100011X	[12B]9B, [12B]18B X111001100011X					
			[12B]5B X00110011000011X	[12B]8B, [12B]17B X1110011000011X					
			[12B]4B X0011001100000X	[12B]7B, [12B]16B X111001100000X					

8/18



FIG. 10*FIG. 11*

9/18




FIG. 12



10/18

FIG. 13*FIG. 14*

11/18

FIG. 15*FIG. 16**FIG. 17*

12/18



FIG. 18*FIG. 19*

FIG.20








FIG.21


15/18

FIG.22**FIG.23****FIG.24**


16/18

FIG.25

(a) FREQUENCY



(b) FREQUENCY



17/18


FIG. 26




FIG.27

FIG. 1

