




- (51) International Patent Classification:
H04R 27/00 (2006.01) *H04S 7/00* (2006.01)
- (21) International Application Number:
PCT/IB2012/052071
- (22) International Filing Date:
26 April 2012 (26.04.2012)
- (25) Filing Language: English
- (26) Publication Language: English
- (30) Priority Data:
13/083,499 8 April 2011 (08.04.2011) US
- (71) Applicant (for all designated States except US): **SONOS, INC.** [US/US]; 223 East De La Guerra Street, Santa Barbara, California 93101 (US).
- (72) Inventors; and
- (75) Inventors/Applicants (for US only): **KALLAI, Christopher** [US/US]; 23 West Padre Street, Santa Barbara, California 93105 (US). **ERICSON, Michael, Darrell, Andrew** [US/US]; PO Box 21813, Santa Barbara, California 93121 (US). **LAMBOURNE, Robert, A.** [GB/US]; 3722 Cedar Vista, Santa Barbara, California 93110 (US). **REIMANN, Robert** [US/US]; 145 Kirkstall Road, Newton, Massachusetts 02460 (US). **TRIPLETT, Mark** [US/US]; 10 W. Hinsdale Ave., Hinsdale, Illinois 60521 (US).
- (74) Agents: **HANLEY, FLIGHT & ZIMMERMAN, LLC** et al.; 150 South Wacker, Suite 2100, Chicago, Illinois 60606 (US).
- (81) Designated States (unless otherwise indicated, for every kind of national protection available): AE, AG, AL, AM, AO, AT, AU, AZ, BA, BB, BG, BH, BR, BW, BY, BZ, CA, CH, CL, CN, CO, CR, CU, CZ, DE, DK, DM, DO, DZ, EC, EE, EG, ES, FI, GB, GD, GE, GH, GM, GT, HN, HR, HU, ID, IL, IN, IS, JP, KE, KG, KM, KN, KP, KR, KZ, LA, LC, LK, LR, LS, LT, LU, LY, MA, MD, ME, MG, MK, MN, MW, MX, MY, MZ, NA, NG, NI, NO, NZ, OM, PE, PG, PH, PL, PT, QA, RO, RS, RU, RW, SC, SD, SE, SG, SK, SL, SM, ST, SV, SY, TH, TJ, TM, TN, TR, TT, TZ, UA, UG, US, UZ, VC, VN, ZA, ZM, ZW.
- (84) Designated States (unless otherwise indicated, for every kind of regional protection available): ARIPO (BW, GH, GM, KE, LR, LS, MW, MZ, NA, RW, SD, SL, SZ, TZ, UG, ZM, ZW), Eurasian (AM, AZ, BY, KG, KZ, RU, TJ, TM), European (AL, AT, BE, BG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, HR, HU, IE, IS, IT, LT, LU, LV, MC, MK, MT, NL, NO, PL, PT, RO, RS, SE, SI, SK, SM, TR), OAPI (BF, BJ, CF, CG, CI, CM, GA, GN, GQ, GW, ML, MR, NE, SN, TD, TG).

Declarations under Rule 4.17:

- as to the identity of the inventor (Rule 4.17(i))
- as to applicant's entitlement to apply for and be granted a patent (Rule 4.17(ii))

[Continued on next page]

(54) Title: MULTI-CHANNEL PAIRING IN A MEDIA SYSTEM

**FIG. 1**

(57) **Abstract:** Technology for grouping, consolidating, and pairing individual playback devices with network capability (players) to stimulate a multi-channel listening environment is disclosed. Particularly, the embodiments described herein enable two or more playback devices to be paired, such that multi-channel audio is achieved. Such embodiments may be used to produce stereo and multi-channel audio environments for television and movies.

**Published:**

- with international search report (Art. 21(3))
- before the expiration of the time limit for amending the claims and to be republished in the event of receipt of amendments (Rule 48.2(h))
- the filing date of the international application is within two months from the date of expiration of the priority period (Rule 26bis.3)

Multi-Channel Pairing in a Media System

Christopher Kallai
Michael Darrell Andrew Ericson
Robert A. Lambourne
Robert Reimann
Mark Triplett

CROSS-REFERENCE TO RELATED APPLICATION

BACKGROUND

[0001] The presently described technology is directed towards technology for use in the area of consumer electronics. In particular, certain embodiments are directed to multi-channel pairing in a media system.

[0002] Music is very much a part of our everyday lives. And thanks to the advancement of technology, music content is now more accessible than ever. The same can be said of other types of media, such as television, movies, and other audio and video content. In fact, now a user can even access the content over the Internet through an online store, an Internet radio station, online music service, online movie service, and the like, in addition to the more traditional means of accessing audio and video content.

[0003] The demand for such audio and video content continues to surge. Given the high demand over the years, technology used to access and play such content has likewise improved. Even still, technology used in accessing the content and the playback of such content can be significantly improved or developed in ways that the market or end users may not anticipate.

SUMMARY

[0004] The embodiments described herein include, but are not limited to, various devices, systems, methods, and computer program products. This section is for the purpose of

summarizing some aspects of certain embodiments. Simplifications or omissions in this section as well as in the abstract or the title of this description may be made to avoid obscuring the purpose of this section, the abstract and the title. Such simplifications or omissions are not intended to limit the scope of the various inventions described herein.

[0005] In brief summary, the embodiments described herein provide technology for grouping, consolidating, and pairing individual playback devices to create or enhance a multi-channel listening environment. Particularly, the embodiments described herein enable two or more playback devices to be paired, such that multi-channel audio is achieved or enhanced. Such embodiments may be used to produce stereo sound or other audio environments suitable for audio content encoded with more than two channels, such as for certain kinds of television, movies, and music.

[0006] For example, an apparatus according to an embodiment comprises a network interface, a plurality of speaker drivers, an amplifier, and a processor. The network interface receives audio data over a network. The amplifier powers the plurality of speaker drivers. The processor processes the audio data to be output through the plurality of speaker drivers. The processor further configures a first equalization of the output from the plurality of speaker drivers in accordance with a first type of pairing and configuring a second equalization of the output from the plurality of speaker drivers in accordance with a second type of pairing.

[0007] In another example, a method according to an embodiment comprises receiving audio data over a network and processing the audio data to be output through a plurality of speaker drivers. The method further includes configuring a first equalization of the output from the plurality of speaker drivers in accordance with a first type of pairing and configuring a second equalization of the output from the plurality of speaker drivers in accordance with a second type of pairing.

[0008] One of the objects, features, and advantages of the present invention is to achieve or enhance a multi-channel listening environment. Many other objects, features, and advantages of the present invention will become apparent upon examining the following detailed description of an embodiment thereof, taken in conjunction with the attached drawings.

BRIEF DESCRIPTION OF THE DRAWINGS

[0010] These and other features, aspects, and advantages of the presently described technology will become better understood by a person skilled in the art with regard to the following description, appended claims, and accompanying drawings where:

[0011] FIG. 1 shows an illustrative configuration in which certain embodiments may be practiced;

[0012] FIG. 2A shows an illustrative functional block diagram of a player in accordance with certain embodiments;

[0013] FIG. 2B shows an example of a controller that may be used to remotely control one or more players of FIG. 2A;

[0014] FIG. 2C shows an example of a controller that may be used to remotely control one or more players of FIG. 2A;

[0015] FIG. 2D shows an example internal functional block diagram of a controller in accordance with certain embodiments;

[0016] FIG. 3A provides an illustration of a zone scene configuration;

[0017] FIG. 3B shows that a user defines multiple groups to be gathered at the same time;

[0018] FIG. 4 shows an example user interface that may be displayed on a controller or a computer of FIG. 1;

[0019] FIG. 5A shows an example user interface to allow a user to form a scene;

[0020] FIG. 5B shows another example user interface to allow a user to form a scene;

[0021] FIG. 5C shows an example user interface to allow a user to adjust a volume level of the zone players in a zone scene individually or collectively;

[0022] FIG. 6 shows a flowchart or process of providing a player theme or a zone scene for a plurality of players, where one or more of the players are placed in a zone;

[0023] FIG. 7 shows an illustrative configuration in which an audio source is played back on two players in accordance to an embodiment;

[0024] FIG. 8 shows an illustrative configuration of a pairing amongst multiple players in accordance to an embodiment;

[0025] FIG. 9 shows a flowchart or process of grouping a plurality of audio products to play separated sound tracks in synchronization to simulate a multi-channel listening environment; and

[0026] FIGS. 10A to 10F show example snapshots of a controller used in certain embodiments.

[0027] In addition, the drawings are for the purpose of illustrating certain embodiments, but it is understood that the inventions are not limited to the arrangements and instrumentality shown in the drawings.

DETAILED DESCRIPTION

I. Overview

[0028] The embodiments described herein relate to multi-channel pairing in a media system. The embodiments are particularly useful in pairing two or more playback devices together to create or enhance multi-channel audio reproduction, like stereo, surround sound, or some other multi-channel environment. The embodiments will also find utility in connection with any system for which multi-channel pairing is desired.

[0029] In an embodiment, two playback devices that are each configured to output a plurality of audio channels independent of each other are selectively paired, such that subsequent to pairing, one playback device is configured to output a first subset of the plurality of audio channels and the other playback device is configured to output a second subset of the plurality of audio channels. The first and second subsets are different. For instance, each playback device is configured to operate in a two-channel mode or stereo mode prior to being paired (e.g., each playback device is configured to play both right and left channel audio). Subsequent to pairing, one playback device is reconfigured to output a first channel (e.g., right channel audio and not left channel audio) and the other playback device is reconfigured to output a second channel (e.g., left channel audio and not right channel audio), which is different from the first channel.

[0030] In another embodiment, a collection of three or more playback devices that are each configured to output a plurality of audio channels independent of another playback device in the collection are selectively paired, such that subsequent to pairing, each of the playback devices is configured to output a different audio channel from the collection. This embodiment is particularly useful in a television or movie theater type setting where a particular playback device of the multiple playback devices is configured to output in two-channel or stereo mode at one time (e.g., when playing a song), and subsequent to pairing, is configured to output as a

front-right channel, a front-center channel, a front-left channel, a rear-right channel, a rear-left channel, a subwoofer channel, and so on (e.g., when watching television or a movie or listening to music that contains more than two-channels).

[0031] In another embodiment, one of the paired playback devices processes the data of an audio item to separate the data into channels, each of the channels representing a single-sound track, for example. The playback device sends the separated channel(s) to the other, respective playback device(s). The playback devices play their distinctive channels in synchrony, thus creating a multi-channel listening environment. Alternatively, each of the paired playback devices processes the data of an audio item, or a portion of the data, and plays only those one or more channels designated for the respective playback device.

[0032] In another embodiment, two or more playback devices may be grouped into a single or consolidated playback device and the consolidated playback device may be paired with one or more playback devices. For instance, two playback devices may be grouped into a first consolidated playback device and two additional playback devices may be grouped into a second consolidated playback device. The first and second consolidated playback devices may be paired, for example. In certain embodiments, each playback device of a consolidated playback device is put into consolidated mode, which may result in a changed equalization for one or more speaker drivers of any particular playback device. Further, one or more additional playback devices may be added to a consolidated playback device.

[0033] In certain embodiments, a playback device that is configured to output an audio channel is paired with one or more additional playback devices, such that the playback device is reconfigured to output a different audio channel. For instance, the playback device might be configured to output a right channel for stereo mode, but subsequent to being paired with one or more additional playback devices, might be reconfigured to output a rear, right channel for theater mode. The playback device may be paired to one or more other playback devices.

[0034] In certain embodiments, a playback device that is configured to output a plurality of audio channels is paired with one or more additional playback devices, such that the playback device is configured to output a subset of the plurality of audio channels relative to the one or more additional playback devices. For instance, the playback device might be configured to output in two-channel or stereo mode, but subsequent to being paired with one or more playback devices might be configured to output a right or left channel. The playback device may be paired to one or more other playback devices.

[0035] In certain embodiments, a playback device comprises a network interface, one or more speaker drivers, an amplifier, and a processor. The network interface receives audio data over a network. The amplifier powers the speaker drivers. The processor processes the audio data to be output through the speaker drivers. The processor further configures a first equalization of the output from the speaker drivers in accordance with a first type of pairing and configuring a second equalization of the output from the speaker drivers in accordance with a second type of pairing. The playback device may operate in any of: non paired mode, paired mode, consolidated mode, and grouped mode.

[0036] In certain embodiments, a controller is configured to, among other things, pair two or more playback devices to establish a multi-channel audio environment. That is, through the controller, a user can select which playback devices to pair. Once programmed, the playback devices may operate in paired mode until disengaged, for example. In some embodiments, the controller is wirelessly coupled to the one or more playback devices. In other embodiments, the controller is wired to the one or more playback devices.

[0037] According to certain embodiments, the action of pairing two or more playback devices is triggered based on a command from a user via a control interface (e.g., a manual command creates a pair) or responsive to an event (e.g., an automatic command creates a pair). Example events include a detection in the change of audio content (e.g., the audio content goes

from having two-channel content to three or more channel content, and vice-versa), a detection of a certain time, a detection of a certain kind of entertainment (e.g., detecting that the user is watching television versus just listening to music), or any other event that is programmed to create a pair amongst playback devices. The event detection might occur by a controller, one of the playback devices, or some other device, for example.

[0038] According to certain embodiments, in an attempt to optimize the multi-channel pairing, the configuration of a playback device may include any of: changing the equalization of the playback device by changing the equalization of one or more specific speaker drivers and optimizing the synchronization between paired devices. Examples of changing the equalization are described more below.

[0039] These embodiments and many additional embodiments are described more below. Further, the detailed description is presented largely in terms of illustrative environments, systems, procedures, steps, logic blocks, processing, and other symbolic representations that directly or indirectly resemble the operations of data processing devices coupled to networks. These process descriptions and representations are typically used by those skilled in the art to most effectively convey the substance of their work to others skilled in the art. Numerous specific details are set forth in order to provide a thorough understanding of the present invention. However, it is understood to those skilled in the art that certain embodiments of the present invention may be practiced without certain, specific details. In other instances, well known methods, procedures, components, and circuitry have not been described in detail to avoid unnecessarily obscuring aspects of the embodiments.

[0040] Reference herein to “embodiment” means that a particular feature, structure, or characteristic described in connection with the embodiment can be included in at least one embodiment of the invention. The appearances of this phrase in various places in the specification are not necessarily all referring to the same embodiment, nor are separate or

alternative embodiments mutually exclusive of other embodiments. The embodiments described herein, explicitly and implicitly understood by one skilled in the art, may be combined with other embodiments.

II. Example Environment

[0041] Referring now to the drawings, in which like numerals may refer to like parts throughout the several views. FIG. 1 shows an exemplary configuration **100** in which certain embodiments may be practiced. The configuration **100** may represent, but not be limited to, a part of a residential home, a business building, or a complex with multiple zones. There are a number of multimedia players of which three examples **102**, **104** and **106** are shown as audio devices. Each of the audio devices may be installed or provided in one particular area or zone and hence referred to as a zone player herein. It is understood that a zone can comprise more than one zone player.

[0042] As used herein, unless explicitly stated otherwise, an audio source or audio sources are generally in digital format and can be transported or streamed over a data network. To facilitate the understanding of the example environment of FIG. 1, it is assumed that the configuration **100** represents a home. Though, it is understood that this technology is not limited to its place of application. Referring back to FIG. 1, the zone players **102** and **104** may be located in one or two of the bedrooms while the zone player **106** may be installed or positioned in a living room. All of the zone players **102**, **104**, and **106** are coupled directly or indirectly to a data network **108**. In addition, a computing device **110** is shown to be coupled on the network **108**. In reality, any other device such as a home gateway device, a storage device, or an MP3 player may be coupled to the network **108** as well.

[0043] The network **108** may be a wired network, a wireless network or a combination of both. In one example, all devices including the zone players **102**, **104**, and **106** are coupled to the network **108** by wireless means based on an industry standard such as IEEE 802.11. In yet

another example, all devices including the zone players **102**, **104**, and **106** are part of a local area network that communicates with a wide area network (e.g., the Internet). In still another example, all devices including the zone players **102**, **104** and **106** and a controller **142** forms an ad-hoc network and may be specifically named, e.g., a household identifier: Smith Family, to be differentiated from a similar neighboring setup with a household identifier, e.g., Kallai Family.

[0044] Many devices on the network **108** are configured to download and store audio sources. For example, the computing device **110** can download audio sources, such as music or audio associated with videos, from the Internet (e.g., the “cloud”) or some other source and store the downloaded audio sources locally for sharing with other devices on the Internet or the network **108**. The computing device **110** or any of the zone players **102**, **104**, and **106** can also be configured to receive streaming audio. Shown as a stereo system, the device **112** is configured to receive an analog audio source (e.g., from broadcasting) or retrieve a digital audio source (e.g., from a compact disk). The analog audio sources can be converted to digital audio sources. In accordance with certain embodiments, the various audio sources may be shared among the devices on the network **108**.

[0045] Two or more zone players (e.g., any two or more of the zone players **102**, **104**, and **106**) may be grouped together to form a new zone group. Any combinations of zone players and an existing zone group may be grouped together. In one instance, a new zone group is formed by adding one zone player to another zone player or an existing zone group.

[0046] In certain embodiments, there are two or more zone players in one environment (e.g., a living room in a house). Instead of grouping these two zone players to play back the same audio source in synchrony, these two zone players may be configured to play two separate sounds in left and right channels. In other words, the stereo effects of a sound are reproduced or enhanced through these two zone players, one for the left sound and the other for the right sound. Likewise, for a 3-channel (or 2.1 sound effects) sound, three such zone players may be

reconfigured as if there are three speakers: left and right speakers and a subwoofer to form a stereo sound. The details of the reconfiguring the zone players and operating these audio products are described more below. Similar configurations with multiple channels (greater than 3, such as 4, 5, 6, 7, 9 channels and so on) also apply. For example, configurations that use more than two channels may be useful in television and theater type settings, where video content such as in the form of television and movies is played together with audio content that contains more than two channels. Further, certain music might similarly be encoded with more than two channel sound.

[0047] In certain embodiments, two or more zone players may be consolidated to form a single, consolidated zone player. The consolidated zone player may further be paired with a single zone player or yet another consolidated zone player. A consolidated zone player may comprise one or more individual playback devices. Each playback device of a consolidated playback device is preferably set in a consolidated mode.

[0048] According to some embodiments, one can continue to do any of: group, consolidate, and pair until a desired configuration is complete. The actions of grouping, consolidation, and pairing are preferably performed through a control interface and not by physically connecting and re-connecting speaker wire, for example, to individual, discrete speakers to create different configurations. As such, certain embodiments described herein provide a more flexible and dynamic platform through which sound reproduction can be offered to the end-user.

[0049] It is understood that the technology described herein is not limited to its place of application. For example, it is understood that zones and zone players, and the embodiments described herein, may also be used in vehicles, on water craft, airplanes, amphitheaters, outdoors, along the streets in a village or city, and so on, in addition to homes, offices, gyms, schools, hospitals, hotels, movie theaters, malls, stores, casinos, museum, entertainment parks, or any other place where audio content is played. As such, it will be appreciated that the

embodiments described herein may be used in connection with any system or application for which multi-channel pairing is desired.

III. Example Playback Devices

[0050] Referring now to FIG. 2A, there is shown an exemplary functional block diagram of a zone player **200** in accordance with an embodiment. The zone player **200** includes a network interface **202**, a processor **204**, a memory **206**, an audio processing circuit **210**, a module **212**, optionally, an audio amplifier **214** that may be internal or external, and optionally, a speaker unit **218** connected to the audio amplifier **214**. The network interface **202** facilitates a data flow between a data network (i.e., the data network **108** of FIG. 1) and the zone player **200** and typically executes a special set of rules (i.e., a protocol) to send data back and forth. One of the common protocols used in the Internet is TCP/IP (Transmission Control Protocol/Internet Protocol). In general, a network interface **202** manages the assembling of an audio source or file into smaller packets that are to be transmitted over the data network or reassembles received packets into the original source or file. In addition, the network interface **202** handles the address part of each packet so that it gets to the right destination or intercepts packets destined for the zone player **200**. Accordingly, in certain embodiments, each of the packets includes an IP-based source address as well as an IP-based destination address.

[0051] The network interface **202** may include one or both of a wireless interface **216** and a wired interface **217**. The wireless interface **216**, also referred to as an RF interface, provides network interface functions by a wireless means for the zone player **200** to communicate with other devices in accordance with a communication protocol (such as the wireless standard IEEE 802.11a, 802.11b, 802.11g, 802.11n, or 802.15.1). The wired interface **217** provides network interface functions by a wired means (e.g., an Ethernet cable). In one embodiment, a zone player includes both of the interfaces **216** and **217**, and other zone players include only a RF or wired interface. Thus these other zone players communicate with other devices on a network or retrieve

audio sources via the zone player. The processor **204** is configured to control the operation of other parts in the zone player **200**. The memory **206** may be loaded with one or more software modules that can be executed by the processor **204** to achieve desired tasks. According to one embodiment, a software module implementing an embodiment, such as described herein, is executed, the processor **204** operates in accordance with the software module in reference to a saved zone group configuration characterizing a zone group created by a user, the zone player **200** is caused to retrieve an audio source from another zone player or a device on the network and synchronize the players in the zone group to play back the audio source as desired.

According to another embodiment, a software module implementing an embodiment described herein creates a pair between two or more zone players to create a desired multi-channel audio environment.

[0052] According to one embodiment, the memory **206** is used to save one or more saved zone configuration files that may be retrieved for modification at any time. Typically, a saved zone group configuration file is transmitted to a controller (e.g., the controlling device **140** or **142** of FIG. 1, a computer, a portable device, or a TV) when a user operates the controlling device. The zone group configuration provides an interactive user interface so that various manipulations or control of the zone players may be performed.

[0053] In certain embodiments, the audio processing circuit **210** resembles the circuitry in an audio playback device and includes one or more digital-to-analog converters (DAC), an audio preprocessing part, an audio enhancement part or a digital signal processor and others. In operation, when an audio source is retrieved via the network interface **202**, the audio source is processed in the audio processing circuit **210** to produce analog audio signals. The processed analog audio signals are then provided to the audio amplifier **214** for playback on speakers. In addition, the audio processing circuit **210** may include necessary circuitry to process analog signals as inputs to produce digital signals for sharing with other devices on a network.

[0054] Depending on an exact implementation, the module **212** may be implemented as a combination of hardware and software. In one embodiment, the module **212** is used to save a scene. The audio amplifier **214** is typically an analog circuit that powers the provided analog audio signals to drive one or more speakers.

[0055] It is understood that zone player **200** is an example of a playback device. Examples of playback devices include those zone players that are commercially offered for sale by Sonos, Inc. of Santa Barbara, California. They currently include a ZonePlayer 90, ZonePlayer 120, and Sonos S5. The ZonePlayer 90 is an example zone player without a built-in amplifier, whereas the ZonePlayer 120 is an example zone player with a built-in amplifier. The S5 is an example zone player with a built-in amplifier and speakers. In particular, the S5 is a five-driver speaker system that includes two tweeters, two mid-range drivers, and one subwoofer. When playing audio content via the S5, the left audio data of a track is sent out of the left tweeter and left mid-range driver, the right audio data of a track is sent out of the right tweeter and the right mid-range driver, and mono bass is sent out of the subwoofer. Further, both mid-range drivers and both tweeters have the same equalization (or substantially the same equalization). That is, they are both sent the same frequencies, just from different channels of audio. While the S5 is an example of a zone player with speakers, it is understood that a zone player with speakers is not limited to one with a certain number of speakers (e.g., five speakers as in the S5), but rather can contain one or more speakers. Further, a zone player may be part of another device, which might even serve a primary purpose different than audio.

IV. Example Controller

[0056] Referring now to FIG. 2B, there is shown an exemplary controller **240**, which may correspond to the controlling device **140** or **142** of FIG. 1. The controller **240** may be used to facilitate the control of multi-media applications, automation and others in a complex. In particular, the controller **240** is configured to facilitate a selection of a plurality of audio sources

available on the network, controlling operations of one or more zone players (e.g., the zone player **200**) through a RF interface corresponding to the wireless interface **216** of FIG. 2A. According to one embodiment, the wireless means is based on an industry standard (e.g., infrared, radio, wireless standard IEEE 802.11a, 802.11b 802.11g, 802.11n, or 802.15.1). When a particular audio source is being played in the zone player **200**, a picture, if there is any, associated with the audio source may be transmitted from the zone player **200** to the controller **240** for display. In one embodiment, the controller **240** is used to synchronize audio playback of more than one zone player by grouping the zone players in a group. In another embodiment, the controller **240** is used to control the volume of each of the zone players in a zone group individually or together.

[0057] In an embodiment, the controller **240** is used to create a pairing between two or more playback devices to create or enhance a multi-channel listening environment. For example, the controller **240** may be used to select and pair two or more playback devices. In addition, the controller **240** may be used to turn pairing on or off. The controller **240** may also be used to consolidate playback devices, and further to set a particular playback device in consolidated mode. Accordingly, in some embodiments, the controller **240** provides a flexible mechanism for dynamically configuring a multi-channel audio environment. In some instances, the pairing creates a multi-channel listening environment. In some instances, the pairing enhances a multi-channel listening environment by increasing the separation between devices. For example, two individual playback devices, which are positioned at a distance from each other, may provide more channel separation to the listener than the audio coming from only a single device.

[0058] The user interface for the controller **240** includes a screen **242** (e.g., a LCD screen) and a set of functional buttons as follows: a “zones” button **244**, a “back” button **246**, a “music” button **248**, a scroll wheel **250**, “ok” button **252**, a set of transport control buttons **254**, a mute button **262**, a volume up/down button **264**, a set of soft buttons **266** corresponding to the labels **268** displayed on the screen **242**.

[0059] The screen **242** displays various screen menus in response to a user's selection. In one embodiment, the "zones" button **244** activates a zone management screen or "Zone Menu", which is described in more details below. The "back" button **246** may lead to different actions depending on the current screen. In one embodiment, the "back" button triggers the current screen display to go back to a previous one. In another embodiment, the "back" button negates the user's erroneous selection. The "music" button **248** activates a music menu, which allows the selection of an audio source (e.g., a song) to be added to a zone player's music queue for playback.

[0060] The scroll wheel **250** is used for selecting an item within a list, whenever a list is presented on the screen **242**. When the items in the list are too many to be accommodated in one screen display, a scroll indicator such as a scroll bar or a scroll arrow is displayed beside the list. When the scroll indicator is displayed, a user may rotate the scroll wheel **250** to either choose a displayed item or display a hidden item in the list. The "OK" button **252** is used to confirm the user selection on the screen **242**.

[0061] There are three transport buttons **254**, which are used to control the effect of the currently playing song. For example, the functions of the transport buttons may include play/pause and forward/rewind a song, move forward to a next song track, or move backward to a previous track. According to one embodiment, pressing one of the volume control buttons such as the mute button **262** or the volume up/down button **264** activates a volume panel. In addition, there are three soft buttons **266** that can be activated in accordance with the labels **268** on the screen **242**. It is understood that, in a multi-zone system, there may be multiple audio sources being played respectively in more than one zone players. The music transport functions described herein shall apply selectively to one of the sources when a corresponding one of the zone players or zone groups is selected.

[0062] FIG. 2C shows an exemplary controller **260** which may correspond to the controlling device **140** or **142** of FIG. 1. The controller **260** is provided with a touch screen that allows a user to interact with the controller, for example, to navigate a playlist of many items, to control operations of one or more players. In one embodiment as it will be further shown in FIGS. 10A to 10F, a user may interact with the controller to make a multi-channel audio environment, such as create a stereo pair for example, and may even be used to separate the multi-channel audio environment, such as disengage a stereo pair. It should be noted that other network-enabled portable devices such as an iPhone, iPad or any other smart phone or network-enabled device may be used as a controller to interact or control multiple zone players in an environment (e.g., a networked computer such as a PC or Mac may also be used as a controller). According to one embodiment, an application may be downloaded into a network enabled device. Such an application may implement most of the functions discussed above for the controller **240** using a navigating mechanism or touch screen in the device. Those skilled in the art will appreciate the flexibility of such an application and its ability to be ported to a new type of portable device given the detailed description herein.

[0063] FIG. 2D illustrates an internal functional block diagram of an exemplary controller **270**, which may correspond to the controller **240** of FIG. 2B, a computing device, smart phone, or any other communicative device. The screen **272** on the controller **270** may be an LCD screen. The screen **272** communicates with and is commanded by a screen driver **274** that is controlled by a microcontroller (e.g., a processor) **276**. The memory **282** may be loaded with one or more application modules **284** that can be executed by the microcontroller **276** with or without a user input via the user interface **278** to achieve desired tasks. In one embodiment, an application module is configured to facilitate grouping a number of selected zone players into a zone group and synchronizing the zone players for one audio source. In another embodiment, an application module is configured to control together the audio sounds (e.g., volume) of the zone players in a zone group. In operation, when the microcontroller **276** executes one or more of the application

modules **284**, the screen driver **274** generates control signals to drive the screen **272** to display an application specific user interface accordingly, more of which will be described below.

[0064] The controller **270** includes a network interface **280** referred to as a RF interface **280** that facilitates wireless communication with a zone player via a corresponding RF interface thereof. In one embodiment, the commands such as volume control and audio playback synchronization are sent via the RF interfaces. In another embodiment, a saved zone group configuration is transmitted between a zone player and a controller via the RF interfaces. The controller **270** may control one or more zone players, such as **102**, **104** and **106** of FIG. 1. Nevertheless, there may be more than one controller, each preferably in a zone (e.g., a room or rooms nearby each other) and configured to control any one and all of the zone players.

[0065] In one embodiment, a user creates a zone group including at least two zone players from the controller **240** that sends signals or data to one of the zone players. As all the zone players are coupled on a network, the received signals in one zone player can cause other zone players in the group to be synchronized so that all the zone players in the group play back an identical audio source or a list of identical audio sources in a timely synchronized manner such that no (or substantially no) audible delays or hiccups could be heard. Similarly, when a user increases the audio volume of the group from the controller, the signals or data of increasing the audio volume for the group are sent to one of the zone players and causes other zone players in the group to be increased together in volume and in scale.

[0066] According to one implementation, an application module is loaded in memory **282** for zone group management. When a predetermined key (e.g. the “zones” button **244**) is activated on the controller **240**, the application module is executed in the microcontroller **276**. The input interface **278** coupled to and controlled by the microcontroller **276** receives inputs from a user. A “Zone Menu” is then displayed on the screen **272**. The user may start grouping zone players into a zone group by activating a “Link Zones” or “Add Zone” soft button, or de-grouping a zone

group by activating an “Unlink Zones” or “Drop Zone” button. The detail of the zone group manipulation will be further discussed below.

[0067] As described above, the input interface **278** includes a number of function buttons as well as a screen graphical user interface. It should be pointed out that the controller **240** in FIG. 2B is not the only controlling device that may practice the embodiments. Other devices that provide the equivalent control functions (e.g., a computing device, a hand-held device) may also be configured to practice the present invention. In the above description, unless otherwise specifically described, it is clear that keys or buttons are generally referred to as either the physical buttons or soft buttons, enabling a user to enter a command or data.

[0068] One mechanism for ‘joining’ zone players together for music playback is to link a number of zone players together to form a group. To link a number of zone players together, a user may manually link each zone player or room one after the other. For example, there is a multi-zone system that includes the following zones:

- Bathroom
- Bedroom
- Den
- Dining Room
- Family Room
- Foyer

[0069] If a user wishes to link five of the six zone players using the current mechanism, the user may start with a single zone and then manually link each zone to that zone. This mechanism may be sometimes quite time consuming. According to one embodiment, a set of zones can be dynamically linked together using one command. Using what is referred to herein as a theme or a zone scene, zones can be configured in a particular scene (e.g., morning, afternoon, or garden),

where a predefined zone grouping and setting of attributes for the grouping are automatically effectuated.

[0070] For instance, a “Morning” zone scene/configuration command would link the Bedroom, Den and Dining Room together in one action. Without this single command, the user would need to manually and individually link each zone. FIG. 3A provides an illustration of one zone scene, where the left column shows the starting zone grouping – all zones are separate, the column on the right shows the effects of grouping the zones to make a group of 3 zones named after “Morning”.

[0071] Expanding this idea further, a Zone Scene can be set to create multiple sets of linked zones. For example, a scene creates 3 separate groups of zones, the downstairs zones would be linked together, the upstairs zones would be linked together in their own group, and the outside zones (in this case the patio) would move into a group of its own.

[0072] In one embodiment as shown in FIG. 3B, a user defines multiple groups to be gathered at the same time. For example: an “Evening Scene” is desired to link the following zones:

- Group1
 - Bedroom
 - Den
 - Dining Room
- Group 2
 - Garage
 - Garden

where Bathroom, Family Room and Foyer should be separated from any group if they were part of a group before the Zone Scene was invoked.

[0073] A feature of certain embodiments is that that zones do not need to be separated before a zone scene is invoked. In one embodiment, a command is provided and links all zones in one step, if invoked. The command is in a form of a zone scene. After linking the appropriate zones, a zone scene command could apply the following attributes:

Set volumes levels in each zones (each zone can have a different volume)

Mute/Unmute zones.

Select and play specific music in the zones.

Set the play mode of the music (Shuffle, Repeat, Shuffle-repeat)

Set the music playback equalization of each zone (e.g., bass treble).

[0074] A further extension of this embodiment is to trigger a zone scene command as an alarm clock function. For instance the zone scene is set to apply at 8:00am. It could link appropriate zones automatically, set specific music to play and then stop the music after a defined duration. Although a single zone may be assigned to an alarm, a scene set as an alarm clock provides a synchronized alarm, allowing any zones linked in the scene to play a predefined audio (e.g., a favorable song, a predefined playlist) at a specific time or for a specific duration. If, for any reason, the scheduled music failed to be played (e.g., an empty playlist, no connection to a share, failed UPnP, no Internet connection for an Internet Radio station), a backup buzzer will sound. This buzzer will be a sound file that is stored in a zone player.

[0075] FIG. 4 shows an exemplary user interface **400** that may be displayed on a controller **142** or a computer **110** of FIG. 1. The interface **400** shows a list of items that may be set up by a user to cause a scene to function at a specific time. In the embodiment shown in FIG. 4, the list of items includes “Alarm”, “Time”, “Zone”, “Music”, “Frequency” and “Alarm length”. “Alarm” can be set on or off. When “Alarm” is set on, “Time” is a specific time to set off the alarm. “Zone” shows which zone players are being set to play a specified audio at the specific time. “Music” shows what to be played when the specific time arrives. “Frequency” allows the user to define a frequency of the alarm. “Alarm length” defines how long the audio is to be

played. It should be noted that the user interface **400** is provided herein to show some of the functions associated with setting up an alarm. Depending on an exact implementation, other functions, such as time zone, daylight savings, time synchronization, and time/date format for display may also be provided.

[0076] According to one embodiment, each zone player in a scene may be set up for different alarms. For example, a “Morning” scene includes three zone players, each in a bedroom, a den, and a dining room. After selecting the scene, the user may set up an alarm for the scene as whole. As a result, each of the zone players will be activated at a specific time.

[0077] FIG. 5A shows a user interface **500** to allow a user to form a scene. The panel on the left shows the available zones in a household. The panel on the right shows the zones that have been selected and be grouped as part of this scene. Depending on an exact implementation of a user interface, Add/Remove buttons may be provided to move zones between the panels, or zones may be dragged along between panels.

[0078] FIG. 5B shows another user interface **520** to allow a user to form a scene. The user interface **520** that may be displayed on a controller or a computing device, lists available zones in a system. A checkbox is provided next to each of the zones so that a user may check in the zones to be associated with the scene.

[0079] FIG. 5C shows a user interface **510** to allow a user to adjust a volume level of the zone players in a zone scene individually or collectively. As shown in the user interface **510**, the ‘Volumes...’ button (shown as sliders, other forms are possible) allows the user to affect the volumes of the associated zone players when a zone scene is invoked. In one embodiment, the zone players can be set to retain whatever volume that they currently have when the scene is invoked. Additionally the user can decide if the volumes should be unmuted or muted when the scene is invoked.

V. Providing Example Player Themes or Zone Scenes

[0080] FIG. 6 shows a flowchart or process **600** of providing a player theme or a zone scene for a plurality of players, where one or more of the players are placed in a zone. The process **600** is presented in accordance with one embodiment of the present invention and may be implemented in a module to be located in the memory **282** of FIG. 2C.

[0081] The process **600** is initiated when a user decides to proceed with a zone scene at **602**. The process **600** then moves to **604** where it allows a user to decide which zone players to be associated with the scene. For example, there are ten players in a household, and the scene is named after “Morning”. The user may be given an interface to select four of the ten players to be associated with the scene. At **606**, the scene is saved. The scene may be saved in any one of the members in the scene. In the example of FIG. 1, the scene is saved in one of the zone players and displayed on the controller **142**. In operation, a set of data pertaining to the scene includes a plurality of parameters. In one embodiment, the parameters include, but may not be limited to, identifiers (e.g., IP address) of the associated players and a playlist. The parameters may also include volume/tone settings for the associated players in the scene. The user may go back to **602** to configure another scene if desired.

[0082] Given a saved scene, a user may activate the scene at any time or set up a timer to activate the scene at **610**. The process **600** can continue when a saved scene is activated at **610**. At **612**, upon the activation of a saved scene, the process **600** checks the status of the players associated with the scene. The status of the players means that each of the players shall be in condition to react in a synchronized manner. In one embodiment, the interconnections of the players are checked to make sure that the players communicate among themselves and/or with a controller if there is such a controller in the scene.

[0083] It is assumed that all players associated with the scene are in good condition. At **614**, commands are executed with the parameters (e.g., pertaining to a playlist and volumes). In one

embodiment, data including the parameters is transported from a member (e.g., a controller) to other members in the scene so that the players are caused to synchronize an operation configured in the scene. The operation may cause all players to play back a song in identical or different volumes or to play back a pre-stored file.

VI. Example Multi-channel Environments

[0084] FIG. 7 shows an example configuration in which an audio source is played back on two players **702** and **704**, according to an example embodiment. These two players **702** and **704** may be located in and around one place (e.g., a hall, room, or nearby rooms) and are designated to play two sound tracks respectively. For example, an audio source may have left and right sound channels or tracks (e.g., stereo sound). Instead of grouping the players **702** and **704** to play back the audio source together in synchrony, where each player **702** and **704** plays the same audio content at substantially the same time, the players **702** and **704** can be paired to play different channels of the audio source in synchrony. As a result of pairing, the stereo sound effects can be simulated or enhanced via two players **702** and **704** versus one player or none of the players, for example.

[0085] In certain embodiments, each player of players **702** and **704** includes a network interface, one or more speaker drivers (two or more speaker drivers in some instances, such as when the player can play in stereo mode absent pairing), an amplifier, and a processor, such as shown in FIG. 2A. The network interface receives audio data over a network. One or more amplifiers power the speaker drivers. The processor processes the audio data to be output through the speaker drivers. The processor may further configure a first equalization of the output from the speaker drivers in accordance with a first type of pairing and configuring a second equalization of the output from the speaker drivers in accordance with a second type of pairing.

[0086] In an embodiment, the two players **702** and **704** are configured to output a plurality of audio channels independent of each other. For example, each player **702** and **704** may be configured to output audio content in stereo independently from each other. Subsequent to pairing, one playback device (e.g., player **702**) is configured to output a first subset of the plurality of audio channels and the other playback device (e.g., player **704**) is configured to output a second subset of the plurality of audio channels. The first and second subsets are different. In this example, subsequent to pairing players **702** and **704**, player **702** might play the right channel and player **704** might play the left channel. In another example, player **702** might play the right channel plus a center channel (e.g., in television or theater mode) and player **704** might play the left channel plus the center channel. Even in the latter example, the first and second subsets are different in that player **702** is playing channels Right + Center and player **704** is playing channels Left + Center. In yet another embodiment, subsequent to pairing, player **702** might play all channels except certain bass frequencies, which may be played via player **704**, thereby using player **704** as a subwoofer.

[0087] In another embodiment, a collection of three or more playback devices (e.g., players **702**, **704**, and one or more additional players) are each configured to output a plurality of audio channels independent of another playback device in the collection. Subsequent to pairing, each of the playback devices is configured to output a generally different audio channel(s) from the collection. This embodiment is particularly useful in a television or movie theater setting where a particular playback device of the multiple playback devices is configured to output in two-channel or stereo mode at one time (e.g., when playing a song), and subsequent to pairing, is configured to output as a front-right channel, a front-center channel, a front-left channel, a rear-right channel, a rear-left channel, and so on (e.g., when watching a movie or television).

[0088] In another embodiment, one of the paired playback devices (e.g., player **702** or player **704**) processes the data of the audio item, essentially separating the data into channels, each of the channels representing a single-sound track, for example, and being played back in one of the

playback devices, thus creating or enhancing a multi-channel listening environment. In an alternative embodiment, both playback devices (e.g., players **702** and **704**) may receive and process the data of the audio item and each playback device may output only the audio content designated for the respective player. For example, player **702** might receive both left and right channel audio, but only play the left channel, whereas player **704** might also receive both left and right channel audio, but only play the right channel.

[0089] In another embodiment, two or more playback devices (e.g., players **702** or **704**) may be grouped into a single or consolidated playback device and the consolidated playback device (e.g., consolidated player **702 + 704**) may be paired with one or more playback devices. For instance, two playback devices maybe grouped into a first consolidated playback device and two additional playback devices maybe grouped into a second consolidated playback device. Then, the first and second consolidated playback devices may be paired to create or enhance a multi-channel listening environment.

[0090] In certain embodiments, a playback device (e.g., either player **702** or **704**) that is configured to output an audio channel is paired with one or more additional playback devices, such that the playback device is configured to output a different audio channel than previously configured. For instance, the playback device might be configured to output a right channel in stereo mode, but subsequent to being paired with one or more additional playback devices, might be configured to output a rear, right channel in theater mode. The playback device may be paired to one or more other playback devices.

[0091] In certain embodiments, a playback device (e.g., either player **702** or **704**) that is configured to output a plurality of audio channels is paired with one or more additional playback devices, such that the playback device is configured to output a subset of the plurality of audio channels relative to the one or more additional playback devices. For instance, the playback device might be configured to output in two-channel or stereo mode, but subsequent to being

paired with one or more playback devices might be configured to output a right or left channel. The playback device may be paired to one or more other playback devices.

[0092] According to certain embodiments, the action of pairing two or more playback devices is triggered based on a command from a user via a control interface (e.g., a manual command) or responsive to an event (e.g., an automatic command). For example, using a controller, a user can create a pairing between two or more playback devices or disengage the pairing between two or more playback devices. In another example, pairing may be triggered by the audio content itself, a signal received from a source device, or some other predefined event, such that pairing occurs when the event is detected by the controller or playback device, for example. In addition, another device might be programmed to detect the event and provide a pairing signal to the controller and/or playback devices.

[0093] Further, it is understood that going from a configuration of no pairing (unpaired or non paired) to a configuration of pairing or from one kind of pairing (e.g., a pairing used in a type of stereo mode or theater mode) to a different kind of pairing (e.g., another pairing used in a type of stereo mode or theater mode) are all various types of “pairing” that can occur according to certain embodiments. In addition, disengaging a pairing between multiple playback devices might go from pairing to no pairing or from pairing of a first kind back to pairing of a previous kind, for example.

[0094] In one example, a first type of pairing might include “no pairing” with another playback device and a second type of pairing might include pairing with one or more additional playback devices. In a second example, a first type of pairing might include pairing with a second playback device and a second type of pairing might include pairing with a plurality of playback devices. In a third example, a first type of pairing might include reproducing two channel sound via the speaker drivers and a second type of pairing comprises reproducing no more than one channel of the two channel sound via the speaker drivers. In a fourth example, a

first type of pairing might comprise reproducing a first audio channel via the speaker drivers and the second type of pairing might include reproducing a second audio channel via the speaker drivers. In a fifth example, a first type of pairing might include reproducing the audio content via the speaker drivers in stereo mode and a second type of pairing might include reproducing the audio content via the speaker drivers in theater mode. In a sixth example, a first type of pairing might include reproducing the audio content via the speaker drivers and a second type of pairing comprises reproducing the audio content via the speaker drivers when in consolidated mode. It is understood that various variations and modifications may be made to the examples described just above with the attainment of some or all of the advantages of the technology described herein.

[0095] According to certain embodiments, the configuration of a playback device may include any of: changing the equalization of the playback device by changing the equalization of one or more specific speaker drivers and optimizing the synchronization between paired devices. Changing the equalization of the playback device might include any of: turning on or off (or effectively muting) one or more specific speaker drivers, changing the channel output of one or more speaker drivers, changing the frequency response of one or more specific speaker drivers, changing the amplifier gain of any particular speaker driver, changing the amplifier gain of the playback device as a whole.

[0096] In certain embodiments, changing the equalization of a playback device (e.g., changing the equalization of one or more speaker drivers of the playback device) may affect frequency dependent parameters. Examples might include the adjustment of the strength of frequencies within the audio data, a phase adjustment, and time-delay adjustment. In addition, a particular equalization may use a first type of pass filter, such as one that attenuates high, middle, or low frequencies, for example, while allowing other frequencies to pass unfiltered (or substantially unfiltered). Filters might also be different kinds or of a different order (e.g., first order filter, second order filter, third order filter, fourth order filter, and so on). For example, a first equalization of a playback device might include using a first type of pass filter to modify the

output based on a first type of pairing and a second equalization of the playback device might include using a second type of pass filter to modify the output based on the second type of pairing. In this example, the first and second type of pass filters have one or different properties and/or behaviors, thus changing the equalization and sonic behavior of the device.

[0097] By way of illustration, when two S5 devices are paired to create a stereo pair, for example, one S5 device may be configured as the “left” and the other S5 device may be configured as the “right.” In one embodiment, the user may determine which is left or right. In this configuration, for example, the left and right audio data may be sent to both S5 devices, but the left audio data of the track is played out of the S5 device configured as left and the right audio data of a track is played out of the S5 device configured as right. In addition, the equalization of each S5 device is changed in an attempt to reduce or eliminate certain constructive or destructive interference. For example, one tweeter on each S5 device may be turned off or substantially muted. In certain embodiments, the crossover frequency to each driver may even be changed from a previous configuration so that two or more drivers are not necessarily outputting the exact same audio data, otherwise constructive and/or destructive interference may occur. In certain embodiments, the amplifier gain is adjusted for a particular speaker driver and/or for the playback device as a whole.

[0098] In operation, according to certain embodiments, a controller **706** (e.g., a controller **142** of FIG. 1 or **240** of FIG. 2B or a portable device) is used to initiate the operation. Through a user interface, the controller **706** causes a player **702** to retrieve the audio source, provided the audio source is on a network **708** (e.g., the Internet or a local area network). Similarly, the controller **706** may also cause a designated device (e.g., another networked device) to establish a communication session with the player **702** to deliver the requested audio source. In any case, either one or both of the players **702** and **704** may have access to the data representing the audio source.

[0099] In certain embodiments, a module in the player **702** is activated to process the data. According to one embodiment, the right and left sound tracks are separated. One sound track is retained locally in one player and the other sound track is pushed or uploaded to the other device (e.g., via an ad-hoc network). When the right and left sound tracks are played back simultaneously or substantially simultaneously, the stereo sound effect can be appreciated.

[00100] In another embodiment, several tracks are separated, such as in television or theater mode. For example, the tracks may be separated into a center channel, right front channel, left front channel, right rear channel, left rear channel, and so on. Accordingly, one or more sound tracks may be retained locally in one player and the other sound tracks are pushed or uploaded to the other devices.

[00101] In yet another embodiment, one player might process the data and retain one or more tracks locally, while the remaining data is sent onto another player. The receiving player may then process the data and retain one or more tracks locally and send any remaining data onto another player. This process, or one like it, may continue until all of the tracks are retained locally by corresponding player devices.

[00102] In yet another embodiment, each player might receive and process the data and play only the channel or channels that are designated for that player.

[00103] In certain embodiments, it is important to maintain good synchronization, especially when pairing two or more independently clocked playback devices so that the multi-channel audio content is played back as it was originally intended. According to an embodiment, a message may be initiated from one device to another that is also activated to send back an acknowledgement. Upon receiving the acknowledgement, the time delay in transporting data from one device to another can be measured. The time delay will be considered when synchronizing the two players to play back the two separated sound tracks. In certain embodiments, if sending a packet (e.g., a packet in accordance with SNTP protocol) to a

playback device and receiving a response takes more than fifteen milliseconds, for example, the timing information contained within that packet, such as clock information, is discarded. If sending and receiving a packet is less than fifteen milliseconds, then the information from the packet is used to adjust playback, if so necessary.

[00104] Additional details of synchronizing operations of two or more independently clocked players are provided in commonly assigned US application No.: 10/816,217, filed Apr. 1, 2004, entitled "System and Method For Synchronizing Operations Among A Plurality Of Independently Clocked Digital Data Processing Devices" which is hereby incorporated by reference.

[00105] FIG. 8 shows an example configuration of a pairing amongst multiple players **802**, **804**, **806**, **808**, **810**, and **812** in a theater-like environment, in accordance to an embodiment. Player **802** may operate as a front-left channel, player **804** may operate as a center channel, player **806** may operate as a front-right channel, player **808** may operate as a subwoofer, player **810** may operate as a rear, right channel, and player **812** may operate as a rear, right channel. In this example, the players **802**, **804**, **806**, **808**, **810**, and **812** are wirelessly coupled over network **815** so as to receive and transmit data over a wireless network, and obtain power from power outlets in the wall or through some other power source (e.g., a battery). Players **802**, **804**, **806**, **808**, **810**, and **812** may be wired, if so configured in an alternate embodiment. Controller **814** may be a network-enabled device, examples of which include a smart phone, tablet computer, laptop computer, desktop computer, or a television.

[00106] In one embodiment, a designated player, such as player **804**, receives multi-channel audio content from a source **816**. Source **816** might include audio and/or video content downloaded or streamed from the Internet, a DVD or Blu-Ray player, or from some other source of audio and/or video content. Player **804** separates the multi-channel audio and sends respective audio channels to its playback owner. For example, if a particular audio channel is designated for

the front, right speaker, then that content is wirelessly directed from player **804** to player **802**, and so on. Players **802**, **804**, **806**, **808**, **810**, and **812** play the audio content synchronously, so as to create a multi-channel listening environment. Moreover, if source **816** provides video content along with audio content, then the audio content is preferably played in synchrony with the video content.

[00107] In another embodiment, each player of players **802**, **804**, **806**, **808**, **810**, and **812** may separate out its own one or more channels for playback. That is, either all audio content, or a portion thereof, is sent to each player (e.g., from source **816** or another playback device) and the player itself obtains its own data for playback.

[00108] In addition, players **802**, **804**, **806**, **808**, **810**, and **812** may be reconfigured to operate in many different configurations, such as described above. For example, players **802** and **806** may be paired to operate in stereo mode, while the other players remain in sleep mode or turned off (player **808** may remain on in any particular configuration, if so desired and configured, because it is operating as a subwoofer). In another example, players **802** and **810** may be consolidated and output left channel audio, while players **806** and **812** may be consolidated and output right channel audio. In yet another example, some of players **802**, **804**, **806**, **808**, **810**, and **812** are consolidated into a single player and paired with additional playback devices, such as in an adjacent room. In a further example, players **802**, **804**, **806**, **808**, **810**, and **812** are grouped and not paired, when the audio content is music (versus movie content, for example). These are just some configuration examples. Many other configurations are possible using the teachings described herein.

[00109] FIG. 9 shows a flowchart or process **900** of grouping a plurality of audio products to play separated sound tracks in synchronization to simulate a multi-channel listening environment. The process **900** is presented in accordance with certain embodiments and may be implemented in a module to be located in the memory **282** of FIG. 2D. To facilitate the

description of process **900**, a listening environment of stereo sound with left and right channels is described. Those skilled in the art can appreciate that the description can be equally applied to other forms of multi-channel listening environment (e.g., three, five, seven channel environments).

[00110] Typically, there is a plurality of players being controlled by one or more controllers, where these players are disposed in various locations. For example, there are five players in a house; three of them are respectively disposed in three rooms while two players are disposed in a larger room. Accordingly, these two players would be candidates to be paired to simulate a stereo listening environment, instead of just playing synchronized audio from both in a grouped fashion. In another example, there are four players in a large space or adjacent spaces, two pairs of the players may be paired to simulate a stereo listening environment, in which two players in one consolidated pair can be grouped to play back one (left) sound track and the other two in the other consolidated pair can be grouped to play back one (right) sound track.

[00111] In any case, two groups of players or two players are decided to be paired at **902**. If no players are paired, the process **900** will not be activated. It is assumed that two players from a group of players being controlled by a controller are selected to be paired at **902**. The process **900** proceeds.

[00112] At **904**, a user may decide which player is to play back which sound track. Depending on the location of the user or listener(s) with respect to the selected players, it is assumed that a player or unit A is chosen to play back a left sound track and another player or unit B is chosen to play back a right sound track. In an alternative embodiment, the players themselves (or the controller) may automatically determine which unit is configured to play the right channel and which unit is configured to play the left channel without input from the user.

[00113] According to one embodiment, a time delay in transporting data between the two units A and B is measured at **906**. This time delay may facilitate sound synchronization between

the two units as one of the units will receive a processed sound track from the other. The user may continue to operate on a controller to select a title (e.g., an audio source or an item from a playlist) for playback on the two units at **910**.

[00114] Once the title is determined at **912**, the data for the title is accessed. Depending on where the data is located, the controller may be configured to cause one of the two units to obtain or stream in the data. In one embodiment, the controller or unit A initiates a request to a remotely-networked device providing or storing the data. Assuming an authentication procedure, if any, completes successfully, the remote device starts to upload the data to the unit A. Likewise, if the data is locally stored in the unit A, the data can be accessed locally without requesting the same from the network. As the data is being received or accessed in the unit A, a processing module is activated in the unit A to process the data, essentially separating the data into two streams of sound tracks at **914**. In an alternative embodiment, each unit may receive and process the data, essentially separating the data into a stream to be played by the respective unit.

[00115] At **916**, one of the streams is uploaded from the unit A to unit B via a local network (e.g., the ad-hoc network formed by all the players being controlled by the controller). As the streams are being distributed, the two units are configured to play back the streams respectively, each reproducing the sound of a single sound track at **918**. Together, in synchrony, the two units create a stereo sound listening environment.

[00116] It should be noted that the delay time, if noticeable, may be incorporated into the unit A to delay the consumption of the stream by the delay time to synchronize with the unit B. Alternatively, a non-selected player may be used to process a streaming data of the title and configured to supply two streams to the pair of players, thus equalizing the delay time that would be otherwise experienced by the unit B.

[00117] FIGS. 10A-10F show illustrative screenshots of a controller for creating a stereo pair in accordance with certain embodiments. The screenshots are from a computing device (e.g., a

tablet computer, laptop, or desktop) used as a controller. Those skilled in the art can appreciate that FIGS. 10A-10F may be readily modified to be used in a portable device with network capability, such as, for example, iPhone or iTouch or other smart phone or other network-enabled devices. Additionally, the controller might exist as part of a player itself or directly/indirectly coupled to the player, and therefore such screenshots may be modified accordingly – such a controller need not have network capability as the player will have network connectivity.

[00118] FIG. 10A shows a graphic interface **1000** that may be displayed on a controller when a user desires to create a stereo pair with two players in a system. It is understood that the system may include two or more players. If a stereo pair is desired, such as discussed with respect to the example of FIGS. 10A-10F, then any two players (one or both of which may be a consolidated player) in the system may be paired. However, if pairing more than two players is desired, such as creating an environment which is capable of playing more than two channel audio data, then the graphic interface **1000** may include an additional option or options. For example, an option might include “Make a Movie Surround Sound Pairing,” “Make a Music Surround Sound Pairing,” or “Make a Dolby Pro Logic Pairing.” Any descriptive language may be used to appropriately indicate to the user the type of pairing that can be created. Upon selecting an option, a setup wizard on the controller may help the user appropriately configure the system such that multi-channel discrete audio may be effectively realized by the system.

[00119] Turning back to FIG. 10A, the interface **1000** allows a user to initiate a stereo pair with a zone player named “ZPS5-Black.” In certain embodiments, the system recognizes that ZPS5-Black is part of a particular zone (e.g., kitchen, family room, bedroom, and so on). The system may allow the user to pair ZPS5-Black with another player in the same zone only, or alternatively, the system may allow the user to pair ZPS5-Black with another player in a different zone (such as an adjacent zone). Pairing players in different zones may be particularly useful

when an open space is divided into two or more zones (e.g., an open space might include a kitchen and family room, for example).

[00120] Additionally, the system may be programmed such that pairing players from different zones creates another zone to reflect the players in paired mode (e.g., a single kitchen-family room zone during paired operation might originate from a kitchen zone and a family room zone during non-paired operation). In such an embodiment, a user may be able to switch between zones or dynamically create new zones.

[00121] In certain embodiments, if another similar player is available to be paired, then the screenshot of FIG. 10B may be displayed. If the user wishes to continue with creating a pair, then the user may select “OK.” If not, then the user may select “Cancel.” In another embodiment, a different player (e.g., a player that is not an S5) may be paired together. That is, different types of players may be paired, if the players are so designed to be paired. To accommodate the differences in player type, the equalization of one or more players may be adjusted accordingly to compensate for things like the number and size of speaker drivers used in one player versus the other player. In yet another embodiment, a list of the players in the system may be displayed (not shown), from which the user selects two or more players to make the stereo pair. The list of players may be automatically determined by the system based on a player’s particular location within a home, room, or configuration with other players within a room, for example.

[00122] Turning now to FIG. 10C, in this example, it is assumed that the user may select a zone player named “ZPS5-White” to be paired with “ZPS5-Black” to create a stereo pair. If so desired, the user may select “OK” to proceed with the pairing. Otherwise, the user may select “Cancel.” In certain embodiments, ZPS5-White may be in the same zone as ZPS5-Black. In other embodiments, ZPS5-White may be in a different zone as ZPS5-Black.

[00123] Upon selecting “OK” in FIG. 10C, a screenshot like that of FIG. 10D may be displayed to the user, thereby instructing the user to press the mute button (or some other

designated button) on the “LEFT” player of the stereo pair. Further, a light on the players may flash to further indicate that each of the players is a possibility for left channel pairing. Upon selection of the left player, FIG. 10E may be displayed to inform the user that a pair has been created along with a name for the pair, if so desired. Responsively, the system will play the left channel audio from the user designated player and will automatically play the right channel audio from the other player. FIG. 10F provides an example screenshot to allow the user to separate the stereo pair if so desired.

[00124] In an alternative embodiment, the creation of a stereo pair may be an option for a particular zone or a number of zones (e.g., a household of zones). For example, an option like “Create a Stereo Pair” may exist such that upon selection, a setup wizard may launch asking the user to press a flashing mute button (or some other designated button) on whichever speaker the user wanted to be the left speaker in the zone, a portion of zones, or all of the zones. In one embodiment, flashing would occur for all of the same speaker types. In another embodiment, flashing would occur for all speaker types that are capable of being paired. After choosing the left speaker, the wizard screen would ask the user to do the same for the right speaker. Preferably, only the speakers that are capable of being paired as the right speaker are flashing so as to appropriately narrow the choices for the user.

[00125] Additionally, in one embodiment and as shown in FIG. 3A or 3B, a graphic display is provided to show to the user all the players in a system and how they are grouped or named. A nickname for the stereo pair in the display **1040** may be highlighted and would be further displayed in FIG. 3A if FIG. 3A is modified after the stereo pair is complete

[00126] A similar graphic interface may be used to create a pair in an environment having more than two channels. For example, in a home theater environment, the system may list more than two separate players from which the user can create a pairing by selecting which player is to

operate as the front right, center, front left, rear right, and rear left. A subwoofer may also be added to the list, so that it can be integrated into the multi-channel pairing by the user.

[00127] As an example, similar to what is described in the various embodiments above with respect to creating a stereo pair, the system may flash an indicator light on all relevant players and a setup wizard may ask the user to select the “front-left,” then the “front-right,” then the “front-center,” then the “rear-left,” then the “rear-right,” and so on until all of the players are appropriately paired. Preferably, only the speakers that are capable of being paired as the next speaker are flashing so as to appropriately narrow the choices for the user.

VII. Conclusion

[00128] The components, elements, and/or functionality of the systems discussed above may be implemented alone or in combination in various forms in hardware, firmware, and/or as a set of instructions in software, for example. Certain embodiments may be provided as a set of instructions residing on a computer-readable medium, such as a memory, hard disk, CD-ROM, DVD, and/or EPROM, for execution on a processing device, such as a controller and/or playback device.

[00129] Various inventions have been described in sufficient detail with a certain degree of particularity. It is understood to those skilled in the art that the present disclosure of embodiments has been made by way of examples only and that numerous changes in the arrangement and combination of parts may be resorted without departing from the spirit and scope of the invention as claimed. While the embodiments discussed herein may appear to include some limitations as to the presentation of the information units, in terms of the format and arrangement, the embodiments have applicability well beyond such embodiment, which can be appreciated by those skilled in the art. Accordingly, the scope of the present invention is defined by the appended claims rather than the forgoing description of embodiments.

[00130] For example, the following represent but a few of many apparatus, method and system combinations based on the description provided above. These are provided for purposes of non-limiting illustration, and it is understood that many more combinations can be described and claimed based on the present description.

[00131] 1. An apparatus for providing audio in a multi-channel listening environment, the apparatus comprising:

- a network interface to facilitate communication on a network, wherein the network interface receives audio data over the network;
- a plurality of speaker drivers;
- an amplifier for powering the plurality of speaker drivers; and
- a processor for processing the audio data to be output through the plurality of speaker drivers and further for configuring a first equalization of the output from the plurality of speaker drivers in accordance with a first type of pairing and configuring a second equalization of the output from the plurality of speaker drivers in accordance with a second type of pairing.

[00132] 2. The apparatus of 1, wherein the first equalization comprises using a first type of pass filter to modify the output based on the first type of pairing, wherein the second equalization comprises using a second type of pass filter to modify the output based on the second type of pairing, and wherein the first type of pass filter and the second type of pass filter are different.

[00133] 3. The apparatus of 1, wherein the apparatus comprises a playback device, and wherein the first type of pairing comprises no pairing with another playback device and the second type of pairing comprises pairing with one or more additional playback devices.

- [00134]** 4. The apparatus of 1, wherein the apparatus comprises a playback device, and wherein the first type of pairing comprises pairing with a second playback device and the second type of pairing comprises pairing with a plurality of playback devices.
- [00135]** 5. The apparatus of 1, wherein the first type of pairing comprises reproducing two channel sound via the plurality of speaker drivers and wherein the second type of pairing comprises reproducing no more than one channel of the two channel sound via the plurality of speaker drivers.
- [00136]** 6. The apparatus of 1, wherein the first type of pairing comprises reproducing a first audio channel via the plurality of speaker drivers and wherein the second type of pairing comprises reproducing a second audio channel via the plurality of speaker drivers, and wherein the first audio channel and the second audio channel are different.
- [00137]** 7. The apparatus of 1, wherein the first type of pairing comprises reproducing the audio content via the plurality of speaker drivers in stereo mode and wherein the second type of pairing comprises reproducing the audio content via the plurality of speaker drivers in theater mode.
- [00138]** 8. The apparatus of 1, wherein the first type of pairing comprises reproducing the audio content via the plurality of speaker drivers and wherein the second type of pairing comprises reproducing the audio content via the plurality of speaker drivers when in consolidated mode.
- [00139]** 9. The apparatus of 1, wherein the processor is further configured to separate the audio data into separate audio channels, wherein at least one separate audio channel is output from the plurality of speaker drivers and at least one additional separate audio channel is transmitted by the network interface over the network.
- [00140]** 10. The apparatus of 1, wherein the apparatus is a playback device and the network interface receives a signal from a controller over the network to pair with one or more playback devices.

- [00141]** 11. The apparatus of 1, wherein the apparatus is a playback device and the network interface receives a signal from a controller over the network to configure the playback device in consolidation mode.
- [00142]** 12. The apparatus of 1, wherein the apparatus is a playback device and further comprises a button that when selected chooses the channel of the playback device.
- [00143]** 13. The apparatus of 1, wherein the network is a wireless network.
- [00144]** 14. A method for providing audio in a multi-channel listening environment, the method comprising:
- receiving audio data over a network;
 - processing the audio data to be output through a plurality of speaker drivers; and
 - configuring a first equalization of the output from the plurality of speaker drivers in accordance with a first type of pairing and configuring a second equalization of the output from the plurality of speaker drivers in accordance with a second type of pairing.
- [00145]** 15. The method of 14, wherein the first equalization comprises using a first type of pass filter to modify the content based on the first type of pairing and wherein the second equalization comprises using a second type of pass filter to modify the output based on the second type of pairing, wherein the first type of pass filter and the second type of pass filter are different.
- [00146]** 16. The method of 14, wherein the first type of pairing comprises no pairing with another playback device and the second type of pairing comprises pairing with one or more additional playback devices.
- [00147]** 17. The method of 14, wherein the first type of pairing comprises pairing with a second playback device and the second type of pairing comprises pairing with a plurality of playback devices.
- [00148]** 18. The method of 14, wherein the first type of pairing comprises reproducing two channel sound via the plurality of speaker drivers and wherein the second type of

pairing comprises reproducing no more than one channel of the two channel sound via the plurality of speaker drivers.

[00149] 19. The method of 14, wherein the first type of pairing comprises reproducing a first audio channel via the plurality of speaker drivers and wherein the second type of pairing comprises reproducing a second audio channel via the plurality of speaker drivers, and wherein the first audio channel and the second audio channel are different.

[00150] 20. The method of 14, wherein the first type of pairing comprises reproducing the audio content via the plurality of speaker drivers and wherein the second type of pairing comprises reproducing the audio content via the plurality of speaker drivers when in consolidated mode.

[00151] 21. The method of 14, wherein the processor is further configured to separate the audio data into separate audio channels, wherein at least one separate audio channel is output from the plurality of speaker drivers and at least one additional separate audio channel is transmitted by the network interface over the network.

[00152] 22. The method of 14, further comprising sending a signal over the network to a controller that selects a channel of the audio data that is output from the plurality of speaker drivers.

[00153] 23. An system to provide multi-channel audio playback, the system comprising:

a collection of at least three playback devices each configured to independently output a plurality of audio channels, each playback device including a network interface, a speaker driver, and an amplifier; and

a processor in at least one of the collection of playback devices to selectively pair the at least three playback devices such that, subsequent to pairing, each of the at least three playback devices is to be configured to output a different audio channel from the others of the at least three playback devices.

- [00154]** 24. The system of 23, wherein the at least three playback devices are to output their respective audio channels in synchrony.
- [00155]** 25. The system of 23, wherein the processor is housed in one of the at least three playback devices, and wherein the processor is to process incoming audio data to separate the data into audio channels to be provided to the other of the at least three playback devices for output of their respective audio channels in synchrony.
- [00156]** 26. The system of 25, wherein the processor is to process incoming audio data to retain one or more audio tracks corresponding to one or more audio channels locally and to send remaining audio tracks to another of the at least three playback devices until all incoming audio tracks are retained locally by a playback device.
- [00157]** 27. The system of 23, wherein the selective pairing is triggered based on a command via a control interface.
- [00158]** 28. The system of 23, wherein the selective pairing is triggered responsive to an event.
- [00159]** 29. The system of 28, wherein the event comprises at least one of a change of audio content, a time, and a type of audio content associated with the plurality of audio channels.
- [00160]** 30. The system of 23, wherein the processor is to change equalization of the at least three playback devices by changing equalization of one or more specific speaker drivers and adjusting synchronization between the paired playback devices.
- [00161]** 31. The system of 30, wherein the equalization comprises a first equalization using a first type of pass filter to modify the output of a first of the at least three playback devices based on a first type of pairing, a second equalization using a second type of pass filter to modify the output of a second of the at least three playback devices based on a second type of pairing, and a third equalization using a third type of pass filter to modify the output of a third of the at least three playback devices based on a third type of pairing.

[00162] 32. The system of 31, wherein the first type of pairing comprises reproducing a first audio channel, the second type of pairing comprises reproducing a second audio channel, and the third type of pairing comprises reproducing a third audio channel from the plurality of audio channels.

[00163] 33. The system of 30, wherein the equalization is based on at least one of a non-paired mode, a paired mode, a consolidated mode, and a grouped mode for the selective pairing of the at least three playback devices.

[00164] 34. The system of 23, wherein at least two of the collection of at least three playback devices is to be grouped into a consolidated playback device, and the consolidated playback device is able to be paired with one or more additional playback devices.

[00165] 35. A method to provide multi-channel audio playback, the method comprising:
receiving audio data including a plurality of audio channels at a collection of at least three playback devices;
selectively pairing, using a processor housed in at least one of the collection of playback devices, the at least three playback devices such that each of the at least three playback devices is configured to output a different audio channel from the others of the at least three playback devices.

[00166] 36. The method of 35, wherein the at least three playback devices are to output their respective audio channels in synchrony.

[00167] 37. The method of 35, wherein the processor is housed in one of the at least three playback devices, and wherein the processor is to process incoming audio data to separate the data into audio channels to be provided to the other of the at least three playback devices for output of their respective audio channels in synchrony.

[00168] 38. The method of 37, wherein the processor is to process incoming audio data to retain one or more audio tracks corresponding to one or more audio channels

locally and to send remaining audio tracks to another of the at least three playback devices until all incoming audio tracks are retained locally by a playback device.

- [00169]** 39. The method of 35, wherein the selective pairing is triggered based on a command via a control interface.
- [00170]** 40. The method of 35, wherein the selective pairing is triggered responsive to an event.
- [00171]** 41. The method of 39, wherein the event comprises a change of audio content.
- [00172]** 42. The method of 35, further comprising changing an equalization of the at least three playback devices by changing equalization of one or more specific speaker drivers and adjusting synchronization between the paired playback devices.
- [00173]** 43. The method of 42, wherein the equalization comprises a first equalization using a first type of pass filter to modify the output of a first of the at least three playback devices based on a first type of pairing, a second equalization using a second type of pass filter to modify the output of a second of the at least three playback devices based on a second type of pairing, and a third equalization using a third type of pass filter to modify the output of a third of the at least three playback devices based on a third type of pairing.
- [00174]** 44. The method of 43, wherein the first type of pairing comprises reproducing a first audio channel, the second type of pairing comprises reproducing a second audio channel, and the third type of pairing comprises reproducing a third audio channel from the plurality of audio channels.
- [00175]** 45. The method of 42, wherein the equalization is based on at least one of a non-paired mode, a paired mode, a consolidated mode, and a grouped mode for the selective pairing of the at least three playback devices.
- [00176]** 46. The method of 35, further comprising grouping at least two of the collection of at least three playback devices into a consolidated playback device, wherein the consolidated playback device is able to be paired with one or more additional playback devices.

[00177] 47. An apparatus for providing audio in a multi-channel listening environment, the apparatus comprising:

- a network interface to facilitate communication on a network, wherein the network interface receives audio data over the network;
- a plurality of speaker drivers;
- an amplifier for powering the plurality of speaker drivers; and
- a processor for processing the audio data to be output through the plurality of speaker drivers, wherein the processor applies a first equalization of the output from the plurality of speaker drivers in accordance with a first type of pairing between the apparatus and at least a second apparatus and ignores a remainder of the audio data that does not correspond to the first equalization.

[00178] 48. The apparatus of 47, wherein the first equalization uses a first filter to select a first number of one or more audio channels from the audio data for output via the apparatus and ignores the remaining one or more channels from the audio data, which are to be independently processed for output by the second apparatus.

[00179] 49. The apparatus of 47, wherein the processor selectively pairs the apparatus with the second apparatus in response to a trigger.

[00180] 50. The apparatus of 49, wherein the trigger comprises at least one of a control interface command, a change in audio content, a time, and a type of audio content.

[00181] 51. An apparatus for providing audio in a multi-channel listening environment, the apparatus comprising:

- a network interface to facilitate communication on a network, wherein the network interface receives audio data over the network;
- a plurality of speaker drivers;
- an amplifier for powering the plurality of speaker drivers; and
- a processor for processing the audio data to be output through the plurality of speaker drivers and further for configuring, based on an external trigger, a first

equalization of the output from the plurality of speaker drivers in accordance with a first type of pairing and configuring a second equalization of the output from the plurality of speaker drivers in accordance with a second type of pairing.

[00182] 52. The apparatus of 51, wherein the trigger comprises at least one of a control interface command, a change in audio content, a time, and a type of audio content.

[00183] 53. An apparatus comprising: a plurality of playback devices grouped into a consolidated playback device.

[00184] 54. The apparatus of claim 54, wherein an equalization of at least one of the plurality of playback devices is changed as a result of the consolidation.

[00185] 55. The apparatus of claim 53, wherein the consolidated playback device is further paired with one or more playback devices.

[00186] 56. The apparatus of claim 53, wherein the plurality of playback devices is grouped wirelessly with each other.

[00187] 57. An apparatus, comprising: a network interface to facilitate communication on a network, wherein the network interface receives more than two channel audio data over the network; at least one speaker driver; at least one amplifier for powering the at least one speaker driver; and a processor for processing the more than two channel audio data such that a single channel of the more than two channel audio data is to be output through the at least one speaker driver, wherein the remaining channels of the more than two channel audio data is sent via the network interface to be output through a plurality of playback devices.

[00188] 58. A method comprising: wirelessly pairing three or more playback devices.

Claims

We claim:

1. An apparatus for providing audio in a multi-channel listening environment, the apparatus comprising:
 - a network interface to facilitate communication on a network, wherein the network interface receives audio data over the network;
 - a plurality of speaker drivers;
 - an amplifier for powering the plurality of speaker drivers; and
 - a processor for processing the audio data to be output through the plurality of speaker drivers and further for configuring a first equalization of the output from the plurality of speaker drivers in accordance with a first type of pairing and configuring a second equalization of the output from the plurality of speaker drivers in accordance with a second type of pairing.
2. The apparatus of claim 1, wherein the first equalization comprises using a first type of pass filter to modify the output based on the first type of pairing, wherein the second equalization comprises using a second type of pass filter to modify the output based on the second type of pairing, and wherein the first type of pass filter and the second type of pass filter are different.
3. The apparatus of claim 1, wherein the apparatus comprises a playback device, and wherein the first type of pairing comprises no pairing with another playback device and the second type of pairing comprises pairing with one or more additional playback devices.

4. The apparatus of claim 1, wherein the apparatus comprises a playback device, and wherein the first type of pairing comprises pairing with a second playback device and the second type of pairing comprises pairing with a plurality of playback devices.
5. The apparatus of claim 1, wherein the first type of pairing comprises reproducing two channel sound via the plurality of speaker drivers and wherein the second type of pairing comprises reproducing no more than one channel of the two channel sound via the plurality of speaker drivers.
6. The apparatus of claim 1, wherein the first type of pairing comprises reproducing a first audio channel via the plurality of speaker drivers and wherein the second type of pairing comprises reproducing a second audio channel via the plurality of speaker drivers, and wherein the first audio channel and the second audio channel are different.
7. The apparatus of claim 1, wherein the first type of pairing comprises reproducing the audio content via the plurality of speaker drivers in stereo mode and wherein the second type of pairing comprises reproducing the audio content via the plurality of speaker drivers in theater mode.
8. The apparatus of claim 1, wherein the first type of pairing comprises reproducing the audio content via the plurality of speaker drivers and wherein the second type of pairing comprises reproducing the audio content via the plurality of speaker drivers when in consolidated mode.
9. The apparatus of claim 1, wherein the processor is further configured to separate the audio data into separate audio channels, wherein at least one separate audio channel is

output from the plurality of speaker drivers and at least one additional separate audio channel is transmitted by the network interface over the network.


10. The apparatus of claim 1, wherein the apparatus is a playback device and the network interface receives a signal from a controller over the network to pair with one or more playback devices.
11. The apparatus of claim 1, wherein the apparatus is a playback device and the network interface receives a signal from a controller over the network to configure the playback device in consolidation mode.
12. The apparatus of claim 1, wherein the apparatus is a playback device and further comprises a button that when selected chooses the channel of the playback device.
13. The apparatus of claim 1, wherein the network is a wireless network.
14. The apparatus of claim 1, wherein the processor selectively pairs the apparatus with a second apparatus in response to a trigger comprising at least one of a control interface command, a change in audio content, a time, and a type of audio content.
15. The apparatus of claim 1, wherein the processor is to process incoming audio data to separate the data into audio channels to be provided to one or more additional playback devices for output of their respective audio channels in synchrony.
16. The apparatus of claim 1, wherein the processor is to process incoming audio data to retain one or more audio tracks corresponding to one or more audio channels locally and

to send remaining audio tracks to at least one other playback device until all incoming audio tracks are retained locally by a playback device.

17. The apparatus of claim 1, wherein the processor is to process incoming audio data to retain one or more audio tracks corresponding to one or more audio channels ignore one or more other audio tracks which are to be processed by at least a second apparatus.
18. A method for providing audio in a multi-channel listening environment, the method comprising:
 - receiving audio data over a network;
 - processing the audio data to be output through a plurality of speaker drivers; and
 - configuring a first equalization of the output from the plurality of speaker drivers in accordance with a first type of pairing and configuring a second equalization of the output from the plurality of speaker drivers in accordance with a second type of pairing.
19. The method of claim 18, wherein the first equalization comprises using a first type of pass filter to modify the content based on the first type of pairing and wherein the second equalization comprises using a second type of pass filter to modify the output based on the second type of pairing, wherein the first type of pass filter and the second type of pass filter are different.
20. The method of claim 18, wherein the first type of pairing comprises no pairing with another playback device and the second type of pairing comprises pairing with one or more additional playback devices.

21. The method of claim 18, wherein the first type of pairing comprises pairing with a second playback device and the second type of pairing comprises pairing with a plurality of playback devices.
22. The method of claim 18, wherein the first type of pairing comprises reproducing two channel sound via the plurality of speaker drivers and wherein the second type of pairing comprises reproducing no more than one channel of the two channel sound via the plurality of speaker drivers.
23. The method of claim 18, wherein the first type of pairing comprises reproducing a first audio channel via the plurality of speaker drivers and wherein the second type of pairing comprises reproducing a second audio channel via the plurality of speaker drivers, and wherein the first audio channel and the second audio channel are different.
24. The method of claim 18, wherein the first type of pairing comprises reproducing the audio content via the plurality of speaker drivers and wherein the second type of pairing comprises reproducing the audio content via the plurality of speaker drivers when in consolidated mode.
25. The method of claim 18, wherein the processing and configuring comprise separating the audio data into separate audio channels, wherein at least one separate audio channel is output from the plurality of speaker drivers and at least one additional separate audio channel is transmitted by the network interface over the network.
26. The method of claim 18, further comprising sending a signal over the network to a controller that selects a channel of the audio data that is output from the plurality of speaker drivers.

27. The method of claim 18, wherein the processing selectively pairing with another playback device in response to a trigger comprising at least one of a control interface command, a change in audio content, a time, and a type of audio content.
28. The method of claim 18, wherein the processing further comprises processing incoming audio data to retain one or more audio tracks corresponding to one or more audio channels locally and to send remaining audio tracks to at least one other playback device until all incoming audio tracks are retained locally by a playback device.
29. The method of claim 18, wherein the processing further comprises processing incoming audio data to retain one or more audio tracks corresponding to one or more audio channels ignore one or more other audio tracks which are to be processed by at least a second apparatus.






FIG. 2A

240





FIG. 2B



270




FIG. 2D




FIG. 3A




FIG. 3B




FIG. 4




FIG. 5A




FIG. 5B






FIG. 5C

**FIG. 6**







FIG. 8

**FIG. 9**




FIG. 10A




FIG. 10B




FIG. 10C




FIG. 10D




FIG. 10E




FIG. 10F

INTERNATIONAL SEARCH REPORT

International application No
PCT/IB2012/052071

A. CLASSIFICATION OF SUBJECT MATTER INV. H04R27/00 H04S7/00 ADD.		
According to International Patent Classification (IPC) or to both national classification and IPC		
B. FIELDS SEARCHED Minimum documentation searched (classification system followed by classification symbols) H04R H04S		
Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched		
Electronic data base consulted during the international search (name of data base and, where practicable, search terms used) EPO-Internal, COMPENDEX, INSPEC, PAJ, IBM-TDB, WPI Data		
C. DOCUMENTS CONSIDERED TO BE RELEVANT		
Category*	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
X	US 2002/124097 A1 (ISELY LARSON J [US] ET AL) 5 September 2002 (2002-09-05) page 1, paragraph 4 - page 3, paragraph 20 page 4, paragraph 35 - page 8, paragraph 71 claims 1-17,25-38; figures 1-7 -----	1-29
X	US 7 571 014 B1 (LAMBOURNE ROBERT A [US] ET AL) 4 August 2009 (2009-08-04) column 2, line 17 - column 3, line 34 column 4, line 11 - column 14, line 29 claims 1-17,25-35; figures 1-2C,5-7D -----	1-29
☐ Further documents are listed in the continuation of Box C. ☒ See patent family annex.		
* Special categories of cited documents : "A" document defining the general state of the art which is not considered to be of particular relevance "E" earlier application or patent but published on or after the international filing date "L" document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified) "O" document referring to an oral disclosure, use, exhibition or other means "P" document published prior to the international filing date but later than the priority date claimed "T" later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention "X" document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone "Y" document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art "&" document member of the same patent family		
Date of the actual completion of the international search 10 August 2012		Date of mailing of the international search report 23/08/2012
Name and mailing address of the ISA/ European Patent Office, P.B. 5818 Patentlaan 2 NL - 2280 HV Rijswijk Tel. (+31-70) 340-2040, Fax: (+31-70) 340-3016		Authorized officer Meiser, Jürgen

INTERNATIONAL SEARCH REPORT

Information on patent family members

International application No

PCT/IB2012/052071

Patent document cited in search report	Publication date	Patent family member(s)	Publication date
US 2002124097	A1	05-09-2002	NONE

US 7571014	B1	04-08-2009	NONE
