



(51) International Patent Classification:
H05B 37/02 (2006.01) *H05B 37/04* (2006.01)

(21) International Application Number:
PCT/US2010/038987

(22) International Filing Date:
17 June 2010 (17.06.2010)

(25) Filing Language: English

(26) Publication Language: English

(30) Priority Data:
61/218,320 18 June 2009 (18.06.2009) US

(71) Applicant (for all designated States except US): **MUSCO CORPORATION** [US/US]; 100 - 1st Avenue West, Oskaloosa, Iowa 52577 (US).

(72) Inventors; and

(75) Inventors/Applicants (for US only): **BLANCHARD, David L.** [US/US]; 301 South I, Oskaloosa, IA 52577 (US). **GORDIN, Myron** [US/US]; 2746 Merino Avenue, Oskaloosa, Iowa 52577 (US).

(74) Agent: **HANSING, Mark D.**; McKee, Voorhees & Sease, PLC, 801 Grand Avenue, Suite 3200, Des Moines, Iowa 50309-2721 (US).

(81) Designated States (unless otherwise indicated, for every kind of national protection available): AE, AG, AL, AM,

AO, AT, AU, AZ, BA, BB, BG, BH, BR, BW, BY, BZ, CA, CH, CL, CN, CO, CR, CU, CZ, DE, DK, DM, DO, DZ, EC, EE, EG, ES, FI, GB, GD, GE, GH, GM, GT, HN, HR, HU, ID, IL, IN, IS, JP, KE, KG, KM, KN, KP, KR, KZ, LA, LC, LK, LR, LS, LT, LU, LY, MA, MD, ME, MG, MK, MN, MW, MX, MY, MZ, NA, NG, NI, NO, NZ, OM, PE, PG, PH, PL, PT, RO, RS, RU, SC, SD, SE, SG, SK, SL, SM, ST, SV, SY, TH, TJ, TM, TN, TR, TT, TZ, UA, UG, US, UZ, VC, VN, ZA, ZM, ZW.

(84) Designated States (unless otherwise indicated, for every kind of regional protection available): ARIPO (BW, GH, GM, KE, LR, LS, MW, MZ, NA, SD, SL, SZ, TZ, UG, ZM, ZW), Eurasian (AM, AZ, BY, KG, KZ, MD, RU, TJ, TM), European (AL, AT, BE, BG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, HR, HU, IE, IS, IT, LT, LU, LV, MC, MK, MT, NL, NO, PL, PT, RO, SE, SI, SK, SM, TR), OAPI (BF, BJ, CF, CG, CI, CM, GA, GN, GQ, GW, ML, MR, NE, SN, TD, TG).

Declarations under Rule 4.17:

— as to applicant's entitlement to apply for and be granted a patent (Rule 4.17(ii))

Published:

— without international search report and to be republished upon receipt of that report (Rule 48.2(g))

(54) Title: APPARATUS AND METHOD FOR BYPASSING FAILED LEDS IN LIGHTING ARRAYS




Fig. 1

(57) Abstract: An apparatus, method and system for controlling one or multiple lighting sources such as those powered by driver circuits or voltage splitting methods, to provide an alternative current path around a failed lighting source when one or more individual lighting sources fail.



1 **TITLE: APPARATUS AND METHOD FOR BYPASSING FAILED LEDS IN**
2 **LIGHTING ARRAYS**
3
4

5 **CROSS-REFERENCE TO RELATED APPLICATIONS**

6 This application claims priority under 35 U.S.C. § 119 to provisional application
7 Serial No. 61/218,320 filed June 18, 2009, herein incorporated by reference in its
8 entirety.
9

10 **I. BACKGROUND OF INVENTION**

11 **A. *Field of Invention***

12 The present invention relates to methods of controlling multiple lighting sources
13 such as those powered by driver circuits and voltage splitting methods, which provides
14 alternative failure modes when one or more individual lighting sources fail.
15

16 **B. *Problems in the Art***

17 LED lighting often consists of an array of LEDs comprising a number of LEDs
18 connected in series to form a string of LEDs, and a number of strings of LEDs connected
19 in parallel. The array may be conveniently comprised in a single fixture, such as found in
20 overhead lighting, or may be spread out among two or more fixtures such as found in
21 pathway lighting.

22 The electro-optic properties of LEDs are such that the LED functions best when
23 current through the LED rather than voltage applied across the LED is controlled.
24 Connecting a large number of LEDs in a series string results in a relatively low amperage
25 and relatively high total voltage drop across the string. This is beneficial for lighting
26 circuits using multiple LEDs. However, this has the disadvantage that a single LED open
27 circuit failure will prevent current from flowing through all other LEDs connected in
28 series, resulting in the elimination of the illumination provided by all remaining functional
29 LEDs in that series string. This severely reduces the illumination produced by the LED
30 array.

31 Therefore, many opportunities exist for improving the current state of lighting
32 using multiple LEDs or other solid state sources. It is the intention of this invention to
33 solve or improve over such problems and deficiencies in the art.

II. SUMMARY OF THE INVENTION

It is therefore a principle object, feature, advantage, or aspect of the present invention to improve over the state of the art or address problems, issues, or deficiencies in the art.

Further objects, features, advantages, or aspects of the present invention include an apparatus, method, or system which provides a relatively inexpensive electronic circuit to be placed in parallel with a single LED or with one or more strings of LEDs that will detect an open LED failure and provide an alternate current path around the LED or string(s) of LEDs.

These and other objects, features, advantages, or aspects of the present invention will become more apparent with reference to the accompanying specification and claims.

A method according to one aspect of the invention comprises automatically detecting an open LED failure and providing an alternate current path around the LED or a string or strings of LEDs including the open LED failure. Optionally, the LED or string(s) can be in a fixture or fixtures each containing multiple LEDs.

Another method according to one aspect of the invention comprises automatically detecting an open LED failure and providing an alternate current path. Said current path may be around the LED or around a string or strings of LEDs (including the open LED failure) which are used in a series of individual fixtures. Said individual fixtures may be part of a distributed array of LEDs within a plurality of fixtures which may include one or more LEDs in each fixture.

An apparatus according to one aspect of the invention comprises an alternative current path circuit placed in parallel with an LED or a string of LEDs, the alternative current path circuit being substantially inactive, and including components which are substantially inactive except for small leakage and bias current in absence of a condition indicative of an open LED failure, but becoming automatically active to pass at least substantially most of the operating current if a condition indicative of an open LED failure is sensed by the circuit. The components can include a transistor to switch between inactive and active states. The components can function to latch the circuit into an active state until automatic sensing of a condition pre-designed to unlatch.

Another aspect of the invention comprises a method of designing an alternative current path circuit, adapted for placement in parallel with an LED or string of LEDs, to be

essentially inactive until a condition indicative of an open LED failure is sensed, and then automatically becoming active to bypass that LED or the string of LEDs including that LED, with substantially all the operating current. The method includes techniques for determining and setting a triggering voltage for automatic triggering of an active state for the circuit.

III. BRIEF SUMMARY OF THE DRAWINGS

Figure 1 shows an open LED protection circuit according to one exemplary embodiment of the invention.

Figures 2A-B show open LED protection circuits using two transistors and resistors R1-R3 according to other exemplary embodiments of the invention.

Figures 3A-B show open LED protection circuits using two transistors, resistors R1-R3, and zener diode D1 according to other exemplary embodiments of the invention.

Figures 4A-B show open LED protection circuits using two transistors and zener diode D1.

Figures 5A-B show an ideal LED and its voltage/current relationship.

Figure 6 is a graph of V_{Toff} , αV_{Toff} , of equation (17) and equation (25) described later with $p = 1$.

Figure 7 is a graph showing V_{trig} , V_{SS} , and V_{latch} with $p = 1$.

Figure 8 is a graph of LED required power source voltage when $m = 10$, $p = 1$, and $0 \leq q \leq 5$.

Figure 9 is a graph of power source overhead voltage for number of LEDs in a sub-string with $q = 1$.

Figures 10A-C show three alternative circuit arrangements according to exemplary embodiments of the present invention.

Figure 10A shows a circuit using a zener diode.

Figure 10B is a circuit that functions similarly to Figure 2A using a PNP transistor and an NMOS FET.

Figure 10C is a circuit that functions similarly to Figure 2A using a PNP transistor and an NPN transistor.

Figure 11A shows a single semiconductor device known as an SCR connected in parallel with an LED according to another exemplary embodiment of the present invention.

1 Figure 11B is a transistorized circuit that functions similarly to Figure 11A with the
2 addition of the ability to modify trigger and sustain current through use of resistive
3 components according to another exemplary embodiment of the present invention.

4 Figure 11C shows a circuit similar to Figure 11B without the series resistors
5 according to another exemplary embodiment of the present invention.

6 Figure 11D shows a circuit similar to Figure 11B with a Darlington transistor
7 configuration which increases the transistor gain according to another exemplary
8 embodiment of the present invention.

9 Figure 12 shows an array of LEDs within a single circuit with bypass circuits
10 included according to another exemplary embodiment of the present invention.

11 Figure 13 shows an embodiment wherein the series connected LEDs can be broken
12 into groups such that one circuit protects a number of LEDs according to another
13 exemplary embodiment of the present invention.

14 Figure 14 shows an embodiment where several strings of LEDs are included in a
15 single fixture or system of fixtures having OLPC (Open LED Protection Circuit) protection
16 for each substring and a current driver for each substring according to another exemplary
17 embodiment of the present invention.

18 Figure 15 shows alternative circuit configurations that can be used to provide
19 OLPC operation according to another exemplary embodiment of the present invention.

20 Figures 16A-D show alternative circuit configurations that can be used to provide
21 OLPC operation according to another exemplary embodiment of the present invention.

22 Figures 17A-D show an alternative circuit configuration that can be used to provide
23 OLPC operation according to another exemplary embodiment of the present invention.

24 Figure 18 shows a graph of the operating voltages versus current for an LED,
25 OLPC, and a single transistor and two-transistor ZOLPC for a protected single LED sub-
26 string.

27 Figure 19 shows a graph of the power dissipation of an LED, OLPC, and a single
28 transistor and two-transistor ZOLPC for a protected single LED sub-string.

29 Figure 20 shows a graph of operating voltage when a protected 3-LED sub-string is
30 implemented.

31 Figure 21 shows a graph of power dissipation when a protected 3-LED sub-string is
32 implemented.

Figure 22 illustrates a view of an embodiment similar to Fig. 13 wherein an array of LEDs is distributed over several fixtures according to another exemplary embodiment of the present invention.

Figure 23 shows a plan/schematic view of a similar installation as Fig. 22.

Figure 24 shows a view of a similar installation as Fig. 22 and 23 having more than one LED circuit according to another exemplary embodiment of the present invention.

IV. DETAILED DESCRIPTION OF EXEMPLARY EMBODIMENTS

A. Overview

To assist in a better understanding of the invention, examples of several exemplary forms it can take will now be described in detail. It is to be understood that these are but a few forms the invention could take. The invention could take many forms and embodiments. The scope of the invention is not limited by the few examples given herein. Also, variations and options obvious to those skilled in the art will be included within the scope of the invention.

B. Figures

From time to time in this description, reference will be made to the appended figures. Reference numbers or letters will be used to indicate certain parts or locations in the figures. The same reference numbers or letters will indicate the same or similar parts or locations throughout the figures unless otherwise indicated.

C. Application

This invention is intended to provide a relatively inexpensive electronic circuit 10, Figure 1, to be placed in parallel with a single LED 20 or with one or more strings of LEDs that will provide an alternate current path around the LED or string(s) of LEDs in response to an open LED failure. When the LED is operational, the alternate circuit path current is significantly less than the LED current. When an LED open failure occurs, the alternate circuit path passes 100% of the LED current and produces a voltage drop that may be less than the LED operating voltage. The circuit components could be adjusted or trimmed so that both the LED operating voltage and current could be maintained when an LED open failure occurs. Embodiments can include fixtures with a single string of LEDs such as illustrated in Figures 10B-C, 11B-D, 12 and 13. Other embodiments can include fixtures

1 with more than one string of LEDs in parallel, which use an individual driving circuit or
 2 scheme for each parallel string, such as illustrated in Figure 14. Still other embodiments
 3 can include individual fixtures that include one or more LEDs that are controlled in
 4 accordance with the principles described herein, but which may include individual LEDs
 5 or strings of LEDs which are physically separated from each other such as in Figure 22-24.
 6 Still other embodiments may combine these elements in other ways.

7 **D. Methods and Embodiments**

8 The circuit in Figure 3A shows one way to build what is sometimes called herein
 9 an Open LED Protection Circuit (OLPC). The LEDs numbered LED1—LEDP, represent
 10 a sub-string of series connected LEDs in an array comprising a number of series connected
 11 sub-strings. The OLPC allows the current that would normally be conducted by the sub-
 12 string to have an alternate path available through, transistors Q_1 and Q_2 , if an open circuit
 13 occurs in the sub-string of LED_{1-P} . Conduction of the current through Q_1 and Q_2 will
 14 permit the remaining series connection of similar sub-strings of LEDs to remain in
 15 operation. The OLPC comprises components Zener diode D_1 , resistors R_{1-3} , capacitors C_{1-2} ,
 16 and transistors Q_{1-2} . While the LEDs, LED_{1-P} , are operating normally, the OLPC will be
 17 inactive, conducting only small leakage and bias currents. If any of the LEDs, LED_{1-P} , fail
 18 open circuited, the OLPC will activate providing a current path around LED_{1-P} . Capacitors
 19 C_1 and C_2 filter transients to prevent false triggering of the protective circuit when the sub-
 20 string LEDs, LED_{1-P} , are functional.

21 During normal operation LEDs, LED_{1-P} , conduct the majority of the current I_{source} .
 22 The small reverse leakage current I_{IZ} , of Zener diode D_1 , the small leakage currents, I_{CE} , of
 23 Q_1 and Q_2 , and the small current I_{bias} can be used to set the upper boundary for the value of
 24 R_2 . The voltage value equal to R_2 multiplied by the sum of $(I_{bias} + I_{IZ} + I_{CE2})$, must be much
 25 less than the forward voltage V_{be1} , to prevent Q_1 from conducting during normal operation
 26 of the sub-string, LED_{1-P} . Thus, R_2 must be small enough to prevent Q_1 from turning on
 27 due to leakage currents.

28 Under an open circuit failure condition of the sub-string, the voltage $R_2 I_{bias}$ or $R_2 I_{IZ}$,
 29 must be greater than the forward voltage V_{be1} , by a sufficient amount to cause both Q_1 and
 30 Q_2 to turn on and conduct the current I_{source} . Once both Q_1 and Q_2 start conducting, the
 31 shunt circuit operation will latch itself on to conduct the total current I_{source} . Once the
 32 shunt circuit is latched on, Q_1 and Q_2 will continue to conduct I_{source} until the magnitude of

I_{source} is reduced to a value such that the voltage, $\frac{1}{2}(R_2 I_{source})$, is less than the forward voltage V_{be1} . The minimum value of the I_{source} then sets lower boundary for R_2 . Therefore, the voltage $\frac{1}{2}(R_2 I_{source})$, must be greater than V_{be1} , the turn-on voltage. The magnitude of I_{source} may vary when linear dimming is applied to the system and the value of R_2 must be sufficient to maintain latched operation at the lowest dimming values of I_{source} .

The operation of the latch formed by Q_1 and Q_2 is explained as follows. Q_1 conducts collector current I_{C1} , when the magnitude of $R_2(I_{bias} + I_z)$ exceeds the junction voltage value of V_{be1} . Q_2 conducts collector current I_{C2} when the magnitude of $R_3 I_{C1}$ exceeds the junction voltage value of V_{be2} . The voltage produced at R_2 provides positive feedback to the base of Q_1 to keep Q_1 conducting; creating a latching circuit comprising transistors Q_1 and Q_2 . When the latch circuit turns on, Q_1 and Q_2 will be in saturation and the voltage magnitude that appears across the OLPC active voltage V_{latch} , will have a magnitude of $V_{be1} + V_{be2}$, and the sum of each of the collector currents, $I_{C1} + I_{C2}$, will equal I_{source} . The latching operation will cease when the product of $R_2 I_{source} / 2$ becomes less than V_{be1} . Then the positive feedback is no longer sufficient to sustain the latched operation of Q_1 and Q_2 . The current gain of transistors Q_1 and Q_2 , the magnitude of the resistors R_1 and R_2 , and the values of V_{be1} and V_{be2} , will determine the minimum value required for the current I_{source} , which will maintain the latch condition. The values of V_{be1} , V_{be2} , D_1 , R_1 , and R_2 also determine the conditions necessary to turn-on (trigger) the latch circuit in the event an open circuit of any of the LEDs, LED_{1-P} , in the sub-string occurs.

The latch is set, or triggered, whenever any one or all of the sub-string LEDs become open circuited. The trigger must be present under three operating conditions: first, latch triggering must occur if the LED becomes open circuited while the LED circuit has power applied. Second, the trigger must occur if the LED is already open circuited and power is applied. Third, the latch must release and then re-trigger when current is pulsed while using Pulse Width Modulation (PWM) dimming or other dimming methods using variably switched current while an open-circuited LED sub-string exists. Furthermore, the trigger must be able to latch Q_1 and Q_2 at any value for I_{source} between a specified minimum and maximum value, for all the three conditions. The latch trigger voltage must not occur in any one of the three operating conditions if there are no open-circuited LEDs in the sub-circuit.

1 The operation of the latch trigger assumes the following two power source
 2 conditions: First, the LED current is set and controlled by the LED power source. Second,
 3 the unloaded output voltage of the power source is greater than the forward voltage (ON
 4 voltage) of the LED plus the trigger voltage needed over the system operating temperature
 5 range. The circuit shown in Figure 5A is a piece-wise model of a typical high brightness
 6 LED used to represent the current versus voltage operation of the non-linear LED. Note
 7 that the diode D used in this model is an ideal diode, which allows current to flow in one
 8 direction and blocks current flow in the other direction but does not have any offset voltage
 9 or any forward resistance to current flow. The battery is used to represent the offset
 10 voltage needed before conduction begins and the resistance models the low dynamic
 11 resistance of the LED when it is conducting. The capacitor models the junction
 12 capacitance along with the LED stray package capacitance. This capacitance becomes
 13 significant when transients exist. Figure 5B shows the electrical DC current voltage
 14 relationship of the piece-wise model of Figure 5A.

15 The typical high brightness LED electrical characteristics modeled in Figures 5A-B
 16 shows that the voltage V_{LED} , ranges from approximately 3 to 3.5 volts depending on the
 17 value of the LED operating current. Also in Figure 3A, it is well known that the value of
 18 V_{be1} and V_{be2} for full conduction of transistors Q_1 and Q_2 is approximately 0.7 Volts at
 19 25°C. In Figure 3A, components R_1 and R_2 provide a voltage divider across the LED sub-
 20 string LED_{1-P} , and produce a voltage V_{be1} that is less than 0.6 volts when the LED is
 21 operating properly. The components comprising Zener diode D_1 and resistor R_2 , provide a
 22 trigger voltage greater than or equal to 0.7 volts when the LED is open circuited. The use
 23 of resistor R_1 , Zener diode D_1 , or both R_1 and D_1 , is optional in the circuit, as shown in the
 24 circuits of Figures 2A-4B. The primary purpose of R_1 and/or D_1 is to establish the trigger
 25 voltage for the latch when an open circuit is present in the LED sub-string. Because the
 26 dynamic resistance of the Zener diode is much less than the value of R_1 , using the Zener
 27 diode will produce a much smaller trigger voltage than would be present with using R_1 .
 28 However, the Zener diode voltage varies with temperature more dramatically than does the
 29 resistance of R_1 . The choice of using R_1 , D_1 , or both R_1 and D_1 , will depend on the
 30 application requirements.

31 Once transistors Q_1 and Q_2 are triggered on, the voltage across the sub-string will
 32 drop to V_{latch} which is approximately 1.4 Volts. Once conduction starts, Q_2 will hold the

1 voltage V_{be1} to a value greater than 0.7 volts. For the circuit of Figure 3A, the sub-string
 2 voltage is V_{latch} during conduction which will be less than the Zener diode conduction
 3 voltage, so D_1 will not conduct current. Also, because the magnitude of V_{latch} is small, the
 4 voltage divider comprising R_1 and R_2 will have a negligible effect on the voltage V_{be1} .

5 The trigger voltage that initiates conduction of Q_1 and Q_2 when the LED is open
 6 circuited is generated automatically by the application of the LED power source only if the
 7 power source open circuit voltage is sufficiently greater than the LED operating voltage.
 8 When any open circuit exists, the voltage developed across the open circuited sub-string
 9 will rise toward the power source unloaded voltage until the sub-string voltage equals V_{trig} ,
 10 the voltage necessary to turn on Q_1 and Q_2 . The voltage rise is not instantaneous because
 11 of the capacitance of the LED as represented in Figure 5A, and other stray circuit
 12 capacitance. The circuit components, Zener diode D_1 and resistors R_1 , R_2 , will use this
 13 rise in voltage across the open sub-string to cause the voltage V_{be1} to rise until it exceeds
 14 0.7 volts, thus turning on Q_1 and Q_2 . Once Q_1 and Q_2 conduct, the positive feedback from
 15 Q_2 will latch the circuit on and the voltage will drop from the V_{trig} value it attained down to
 16 the value V_{latch} of the latched voltages of Q_1 and Q_2 of approximately 1.4 Volts, thereby
 17 turning off conduction of Zener diode D_1 .

18 The preceding operational discussion indicates the necessity of the two conditions
 19 imposed on the LED driver or power source in these embodiments: i.e., the power source
 20 must be a current controlled source capable of sufficient voltage to attain trigger voltage
 21 V_{trig} for the number of OLPCs in operation. When a single LED sub-string in the array is
 22 open, having sufficient voltage will not be a problem. However, if a number of LED sub-
 23 strings fail open circuited, the voltage that appears across each open circuit can only attain
 24 the power source open circuit voltage divided by the number q , of open LED sub-string
 25 circuits. In such a situation, the open circuit power source voltage must exceed q times
 26 V_{trig} . Consequently, there is a limit to the number q of open LED sub-strings that can be
 27 accommodated by the power source. The number of open circuited LED sub-strings in a
 28 given series string which can be bypassed by OLPCs is determined by the ratio of the
 29 power source open circuit Voltage (unloaded voltage) and the magnitude of V_{trig} .

30 The equations describing the operation of the LED Shunt circuit can be determined
 31 by referring to Figure 3A and by applying the operation principles described above. The
 32 triggering characteristics are dependent on the high brightness LED forward voltage V_{LED} ,

as well as the turn on or forward voltage V_{be} of the transistors Q_1 , Q_2 , and the reverse voltage of Zener diode D_1 . These three voltages are temperature dependent, and each device has its own magnitude of temperature coefficient. The transistors Q_1 and Q_2 , and the LEDs, LED_{1-P} , all have negative temperature coefficients. The Zener diode D_1 , has a temperature coefficient which depends on the Zener voltage magnitude and which may be either negative or positive. In lighting applications that include outdoor environments, it is necessary to consider the extremes of the ambient temperatures as well as the operating device junction temperatures.

Figures 2A-4B illustrate several alternative circuits. The differences in the operation of the circuits between the 'A' and 'B' versions (i.e. Figure 2A vs. 2B, Figure 3A vs. 3B, and Figures 4A vs. 4B) only involve the voltage reference point of V_{e1} or V_{e2} in the equations and the change of references of Q_1 to Q_2 . The performance and operation are described by the same equations as presented in the following analysis. The equations include the temperature effects needed to design and describe the operation for the OLPC configuration shown in Figure 3A. The different options using D_1 , R_1 , or both D_1 and R_1 will be included when needed.

The variables used in the equations are defined as follows:

V_{SS} = the voltage across an LED sub-string = p times V_{LED} .

V_{trig} = the V_{SS} open circuit voltage at which Q_1 turns on

V_{thL} = the threshold voltage of the LED or the voltage where current conduction through the LED starts at the temperature of T_{REF} . It is the same as the battery voltage shown in Figure 5A.

V_{tcL} = the LED voltage temperature coefficient.

V_{Lmax} = the maximum LED sub-string forward voltage at rated current.

V_{trig} = the voltage across the LED sub-string necessary to cause Q_1 and Q_2 to turn on.

V_{beth} = the transistor base-emitter cut-on voltage at junction temperature of T_{REF} .

V_{Zth} = the cut-on reverse voltage of the Zener diode at junction temperature of T_{REF} .

V_z = the Zener diode reverse voltage.

V_{beon} = the transistor base-emitter voltage at full conduction at junction temperature of T_{REF} .

V_{Ton} = the transistor base-emitter voltage at full conduction as a function of Temperature.

$V_{be1} = V_{be2} = V_{be}$ = the base-emitter voltage of Q_1 and Q_2 .

V_{Toff} = the voltage at V_{be} to keep Q_1 or Q_2 from turning on.

V_{tcT} = the transistor V_{be} voltage temperature coefficient.

V_{tcZ} = the temperature coefficient of the Zener diode reverse voltage.

V_{latch} = the latched voltage of Q_1 and Q_2 when the OLPC is activated.
 I_{bias} = the current through R_1 and R_2 .
 I_{CE} = the DC leakage current of Q_1 or Q_2 .
 I_{Lz} = the Zener diode leakage current.
 I_z = the forward current magnitude of the Zener diode
 I_s = the source current from the power source or LED Driver.
 I_{b1} = the base current for transistor Q_1 needed to initiate the Q_1 and Q_2 latch.
 R_d = the LED dynamic resistance.
 R_z = the reverse voltage Zener diode "ON" dynamic resistance.
 R_{Lj-c} = thermal resistance for LED junction-to-case.
 R_{Zj-c} = thermal resistance for Zener diode junction-to-case.
 R_{Tj-c} = thermal resistance for transistor junction-to-case.
 R_{c-a} = thermal resistance of the array heat sink case to ambient.
 k = ratio of R_1/R_2 .
 m = total integer number of LEDs connected in series and mounted on an array heat sink.
 n = total integer number of LED sub-strings in an array.
 p = integer number of series connected LEDs in a sub-string.
 q = integer number of LED sub-strings that have failed open.
 T_{jL} = LED junction temperature in $^{\circ}\text{C}$.
 T_{jT} = transistor junction temperature in $^{\circ}\text{C}$
 T_C = temperature of the Case or Heat Sink in $^{\circ}\text{C}$.
 T_A = ambient temperature in $^{\circ}\text{C}$.
 T_{REF} = reference temperature of 25°C .
 T_{jZ} = the temperature of the Zener diode junction in $^{\circ}\text{C}$.

Analysis for Holding Q_L OFF With an Operating LED:

From Figures 2A-B and 3A-B, when the LED is conducting, the following conditions apply. The equations are generalized to account for some number q of protected open LED sub-strings to exist on the array fixture containing a total number m of series connected LEDs.

$$0 \leq pq \leq m; p, q \text{ and } n \text{ are integers satisfying } 1 \leq p \leq m/n;$$

(1)

$$I_s = I_{bias} + I_{LED} + I_{Lz} + I_{CE} \quad (2)$$

For Figures 2A-B, $I_{Lz} = 0$, For Figures 4A-B, $I_{bias} = 0$.

$$I_{b1} = I_{b2} = 0 \quad (3)$$

$$V_{LED} = V_{thL} + R_d I_{LED} + V_{icL} (T_{jL} - T_{REF}) \quad (4)$$

$$V_{SS} = p V_{LED} = p [V_{thL} + R_d I_{LED} + V_{icL} (T_{jL} - T_A)] \quad (5)$$

$$T_{jL} = [R_{Lj-c} + (m - pq) R_{c-a}] V_{LED} I_{LED} + 2q R_{c-a} V_{Ton} I_{LED} + T_A \quad (6)$$

$$V_{Ton} = V_{beon} + V_{icT} (T_{jT} - T_{REF}) \quad (7)$$

$$T_{jT} = [R_{Tj-c} + 2q R_{c-a}] V_{Ton} I_{LED} + (m - pq) R_{c-a} V_{LED} I_{LED} + T_A \quad (8)$$

Combining equations (3), (4), (5), (6), (7), and (8) leads to the relationship V_{Ton} and LED sub-string voltage. V_{SS} temperature relationship given below.

$$V_{SS} = p \left\{ \frac{V_{thL} + R_d I_{LED} + V_{icL} (2qR_{c-a} V_{Ton} I_{LED} + T_A - T_{REF})}{1 - [R_{Lj-c} + (m - pq)R_{c-a}] V_{icL} I_{LED}} \right\} \quad (9)$$

$$V_{Ton} = \frac{V_{beon} + V_{icT} [(m - pq)R_{c-a} V_{LED} I_{LED} + T_A - T_{REF}]}{1 - (R_{Tj-c} + 2qR_{c-a}) V_{icT} I_{LED}} \quad (10)$$

$$V_{LED} = \frac{V_{thL} + R_d I_{LED} + V_{icL} (2qR_{c-a} V_{Ton} I_{LED} + T_A - T_{REF})}{1 - (R_{Lj-c} + (m - pq)R_{c-a}) V_{icL} I_{LED}} \quad (11)$$

While the LED is operating normally, the voltage divider formed by resistors R_1 and R_2 (and/or the Zener diode D_1 leakage current) must not allow transistor Q_1 to conduct. Q_1 conduction is determined by the magnitude of V_{be} and this magnitude is also dependent on Q_1 's junction temperature. Since Q_1 is not conducting, the Q_1 and Q_2 junction temperature will be determined by the case or heat sink temperature. Assuming that the case of Q_1 is at the same temperature as the LED array heat sink case, the following temperature relationship for Q_1 is determined.

$$V_{Toff} < V_{beth} + V_{icT} (T_{jT} - T_{ref}) \quad (12)$$

$$T_{jT} = T_C = (m - pq)R_{c-a} V_{LED} I_{LED} + 2qR_{c-a} V_{Ton} I_{LED} + T_A \quad (13)$$

Combining equations (12) and (13) leads to the below equation for V_{Toff} as a function of Temperature:

$$V_{Toff} = V_{beth} + V_{icT} [(m - pq)R_{c-a} V_{LED} I_{LED} + 2qR_{c-a} V_{Ton} I_{LED} + T_A - T_{REF}] \quad (14)$$

Equation (9) gives the temperature variation that will be applied to the voltage divider comprising R_1 and R_2 . Equation (14) shows the boundary conditions needed to be met by the voltage divider to prevent unwanted conduction of Q_1 . These two equations are used to determine ratio, R_1/R_2 , which will assure Q_1 stays off when the LED is functioning properly. The following analysis develops the conditions that can lead to the desired ratio of R_1 to R_2 .

$$V_{off} = \frac{V_{SS} R_2}{R_1 + R_2} + (I_{IZ} + I_{CE}) \frac{R_1 R_2}{(R_1 + R_2)} < V_{Toff} \quad (15)$$

Because there will be some variation in the value of the cut-on voltage V_{beth} from transistor to transistor, some additional protection should be allocated to the inequality of equation (15). Selecting a multiplier, α , to give a safety factor, leads to the following equation for the ratio R_1/R_2 .

$$0 < \alpha < 1 \quad (16)$$

$$\frac{V_{SS}R_2}{R_1 + R_2} + (I_{IZ} + I_{CE})\frac{R_1R_2}{R_1 + R_2} \leq \alpha V_{Toff} \quad (17)$$

$$k = \frac{R_1}{R_2} \Rightarrow \frac{V_{SS}}{1+k} + (I_{IZ} + I_{CE})\frac{kR_2}{1+k} \leq \alpha V_{Toff} \quad (18)$$

$$k > \frac{V_{SS} - \alpha V_{Toff}}{\alpha V_{Toff} - (I_{IZ} + I_{CE})R_2} \approx \frac{V_{SS}}{\alpha V_{Toff}} - 1; \text{ for } \alpha V_{Toff} \gg (I_{IZ} + I_{CE})R_2 \quad (19)$$

$$\alpha V_{Toff} < V_{Toff} = V_{beth} + V_{icT} [(m - pq)R_{c-a}V_{LED}I_{LED} + 2qR_{c-a}V_{Ton}I_{LED} + T_A - T_{REF}] \quad (20)$$

A second requirement of certain exemplary embodiments is that the Zener diode D_1 does not conduct while the LED is operating normally. The Zener diode is required to conduct current only during the short interval when Q_I is triggered on. Therefore, the temperature of the Zener diode junction will be the same temperature as the case or heat sink. The Zener diode voltage must satisfy the following:

$$V_{SS} < V_z; \quad I_z \approx 0 \quad (21)$$

$$V_z = V_{Zth} + V_{icZ}(T_{jZ} - T_{REF}) \quad (22)$$

$$T_{jZ} = T_C = (m - pq)R_{c-a}V_{LED}I_{LED} + 2qR_{c-a}V_{Ton}I_{LED} + T_A \quad (23)$$

$$V_{SS} < V_z = V_{Zth} + V_{icZ} [(m - pq)R_{c-a}V_{LED}I_{LED} + 2qR_{c-a}V_{Ton}I_{LED} + T_A - T_{REF}] \quad (24)$$

For Figure 4A-B:

$$(I_{IZ} + I_{CE})R_2 \leq \alpha V_{Toff} \quad (25)$$

The previous equations show temperature dependence of V_{LED} , V_z and V_{be} . Resistors R_1 and R_2 are selected to be 1% resistors with ± 100 ppm/ $^{\circ}\text{C}$ temperature coefficient. The value of k and α must be selected to insure the voltage V_{be} for Q_I meets the boundary requirements. Graphing the V_{Toff} , αV_{Toff} , and $V_{SS}/(1+k)$ versus temperature will aid in selecting suitable parameter values for α and k . The parameter values used to produce the graph of Figure 6 are: for T_A ranging from -60°C to $+150^{\circ}\text{C}$, $V_{beth} = 0.6\text{V}$,

$V_{beon}=0.7$ Volts, $V_{tcT}=-2.2\text{mV}/^\circ\text{C}$, $V_{thL}=2.95\text{V}$, $R_d=0.67\Omega$, $V_{tcL}=-4\text{mV}/^\circ\text{C}$, $R_{Lj-c}=8^\circ\text{C}/\text{W}$,
 $I_{CE}=50\mu\text{A}$, $I_{IZ}=3\mu\text{A}$, $m=84$, $R_{Tj-c}=8.3^\circ\text{C}/\text{W}$, $p=1$, and $R_{c-a}=0.2^\circ\text{C}/\text{W}$, and $I_{LED}=0.75\text{ A}$.

The graph in Figure 6 shows that the slope of the line representing Equation (17) is much less than the slopes of the lines representing V_{Toff} or αV_{Toff} . Also, the lowest margin for keeping Q_I off occurs at the highest temperature. A comfortable margin at high temperatures results when $R_2=1000$ ohms, $\alpha=0.8$ and $k=18$. Figures 4A-B removes parameters R_I and k leaving only the leakage currents I_{IZ} and I_{CE} to determine the value of R_2 that can be used. Figure 6 shows the results for a value of $R_2=3600$ ohms. Resistor R_2 should as large as possible to allow Q_I Q_2 to remain in latched conduction when the low currents result with light dimming operations.

Analysis for Triggering Q_I ON When LED is Open:

When an open LED sub-string is encountered, Q_I in Figure 3A must turn on, and then turn on Q_2 to provide a current path around the open LED sub-string. As stated before, once both Q_I and Q_2 turn on, a latch is formed that provides a bypass around the LED sub-string. This current path will be maintained until the current in that path is forced to go near zero. When the LED sub-string is open, the voltage across the open sub-string will go toward the magnitude allowed by the power source. The power source open circuit magnitude must be sufficient to cause the base voltage of Q_I in Figure 3A to exceed V_{be} by a margin sufficient to cause collector current I_{C1} , to be sufficient to turn on Q_2 . The voltage V_{be} , must be substantially greater than 0.7 volts at 25°C to insure full conduction of Q_I . The V_{SS} open circuit voltage at which Q_I turns on is called V_{trig} . Once Q_2 is on, the positive feedback of I_{C2} latches Q_I on, and causes the voltage V_{SS} to drop to the value of $V_{be1} + V_{be2}$. The following equations relate to the turn on of Q_I to latch the shunt circuit bypassing the open LED. The cut-on voltage V_{beth} , is replaced with V_{beon} . Note that the Zener diode current will not be zero during triggering. The duty cycle for the Zener current will be approximately 0.5% during PWM operation. Initially, I_Z will peak at nearly I_{LED} until Q_I and Q_2 start conducting current.

$$\frac{(V_{trig} - V_Z)R_2}{R_z + R_2} \geq V_{Ton} \Rightarrow V_{trig} \approx V_{Ton} + V_Z; \text{ for } R_2 \gg R_z \quad (26)$$

$$V_z = V_{Zth} + I_Z R_z + V_{tcZ} (T_{jZ} - T_{ref}) \quad (27)$$

$$I_Z = I_{LED} - I_{b2} - I_{C2} - \frac{V_z}{(R_3 + R_2)} \approx I_{LED} \quad (28)$$

$$T_{jZ} = R_{Zj-c} (R_z I_{LED} + V_{Zth}) I_{LED} 0.005 + (m - pq) R_{c-a} V_{LED} I_{LED} + 2q R_{c-a} V_{Ton} I_{LED} + T_A \quad (29)$$

$$V_{trig} \geq V_{beon} + V_{Zth} + 0.005 R_{Zj-c} V_{tcZ} (R_z I_{LED} + V_{Zth}) I_{LED} + (V_{tcT} + V_{tcZ}) [(m - pq) R_{c-a} V_{LED} I_{LED} + 2q R_{c-a} V_{Ton} I_{LED} + T_A - T_{REF}] \quad (30)$$

Equations (26) through (30) apply for the circuits shown Figures 3A-B and 4A-B.

$$\frac{(V_{trig})}{1+k} \geq V_{Ton} = V_{beon} + V_{tcT} (T_{jT} - T_{REF}) \quad (31)$$

$$V_{trig} > (1+k) \{ V_{beon} + V_{tcT} [(m - pq) R_{c-a} V_{LED} I_{LED} + 2q R_{c-a} V_{Ton} I_{LED} + T_A - T_{REF}] \} \quad (32)$$

Equations (31) and (32) apply for the circuits shown in Figure 2A-B.

Figure 7 shows a graph of the V_{trig} boundary for the circuits of Figures 2A-4B as a function of the ambient temperature. The graph of Figure 7 use the same parameter values used to determine the α and k values which were used for the graph of Figure 6, with the exception of a change in the cut-on voltage V_{beth} , value to 0.7 volts at 25°C. The added parameter values (at 25°C) used for the Zener diode are: $V_{zth} = 3.79$ V and $R_z = 80\Omega$. Figure 7 also shows a plot of V_{SS} as temperature varies for comparison with V_{trig} . As shown in the graph of Figure 7, it is important when using Figure 2A-B in the application, that a minimum value for k be used to minimize the magnitude of V_{trig} . Conflicting requirements for the value of k include the need to maximize k to hold off the conduction of Q_I when the LED sub-string is functioning normally, and the need to minimize the value for k to keep the value of V_{trig} low. For the circuits of Figures 3A-B and 4A-B, the value of V_z needs to be large enough to keep Q_I from turn-on when the LED sub-string is functioning, but small enough to keep V_{trig} low.

If more than one LED sub-string should fail open, a greater power source voltage must be available to cause the increased number of OLPCs to trigger. For example, if there are 10 LEDs in series with each LED having an OLPC, the power source would be required to provide approximately 40 Volts to operate the LEDs at the lowest temperature. If one open LED occurs, the required power source voltage would become 38.4 volts plus the largest trigger voltage. The greatest trigger voltage will be found at the lowest operating temperature for negative coefficient devices or the highest operating temperature

for positive temperature coefficient devices. From Figure 7, the power source would need to furnish an additional 8.5 Volts ($V_{trig} - pV_{LED}$). Therefore, for each additional LED sub-circuit n failure allowed, the power source must be able to provide an additional n times 8.5 volts in order to activate the OLPC.

Once the latches have been triggered on, the voltage V_{SS} drops to V_{latch} , the sum of the voltages V_{be1} and V_{be2} of Figure 5. As a result, the power dissipation of the LED sub-string is reduced to approximately half the power of one LED. Transistors Q_1 and Q_2 are now dissipating half of the power previously being dissipated by one LED in the LED sub-circuit. The two voltages, V_{be1} and V_{be2} are both temperature dependent and each have approximately the same magnitude. The temperature characteristics are now given by the following equations:

$$V_{latch} = V_{be1} + V_{be2} \approx 2V_{be} \quad (33)$$

$$V_{be} = V_{beon} + V_{icT} \left[(m - pq) R_{c-a} V_{LED} I_{LED} + 2q R_{c-a} V_{Ton} I_{LED} + T_A - T_{REF} \right] \quad (34)$$

$$V_{latch} = 2V_{be} = 2 \left\{ V_{beon} + V_{icT} \left[(m - pq) R_{c-a} V_{LED} I_{LED} + 2q R_{c-a} V_{Ton} I_{LED} + T_A - T_{REF} \right] \right\} \quad (35)$$

Figure 7 shows the magnitude of the voltage V_{latch} , is approximately half the value of V_{LED} . The power source voltage must adjust to the new output voltage required for the total series string but maintain the same output current. In addition, the power source voltage must provide sufficient voltage $V_{Supply(min)}$ to trigger the protection circuit on.

Equations (36) through (38) describe the power source voltage required to trigger and sustain operation of one or more OLPCs in a series string of LED substrings protected by OLPCs: A total number m of LEDs connected in series that has some number q , of open LED sub-circuits, will require a power source voltage that is determined by the following equations. In the following equations the resistor R_W , accounts for any wiring losses in connecting the LED sub-circuits together and/or to the power source. For any array, this would be the wiring between the power source and the array. For applications having isolated LEDs connected in series, R_W accounts for the wiring voltage drops between individual LEDs. Equation (36) indicates power source voltage $V_{Supply(Trig min)}$ needed to trigger the OLPC. Once the OLPC circuit triggers, the required power source voltage drops to the value necessary to sustain LED operation. Equation (37) indicates that the power source sustaining voltage $V_{Supply(Sustain min)}$ is significantly lower than the voltage needed to trigger the OLPC. Equation (38) indicates that the voltage overhead $V_{overhead}$ which is the difference between the power source trigger voltage and the power source sustaining

voltage. This voltage is determined by the number of sub-string failures accepted q and the number of series connected LEDs p in a sub-string.

$$V_{Supply(Trig\ min)} = q(V_{trig(max)} + V_{latch}) + (m - pq)V_{LED} + R_W I_{LED} \quad (36)$$

$$V_{Supply(Sustain\ min)} = qV_{latch} + (m - pq)V_{LED} + R_W I_{LED} \quad (37)$$

$$V_{overhead} \geq qV_{beon} + qV_{Zth} + 0.005 qR_{Zj-c} V_{tcZ} (R_z I_{LED} + V_{Zth}) I_{LED} + q(V_{tcT} + V_{tcZ}) [(m - pq)R_{c-a} V_{LED} I_{LED} + 2qR_{c-a} V_{Ton} I_{LED} + T_A - T_{REF}] \quad (38)$$

As the number p , of LEDs used in the sub-string increases, the value of V_z will increase. As a result, the temperature coefficient of V_z becomes more positive and will cause the value of $V_{Supply(min)}$ to be determined by the highest operating temperature requirements of the system, where $V_{trig(max)}$ occurs. Equation (36) indicates that value needed for $V_{trig(max)}$ and the number of LED sub-strings allowed to fail, will define the LED driver or power source maximum output voltage requirements. A graph of equation (36) showing values for $V_{Supply(Trig\ min)}$ vs. temperature is shown in Figure 8, with $m=10$, $p=1$, and q ranges from 0 to 5.

The value of V_{Zth} increases as p increases. Modifying Equation (38) for V_{Zth} to be scaled by the value of p produces a graph of $V_{overhead}$ as a function of p with $q = 1$ and at a fixed ambient temperature. The maximum voltage overhead will occur at the minimum ambient temperature provided V_{Zth} has a negative temperature coefficient. The Voltage overhead graph shown in Figure 9 assumes a minimum ambient temperature of -40°C , and a 4.7 Volt Zener diode as the model in scaling Equation (38) to produce Equation (39) for use in plotting Figure 9.

$$V_{overhead} = qV_{Trig} = q \left\{ V_{beon} + pV_{Zth(4.7)} + 0.005 pR_{Zj-c(4.7)} V_{tcZ} (R_{z(4.7)} I_{LED} + V_{Zth(4.7)}) I_{LED} + (V_{tcT} + pV_{tcZ(4.7)}) [(m - pq)R_{c-a} V_{LED} I_{LED} + 2qR_{c-a} V_{Ton} I_{LED} + T_A - T_{REF}] \right\} \quad (39)$$

Summary:

The previous analysis has led to the generalized set of equations that take into account temperature effects in designing an LED array that include OLPC. Graphs showing the relationship between the various parameters used are easily constructed from these equations. An important objective in using these equations is to produce a design that minimizes V_{trig} and determines the value of $V_{supply(min)}$. The component values for R_1 and R_2 determine the current magnitude where Q_1 and Q_2 will stop conducting I_{LED} once

the OLPC becomes latched. These resistors also must be selected to assure false triggering does not occur due to the leakage currents from Q_1 and Q_2 . Capacitors C_1 and C_2 provide filtering for transients and prevent Q_1 and Q_2 from false triggering. The values of C_1 and C_2 are influenced by the value of C_{CE} of transistors Q_1 and Q_2 because these components form a capacitor divider across V_{SS} .

$$\frac{V_{Ton}}{I_{LED(\min)}} < R_1 = R_2 < \frac{V_{off}}{(I_{bias} + I_{CEO} + I_{IZ})} \quad (40)$$

$$C_1 = C_2 > kC_{CE} \quad (41)$$

For Figures 2A-B and 3A-B;

$$R_1 \geq kR_2 \quad (42)$$

For Figures 3A-B and 4A-B;

$$V_z > V_{SS} + V_{Ton} \quad (43)$$

Transistors Q_1 and Q_2 will share the current I_{LED} , when the OLPC is active. The sum of I_{C1} and I_{C2} must be equal to I_{LED} . If complementary transistors are used for Q_1 and Q_2 , then each collector current will be approximately equal to $I_{LED}/2$. As shown by the following equations, the base current specification for Q_1 and Q_2 must be capable of magnitudes approaching the value of I_{LED} .

$$I_{B1} \approx I_{C2} \quad (44)$$

$$I_{B2} \approx I_{C1} \quad (45)$$

$$I_{E1} = I_{E2} \cong I_{LED} \quad (46)$$

$$I_{C1} + I_{C2} = I_{LED} \quad (47)$$

The power source must satisfy two criteria. First, it must be large enough to supply V_{trig} to activate the OLPC at the specified maximum number of open LED sub-circuits. Secondly, it must adjust to the needed voltage for the number of active OLPC and the remaining active LEDs without modifying the set current magnitude. The power source voltage requirements as the temperature varies are given in the following equations:

For Figure 2A-B:

$$V_{trig} > (1+k)\{V_{be} + V_{tcT}[(m-pq)R_{c-a}V_{LED}I_{LED} + 2qR_{c-a}V_{Ton}I_{LED} + T_A - T_{REF}]\} \quad (48)$$

$$k > \frac{V_{SS} - \alpha V_{Toff}}{\alpha V_{Toff} - (I_{IZ} + I_{CE})R} \approx \frac{V_{SS}}{\alpha V_{Toff}} - 1; \text{ for } \alpha V_{Toff} \gg (I_{IZ} + I_{CE})R_2 \quad (49)$$

For Figures 3A-B and 4A-B:

$$V_{trig} \geq V_{beon} + V_{zth} + 0.005R_{Zj-c}V_{tcZ}(R_zI_{LED} + V_{Zth})I_{LED} + (V_{tcT} + V_{tcZ})[(m-pq)R_{c-a}V_{LED}I_{LED} + 2qR_{c-a}V_{Ton}I_{LED} + T_A - T_{REF}] \quad (50)$$

For the power source voltage:

$$V_{Supply(Trig\ min)} = q(V_{trig(max)} + V_{latch}) + (m - pq)V_{LED} + R_W I_{LED} \quad (51)$$

2

3

E. Additional Exemplary Method and Embodiment

4

5

The three circuits of Figures 10A-C are similar ways of providing an alternate path for the total current of an open LED.

6

7

Figure 10A shows an electronic circuit according to an exemplary embodiment placed in parallel with each series connected LED or group of series connected LEDs.

8

9

When an open circuit failure of an LED or series group occurs, an alternate conduction path around the open LED or series group is formed and only the illumination provided by

10

the single LED or protected group is eliminated, rather than that provided by the entire

11

string of series connected LEDs. Alternatively, when a short circuit failure of an LED

12

occurs, the illumination of the failed LED is not present, the bypass circuit is not activated,

13

and the remaining LEDs remain lit since they continue to be supplied series current

14

through the shorted LED. Consequently, with the added electronic circuit, the operation of

15

the series connected LED string is essentially the same for either a short circuited or open

16

circuited LED failure.

17

Figure 10B shows an electronic circuit that functions similarly to Figure 10A using

18

a PNP transistor and an NMOS FET. The advantage of Figure 10B over Figure 10A is that

19

the threshold voltage of activation can be adjusted easily without having to change

20

semiconductor devices.

21

Figure 10C shows a circuit that functions similarly to Figure 10A using a PNP

22

transistor and an NPN transistor. The advantage of Figure 10C over Figures 10A and 10B,

23

is that a lower threshold voltage can be obtained when high currents must be bypassed.

24

All three circuits of Figures 10A-C will provide an alternate path for the total

25

current of an open LED. The voltage drop across the shunt path must be slightly higher

26

than the operating LED was at maximum current. Consequently, the power dissipation of

27

the alternative circuit path when active will be slightly greater than the operating LED. It

28

should be noted that while Figure 10A shows a single LED and Figures 10B and 10C show

29

a string of LEDs, any of the circuits may be used with either a single LED or string of

30

LEDs as desired.

31

Figure 11A shows a single semiconductor device known as an SCR connected in

32

parallel with an LED. Resistors R9 and R10 form a voltage divider to develop a trigger

1 voltage to the SCR when the LED fails open. Because the open circuit voltage across the
2 LED will try to reach the voltage applied to the series LED string, the trigger voltage is
3 sufficient to trigger the SCR on. The impedance of the voltage divider must be low
4 enough to provide the SCR specified gate current. Once the SCR is triggered, the voltage
5 across the LED will decrease to approximately 1.4 volts in this example. Conduction of
6 the SCR will continue as long as the current is greater than the sustaining current, and the
7 voltage dropped across the SCR is above the sustaining voltage. Conduction will cease
8 when either the voltage or the current drops below the respective sustaining magnitudes.
9 Once triggered, the voltage applied to the gate does not need to maintain any threshold.

10 The circuit of Figure 11B is a transistorized circuit that functions similarly to
11 Figure 11A. The electronic bypass circuit comprises transistors Q35, Q36, R20, and R21.
12 Additional components, such as diodes or resistors, may be added in order to produce a
13 voltage match to the operating LED if necessary. When activated, the total power
14 dissipation of the bypass circuit is less than or equal to the power dissipation of the
15 functioning LED or LEDs that it replaces. The advantage of Figure 11B is that the trigger
16 current and the sustaining current can be modified and determined by the gain of the
17 transistor and by the resistive components. In addition, R20 and R21 provide values that
18 can be used to adjust the conduction voltage to match or track the operational LED forward
19 voltage. The circuit of Figure 11B can be preferred in many situations. The circuit of
20 Figure 11C is another transistorized circuit that functions similarly to Figure 11A. The
21 circuit of Figure 11D is a circuit similar to Figure 11B with a Darlington transistor
22 configuration which increases the transistor gain which maybe desirable in some
23 circumstances.

24 The purpose of these circuits is to provide an alternate current path around an open
25 LED failure in a series connected string of LEDs in order to maintain the original current
26 magnitude in the remaining operational LEDs. The circuit provides a path that has the
27 same magnitude of current as the functioning LED and has a voltage drop that is less than
28 or equal to the voltage drop of the functioning LED. Once the alternate current path is
29 established, the alternate path remains operational until power is removed (and is
30 reestablished once power is again applied. In addition, the alternate conducting path is
31 able to operate over the entire LED operating current range.

1 Figure 12 shows an array of LEDs within a single circuit with bypass circuits such
2 as described above included. When an LED fails and becomes an open circuit, the voltage
3 applied to the entire series LED string will appear across the open LED, which will trigger
4 the alternate circuit ON causing a low impedance shunt to appear across the open LED.
5 Once the circuit is triggered ON, the circuit is latched ON and the current will continue in
6 the alternate path until the string current falls below a sustaining current value, or the
7 voltage applied to the string falls below a sustaining voltage. The sustaining current is
8 determined by the values of the resistors and current gain of the transistor. The sustaining
9 voltage is established by the transistor base emitter junction voltage.

10 ***F. Additional Method and Embodiment***

11 Figure 13 shows an alternate embodiment wherein the series connected LEDs can
12 be broken into groups such that one circuit protects a number of LEDs. For example, one
13 open LED bypass circuit would protect a group of, e.g., 10 LEDs. So if one LED failed as
14 an open circuit in a series circuit of, e.g., 100 LEDs, a bypass circuit would bypass a group
15 of 10 LEDs including the failed LED, leaving 90 out of the hundred LEDs operational.
16 Since the LED string is driven by a current source, the voltage across the string will adjust
17 to the correct value for the reduced number of active LEDs. The fixtures can be connected
18 as an array of lights which may include a bypass circuit for each light, or for several lights
19 as part of a string. If the configuration is set to bypass several fixtures if one light fails, the
20 fixtures can potentially be wired so that alternating lights will be out, rather than several
21 lights in a row.

22 Figure 14 shows an additional embodiment where several strings of LEDs are
23 included in a single fixture or system of fixtures having OLPC protection for each
24 substring. Each string has a separate current driver.

25 ***G. Additional Method and Embodiment***

26 The circuits shown in Figures 15 – 17D provide an alternative circuit configuration
27 that can be used to provide OLPC operation. The circuits of Figures 16A-D and 17A-D
28 are functionally similar to the simpler circuit shown in Figure 15.

29 The OLPC circuit of Figure 15 is a Zener diode D1, that conducts the current of the
30 LED series sub-string when any one of the diodes, LED1 – LEDP, becomes open circuited.
31 When an open circuit occurs, the voltage across the sub-string containing the open LED
32 will try to attain the LED power source (or driver) open-circuit voltage, but the sub-string

1 voltage will be clamped to the reverse breakdown voltage of the Zener diode D1, and all of
2 the current that was going through the sub-string will now be conducted by the Zener
3 diode. To prevent the Zener diode from conducting current when the LED sub-string is
4 functioning properly, the magnitude of the Zener reverse breakdown voltage must be
5 greater than the LED sub-string maximum forward voltage. As a result of the larger
6 operating voltage for an activated Zener diode OLPC, the power dissipation of the
7 activated OLPC will be greater than the power dissipation of the functioning LED sub-
8 string it protected. The Zener diode form of the OLPC will be designated ZOLPC for the
9 remainder of the discussion.

10 The ZOLPC does not form a latching circuit so a triggering voltage is not required.
11 Conduction is determined only by the magnitude of the voltage applied to the ZOLPC, and
12 as a result, any false conduction would quickly be extinguished by the lower conduction
13 voltage of a parallel operating LED sub-string. Therefore, the maximum power source
14 open-circuit voltage needed to assure operation of the ZOLPC will be determined by total
15 number of series LEDs plus the operating LED sub-strings plus the maximum voltage of
16 the ZOLPC times the number of allowed active ZOLPCs.

17 Since the ZOLPC does not form a latching circuit and the implementation requires
18 the ZOLPC to have a slightly greater conduction threshold voltage than the parallel LED
19 substring, the power dissipated by the ZOLPC will be significantly greater than the power
20 dissipated by the protected LED sub-string, should an LED in the sub-string become open
21 circuited. The power dissipation for LED sub-strings containing more than 1 or 2 LEDs
22 may become prohibitive for the ZOPLC arrangement. For this reason, this shunt circuit
23 configuration is not the preferred circuit configuration for the OLPC.

24 The simple circuit shown in Figure 15 only requires a Zener diode to construct the
25 ZOLPC. When used to protect a high power LED, 1 Watt or more, it requires a power
26 Zener diode. Power Zener diodes are not readily available in the market place and are
27 expensive devices. Figures 16A-D show various ways to shift the power dissipation of the
28 zener diode to a power transistor or power FET. For all the circuits shown in Figure 16A-
29 D, the Zener diode is used only to hold the power device off until an open LED in the
30 sub-string occurs. Once an open circuit in the LED sub-string exists, the voltage across the
31 ZOLPC will automatically rise towards the open circuit voltage of the power source.
32 When the voltage exceeds the Zener diode reverse breakdown voltage, a current flows

1 through the diode and will turn on the power transistor. The current gain of the power
2 transistor is used to produce negative current feedback to the positive terminal of ZOLPC
3 clamping the voltage across the LED sub-string to a value slightly greater than the Zener
4 voltage. The power transistor now conducts the current that originally was conducted by
5 the LED, minus the current needed to bias the power transistor on. The power dissipation
6 in the clamping transistor is approximately the voltage across ZOLPC time the current
7 I_{LED} . All the circuits in Figure 16A-D provide the same function and can be implemented
8 with power transistor types NPN, PNP, NMOS FETs, or PMOS FETs.

9 The gain of the power transistor will influence the voltage across the ZOLPC. If
10 the gain of the power transistor is low, there will be an increase in the voltage across the
11 ZOLP as the series current applied to the LED Lighting System is increased. Figures 17A-
12 D show a two transistor ZOLP configuration which can be implemented to increase the
13 gain of the system and reduce the change in voltage across the ZOLPC as the LED
14 Lighting System current increases. Transistors Q_1 in Figures 17A-D provide additional
15 current gain to bias the power transistors Q_2 on. Because of the added gain, any increase in
16 voltage across ZOLPC gets amplified and causes the current through the power device to
17 increase, producing a tighter clamp on the voltage magnitude across ZOLP.

18 The temperature characteristics of the LED and the ZOLPC devices are important
19 parameters that must be considered in the design. In order to minimize the power
20 dissipation of the active ZOLPC, all components should have negative temperature
21 coefficients to match the negative temperature coefficient of the LEDs. The ZOLPC is not
22 a preferred embodiment of the invention, so the temperature analysis is not included here.

23 Figure 18 shows a graph of the operating voltages for LED, the OLPC, and a single
24 transistor and two-transistor ZOLPC for a protected single LED sub-string. Figure 19
25 shows a graph of the power dissipation of the LED, the OLPC, and a single transistor and
26 two-transistor ZOLPC for a protected single LED sub-string. For a protected sub-string
27 with multiple LEDs, the OLPC trigger voltage will increase but not the active voltage of
28 the OLPC. Consequently, the power dissipated by the active OLPC does not increase with
29 the number of LEDs in the sub-string. For the ZOLPC, the active voltage must increase to
30 accommodate the increased voltage of the sub-string when the LEDs are active. Since the
31 ZOLPC active voltage is higher, the power dissipated by active ZOLPC will also increase
32 as the number of LEDs protected in the sub-string increases. Figure 20 shows a graph of

operating voltage when a protected 3-LED sub-string is implemented. Figure 21 shows a graph of power dissipation when a protected 3-LED sub-string is implemented.

These graphs are valid representations for operation at 25°C and show the performance difference one can expect from the various circuit arrangements described. The value of the voltage where the ZOLPC circuit becomes active must be adjusted to insure the ZOLPC circuit is not active at the LED Sub-string operating voltage at the lowest temperature. Similarly, the trigger voltage of the OLPC circuit must be greater than the LED Sub-string operating voltage at the lowest temperature.

H. Additional Method and Embodiment

Figure 22 illustrates a view of an embodiment similar to Fig. 13 wherein an array of LEDs is distributed over several fixtures. A grouping of bollard type pathway light fixtures 10 are arranged along and provide illumination 40 for pathway 42. These fixtures enclose one or more LEDs within each housing.

Fig. 23 illustrates a plan view of this type of installation. Fixtures 10 are connected by means of circuit 740. Driver 710 provides power to circuit 740 and could be located remotely or within one of the fixtures. Fixtures 10 include one or more LEDs and a bypass circuit. If the LED or LEDs in one fixture fail, the rest of the fixtures remain illuminated.

Fig. 24 illustrates a similar installation having two series circuits 840 and 850 which power alternate lamps 10 and 20. Control 810 can contain separate bypass circuits for groups of fixtures 10 and 20. If a single lamp 10 fails open, the bypass circuit will bypass circuit 840. The remaining lamps 10 will not be illuminated, but circuit 850 will still be receiving power. Lamps 20 will remain illuminated. Note that many circuits could be provided, with each circuit having two or more fixtures or LEDs per circuit. Depending on the application and wiring costs (including burial, conduit use, terrain, etc.) it could be advantageous to configure this system with various types of bypass systems. These systems could allow a bypass circuit for each LED or single-LED fixture, a bypass circuit for multiple LEDs within a fixture, or for multiple fixtures. For instance, these groups of LEDs or fixtures could be distributed such that in the event of a single bypass, no two lights in close proximity would be disabled which could still allow use of the pathway. Alternatively, several LEDs or fixtures in a row might be wired as part of a single string, all of which would be bypassed in the event of an open LED. This might be more

- 1 appropriate where generalized lighting is more available in addition to the pathway
- 2 lighting.

1 What is claimed is:

2 1. A method for controlling multiple light sources operatively connected in series,
3 such as those powered by a driver circuit, by providing an alternative current path around
4 at least one of the multiple light sources when one light source fails comprising:

5 (a) automatically sensing a condition indicative of a failure of a light source of
6 the multiple light sources;

7 (b) automatically providing an alternative current path around the at least one
8 light sources by:

9 (b1) allowing significantly less than operating current through the
10 alternative current path until the condition indicative of a failure of a lighting
11 source;

12 (b2) triggering substantially all operating current to pass through the
13 alternative current path;

14 (c) to allow operating current to bypass the light source sensed to have failed so
15 it is available for other light sources.

16
17 2. The method of claim 1 further comprising passing essentially 100% of the
18 operating current around the failed lighting source.

19
20 3. The method of claim 1 wherein the multiple light sources comprise a substring of
21 light sources and the other light sources are in operative electrical connection with the
22 substring of multiple light sources.

23
24 4. The method of claim 1 further comprising adjusting or trimming voltage and/or
25 current so that operating voltage and current to the other light sources can be maintained
26 when a single light source open failure occurs.

27
28 5. The method of claim 1 further comprising detecting an open failure by monitoring
29 voltage relative to a pre-set triggering voltage.

30
31 6. The method of claim 1 wherein the alternative current pathway is not activated on a
32 short circuit of a single light source.

1
2
3
4
5
6
7
8
9
10
11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32

7. The method of claim 1 wherein the alternative current pathway is operated until power drops below a certain level or is removed from the circuit.

8. The method of claim 1 wherein the light source comprises an LED or other solid state source.

9. The method of claim 1 wherein the bypass occurs at a predesigned triggering voltage and the alternative current path is latched to active for any of the following conditions;

(a) the sensed failure occurs while operating power is through the multiple light sources; or

(b) the failure occurs before operating power is applied to the multiple light sources.

10. An apparatus for controlling multiple light sources such as those powered by a driver circuit, to provide alternative failure mode when one or more individual light source fails, comprising:

(a) an alternative current path circuit in parallel with a subset of the multiple lighting sources;

(b) the alternate circuit path current being significantly less than the single lighting source current such that when the single light source open failure occurs, the alternative circuit detects the same and passes on the order of 100% of the single lighting source current to maintain current to the other lighting sources.

11. The apparatus claim 10 further comprising producing a voltage drop that is less than the light source operating voltage.

12. The apparatus claim 10 further comprising a component to adjust or trim operating voltage and/or current that can be maintained when a light source open failure occurs.

1 13. The apparatus claim 10 wherein the circuit is electronic or primarily electronic.

2

3 14. The apparatus claim 10 wherein the light source comprises an LED or other solid
4 state lighting source.

5

6 15. The apparatus claim 10 wherein the circuit comprises a zener diode, a PNP
7 transistor and an NMOS FET, a PNP transistor and an NPN transistor, an SCR, or a
8 transistorized circuit.

9

10 16. A method for operating a solid state light source comprising:

- 11 a. providing an alternate current path around the solid state light source;
- 12 b. holding the alternative current path inactive so long as a condition
13 indicative of an open solid state light source failure is not sensed;
- 14 c. activating the alternate current path upon detecting a condition indicative of
15 an open solid state light source failure.

16

17 17. The method of claim 16 further comprising providing the alternative current path
18 around a plurality of solid state light sources and activating the alternative current path
19 upon detecting a condition indicative of an open solid state light failure of any of the
20 plurality of solid state light sources.

21

22 18. The method of claim 17 further comprising operatively connecting the plurality of
23 LEDs with other LEDs.

24

25 19. An LED lighting apparatus comprising:

- 26 a. a string of a plurality of LED light sources connected in series;
- 27 b. an alternative current path circuit placed in parallel with the string of LEDs;
- 28 c. the alternative current path circuit including a transistor circuit wherein
29 i. the transistor circuit is substantially inactive except for conducting
30 small leakage and bias currents when the string of LEDs is fully
31 operational;

- 1 ii. the transistor circuit becomes automatically active to pass at least
2 substantially most of the operating current if sufficient voltage
3 indicative of an open LED failure triggers the transistor.
4

5 20. The apparatus of claim 19 wherein the transistor circuit comprises a zener diode,
6 resistors, capacitors, and two transistors, wherein the capacitors filter transients to prevent
7 false triggering of the transistors.
8

9 21. The apparatus of claim 20 wherein the transistor circuit in the inactive state
10 functions to present much less than forward voltage to prevent the transistors from
11 conducting, but presents much greater than the forward voltage when triggered by a
12 condition indicative of an open LED failure.
13

14 22. A method of designing an alternative current path circuit adapted for placement in
15 parallel with an LED or string of LEDs to be essentially inactive until a condition
16 indicative of an open LED failure is sensed, and then automatically becoming active to
17 bypass that LED or the string of LEDs including that LED, with substantially all the
18 operating current, the method comprising: determining and setting a triggering voltage for
19 automatic triggering of an active state for the circuit.




Fig. 1

2/27




FIG 2A




FIG 2B

3/27




FIG 3A




FIG 3B

4/27




FIG 4A




FIG 4B

5/27




Fig. 5A





Fig. 5B


6/27



Graph of V_{toff} , αV_{toff} , Equations (17) and (25) with $p = 1$.

Fig. 6

7/27



Graph showing V_{mig} , V_{ss} , and V_{tach} with $p = 1$.

Fig. 7

8/27





Fig. 8

9/27



Power Supply Overhead Voltage required for number of LED's in Sub-String with $q = 1$.

Fig. 9

10/27




FIG 10A




FIG 10B




FIG 10C

11/27




FIG 11A




FIG 11B

12/27




FIG 11C




FIG 11D




FIG 12

14/27




FIG 13

15/27




FIG 14




FIG 15

17/27




FIG 16A




FIG 16B

18/27




FIG 16C




FIG 16D

19/27




FIG 17A




FIG 17B

20/27




FIG 17C




FIG 17D

21/27





Fig. 19


22/27



Active Single LED Sub-String For Active I-LED, OLPC, and ZOLPC Voltages versus Current

Fig. 18

23/27



Three - LED Sub-String For Active 3-LED's, OLPC, and ZOLPC Voltages versus Current

Fig. 20

24/27




Fig. 21




Fig. 22

26/27




Fig. 23




Fig. 24